


SCHEMATIC  
VIEW FROM BASE END  
FUSE RECOMMENDED BUT NOT SUPPLIED

SPECIFICATIONS											
WIRING	INPUT		OUTPUT				SHAFT ROTATION TO INCREASE VOLTAGE	TERMINAL CONNECTIONS			
	VOLTS	HERTZ	VOLTS	CONSTANT CURRENT LOAD		CONSTANT IMPEDANCE LOAD		FOR INCREASING VOLTAGE AS VIEWED FROM BASE END			
				MAX. AMPS	MAX. KVA	MAX. AMPS		MAX. KVA	INPUT	JUMPER	OUTPUT
SINGLE PHASE	120	50/60	0-120	10	1.2	13	1.56	CW	1-4	—	4-3
			0-140	10	1.4	—	—	CCW	1-4	—	1-3
								CW	4-5	—	4-3
								CCW	1-2	—	1-3
UNLESS OTHERWISE SPECIFIED, TOLERANCE IS ± DECIMALS HOLES ANGLES .XX .XXX .003 .002 *° 1-1/2°			UNITS IN [mm]		TITLE: SPEC. CONTROL DRAWING VARIABLE TRANSFORMER MODEL: 1010B						
MATERIAL :		ALL DIMENSIONS APPLY AFTER PLATING									
The information and design disclosed herein was originated by and is the property of STACO ENERGY PRODUCTS CO., which reserves all patent, proprietary, design, manufacturing, reproduction, use and sale rights thereto, and to any article disclosed therein except to the extent rights are expressly granted to others. The foregoing does not apply to vendor proprietary parts.				DRAWN BY S.A. SMITH		DATE 9/16/97		FIRST USED ON		DO NOT SCALE DWG.	
				CHECKER		DATE		WEIGHT APPROX. 9 LBS		CAGE CODE 83008	
				ENGINEER		DATE		SCALE 1=1		SHEET 1 OF 1	
										DWG. SIZE D	
										DWG. NO. 031-1605	



**STACO ENERGY  
PRODUCTS CO.**  
A Components Corporation of Arvinest Company  
3031 Gadon Boulevard Dayton, Ohio 45403 USA

# Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

[Staco:](#)

[1010B](#)