


Installation Instructions for CS Series Digital Current Detectors

PK 87893



GENERAL INFORMATION

The CS Series of current detectors have a single digital (TTL logic level, open collector) output that will sink 20mA of output current. This is an open collector output. Normal mounting is with two screws inserted through the mounting holes in the housing. Three 0.20 inch long printed circuit board mounting pins are optional. As is a version adapted for AMP part #102241-1. These sensors will not be damaged by overcurrent in the sensed conductor.

SOLDERING INSTRUCTIONS

Hand Soldering - Use 60/40 rosin core solder, employing a 399°C (750°F) controlled temperature, 1/8" chisel tip soldering iron. To avoid delamination of the terminals from the ceramic, do not hold the iron on the terminals for more than four seconds. The temperature of the lead at the ceramic conductor interface must not exceed 250°C (482°F).

Wave Soldering - Use Loncoflux 106A35 or equivalent. Preheaters should be set for 95°C (200°F) on top (component side) of printed circuit board just prior to board entering wave. (This may have to be adjusted depending upon board thickness.) Solder temperature should be a maximum of 260°C (500°F), preferably 252°C to 260°C (485°F to 500°F). Set conveyor speed to approximately 4.5 feet per minute (1.37 meter/min.). Select a speed which gives full solder fillets and minimum of bridging and icicles. The printed circuit board requires rigid support during wave soldering.

CLEANING

Proper cleaning fluids should be selected based on the type of contaminants to be removed. MICRO SWITCH recommends alcohols, chlorinated solvents, and fluorinated solvents.

WARNING

Electrical - Do not exceed maximum supply ratings. Do not reverse supply voltage polarity.

Handling - The terminals are fragile. Handle with care.


Dielectric Isolation - The sensor is not rated for dielectric isolation. Therefore, the user must provide the necessary dieisolation between the sensed conductor and sensor housing.

OPERATING CHARACTERISTICS

Catalog Listing	Mtg. Dim. Fig.	Pinout Style	Operate Current @ 25°C (Amp-Turns)			Operate Current -25°C to +85°C (Amp-Turns)	Release Current -25°C to +85°C (Amp-Turns Min.)	SUPPLY Volt. (Volts DC)	Output Volt. (Volts)	Output Current (mA) Sinking	Response Time
			Min.	Nom.	Max.						
CSDA1BA	1	2	0.32	0.50	0.88	0.50 + 0.5/-0.25	0.08	6 to 16	0.4	20mA	100
CSDA1BC	1	2	2.2	3.5	6.5	3.5 + 4.0/-1.8	0.60	6 to 16	0.4	20mA	100
CSDB1CC	2	--	2.2	3.5	6.5	3.5 + 4.0/-1.8	0.60	8 to 16	0.4	100mA	100
CSDC1BA	1	2	0.32	0.50	0.88	0.50 + 0.5/-0.25	0.08	5 ± 0.2	0.4	20mA	100
CSDC1BC	1	2	2.2	3.5	6.5	3.5 ± 4.0/-1.8	0.60	5 ± 0.2	0.4	20mA	100
CSDA1AA	1	1	0.32	0.50	0.88	0.50 + 0.5/-0.25	0.08	6 to 16	0.4	20mA	100
CSDA1AC	1	1	2.2	3.5	6.5	3.5 + 4.0/-1.8	0.60	6 to 16	0.4	20mA	100
CSDC1AA	1	1	0.32	0.50	0.88	0.50 + 0.5/-0.25	0.08	5 ± 0.2	0.4	20mA	100
CSDC1AC	1	1	2.2	3.5	6.5	3.5 + 4.0/-1.8	0.60	5 ± 0.2	0.4	20mA	100
CSDC1DA	1	3	0.32	0.50	0.88	0.50 + 0.5/-0.25	0.08	5 ± 0.2	0.4	20mA	100
CSDA1DA	1	3	0.32	0.50	0.88	0.50 + 0.5/-0.25	0.08	6 to 16	0.4	20mA	100
CSDC1DC	1	3	2.2	3.5	6.5	3.5 + 4.0/-1.8	0.60	5 ± 0.2	0.4	20mA	100
CSDA1DC	1	3	2.2	3.5	6.5	3.5 + 4.0/-1.8	0.60	6 to 16	0.4	20mA	100

Honeywell Sensing & Control

Figure 1



NOTE: Pinout reversed for AMP connector

Technical drawing of a Micro Switch, Freeport, Ill. U.S.A. The drawing includes three views: a top view, a front view, and a side view. Dimensions are provided in both inches and millimeters.

Top View Dimensions:

- Overall width: 2.68 inches (68.1 mm)
- Overall height: 2.5 inches (63.5 mm)
- Distance from left edge to center: 1.34 inches (34.0 mm)
- Distance from right edge to center: 1.34 inches (34.0 mm)
- Distance from top edge to center: 1.25 inches (31.8 mm)
- Distance from bottom edge to center: 1.25 inches (31.8 mm)
- Distance from left edge to mounting hole center: 0.8 inches (20.3 mm)
- Distance from right edge to mounting hole center: 0.8 inches (20.3 mm)
- Distance from top edge to mounting hole center: 1.22 inches (31.0 mm)
- Distance from bottom edge to mounting hole center: 1.22 inches (31.0 mm)
- Distance between mounting holes: 0.6 inches (15.2 mm)
- Distance from center to mounting hole: 0.3 inches (7.6 mm)

Front View Dimensions:

- Overall width: 2.54 inches (64.5 mm)
- Overall height: 2.76 inches (70.1 mm)
- Distance from left edge to center: 1.27 inches (32.3 mm)
- Distance from right edge to center: 1.27 inches (32.3 mm)
- Distance from top edge to center: 1.38 inches (35.0 mm)
- Distance from bottom edge to center: 1.38 inches (35.0 mm)
- Distance from left edge to mounting hole center: 0.8 inches (20.3 mm)
- Distance from right edge to mounting hole center: 0.8 inches (20.3 mm)
- Distance from top edge to mounting hole center: 1.22 inches (31.0 mm)
- Distance from bottom edge to mounting hole center: 1.22 inches (31.0 mm)
- Distance between mounting holes: 0.6 inches (15.2 mm)
- Distance from center to mounting hole: 0.3 inches (7.6 mm)

Side View Dimensions:

- Overall width: 1.12 inches (28.4 mm)
- Overall height: 1.00 inches (25.4 mm)
- Distance from left edge to center: 0.56 inches (14.2 mm)
- Distance from right edge to center: 0.56 inches (14.2 mm)
- Distance from top edge to center: 0.5 inches (12.7 mm)
- Distance from bottom edge to center: 0.5 inches (12.7 mm)
- Distance from left edge to mounting hole center: 0.8 inches (20.3 mm)
- Distance from right edge to mounting hole center: 0.8 inches (20.3 mm)
- Distance from top edge to mounting hole center: 1.22 inches (31.0 mm)
- Distance from bottom edge to mounting hole center: 1.22 inches (31.0 mm)
- Distance between mounting holes: 0.6 inches (15.2 mm)
- Distance from center to mounting hole: 0.3 inches (7.6 mm)

While we provide application assistance on MICRO SWITCH products, personally and through our literature, it is up to the customer to determine the suitability of the product in the application.

Helping you control your world

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Honeywell:

[CSDA1AA](#) [CSDA1BA](#) [CSDA1DA](#) [CSDA1BC](#) [CSDA1DC](#) [CSDC1DA](#) [CSDA1AC](#) [CSDC1BA](#) [CSDC1AC](#)