

# GLT240128 Technical Manual

**Revision: 1.2** 

# Contents

Co	Contents ii					
1	Gett 1.1 1.2 1.3 1.4	ing StartedDisplay Options AvailableAccessoriesFeaturesConnecting to a PC1.4.1Connection for Non-USB Modules1.4.2Connection for USB ModulesInstalling the Software1.5.1MOGD#	1 2 3 4 5 5 5			
2	Har 2.1 2.2 2.3 2.4 2.5 2.6 2.7 2.8	dware Information         Communication Connectors         2.1.1       Power/Data Connector for Non-USB modules only         2.1.2       USB Connector for USB modules only         Touchpad Interface Connector	6 8 9 10 10 11 12 12 13 14			
3	<b>Trou</b> 3.1 3.2 3.3 3.4	<b>ibleshooting</b> The display does not turn on when power is applied.         The display module is not communicating.         The display module is communicating, however text cannot be displayed.         There is a problem uploading fonts or bitmaps.	<b>15</b> 15 15 16 16			
4	Com 4.1 4.2 4.3 4.4 4.5 4.6	Introduction         4.1.1       I <sup>2</sup> C Communication Summary         4.1.2       I <sup>2</sup> C Transaction Example         4.1.3       Serial Communication         4.1.4       USB Communication         Turn Flow Control On       Image: Control Off         Turn Flow Control Off       Image: Control Off         Changing the I <sup>2</sup> C Slave Address       Image: Control Baud Rate         Setting a Non-Standard Baud Rate       Image: Control Baud Rate	<ol> <li>16</li> <li>16</li> <li>16</li> <li>17</li> <li>18</li> <li>18</li> <li>18</li> <li>19</li> <li>19</li> <li>20</li> <li>21</li> </ol>			

5	Fonts         5.1       Introduction         5.1.1       Font File Format         5.1.2       Creating a Font         5.3       Setting the Current Font         5.4       Font Metrics         5.5       Set Box Space Mode	<ul> <li>22</li> <li>22</li> <li>22</li> <li>24</li> <li>24</li> <li>25</li> <li>26</li> </ul>
6	Text6.1Introduction6.1.1Character Set6.1.2Control Characters6.3Setting the Cursor Home6.4Setting the Cursor Coordinate6.5Auto Scroll On6.6Auto Scroll Off	26 26 26 26 27 27 27 27
7	Bitmaps         7.1       Introduction	28 28 29 30
8	Bar Graphs and Drawing8.1Introduction8.2Set Drawing Color8.3Draw Pixel8.4Drawing a Line8.5Continue a Line8.6Draw a Rectangle8.7Drawing a Solid Rectangle8.8Initializing a Bar Graph8.9Drawing a Bar Graph	<b>30</b> 30 31 31 32 32 32 33 34
	8.10 Initializing a Strip Chart       8.10         8.11 Shifting a Strip Chart       8.11	34 35

	9.7	Set Dragging Threshold	;9
	9.8	Set Pressure Threshold	;9
	9.9	Run Touchpad Calibration    3	;9
10	Disp	av Functions 4	10
10	10.1	Introduction	10
	10.2	Clear Screen 4	10
	10.3	Display On 4	10
	10.4	Display Off	1
	10.5	Set Brightness	1
	10.6	Set and Save Brightness 4	1
	10.0	Set Contrast	12
	10.7	Set and Save Contrast	12
	10.0		r <u>~</u>
11	Files	stem 4	13
	11.1	Introduction	13
		11.1.1 File Upload Protocol	13
		11.1.2 XModem Upload Protocol	15
	11.2	Wipe Filesystem	15
	11.3	Deleting a File	6
	11.4	Get Filesystem Space	-6
	11.5	Get Filesystem Directory	18
	11.6	Filesystem Upload	18
	11.7	Downloading a File	18
	11.8	Moving a File	19
12	Data	Security 4	9
	12.1	Introduction	9
	12.2	Set Remember	60
	12.3	Data Lock	60
	12.4	Set and Save Data Lock	62
	12.5	Dump the Filesystem	62
	12.6	Write Customer Data	52
	12.7	Read Customer Data	52
13	Misc	llaneous 5	;3
	13.1	Introduction $\ldots$ $\ldots$ $\ldots$ $\ldots$ $\ldots$ $5$	;3
	13.2	Read Version Number	;3
	13.3	Read Module Type    5	;3
1/	Com	nond Summory 5	5
14	14.1	Communications 5	55
	14.1	Continuutivations	;) ;5
	14.2	гощь	ני דד
	14.5	۲۵٫۱	50 7-7
	14.4	סונווומףא	0
	14.5	Bar Graphs and Drawing	0
	14.6	10ucnpaa	)/

14	.7 Display Functions	7
14	.8 Filesystem	8
14	.9 Data Security	8
14	.10Miscellaneous	9
14	.11Command By Number	9
15 Ap	opendix 6	1
15	1 Optical Characteristics	51
15	.2 Specifications	51
	15.2.1 Environmental	1
	15.2.2 Electrical	2
	15.2.3 Touch	2
15	.3 Physical Layout	2
15	.4 Ordering Information	4
15	.5 Definitions	4
15	.6 Contacting Matrix Orbital	4
15	.7 Revision History	5

# **1 Getting Started**



The GLT240128 is an intelligent graphic LCD display designed to decrease development time by providing an instant touch screen solution to any project. With the ability to communicate via serial RS-232 protocol at regular and TTL levels as well as USB and I<sup>2</sup>C, the versatile GLT240128 can be used with virtually any controller. The ease of use is further enhanced by an intuitive command structure to allow display settings such as backlight brightness, contrast and baud rate to be software controlled. Additionally, text and fonts may be uploaded to the display and stored in the on board memory. Finally, simple touch commands allow for the seemless integration of user control into the display environment.

#### 1.1 Display Options Available

The GLT240128 comes in three backlight options, grey text on a white backlight, white text with a blue backlight, and standard grey text on a yellow-green backlight. Extended voltage options are also available to allow you to select the display which will best fit your project needs. Please see table 81 for ordering information.



Figure 1: GLT240128 Options

#### 1.2 Accessories

**NOTE** Matrix Orbital provides all the interface accessories needed to get your display up and running. You will find these accessories and others on our e-commerce website at http://www.matrixorbital.com. To contact a sales associate see Section 15.6 for contact information.



Figure 2: 5V Power Adapter

Figure 3: 12V Power Adaptor (-V/-VPT)



Figure 4: 3ft Mini-B USB Cable

Figure 5: Breadboard Cable



Figure 6: Communication & Power Cable

Figure 7: Serial Cable

#### 1.3 **Features**

- 240 x 128 pixel graphics display
- Integrated Touchpad Overlay
- Selectable communication protocol, RS-232, TTL, and I<sup>2</sup>C for Non-USB models; USB only for USB models

Matrix Orbital

- 128 byte buffered communication
- 16 KB flash memory for fonts and bitmaps
- Lightning fast communication speeds, up to 115 kbps for Serial and 100 kbps for I<sup>2</sup>Cprotocol
- \* Use of up to 127 modules on the same 2 wire I<sup>2</sup>C interface
- Display text using built in or user supplied fonts
- Software adjustable contrast and backlight brightness
- Default 19.2 kbps serial communication speed
- Extended voltage, and efficient power supply available

#### 1.4 Connecting to a PC

The GLT240128 connects seamlessly to a PC and it is an excellent means of testing the functionality and uploading new fonts and bitmaps. For the Non-USB version, you will require a standard RS-232 9-pin serial cable such as the one pictured in Figure 7, as well as a modified 5V or 12V power adapter, depending on the voltage model, such as the ones pictured in Figures 2 and 3. For the USB model, of course, all you will need is a USB to mini USB cable such as the one in Figure 4.

#### 1.4.1 Connection for Non-USB Modules

In order to connect your Non-USB display to a personal computer follow these easy instructions:

- 1. Plug the serial cable into the com port you wish to use.
- 2. Connect the appropriate modified power adapter to a power lead from your PC power supply (you will have to open your computer case).
- 3. Connect the serial cable to the DB-9 connector on the back of the display.
- 4. Connect the appropriate power adapter to the 4-pin connector on the back of the display.



**WARNING** DO NOT use the standard floppy drive power connector on the Power/Data Connector, as this will not provide you with the correct voltage and will damage the display module.



Figure 8: PC vs Matrix Orbital Display Module Wiring

#### 1.4.2 Connection for USB Modules

In order to connect your USB display to a personal computer simply plug the mini-B USB cable, such as that shown in Figure 4 from the PC to the USB connector on the display.



#### 1.5 Installing the Software

#### 1.5.1 MOGD#

MOGD# is the latest updated version of MOGD and can be used to manage font and graphics downloads as well as exercise all of the features of our graphical displays. MOGD# provides a new user friendly interface as well as many feature enhancements.

To install MOGD# from the Matrix Orbital website, follow the following steps:

- 1. Go to the website location: http://www.matrixorbital.ca/software/software\_graphic/MOGDsharp/
- 2. Click on "Download Here"
- 3. Locate the file MogdSharp.zip on your desktop
- 4. Unzip MogdSharp.zip to a temporary directory using a program such as Winzip
- 5. Double click on "setup.exe"

Matrix Orbital

- 6. Follow the instructions on the screen to complete the installation
- 7. MOGD# requires the .NET framework 2.0 and will download and install it automatically

After the installation is complete there will be a Matrix Orbital entry under "Start->Programs->Matrix Orbital" in the start menu. Click on the 'Mogd Sharp' entry to run the program.

Be sure to check the information selected in the configuration panel the first time MOGD# is run. Once this information is entered correctly the program can be used to control all functions of the graphic display.

Configuration	۲	<b>Port</b> The serial port the display is plugged in to.
Port		
COM1	-	<b>Speed</b> The communication speed the display module is set to
Speed		(Default 19,200)
115200	-	<b>Display Type</b> The type of display (GLT240128)
Display Type		Display Type The type of display (GD12+0120)
GLC24064	-	<b>PCB Revision</b> The revision of the display you are using.
Pcb Revision		(Found on the back of the PCB).
2.0	-	
Configure Display Defa	ults	

Figure 9: Mogd Sharp Settings

• Winzip is available as a free download from http://www.winzip.com

### 2 Hardware Information

Refer to the following diagram for this chapter:



Figure 10: GLT240128 Non-USB



Figure 11: GLT240128 USB

#### 2.1 Communication Connectors

#### 2.1.1 Power/Data Connector for Non-USB modules only

The *Power/Data Connector* provides a standard connector for powering the display module. The GLT240128 requires five volts for the standard display module, between nine to fifteen for the wide voltage (V) model, and between nine to thirty-five volts for the wide voltage with efficient power supply module (VPT). The voltage is applied through pins one and four of the four pin *Power/Data Connector*. Pins two and three are reserved for serial transmission, using either the RS-232 or TTL protocol levels, depending on what has been selected by the *Protocol Select Jumpers*.

Matrix Orbital



Pin 1GNDPin 2Tx/SDA (I2C data)Pin 3Rx/SCL (I2C clock)Pin 4Vcc (see table 78 on page 62)

Figure 12: Power Connector and Pin-out

#### 2.1.2 USB Connector for USB modules only

The *USB Connector* provides a standard connector for powering and communicating to the USB display module. As with the non-USB version, the GLT240128-USB requires five volts for the standard display module as per table 78.



Figure 13: USB Connector for GLT240128

#### 2.2 Touchpad Interface Connector

The GLT240128 provides a *Touchpad Interface Connector* which allows for the touchpad to be interfaced to the display. This connector should remain plugged in while the unit is in operation and should not be tampered with in any way.



Figure 14: Touchpad Interface Connector

#### 2.3 DB-9 Connector for Non-USB modules only

The GLT240128 provides a *DB-9 Connector* to readily interface with serial devices which use the EIA232 standard signal levels of  $\pm$ 9V. It is also possible to communicate at TTL levels of 0 to +5V by setting the *Protocol Select Jumpers* to TTL. As an added feature it is also possible to apply power through pin 9 of the *DB-9 Connector* in order to reduce cable clutter. However, in order to accomplish this you must set the *Power Through DB-9 Jumper*.

Matrix Orbital



Pin 2RX/SCL (I²C clock)Pin 3TX/SDA (I²C data)Pin 5GNDPin 9PWR (Must solder power through DB-9 jumper. See table 7

Figure 15: RS-232 Pin-out

#### 2.4 Power Through DB-9 Jumper

In order to provide power through pin 9 of the *DB-9 Connector* you must place a solder jumper on the *Power through DB-9 Jumper* pictured in Figure 16 below. The GLT240128 allows all voltage models to use the power through DB-9 option, see table 78 for display module voltage requirements.



Figure 16: Power Through DB-9 Jumper



**WARNING** Do not apply voltage through pin 9 of the DB-9 connector AND through the Power/Data Connector at the same time.

**NOTE** We do not recommend that you use pin 9 (Ring Indicator) of the PC to power the display module. You will have to make a special DB9 cable.

#### 2.5 Optional USB Header for USB modules only

The GLT240128 USB version has an optional four pin header for internal USB communications with host units. This provides the same communication lines as the regular header, albeit in a different form factor for greater customization. Again, please 78 see for power requirements.



Figure 17: Optional Internal USB Header

#### 2.6 Protocol Select Jumpers

The *Protocol Select Jumpers*, pictured below in Figure 18, provide the means necessary to toggle the display module between RS-232 and TTL protocol levels. As a default for Non-USB modules, the jumpers are set to RS-232 mode with zero ohm resistors on the 232 jumpers. In order to place the display module in I<sup>2</sup>C mode you must first remove the zero ohm resistors from the 232 jumpers and then solder the resistors on to the I<sup>2</sup>C jumpers, or bridge solder across the pads. The display will now be in I<sup>2</sup>C mode and have a default slave address of 0x50 unless the I<sup>2</sup>C address has been changed. Similarly, in order to change the display to TTL mode, simply remove the zero ohm resistors from the 232 or I<sup>2</sup>C jumpers and solder them to the TTL jumpers. Although RS-232, USB, TTL and I<sup>2</sup>C are present, only 232/TTL/I<sup>2</sup>C are for use in the Non-USB module. For the USB module operation the USB jumpers must be in place. There are three, one is for power. If you wish to power it up from a non-USB source, you must remove one of the jumpers. The jumper to remove is the rightmost USB jumper as seen if Figure 19.



Figure 18: Protocol Select Jumpers for Serial and  $I^2C$  modules



Figure 19: Protocol Jumpers for USB modules

#### 2.7 Filesystem Lock Jumper

The Filesystem Lock Jumper allows you to lock the filesystem on the GLT240128 so that no fonts or bitmaps can be either written or deleted from the on board memory. This feature is useful in order to protect data integrity of production units, if protection of other settings is required see Section 12

To lock the filesystem, solder a zero ohm resistor or use a solder jumper pictured in Figure 20 below.



Figure 20: Filesystem Lock Jumper

#### 2.8 Manual Override

The *Manual Override* is provided to allow the GLT240128 to be reset to some of the factory defaults. This can be particularly helpful if the display module has been set to an unknown baud rate or  $I^2C$  and you are no longer able to communicate with it. If you wish to return the module to its default settings you must:

- 1. Power off the display module.
- 2. Place a Jumper on the Manual Override pins, as pictured below.
- 3. Power up the display module.
- 4. The display module is now set to its default values listed below in table 1.
- 5. Edit and save settings.



Figure 21: Manual Override Jumper

Table 1: Default Values		
Contrast	128	
Backlight	255	
Baud Rate	19.2 kbps	
Data Lock	False	

**NOTE** The display module will revert back to the old settings once turned off, unless the settings are saved.

# 3 Troubleshooting

#### 3.1 The display does not turn on when power is applied.

- First, you will want to make sure that you are using the correct power connector. Standard floppy drive power cables from your PC power supply may fit on the Power/Data Connector however they do not have the correct pinout as can be seen in Figure **??**. Matrix Orbital supplies power cable adapters for connecting to a PC, which can be found in the Accessories Section on page 2.
- The next step is to check the power cable which you are using for continuity. If you don't have an ohm meter, try using a different power cable, if this does not help try using a different power supply.
- The last step will be to check the *Power / Data Connector* on the GLT240128. If the *Power / Data Connector* has become loose, or you are unable to resolve the issue, please contact Matrix Orbital see 15.6 on page 64 for contact information.

#### 3.2 The display module is not communicating.

- First, check the communication cable for continuity. If you don't have an ohm meter, try using a different communication cable. If you are using a PC try using a different Com port.
- Second, please ensure that the display module is set to communicate on the protocol that you are using, by checking the *Protocol Select Jumpers*. To change the protocol used by the display module see Section 2.6 on page 12.
- Third, ensure that the host system and display module are both communicating on the same baud rate. The default baud rate for the display module is 19200 bps.
- \* If you are communicating to the display via I<sup>2</sup>C please ensure that the data is being sent to the correct address. The default slave address for the display module is 0x50.

**NOTE** I<sup>2</sup>C communication will always require pull up resistors.

• Finally, you may reset the display to it's default settings using the Manual Override Jumper, see Section 2.8 on the preceding page.

# 3.3 The display module is communicating, however text cannot be displayed.

- The cause of this is often that no font has been loaded onto the display. To load a font onto the display see Section 4.2.1 on page 16.
- Another common cause may be that the contrast settings have been set to low. The solution to this problem is to adjust the contrast settings, the default setting that will work in most environments is 128

**NOTE** Optimal contrast settings may vary according to factors such as temperature, viewing angle and lighting conditions.

#### 3.4 There is a problem uploading fonts or bitmaps.

- First, ensure that you can communicate to the display. A good test is to use a PC, with MOGD# installed, to connect to the display. See Section 1.4 on page 4for setting up a PC to test the GLT240128.
- Second, ensure that the Filesystem Lock Jumper has not been set. See Section 2.7 on page 13.
- Third, please ensure that the display module's memory is not full. The GLT240128 has 16 Kb of memory for fonts and bitmaps.

**NOTE** If you are unable to resolve any issue please contact Matrix Orbital. See 15.6 on page 64 for contact information.

# 4 Communications

#### 4.1 Introduction

The commands listed in this chapter describe how to configure data flow on the GLT24064.

#### 4.1.1 I<sup>2</sup>C Communication Summary

The GLT24064 is capable of communicating at 100 KHz in I<sup>2</sup>C mode, with 127 units addressable on a single I<sup>2</sup>C communication line. However, in order to communicate via I<sup>2</sup>C you must first ensure that pull up resistors, with a nominal value of 1K to 10K, are placed on the SCL and SDA communication lines coming from pins two and three of the Data / Power Connector respectively. Data responses by the module are automatically output via RS232, in case the host will be querying the module, it is necessary for the host to inform the module that its responses are to be output via I<sup>2</sup>C. This can be done by sending command 254 /160 / 0 to turn off auto transmission of data in RS232. This will keep the data in the buffer until the master clocks a read of the slave. The I<sup>2</sup>C data lines operate at 5V normally or 3.3V for -1U style units. The GLT24064 uses 8-bit addressing, with the 8th or Least Significant Bit (LSB) bit designated as the read/write

bit, a 0 designates a write address and a 1 designates a read address. The default read address of the display module will be 0x51, whereas the write address is 0x50 by default. This address may be changed by using cmd 254 / 51 / <address>. The GLT24064 should only be sent addresses that are even (LSB is 0). When the I<sup>2</sup>C master wishes to write to the display, the effective address is \$50 (0101 0000), since the LSB has to be 0 for an I<sup>2</sup>C master write. When the I<sup>2</sup>C master wishes to read the GLT24064, the effective address is \$51 (0101 0001), since the LSB has to be 1 for an I<sup>2</sup>C master read.

If we take a standard Phillips 7 bit address of \$45 (100 0101), Matrix Orbital's GLT24064 would describe this Phillips I<sup>2</sup>C address as \$8A (1000 1010). The read address would be \$8B (1000 1011).

The unit does not respond to general call address (\$00).

When communicating in I<sup>2</sup>C the GLT24064 will send an ACK on the 9th clock cycle when addressed. When writing to the display module, the display will respond with a ACK when the write has successfully been completed. However if the buffer has been filled, or the module is too busy processing data it will respond with a NAK. When performing a multiple byte read within one I<sup>2</sup>C transaction, each byte read from the slave should be followed by an ACK to indicate that the master still needs data, and a NAK to indicate that the transmission is over.

The GLT24064 has some speed limitations, especially when run in  $I^2C$  mode. Here are some considerations when writing  $I^2C$  code:

\* to be able to read the replies of query commands (eg. cmds 54, 55) the following command must be sent (only needs to be sent once, so this can be done somewhere in init): 254 / 160 / 0 this command puts the reply data in the I<sup>2</sup>C output buffer instead of the RS232 output buffer. Please note that due to a 16 byte output buffer, query commands that reply with more than 16 bytes cannot be read (eg cmd Get FileSystem Directory)

- \* 3ms delay between the read commands
- \* 625us delay in between data bytes within a transaction is necessary
- \* 375us between transactions is necessary

NOTE These delays are consrevative, and may be decreased based on performance

#### 4.1.2 I<sup>2</sup>C Transaction Example

The typical I<sup>2</sup>C transaction contains four parts: the start sequence, addressing, information, and stop sequence. To begin a transaction the data line, SDA, must toggle from high to low while the clock line, SCL, is high. Next, the display must be addressed using a one byte hexadecimal value, the default to write to the unit is 0x50, while read is 0x51. Then information can be sent to the unit; even when reading, a command must first be sent to let the unit know what type of information it is required to return. After each bit is sent, the display will issue an ACK or NACK as described above. Finally, when communication is complete, the transaction is ended by toggling the data line from low to high while the clock line is high. An example of the use of this algorithm to write a simple "HELLO" message can be seen in 2.

Table 2: I <sup>2</sup> C Transaction Algorithm		
START	Toggle SDA high to low	
Address	0x50	
Information	0x48 0x45 0x4C 0x4C 0x4F	
STOP	Toggle SDA low to high	

 $\pi$  11  $\alpha$   $\tau^2 \alpha \pi$ . • 4.1 • . 1

#### 4.1.3 Serial Communication

In addition to being able to communicate via I<sup>2</sup>C the GLT24064 communicates natively through the RS-232 protocol at at a default baud rate of 19,200 bps and is capable of standard baud rates from 9600 to 115,200 bps. Furthermore the GLT24064 is also capable of reproducing any non-standard baud rate in between using values entered into our baud rate generation algorithm and set through command 164 (0xA4). The display module communicates at standard voltage levels of -30V to +30V or at TTL levels of 0 to +5V by setting the Protocol Select Jumpers to TTL.

#### **USB** Communication 4.1.4

The GLT24064 is a USB device that offers identical communication protocol as the serial comport. capable of communicating via a USB interface. The USB communications are identical to the serial communications. Communication is via a virtual com port, which is created in the operating system by the drivers necessary to install the USB display. The GLT24064 communicating via USB is capable of baud rates of 19,200 bps to 115,200 bps. Other baud rates are subject to the limitation of the virtual com port driver. For further information regarding supported operating systems, and driver limitations please contact technical support.

#### 4.2 **Turn Flow Control On**

Syntax	Hexadecimal	0xFE 0x3A [full] [empty]	
-	Decimal	254 58 [full] [ei	mpty]
	ASCII	254 ":" [full] [e	empty]
Parameters	Parameter	Length	Description
	full	1	Bytes remaining before issuing a
			almost full message. (Full is 0)
	empty	1	Bytes available before issuing a
			almost empty message. (Empty is
			128)

Description	This command enables flow control. When the buffer fills so that only [full] bytes are available, the display will return an "almost full" message (0xFE) to the host controller. When the buffer empties so that only [empty] bytes remain, the display will return an "almost empty" message (0xFF) to the host controller. The display will return the "almost full" message for every byte sent to the display until the used buffer space once more drops below the [full] level. Whether the user is in 'flow control mode' or not, the module will ignore display or command bytes which would overrun the buffer. While in 'flow control mode' the unit will return 0xFE when buffer is almost full even though it may have already thrown rejected data away. The buffer size for the display is 128 bytes. When using this command in an application, selection of the value for the buffer [full] should be considered very carefully. This is a critical aspect to be able to use this feature to it's full potential. When using a host system or PC which contains a FIFO, the user should set the value of [full] equal to or greater than the size of the FIFO. The reason for this is that the FIFO may be full when the host system receives 0xFE. In the case of 16550 UART the size at its maximum is 16, therefore the value of [full] should be set to 16 or greater. It is suggested that the "almost full]
	case of 16550 UART the size at its maximum is 16, therefore the value of [full] should be set to 16 or greater. It is suggested that the "almost full" parameter be equal to the largest chunk of data the host will be sending the display (should be less than 127).

**NOTE** This command is not available in  $I^2C$  mode.

Remembered Yes Default Off

#### 4.3 Turn Flow Control Off

Syntax	Hexadecimal	0xFE 0x3B
	Decimal	254 59
	ASCII	254 ";"
Description	This command turns off flow control. Bytes may overflow th without warning.	

 $\label{eq:NOTE} \textbf{NOTE} \quad This command is not available in I^2C mode.$ 

Remembered Yes

## 4.4 Changing the I<sup>2</sup>C Slave Address

Syntax	Hexadecimal	0xFE 0x33 [adr]	
	Decimal	254 51 [adr]	
	ASCII	254 "3" [adr]	
Parameters	Parameter	Length	Description
	adr	1	The new $I^2C$ write address (0x00 -
			0xFF).
Description	0xFF). This command sets the I <sup>2</sup> C write address of the module between 0x00 and 0xFF. The I <sup>2</sup> C write address must be an even number and the read address is automatically set to one higher. For example if the I <sup>2</sup> C write address is set to 0x50, then the read address is 0x51.		

**NOTE** The change in address is immediate.

Remembered	Always
Default	0x50

# 4.5 Changing the Baud Rate

Dyntax	Hexadecima	l 0xFE 0x39	[speed]
	Decimal	254 57 [spe	ed]
	ASCII	254 "9" [sp	eed]
Parameters	Parameter	Length	Description
	speed	1	Hex value corresponding to a baud
			rate.
Description	This command	l sets the RS-23	2 port to the specified [speed]. The change
	takes place im	mediately. [spe	eed] is a single byte specifying the desired
	port speed. V	alid speeds are	e shown in the table below. The display
	module can be	e manually reso	et to 19,200 baud in the event of an error
	during transm	ission, includin	g transmitting a value not listed below, by
	setting the mar	nual override ju	mper during power up. However, it should
	be noted that	this command	will be ignored until the manual override
	jumper is rem	oved again.	
	Hoy Voluo	Roud Data	
	Hex Value	Baud Rate	
	Hex Value	<b>Baud Rate</b> 9600	
	Hex Value 0xCF 0x8A	<b>Baud Rate</b> 9600 14400	
	Hex Value           0xCF           0x8A           0x67	<b>Baud Rate</b> 9600 14400 19200	
	Hex Value           0xCF           0x8A           0x67           0x44	Baud Rate           9600           14400           19200           28800	
	Hex Value           0xCF           0x8A           0x67           0x44           0x33	Baud Rate           9600           14400           19200           28800           38400	
	Hex Value           0xCF           0x8A           0x67           0x44           0x33           0x22	Baud Rate           9600           14400           19200           28800           38400           57600	
	Hex Value           0xCF           0x8A           0x67           0x44           0x33           0x22           0x19	Baud Rate           9600           14400           19200           28800           38400           57600           76800	
	Hex Value           0xCF           0x8A           0x67           0x44           0x33           0x22           0x19           0x10	Baud Rate           9600           14400           19200           28800           38400           57600           76800           115200	
Remembered	Hex Value           0xCF           0x8A           0x67           0x44           0x33           0x22           0x19           0x10	Baud Rate           9600           14400           19200           28800           38400           57600           76800           115200	

### 4.6 Setting a Non-Standard Baud Rate

Syntax	Hexadecimal	0xFE 0xA4 [s	peed]			
-	Decimal	254 164 [spee	d]			
Parameters	Parameter	Length	Description			
	speed	2	Inputed LSB MSB from baud rate			
			formula (12-2047).			
Description	This command sets the RS-232 port to a non-standard baud rate. The command accepts a two byte parameter that goes directly into the modules baud generator. Use the formula, $speed = \frac{CrystalSpeed}{8\times DesiredBaud} - 1$ to calculate the [speed] for any baud rate setting. The speed can be anywhere from 12 to 2047 which corresponds to a baud range of 977 to 153,800 baud. Setting the baud rate out of this range could cause the display to stop working properly and require the Manual Override jumper to be set.					
Remembered Examples	Always					
	Crystal Speed 16 Mhz					
	Desired BAUD 13,500					
	$speed = \frac{1}{8}$ $speed =$ $\bullet LSB = 0x$ $\bullet MSB = 0x$ $\bullet Intended H$ $\frac{16,000,000}{8(147+1)} =$	<u>crystalspeed</u> *DesiredBaud 148.15 – 1 93 (rounded) 00 3aud Rate: 13,5 =13,514 Pe	$f_{2} - 1$ speed = $\frac{16,000,000}{8 * 13,500} - 1$ speed = 147.15			
	NOTES • Results fro	om the formula	are rounded down to the nearest whole number (			

- This formula becomes less acurate as baud rates increase, due to rounding.
- Place the speed result backwards into the formula to receive the actual baud rate. ( $Baud = \frac{CrystalSpeed}{8(speed+1)}$ ) The actual baud rate must be within 3% of the intended baud rate for the device to
- communicate.

73.07

#### **Fonts** 5

#### 5.1 Introduction

The GLT24064 comes loaded with the 'Small Filled' and 'Futura Bk BT 16' fonts by default. However, it is capable of displaying any font that is uploaded to it in the correct format. MOGD# provides a simple method of generating font files from your installed fonts. For instructions on how to install MOGD# see Section 1.5.1 on page 5.

#### 5.1.1 **Font File Format**

A font file consists of three parts, a header, a character table and bitmap data.

1. Header (4 bytes)

- (a) Nominal Width (1 byte)
- (b) Height (1 byte)(c) ASCII Start Value (1 byte)
- (d) ASCII End Value (1 byte)
- 2. Character Table (3 bytes for every character between the ASCII Start and End values inclusive)
  - (a) High Offset MSB (1 byte)
  - (b) Low Offset LSB(1 byte)
  - (c) Character Width (1 byte)
- 3. Bitmap Data

#### 5.1.2 Creating a Font

The following is an example of how to create a font file for the letters h, i and j.

First you must create the bitmaps containing the character data in bitmap form. Figure 22 below illustrates the bit pattern for the *h*, *i* and *j* bitmap data.



Figure 22: Bitmaps for h, i, and j

Second you may begin to create the font file starting with the header. The header will contain the nominal width, the height and the ASCII start and end values inclusive that you wish to create characters for.

Table 8: Font File Header					
Nominal Width	Height	ASCII Start Val	ASCII End Val		
0x05	0x07	0x68	0x6A		

Next we will have to find out how many bytes each character will use up, in order to create the character table. The bitmaps are encoded horizontally and may have variable widths, h has a width of five, i a width of three and j a width of four, see the figure below for an example of encoding the first letter h:

Bitmap Data					Byte	Hex Value
1	0	0	0	0		
1	0	0	0	0	10000100	0x84
1	0	1	1	0	00101101	0x2D
1	1	0	0	1	10011000	0x98
1	0	0	0	1	11000110	0xC6
1	0	0	0	1	00100000	0x20
1	0	0	0	1		

Figure 23: Bitmap Encoding

As you can see the letter h will take up five bytes with the last five bits being zero padded to form a full byte. So if you continue the process you will get the character data as seen in *table 5.1.2*.

Character 1	Data
-------------	------

		Cha	racter I	Byte Size (For Reference)		
h	0x84	0x2D	0x98	0xC6	0x20	0x05
i	0x43	0x24	0x84			0x03
j	0x2D	0x98	0x19	0x60		0x04

The second part of the font file is the character table. The character table is comprised of three bytes for every glyph in the font file.

The first two bytes represents the position, in bytes, of the glyph stored MSB LSB referenced from the beginning of the file (including the header. The third byte is the width of the glyph in pixels. So because there will be 0x09 bytes in the character table (three bytes for each glyph) and four bytes in the header section, the first entry in the table will be 13, or 0x00 0x0D in hexadecimal, and 0x05 for the width.

To calculate the second entry in the character table, representing the position and width of the second glyph, take the offset of the first entry and add the size of the first bitmap in bytes. Since the first glyph occupies 0x05 bytes as seen in table 5.1.2 above, and the offset is 0x00 0x0D, the offset of the second entry will be 0x00 0x12 and the width of the glyph is 0x03.

Calculate the third entry the same way as the second to get *table 9* below.

Table 9: Character Table							
	High Offset (MSB)	Character Width					
h	0x00	0x0D	0x05				
i	0x00	0x12	0x03				
j	0x00	0x15	0x04				

Matrix Orbital

Once completed, place the character table after the header and the character data aat the end, as seen in table 10.

Table 10: Sample Font File							
0x05	0x07	0x68	0x6A	0x00	0x0D	0x05	0x00
0x12	0x03	0x00	0x15	0x04	0x84	0x2D	0x98
0xC6	0x20	0x43	0x24	0x84	0x2D	0x98	0x19
0x60							

Table	10:	Sample	Font File	÷
-------	-----	--------	-----------	---

Red = **Header** 

Blue = **Character Table** 

Purple = Character Data

#### **Uploading a Font File** 5.2

Syntax	Hexadecimal	0xFE 0x24 [refID] [size] [data]		
	Decimal	254 36 [refID]	[size] [data]	
	ASCII	254 "\$" [refID	] [size] [data]	
Parameters	Parameter	Length	Description	
	refID	1	A unique font identification	
			number.	
	size	2	Font file size (LSB to MSB).	
	data	Х	Font file data.	
Description	In order to uploa	ad a font to the C	GLT24064 you must first initiate the	
	upload font file	command (0xFE	E 0x24), you must then pass it a	
	reference identif	fication number,	which must be unique for every font on	
	the display mody	ule. You may the	en pass the display module the two byte	
	file size, which r	needs to be trans	fered LSB, then MSB. The last part of	
	uploading a font	t is transmitting	the font file data.	
	For detailed inst	ructions on uplo	ading a file to the GLT24064 see	
	Section 11 on pe	age 43.	-	
	-	-		

**NOTE** This command is available but not supported in  $I^2C$ .

Remembered Always

### 5.3 Setting the Current Font

Syntax	Hexadecimal	0xFE 0x31 [refID]
-	Decimal	254 49 [refID]
	ASCII	254 "1" [refID]

Parameters	Parameter	Length	Description			
	refID	1	A unique font identification			
			number.			
Description	In order to set the for identification numb established when the fonts are "Small Fill 0x01 and 0x02 resp selected font. Once you are award simply send the con corresponding to the entire filesystem ma	ont on the GL' ber of the font the font is saved led" and "Fut bectfully, with the of the font II mmand bytes ( the font. A direct and be obtained	T24064 you must know the font that you wish to use. The font ID is d to the display. The default installed ura Bk BT 16" and their font ID's are "Small Filled" being the default O for the font that you wish you use, (0xFE 0x31) and then send the font ID ctory listing of the contents of the l by using the "Get Filesystem			
	Directory" command, see Section 11.5 on page 48 for more detailed					
	information.					
Remembered	Yes					

5.4 Font Metrics

Syntax	Hexadecimal	0xFE 0x32 [ln	1] [tm] [csp] [lsp] [srow]	
-	Decimal	254 50 [lm] [tm] [csp] [lsp] [srow]		
	ASCII	254 "2" [lm] [t	tm] [csp] [lsp] [srow]	
Parameters	Parameter	Length	Description	
	lm	1	Left margin: Location in pixels.	
	tm	1	Top margin: Location in pixels.	
	csp	1	Character Spacing: Amount of	
			space in pixels between characters.	
	lsp	1	Line Spacing: Amount of space	
			between lines in pixels.	
	srow	1	Scroll Row: The Y location of the	
			last row in pixels.	
Description	Font metrics def	fine where the ch	naracters are positioned on the screen,	
	by setting where the rows and columns begin based on the			
	[lm][tm][csp][lsp][srow] parameters. [lm] defines the leftmost position			
	and [tm] the top	most. [csp] cont	rols the amount of pixels that are placed	
	in between char	acters and [lsp]	controls the amount of pixels that are	
	placed in betwee	en lines. [srow]	is the location of the top of the last row	
	that will be disp	layed on the GL	T24064. It defines the row that, when	
	filled, will cause	e the display to a	uto scroll if auto scrolling is enabled.	
	The font metrics	s will have to be	reconfigured after changing to a	
	different font.			
Damaanahamad	Vee			
Keinembered	res			

#### 5.5 Set Box Space Mode

Syntax	Hexadecimal	0xFE 0xAC [va	lue]
-	Decimal	254 172 [value]	
Parameters	Parameter	Length	Description
	value	1	Value (0: Off, 1: On)
Description	This command when a box, the display before a	will toggle the bo size of the charac character is writt	x space mode. Box space mode is cter to be written, is printed to the en.
Remembered Default	Yes On		

#### 6 Text

#### 6.1 Introduction

The GLT24064 is an intelligent display module, designed to reduce the amount of code necessary to begin displaying data. This means that it is able to display all ASCII formated characters and strings that are sent to it, which are defined in the current character set. The display module will begin displaying text at the top left corner of the display area, known as home, and continue to print to the display as if it was a page on a typewriter. When the text reaches the bottom right row, it is able to automatically scroll all of the lines up and continue to display text, with the auto scroll option set to on.

#### 6.1.1 Character Set

The graphic displays such as the GLT24064, do not have built in character sets. Instead fonts are uploaded to the display using the commands detailed in Section 5 on page 22.

#### 6.1.2 Control Characters

In addition to a full text set, the GLT24064 display supports the following ASCII Control characters:

**0x0A** Line feed / New line - when this value is not defined in the font file. This command will create a new line on the display. If scrolling is on and the display is at the bottom of the screen, the whole screen is scrolled up.

#### 6.2 Move Cursor Home

Syntax	Hexadecimal	0xFE 0x48
	Decimal	254 72
	ASCII	254 "H"
Description	This command i display area (Ro	moves the text insertion point to the top left of the tow 1, Column 1).
Remembered	No	

### 6.3 Setting the Cursor Position

Syntax	Hexadecimal	0xFE 0x47 [c	ol] [row]
	Decimal	254 71 [col] [	row]
	ASCII	254 "G" [col]	[row]
Parameters	Parameter	Length	Description
	col	1	Column
	row	1	Row
Description	This command s	sets the text ins	ertion point to the [col] and [row]
	specified. The ir	nsertion point is	s positioned using the base size of the
	current font (this command does not position the insertion point at a		
	specific pixel).	The column use	ed is determined by multiplying the width
	of the widest cha	aracter in the fo	ont by the [column]. The row used is
	determined by n	nultiplying the	height of the font by [row + Metrics: line
	spacing].		
Pamambarad	No		
Remembered	110		

6.4 Setting the Cursor Coordinate

Syntax	Hexadecimal	0xFE 0x79 [x] [	y]
	Decimal	254 121 [x] [y]	
	ASCII	254 "y" [x] [y]	
Parameters	Parameter	Length	Description
	Х	1	The horizontal position in pixels.
	у	1	The vertical position in pixels.
Description	This command p	ositions the inser	tion point at a specific pixel (X,Y),
	which references	s the top left corn	er of the font insertion point.

Remembered No

#### 6.5 Auto Scroll On

Syntax	Hexadecimal Decimal ASCII	0xFE 0x51 254 81 254 "Q"
Description	When auto scrol display's conten reaches the end right character p	lling is on, it causes the display to shift the entire tts up to make room for a new line of text when the text of the scroll row defined in the font metrics (the bottom position) see <i>Section 5.4 on page 25</i> .
Remembered	Yes	
Default	On	

#### 6.6 Auto Scroll Off

Syntax	Hexadecimal	0xFE 0x52		
•	Decimal	254 82		
	ASCII	254 "R"		
Description	When auto scrol	ling is disabled, text will wrap to the top left corner of		
	the display area	when the text reaches the end of the scroll row defined		
	in the font metrics (the bottom right character position) see <i>Section 5.4 on page 25</i> . Existing text in the display area is not erased before new			
	text is placed. A series of spaces followed by a "Cursor Home"			
	command may b	be used to erase the top line of text.		

Remembered Yes

# 7 Bitmaps

#### 7.1 Introduction

One of the main features of the GLT24064 is its ability to display bitmap images, that are either loaded onto its on board memory, or written directly to the screen. This chapter will cover creating a bitmap, uploading the bitmap, as well as drawing the bitmap from memory and directly.

#### 7.2 Uploading a Bitmap File

Syntax	Hexadecimal	0xFE 0x5E [refID] [size] [data]
	Decimal	254 94 [refID] [size] [data]
	ASCII	254 "^" [refID] [size] [data]

Parameter	Length	Description	
refID	1	A unique bitmap identification	
		number.	
size	2	Bitmap file size (LSB to MSB).	
data	Х	Bitmap data.	
The GLT24064 i	s capable of sto	oring 128 font and bitmap files up to 16	
Kbytes total. In order to upload a bitmap to the GLT24064 you must			
first initiate the upload font file command (0xFE 0x5E), you must then			
pass it a reference identification number, which must be unique for			
every font on the display module. You may then pass the display			
module the two byte file system size, which needs to be transfered LSB,			
then MSB. This is almost always the entire 16kB, meaning the values			
0x00 0x40 0x00 0x00 must be issued. The last part of uploading a			
bitmap is transmitting the bitmap file data.			
For detailed instructions on uploading a file to the GLT24064 see			
Section 11 on page 43.			
1	0		
	refID size data The GLT24064 i Kbytes total. In o first initiate the u pass it a reference every font on the module the two b then MSB. This 0x00 0x40 0x00 bitmap is transm For detailed instr <i>Section 11 on pa</i>	ParameterLengthrefID1size2dataxThe GLT24064 is capable of stoKbytes total. In order to uploadfirst initiate the upload font filepass it a reference identificationevery font on the display modulmodule the two byte file systemthen MSB. This is almost alway0x00 0x40 0x00 0x00 must be ibitmap is transmitting the bitmaFor detailed instructions on upleSection 11 on page 43.	

 $\label{eq:NOTE} \textbf{NOTE} \quad \text{This command is available but not not supported in } I^2C.$ 

Remembered

# 7.3 Drawing a Bitmap from Memory

Always

Syntax	Hexadecimal	0xFE 0x62 [ref	TD] [X] [Y]
	Decimal	254 98 [refID]	[X] [Y]
	ASCII	254 "b" [refID]	[X] [Y]
Parameters	Parameter	Length	Description
	refID	1	The bitmap identification number.
	Х	1	Left bounds.
	Y	1	Top bounds.
Description	This command w	vill draw a bitma	p that is located in the on board
	memory. The bit	tmap is reference	ed by the bitmaps reference
	identification number, which is established when the bitmap is uploaded to the display module. The bitmap will be drawn beginning at the top		
	left, from the spe	ecified X,Y coor	dinates. A directory listing of the
	contents of the e	ntire filesystem	may be obtained by using the "Get
	Filesystem Direct	ctory" command	, see Section 11.5 on page 48 for more
	detailed informa	tion.	
Remembered	No		

#### 7.4 Drawing a Bitmap Directly

Syntax	Hexadecimal	0xFE 0x64 [X] [	[Y] [W] [H] [D]		
	Decimal	254 100 [X] [Y]	[W] [H] [D]		
	ASCII	254 "d" [X] [Y]	[W] [H] [D]		
Parameters	Parameter	Length	Description		
	Х	1	Left bounds.		
	Y	1	Top bounds.		
	W	1	Width		
	Н	1	Height		
	D	(width*height)/	8Data		
Description	Drawing a bitma	p to the GLT2406	54, without first uploading the image		
	to the memory ca	an be a very usefu	al feature for drawing images that are		
	not used very off	en. In order to ac	complish this, you must supply the		
	display module with the X,Y coordinates, representing the top left				
	corner of where you would like to draw the bitmap on the screen, as well as the width and the height of the bitmap. After you have supplied this data you may then upload the bitmap data to the GLT24064. The length				
	of this file is the	bitmap width mu	ltiplied by height, divided by eight.		
	The bitmap data	is encoded into b	ytes horizontally and is transfered the		
	same as if you w	ere uploading a fi	ile, see Section 11 on page 43 for		
	more information	n about transferri	ng data to the display module.		

**NOTE** Drawing a bitmap directly to the display is supported by flow control. This command is available but not support in  $I^2C$  mode.

Remembered

### 8 Bar Graphs and Drawing

No

#### 8.1 Introduction

Supplementary to the ability of the GLT24064 to display bitmaps and fonts, the GLT24064 also allows for a robust 2D drawing environment. With the ability to draw by pixel, line or rectangle, as well as the ability to continue a line to form a polygon, we are certain that you will spend less time, developing and creating better looking projects. With the addition of custom bar and strip graphs, you are sure to find the right tools to make any graphical layout a success.

#### 8.2 Set Drawing Color

Syntax	Hexadecimal	0xFE 0x63 [cold	or]
-	Decimal	254 99 [color]	
	ASCII	254 "c" [color]	
Parameters	Parameter	Length	Description
	color	1	Drawing color (0: White, 1-255:
			Black).
Description	This command s	sets the drawing c	olor for subsequent graphic commands
	that do not have	the drawing color	r passed as a parameter. The parameter
	[color] is the val	ue of the color w	here white is 0 and black is 1-255.

Remembered No

### 8.3 Draw Pixel

Syntax	Hexadecimal	0xFE 0x70 [x]	[y]
-	Decimal	254 112 [x] [y]	
	ASCII	254 "p" [x] [y]	
Parameters	Parameter	Length	Description
	Х	1	X screen location.
	У	1	Y screen location.
Description	This command y	will draw a pixel	at (x,y) using the current drawing
	color. The unit p	processes these re	equests fast enough to keep up with a
	steady stream at	115 Kbps so flow	w control is not required.
Remembered	No		

# 8.4 Drawing a Line

Syntax	Hexadecimal	0xFE 0x6C [x	1] [y1] [x2] [y2]
-	Decimal	254 108 [x1]	[y1] [x2] [y2]
	ASCII	254 "l" [x1] [	y1] [x2] [y2]
Parameters	Parameter	Length	Description
	x1	1	Left bounds.
	y1	1	Top Bounds.
	x2	1	Right Bounds.
	y2	1	Bottom Bounds.
Description	This command y	will draw a line	from $(x1,y1)$ to $(x2,y2)$ using the current
	drawing color. I	Lines may be dr	awn from any part of the display to any
	other part. How	ever, it may be i	important to note that the line may
	interpolate diffe	rently right to le	eft, or left to right. This means that a line
	drawn in white f	from right to lef	t may not fully erase the same line
	drawn in black f	from left to righ	t.
Remembered	No		
		CL T2 (012)	
Matrix Orbital		GLT240128	

#### 8.5 Continue a Line

Syntax	Hexadecimal	0xFE 0x65 [x]	[y]
-	Decimal	254 101 [x] [y]	
	ASCII	254 "e" [x] [y]	
Parameters	Parameter	Length	Description
	Х	1	Left bounds.
	у	1	Top Bounds.
Description	This command	will draw a line w	with the current drawing color from the
	last line end (x2	,y2) to $(x,y)$ . This	s command uses the global drawing
	color.		
Remembered	No		

### 8.6 Draw a Rectangle

Syntax	Hexadecimal	0xFE 0x72 [co	lor] [x1] [y1] [x2] [y2]
	Decimal	254 114 [color	] [x1] [y1] [x2] [y2]
	ASCII	254 "r" [color]	[x1] [y1] [x2] [y2]
Parameters	Parameter	Length	Description
	color	1	Drawing color (0: White, 1-255:
			Black).
	x1	1	Left bounds.
	y1	1	Top Bounds.
	x2	1	Right Bounds.
	y2	1	Bottom Bounds.
Description	This command o	lraws a rectangu	lar box in the specified color (0: White,
	1: Black). The t	op left corner is	specified by $(x1,y1)$ and the bottom
	right corner by (	x2,y2).	
	-		

Remembered No

### 8.7 Drawing a Solid Rectangle

Syntax	Hexadecimal	0xFE 0x78 [color] [x1] [y1] [x2] [y2]
	Decimal	254 120 [color] [x1] [y1] [x2] [y2]
	ASCII	254 "x" [color] [x1] [y1] [x2] [y2]

Parameters	Parameter	Length	Description
	color	1	Drawing color (0: White, 1-255:
			Black).
	x1	1	Left bounds.
	y1	1	Top Bounds.
	x2	1	Right Bounds.
	y2	1	Bottom Bounds.
Description	This command dr	aws a solid re	ctangle in the specified color (0: White,
-	1: Black). The to	p left corner is	specified by $(x1,y1)$ and the bottom
	right corner by (x	2,y2). Since th	nis command involves considerable
	processing overhe	ead, we strong	ly recommend the use of flow control,
	particularly if the	command is t	o be repeated frequently.
	1		I I I I I I I I I I I I I I I I I I I
Remembered	No		

# 8.8 Initializing a Bar Graph

Syntax	Hexadecimal	0xFE 0x67 [refID] [type] [x1] [y1] [x2] [y2]	
	Decimal	254 103 [refID	] [type] [x1] [y1] [x2] [y2]
	ASCII	254 "g" [refID	] [type] [x1] [y1] [x2] [y2]
Parameters	Parameter	Length	Description
	refID	1	Reference number
	type	1	Type of bar graph.
	x1	1	Left bounds.
	y1	1	Top Bounds.
	x2	1	Right Bounds.
	y2	1	Bottom Bounds.

Description This command initializes a bar graph referred to by number [reference number] of type [type] with size from (x1,y1) (top left) to (x2,y2) (bottom right). A maximum of 16 bar graphs with reference numbers from 0 to 15 can be initialized as:

[type]	Direction	<b>Bar Start Point</b>
0	Vertical	Bottom
1	Horizontal	Left
2	Vertical	Тор
3	Horizontal	Right

The bar graphs may be located anywhere on the display, but if they overlap, they will not display properly.

It is important that [x1] is less than [x2], and [y1] is less than [y2]. This command doesn't actually draw the graph, it must be filled in using the Fill Bar Graph command. The unit saves time by only drawing that part of the bar graph which has changed from the last write, so the representation on the screen may not survive a screen clear or other corrupting action. A write of value zero, followed by new values will restore the proper look of the bar graph. No

Remembered

#### 8.9 Drawing a Bar Graph

Syntax	Hexadecimal Decimal	0xFE 0x69 [ref] 254 105 [ref] [v	[value] alue]
	ASCII	254 "i" [ref] [va	lue]
Parameters	Parameter	Length	Description
·	ref	1	Initialized bar graph reference
			number.
	value	1	The number of pixels to fill.
Description	Once the bar gra	ph has been initia	alized it can be filled in using this
	command. This	command sets the	e bar graph specified by the [ref]
	number to fill in	[value]. [value] i	s given in pixels and should not
	exceed the availa	able height/width	of the graph. (If it does the graph will
	simply be writte	n to its maximum	n size.)

Remembered No

#### 8.10 Initializing a Strip Chart

Syntax	Hexadecimal	0xFE 0x6A [refID] [x1] [y1] [x2] [y2]
	Decimal	254 106 [refID] [x1] [y1] [x2] [y2]
	ASCII	254 "j" [refID] [x1] [y1] [x2] [y2]

Parameters	Parameter	Length	Description
	refID	1	Reference number
	x1	1	Left bounds.
	y1	1	Top Bounds.
	x2	1	Right Bounds.
	y2	1	Bottom Bounds.
Description	A strip chart is a This is normally	n area of the sc used as follow	ereen reserved for horizontal scrolling. s:
	<ul> <li>Initialize to screen.</li> <li>Draw a lint</li> <li>Shift the site of the site of</li></ul>	he strip chart, we he segment at the trip chart to the next line segme way the strip cl horizontally in ce a marquis ef extrip chart is us acter set, with e	which reserves the appropriate area of the ne right or left side of the strip chart. e right or left. ent. hart can produce a graph which scrolls either direction. With text the strip chart fect. ed with text we recommend the use of a 6 or 7 pixel wide each character placed 8 pixels from the start of the previous
	Up to 7 strip cha chart the user mu strip chart.(x1,y [x1] is the place [y1] is the row. 7 column of the ar	arts ( $[ref] = 0 - 0$ ust define an ar 1) is the top left ment of the column The user must t rea to be utilized	6) may be defined. To initialize a strip ea on the display in which to place the t corner of the area to be used, where umn where the strip chart is to begin and hen define [x2] as the bottom right d and [y2] as the bottom right row.
	<b>NOTE</b> The de 0x00, 0x08, 0x1	efinition of x m 0, etc. This rest	nust lie on byte boundaries. That is, x must be defined as triction does not apply to y values.
Remembered	No		
11 Shifting	a Strip Char	t	

#### 8.1 a Strip g

Syntax	Hexadecimal	0xFE 0x6B [ref]	
-	Decimal	254 107 [ref]	
	ASCII	254 "k" [ref]	
Parameters	Parameter	Length	Description
-	ref	1	Reference number of a strip chart
			that has already been created.

Description This command shifts the strip chart left or right. [ref] determines both which strip chart is used and which direction it will shift. The direction is selected by the most significant bit (MSB):

- MSB: 0 shifts left
- MSB: 1 shifts right

For example if [ref] is 1:

- 254 107 1 (hex FE 6B 01) shifts left
- 254 107 129 (hex FE 6B 81) shifts right

This command shifts the contents of the area defined in the Initialize Strip Chart command 8 pixels at a time.

Remembered No

# 9 Touchpad

#### 9.1 Introduction

The Matrix Orbital touch pad interface replaces, and in many ways, supercedes the keypad input interface. It adds the functionality of a dynamically adjustable, software controlled keypad. This feature will add an updated touch to your application system.

#### 9.1.1 Region Mode

This mode will report touch events when they occur in one of thirty-two specified areas or issue a special byte when a press occurs outside any defined region. Depending on the region reporting mode selected, either the down, up, or over characters specified for a region will be transmitted when the area defined is pressed, released, or dragged over respectively. Return values are specified when a region is created, in addition to its position and size. These regions can be deleted either individually or collectively when they are no longer required.

#### 9.1.2 Co-ordinate Mode

This mode will report all touch events in any position on the screen. Each event will be superceded by a single byte value representing a press, release, or drag. Press events will be predeced by a 1, release movements by a 2, and drag moves will return a value 4. Afterwhich, two single byte values representing the x and y co-ordinates of the touch event will be transmitted. Only drag movements greater than the drag threshold specified will be sent to the host.

### 9.2 Set Touch Region

Syntax	Hexadecimal	0xFE 0x84 [n	um] [x] [y] [w] [h] [keyDown] [keyUp]
	Decimal	254 132 [num	1] [x] [y] [w] [h] [keyDown] [keyUp]
Parameters	Parameter	Length	Description
	num	1	Region number, each region must
			be identified by a unique number,
			single byte (32 region max).
	Х	1	X co-ordinate of the top left corner
			of the region, single byte (0-Xmax).
	У	1	Y co-ordinate of the top left corner
			of the region, single byte (0-Ymax).
	W	1	Width of the region, single byte
			(0-Xmax).
	h	1	Height of the region, single byte
			(0-Ymax).
	keyDown	1	Value returned when region is
			pressed, single byte (0-255).
	keyUp	1	Value returned when region is
			released, single byte (0-255).
Description	This command	creates a touchp	ad region that reports the key down or
	key up values sa	wed to it when	a press or release respectively is detected
	within the regio	n defined.	
Remembered	Yes		

# 9.3 Delete Touch Region

Syntax	Hexadecimal	0xFE 0x85 [nur	n]
-	Decimal	254 133 [num]	
Parameters	Parameter	Length	Description
	num	1	Region number to be deleted, single
			byte.
Description	This command of preses will no lo deleted region.	deletes a previous onger be received All events in unde	ly created touchpad region, unique key from events in the area defined by the efined regions will return 255.
Remembered	Yes		

### 9.4 Delete All Touch Regions

Syntax	Hexadecimal	0xFE 0x86
	Decimal	254 134
Description	This command or recommended the	deletes all touch regions previously created. It is nat this command is issued before setting regions.
Remembered	Yes	

#### 9.5 Set Touch Mode

Syntax	Hexadecimal	0xFE 0x87 [mo	de]
	Decimal	254 135 [mode]	
Parameters	Parameter	Length	Description
	mode	1	Touch pad mode. Region mode is 0,
			Co-ordinate mode is 1.
Description	This commnad s returns up and d while Co-ordina coordinates.	sets the reporting lown values on pro ate mode reports e	mode for the touch pad. Region mode ess events within defined regions, very event on the touch pad with
Remembered	Yes		
Default	Co-ordinate Mo	de	

# 9.6 Set Region Reporting Mode

Syntax	Hexadecim	al 0xFE 0x88 [m	ode]
	Decimal	254 136 [mode	e]
Parameters	Parameter	Length	Description
	mode	1	Reporting mode for region press
			events.
Description	This comman	d sets the reporting	g mode for touch events in region mode.
	Defined key	up and key down	values will be sent only when certain
	reporting par	ameters are set.	
			-
	Bit Repo	rting Parameter	
	0	Press	
	1	Release	
	2	Drag	
	3 (	Out of Region	
	4-7	Reserved	]
	Key down v	alues are transmi	tted for press and drag events while
	key up value	s are sent on relea	ses. Any out of region touches will be
	reported with	0xFF.	

Remembered

Yes

Default Examples Report All

0x01	Key down values are sent on touch presses only
0x03	Key down and key up values are sent on presses and releases respectively
0x06	Key down values are reported on press and drag events
0x0F	Key down values are sent on presses and drags, key up values on releases, and 0xFF on out of

### 9.7 Set Dragging Threshold

Syntax	Hexadecimal	0xFE 0x89 [th	reshold]
	Decimal	254 137 [thres	hold]
Parameters	Parameter	Length	Description
	threshold	1	Touch pad dragging threshold,
			single byte value (1 to 255).
Description	This command s before a drag ev	specifies the dist ent is reported to	ance a press must be dragged moved of the host. The lower the threshold the
	more values sen	t to the host, wh	ile the higher the value the less precise
	the drag reporting may be. Distance is calculated as		
	$d = \sqrt{(x_2 - x_1)^2}$	$\frac{y_1}{(y_2 - y_1)^2}$ . C	Care should be taken to find the
	appropriate bala	nce between dat	ta points and accuracy.
Remembered	Yes		
Default	8		

# 9.8 Set Pressure Threshold

Syntax	Hexadecimal	0xFE 0x8A [th	reshold]
	Decimal	254 138 [thresh	nold]
Parameters	Parameter	Length	Description
	threshold	2	Touch pad pressure threshold, two
			byte value (1 to 65535).
Description	This command s	sets the presure re	equired to be placed upon the screen
	before a press ev	vent is recorded.	
Remembered	Ves		
Remembered	105		
Default	1000		

### 9.9 Run Touchpad Calibration

Syntax	Hexadecimal Decimal	0xFE 0x8B 254 139
Description	Decimal This command r number of point them. It can be u calibration is suc 0x15, to the host recommended th	254 139 runs a callibration of the touch pad by specifying a s on the screen and prompting the user to press within used to correct any errors noticed in touch pad events. If ccessful, the display will return two bytes, 0xFE and t, otherwise it will return 0xFE and 0x14 It is nat this command be used when environmental or user read to allow for correct operation
	factors are change	ged to anow for correct operation.

Remembered Always

# **10 Display Functions**

#### 10.1 Introduction

The GLT24064 employs software controlled display settings, which allow for control over, clearing the screen, changing the brightness and contrast or setting timers for turning it on or off. The combination of these allow you complete software control over your display's appearance.

#### 10.2 Clear Screen

Syntax	Hexadecimal	0xFE 0x58
-	Decimal	254 88
	ASCII	254 "X"
Description	This command of the top left posit	clears the display and resets the text insertion position to tion of the screen defined in the font metrics.
Remembered	No	

#### 10.3 Display On

Syntax	Hexadecimal	0xFE 0x42 [min	1]
•	Decimal	254 66 [min]	
	ASCII	254 "B" [min]	
Parameters	Parameter	Length	Description
	min	1	Minutes before turning the display
			on (0 to 90).

Description	This command turns the backlight on after the [minutes] timer has expired, with a ninety minute maximum timer. A time of 0 specifies that the backlight should turn on immediately and stay on. When this command is sent while the remember function is on, the timer will reset and begin after power up.
Remembered	Yes

Default	0

### 10.4 Display Off

Syntax	Hexadecimal	0xFE 0x46
	Decimal	254 70
	ASCII	254 "F"
Description	This command t remain off until	turns the backlight off immediately. The backlight will a 'Display On' command has been received.

Remembered Yes

### 10.5 Set Brightness

Syntax	Hexadecimal	0xFE 0x99 [b	rightness]
	Decimal	254 153 [brig]	htness]
Parameters	Parameter	Length	Description
	brightness	1	Display brightness setting (0 to
			255).
Description	This command s on, this comman	sets the display nd acts the same	[brightness]. If the remember function is as 'Set and Save Brightness'.
Remembered	Yes		
Default	255		

# 10.6 Set and Save Brightness

Syntax	Hexadecimal	0xFE 0x98 [brightness]	
-	Decimal	254 152 [bright	mess]
Parameters	Parameter	Length	Description
	brightness	1	Backlight setting (0 to 255).
Description	This command s	ets and saves the	display [brightness] as default.
Remembered	Always		

#### 10.7 Set Contrast

Syntax	Hexadecimal	0xFE 0x50 [co	ontrast]
-	Decimal	254 80 [contra	st]
	ASCII	254 "P" [conti	ast]
Parameters	Parameter	Length	Description
	contrast	1	Contrast value (0 to 255).
Description	This command s	sets the display's	s contrast to [contrast], where [contrast]
	is a value betwe	en 0x00 and 0x1	F (between 0 to 255). Lower values $F$
	cause 'on' eleme	ents in the displa	ay area to appear lighter, while higher
	values cause 'or	i' elements to ap	pear darker. Lighting and temperature
	conditions will a	affect the actual	value used for optimal viewing.
	Individual displa	ay modules will	also differ slightly from each other in
	appearance. In a	ddition, values	for optimal viewing while the display
	backlight is on r	nay differ from	values used when backlight is off.
	This command of	does not save the	e [contrast] value, and is lost after power
	down; but this c	ommand has the	option of remembering the settings
	when issued wit	h the Remembe	function 'on'. When this is the case,
	this command is	the same as the	Set and Save Contrast command.
	<b>NOTE</b> This c	ommand has or	ly 32 levels for X-Board based displays, meaning eight
	contrast settings	will have the sa	me single effect. Efectively, values 0 through 7, 8 through
	15, and so on wi	ill result in the s	ame setting.

RememberedYesDefault128

#### 10.8 Set and Save Contrast

Syntax	Hexadecimal	0xFE 0x91 [contrast]	
-	Decimal	254 145 [contra	ast]
Parameters	Parameter	Length	Description
	contrast	1	Contrast value (0 to 255).

Description This command sets the display's contrast to [contrast], where [contrast] is a value between 0x00 and 0xFF (between 0 to 255). Lower values cause 'on' elements in the display area to appear lighter, while higher values cause 'on' elements to appear darker. Lighting conditions will affect the actual value used for optimal viewing. Individual display modules will also differ slightly from each other in appearance. In addition, values for optimal viewing while the display backlight is on may differ from values used when backlight is off.

**NOTE** This command saves the [contrast] value so that it is not lost after power down.

Remembered Yes Default 128

### 11 Filesystem

#### 11.1 Introduction

The GLT24064 incorporates a 16 Kbyte on board flash memory in order to allow up to 128 font and bitmap files to be transfered directly onto the display and recalled whenever necessary. The filesystem can address font and bitmap files combined up to 16 Kbytes. It is recommended that fonts and bitmaps are uploaded when possible all together after a filesystem wipe ro preserve memory integrity. These fonts and bitmaps can then be locked to ensure they remain intact. This section covers uploading, downloading, deleting and moving files, as well as getting the remaining space or wiping the filesystem.

#### 11.1.1 File Upload Protocol

In order to allow fonts and bitmaps to be uploaded to the on board flash memory Matrix Orbital has developed a simple protocol that supports RS-232/TTL or I<sup>2</sup>C communications. In order to begin a file transmission the first step will be to provide the display module with the appropriate command bytes, meaning the command prefix, 0xFE, followed by the command number, 0x24 for a font file, or 0x5E for a bitmap file. This will begin the file transfer sequence. The next step will be to request a reference identification number (ref ID) which will allow you to identify the file for future use. Reference ID numbers can be any byte between 0x00 and 0x7F, however each ID must be unique.

The next part of uploading a font file is to provide the display module with the two byte file size of the data that you wish to transfer, LSB to MSB. The LSB must be transmitted first followed by the MSB. After receiving the MSB the display module will send a confirm byte, 0x01, if the file fits and continue, or decline byte, 0x08, and terminate the session.

Byte	Description
0x01	Confirm: Will continue the file transfer.
0x08	Decline: Terminate the session.

Matrix Orbital

Host	Display	Comments
0xFE		Command Prefix
0x24		Upload Font File Command
0x01		Reference ID
0x19		Size (LSB)
0x00		Size (MSB)
	0x01	Confirmation Byte
0x01		Confimation Byte
0x05		Font Width
	0x05	Echo Font Width
0x01		Confimation Byte
0x07		Font Height
	0x07	Echo Font Height
0x01		Confimation Byte
0x49		Font ASCII Start Value
	0x49	Echo Font ASCII Start Value
0x01		Confimation Byte
0x60		Last Font File Byte
	0x60	Echo Last Font File Byte
0x01		Confirm Upload Finished

Table 48: Upload Protocol

The last part of uploading a font file is to upload the file data. After transmitting each byte of the file the module will echo the byte and wait for a confirmation byte of 0x01 until the file has completed uploading. Below is an example of uploading the font file which we created in *Section 5.1.2 on page 22*.

At times that the display or the host sees anything else other than 0x01 for confirmation (usually a 0x08) the upload is aborted.

#### NOTES

- The GLT24064 has watch dog timer, set to 2.1 seconds in between transmissions, in order prevent the display module from staying in a waiting state.
- Once the timeout has been reached the timer will reset the display and issue a 0xFE 0xD4 response to the host to signal that this has happened.

Matrix Orbital

#### 11.1.2 XModem Upload Protocol

In addition to its original simple upload format, Matrix Orbital has added an XModem based protocol. This facilitates much faster download speeds by increasing the packet size from 1 byte to 128 bytes greatly increasing throughput. A two byte CRC check is preformed at the end of each packet in place of the byte echo system seen in the original protocol. However, the overall protocol remains much the same as the original, but much faster.

To begin the upload, a series of command bytes are sent, much like the original protocol. However, no distinction is made between bitmap and font as the XModem protocol is used to upload bin or ebin files that contain all the bitmaps and fonts required for the unit. Once the command bytes are sent, the size of the file is sent in two bytes, least signifcant byte first. Then two additional bytes are sent of the value zero.

At this point the display will respond with an ACK if the file fits, or a NAK otherwise. Please note that these values are different than those of the orignal protocol as seen in the table below. If a NAK is seen at any point by the host, the upload is to be aborted in the same fashion as the regular protocol.

If the file will fit, the start of header byte will be sent by the host, follwed by a block count representing the number of 128 byte blocks remaing to upload in regular and inverted forms. The display will then check to make sure the block count value matches its own before ACKing. The host can then send a 128 byte block of data followed by that blocks high and low CRC16 bytes. The display then preforms a CRC check on the data receive and ACKs if it matches that which was sent. Transfer continues with a block count and continues in this way until the end of file is reached.

Once the end of the upload file is reached, the host should transmit a single end of transmission byte. If the end of file is expected, the display will ACK one last time. This EOT byte along with the other special characters mentioned above is listed in the table below.

Character	Byte	Description
ACK	0x06	Acknowledged; successful data transmission
NAK	0x21	Not Acknowledged; transmission unsuccessful, abort upload
SOH	0x01	Start of Header; begin upload process
EOT	0x04	End of Transmission; file upload complete

Below is an example of uploading a bin or ebin file using the XModem protocol.

#### 11.2 Wipe Filesystem

Syntax	Hexadecimal	0xFE 0x21 0x59 0x21
	Decimal	254 33 89 33
	ASCII	254 "!" "Y" "!"

Description	This command completely erases the display's non-volatile memory. It removes all fonts, font metrics, bitmaps, and settings (current font, cursor position, communication speed, etc.). It is an "odd" command in that it is three bytes in length in order to prevent accidental execution.
	<b>NOTE</b> After deleting the file system it is important to cycle power to your display to ensure the removal process is completed.
Remembered	Yes

# 11.3 Deleting a File

Syntax	Hexadecimal	0xFE 0xAD [type] [refID]		
	Decimal	254 173 [type]	[refID]	
Parameters	Parameter	Length	Description	
	type	1	Type of file (0:Font, 1:Bitmap)	
	refID	1	Reference ID of the file to delete.	
Description	This command erases a single file at a time within the GLT24064			
	memory when given two parameters: [type] and [refID]. The file type and reference number are defined when the file is saved to the			
	GLT24064.	24064.		
	$\left[ typo \right] = 1$	Ritmon		
	• $[type] = 1$ . • $[type] = 0$ :	Font		
	$\bullet$ [type] = 0.	TOIL		

**NOTE** After deleting a file it is important to cycle power to your display to ensure file system integrity.

Remembered

### 11.4 Get Filesystem Space

Yes

Syntax	Hexadecimal	0xFE 0xAF
	Decimal	254 175
Description	This command w remaining in the	will return 4 bytes, LSB to MSB for how many bytes are a 16 KB on board memory.
Remembered	No	

Host	Display	Comments
0xFE		Command Prefix
0xDB		XModem Upload Command
0x85		Command byte 1
0x06		Command byte 2
0x30		Command byte 3
0x00		Size Low Byte
0x40		Size High Byte
0x00		0
0x00		0
	0x06	ACK (NAK if file is too big)
0x01		Start of Header
0x80		Block Count
0x7F		255 - Block Count
	0x06	ACK (NAK if counts don't match)
<128 bytes>		Data Block
0x1E		CRC High Byte
0x47		CRC Low Byte
	0x06	ACK (NAK if CRCs don't match)
0x7F		Block Count
0x80		255 - Block Count
	0x06	ACK (NAKif counts don't match)
<128 bytes>		Data Block
0x5A		CRC High Byte
0x0D		CRC Low Byte
	0x06	ACK (NAKif CRCs don't match)
0x04		End of Transmission
	0x06	ACK (NAK if EOT is not expected)

Table 49: XModem Upload Protocol

#### 11.5 Get Filesystem Directory

Syntax

Hexadecimal 0xFE 0xB3 Decimal 254 179

Description

This command will return a directory of the contents of the file system. The first byte returned will be a hex value representing the number of entries in the filesystem, followed by four bytes for each entry. See the following tables:

	Filesystem Header
Bytes	Description
1	Hex value representing the number
	of entries in the filesystem
	File Entry
Bytes	Description
1	Flag: Hex value of 0x00 indicates
	that this file entry has not been used.
1	FileID/Type: 1st bit is the file type
	(0: Font, 1: Bitmap). Next 7 bits are
	the file ID.
1	File Size: LSB
1	File Size: MSB
No	

Remembered

### 11.6 Filesystem Upload

Syntax	Hexadecimal	0xFE 0xB0 [Siz	ze] [Data]
-	Decimal	254 176 [Size]	[Data]
Parameters	Parameter	Length	Description
	Size	4	LSB to MSB filesystem image data
	Data	var	Actual data to upload
Description	This command w display (16KB). meaning the valu the filesystem da	vill upload a files The size used is tes 0x00 0x40 0x ta can be upload	system image, LSB to MSB to the almost always the entire 16kB, a00 0x00 must be issued. Afterwhich ed LSB to MSB in the same manner as
	a font or bitmap	file.	

Remembered Always

#### 11.7 Downloading a File

Syntax	Hexadecimal	0xFE 0xB2 [7	[ype] [refID]
-	Decimal	254 178 [Туре	e] [refID]
Parameters	Parameter	Length	Description
	Туре	1	File type (0:Font File, 1:Bitmap)
	refID	1	Reference ID number
Description	Download a spe the length of the width and heigh	cified file from file (LSB to M t of the image th	the filesystem. The first 4 bytes will be SB) followed by 2 bytes representing the hen the data contained in the file.
Remembered	No		

#### 11.8 Moving a File

Syntax	Hexadecimal	0xFE 0xB4 [oldT] [oldID] [newT] [newID]		
	Decimal	254 180 [oldT	] [oldID] [newT] [newID]	
Parameters	Parameter	Length	Description	
	oldT	1	Old file type	
	oldID	1	Old file ID	
	newT	1	New file type	
	newID	1	New file ID	
Description	This command c	an be used to m	nove a file to a new file ID, or correct the	
	type of a file that	t was uploaded	incorrectly. The command first checks	
	to see if there is	a file identified	by [oldT] and [oldID]. If it does exist,	
	and there is no fi	le already with	the desired type and ID, the ID and type	
	of the old file wi	ll be changed to	[newT] and [newID] respectively.	
Remembered	Always			

# 12 Data Security

#### 12.1 Introduction

Ensuring that your GLT24064 display's exactly what you want it to can be the difference between a projects success and failure. This is why we incorporate features such as Data Lock into the GLT24064 With this new feature you now are in control over of how and when settings will be changed so there is no need to worry about the module acting exactly like you expected it to because all the settings may be locked and remembered for the next power up.

#### 12.2 Set Remember

Syntax	Hexadecimal	0xFE 0x93 [s	witch]	
-	Decimal	254 147 [swi	ch]	
Parameters	Parameter	Length	Description	
	switch	1	0: Do not remember, 1: Rem	lember
Description	This command	allows you to s	vitch the remember function on	and off.
	To use the reme	mber function,	set remember to on, then set all	of the
	settings that you	u wish to save, s	ettings that are listed as 'Remer	nber:
	Yes' support be	ing saved into t	ne non-volatile memory. After y	ou have
	set all of the con	nmands that ye	u wish to save, you may then cy	cle the
	power and chec	k the display se	ttings to ensure that all the settir	igs have
	been saved. If y	ou wish to use	remember again after cycling the	e power,
	you must set it	o on again.		
	NOTES			
	• Writing to	o non-volatile n	nemory is time consuming and s	lows down the operation of
	the displa	v		ie we de wit die operation of
	<ul> <li>Non-vola 100,000 t</li> </ul>	tile memory ha	s a 'write limit' and may only	be changed approximately
Remembered	No			
Default	Do not rememb	or		
Default	Do not rememb	CI		
12.3 Data Lo	ock			

# SyntaxHexadecimal0xFE 0xCA 0xF5 0xA0 [level]Decimal254 202 245 160 [level]

	Decimal	254 202 245 16	0 [level]
Parameters	Parameter	Length	Description
	level	1	Sets the data lock level

#### Description

Paranoia allows you to lock the module from displaying information, as well as enables the protection of the filesystem and module settings. Each bit corresponds corresponds to a different lock level, while sending a zero will unlock your display as the following tables explains:

Bit	Data Lock Level	Description
0-2	Reserved	Should be left 0
3	Communication	When this bit is set (1) the
	Speed Lock	Baud Rate and I <sup>2</sup> C Slave
		address are locked
4	Setting Lock	When this bit is set (1)
		the display settings such
		as backlight, contrast and
		GPO settings are locked.
		(Internal EEPROM)
5	Filesystem Lock	When this bit is set (1)
		the external EEPROM is
		locked, this has the same
		effect as the File System
		Jumper
6	Command Lock	When this bit is set (1) all
		commands but commands
		202/203 are locked. (cmd
		lock)
7	Display Lock	When this bit is set (1) the
		module is locked from dis-
		playing any new informa-
		tion. (text lock)

#### NOTES

- Sending a new data lock level will override the previous data lock level.
- Data lock levels may be combined.

Remembered	Always	
Default	0	
Examples		
	TT	D

Hex	Dec	Binary	Description
0x00	0	0	Unlock
0x50	80	01010000	Setting and Command Lock

#### 12.4 Set and Save Data Lock

Syntax	Hexadecimal	0xFE 0xCB 0xF5 0xA0 [level]	
-	Decimal	254 203 245 1	60 [level]
Parameters	Parameter	Length	Description
	level	1	Sets the data lock level
Description	This command v section for more	will set and save information.	the data lock level. See the Data Lock
Remembered	Always		
Default	0		

### 12.5 Dump the Filesystem

Syntax	Hexadecimal	0xFE 0x30
-	Decimal	254 48
	ASCII	254 "0"
Description	This will allow y will return a 4 b up the file system	you to dump the filesystem for debugging purposes. It yte value LSB to MSB followed by 16384 bytes making m.

Remembered No

#### 12.6 Write Customer Data

Syntax	Hexadecimal	0xFE 0x34 [data	a]
	Decimal	254 52 [data]	
	ASCII	254 "4" [data]	
Parameters	Parameter	Length	Description
	data	16	Writes the customer data
Description	Writes the custor	mer Data. 16 Byt	es of data can be saved in non-volatile
	memory.		

Remembered No

#### 12.7 Read Customer Data

Syntax	Hexadecimal	0xFE 0x35
	Decimal	254 53
	ASCII	254 "5"

Description Reads whatever was written by Write Customer Data.

Remembered No

# 13 Miscellaneous

#### 13.1 Introduction

This chapter covers the 'Report Version Number' and 'Read Module Type' commands. These commands can be particularly useful to find out more information about the display module before contacting technical support.

#### 13.2 Read Version Number

Syntax	Hexadecimal	0xFE 0x36
-	Decimal	254 54
	ASCII	254 "6"
Description	This command was see the following	will return a byte representing the version of the module, g table as an example:

Hex Value	Version Number
0x19	Version 1.9
0x57	Version 5.7

Remembered No

#### 13.3 Read Module Type

Syntax	Hexadecimal	0xFE 0x37
	Decimal	254 55
	ASCII	254 "7"

Description This command will return a hex value corresponding to the model number of the module see the following table:

Hex	Product ID	Hex	Product ID
1	LCD0821	2	LCD2021
5	LCD2041	6	LCD4021
7	LCD4041	8	LK202-25
9	LK204-25	Α	LK404-55
В	VFD2021	С	VFD2041
D	VFD4021	Е	VK202-25
F	VK204-25	10	GLC12232
13	GLC24064	14	Unused
15	GLK24064-25	16	Unused
21	Unused	22	GLK12232-25
23	Unused	24	GLK12232-25-SM
25	GLK24064-16-1U-USB	26	GLK24064-16-1U
27	GLK19264-7T-1U-USB	28	GLK12232-16
29	GLK12232-16-SM	2A	GLK19264-7T-1U
2B	LK204-7T-1U	2C	LK204-7T-1U-USB
31	LK404-AT	32	MOS-AV-162A
33	LK402-12	34	LK162-12
35	LK204-25PC	36	LK202-24-USB
37	VK202-24-USB	38	LK204-24-USB
39	VK204-24-USB	3A	PK162-12
<b>3B</b>	VK162-12	<b>3</b> C	MOS-AP-162A
3D	PK202-25	3E	MOS-AL-162A
3F	MOS-AL-202A	40	MOS-AV-202A
41	MOS-AP-202A	42	PK202-24-USB
43	MOS-AL-082	44	MOS-AL-204
45	MOS-AV-204	46	MOS-AL-402
47	MOS-AV-402	48	LK082-12
49	VK402-12	<b>4</b> A	VK404-55
<b>4</b> B	LK402-25	4C	VK402-25
<b>4D</b>	PK204-25	<b>4</b> E	Unused
<b>4</b> F	MOS	50	MOI
51	XBoard-S	52	XBoard-I
53	MOU	54	XBoard-U
55	LK202-25-USB	56	VK202-25-USB
57	LK204-25-USB	58	VK204-25-USB
5 <b>B</b>	LK162-12-TC	5C	Unused
71	Unused	72	GLK240128-25
73	LK404-25	74	VK404-25
77	Unused	78	GLT320240
79	GLT480282	7A	GLT240128
No			

Remembered

# 14 Command Summary

### 14.1 Communications

Description	Syntax		Page
Turn Flow Control On	Hexadecimal	0xFE 0x3A [full] [empty]	18
	Decimal	254 58 [full] [empty]	
	ASCII	254 ":" [full] [empty]	
Turn Flow Control Off	Hexadecimal	0xFE 0x3B	19
	Decimal	254 59	
	ASCII	254 ";"	
Changing the I <sup>2</sup> C Slave	Hexadecimal	0xFE 0x33 [adr]	19
Address	Decimal	254 51 [adr]	
	ASCII	254 "3" [adr]	
Changing the Baud Rate	Hexadecimal	0xFE 0x39 [speed]	20
	Decimal	254 57 [speed]	
	ASCII	254 "9" [speed]	
Setting a Non-Standard	Hexadecimal	0xFE 0xA4 [speed]	21
Baud Rate	Decimal	254 164 [speed]	

### 14.2 Fonts

Description	Syntax		Page
Uploading a Font File	Hexadecimal	0xFE 0x24 [refID] [size] [data]	24
	Decimal	254 36 [refID] [size] [data]	
	ASCII	254 "\$" [refID] [size] [data]	
Setting the Current Font	Hexadecimal	0xFE 0x31 [refID]	24
	Decimal	254 49 [refID]	
	ASCII	254 "1" [refID]	
Font Metrics	Hexadecimal	0xFE 0x32 [lm] [tm] [csp] [lsp] [srow]	25
	Decimal	254 50 [lm] [tm] [csp] [lsp] [srow]	
	ASCII	254 "2" [lm] [tm] [csp] [lsp] [srow]	
Set Box Space Mode	Hexadecimal	0xFE 0xAC [value]	26
	Decimal	254 172 [value]	

### 14.3 Text

Description	Syntax		Page
Move Cursor Home	Hexadecimal	0xFE 0x48	26
	Decimal ASCII	254 72 254 "H"	

Description	Syntax		Page
Setting the Cursor	Hexadecimal	0xFE 0x47 [col] [row]	27
Position	Decimal	254 71 [col] [row]	
	ASCII	254 "G" [col] [row]	
Setting the Cursor	Hexadecimal	0xFE 0x79 [x] [y]	27
Coordinate	Decimal	254 121 [x] [y]	
	ASCII	254 "y" [x] [y]	
Auto Scroll On	Hexadecimal	0xFE 0x51	27
	Decimal	254 81	
	ASCII	254 "Q"	
Auto Scroll Off	Hexadecimal	0xFE 0x52	28
	Decimal	254 82	
	ASCII	254 "R"	

# 14.4 Bitmaps

Description	Syntax		Page
Uploading a Bitmap File	Hexadecimal	0xFE 0x5E [refID] [size] [data]	28
	Decimal	254 94 [refID] [size] [data]	
	ASCII	254 "^" [refID] [size] [data]	
Drawing a Bitmap from	Hexadecimal	0xFE 0x62 [refID] [X] [Y]	29
Memory	Decimal	254 98 [refID] [X] [Y]	
-	ASCII	254 "b" [refID] [X] [Y]	
Drawing a Bitmap	Hexadecimal	0xFE 0x64 [X] [Y] [W] [H] [D]	30
Directly	Decimal	254 100 [X] [Y] [W] [H] [D]	
-	ASCII	254 "d" [X] [Y] [W] [H] [D]	

# 14.5 Bar Graphs and Drawing

Description	Syntax		Page
Set Drawing Color	Hexadecimal	0xFE 0x63 [color]	30
	Decimal	254 99 [color]	
	ASCII	254 "c" [color]	
Draw Pixel	Hexadecimal	0xFE 0x70 [x] [y]	31
	Decimal	254 112 [x] [y]	
	ASCII	254 "p" [x] [y]	
Drawing a Line	Hexadecimal	0xFE 0x6C [x1] [y1] [x2] [y2]	31
	Decimal	254 108 [x1] [y1] [x2] [y2]	
	ASCII	254 "l" [x1] [y1] [x2] [y2]	
Continue a Line	Hexadecimal	0xFE 0x65 [x] [y]	32
	Decimal	254 101 [x] [y]	
	ASCII	254 "e" [x] [y]	

Description	Syntax		Page
Draw a Rectangle	Hexadecimal	0xFE 0x72 [color] [x1] [y1] [x2] [y2]	32
	Decimal	254 114 [color] [x1] [y1] [x2] [y2]	
	ASCII	254 "r" [color] [x1] [y1] [x2] [y2]	
Drawing a Solid	Hexadecimal	0xFE 0x78 [color] [x1] [y1] [x2] [y2]	32
Rectangle	Decimal	254 120 [color] [x1] [y1] [x2] [y2]	
	ASCII	254 "x" [color] [x1] [y1] [x2] [y2]	
Initializing a Bar Graph	Hexadecimal	0xFE 0x67 [refID] [type] [x1] [y1] [x2] [y2]	33
	Decimal	254 103 [refID] [type] [x1] [y1] [x2] [y2]	
	ASCII	254 "g" [refID] [type] [x1] [y1] [x2] [y2]	
Drawing a Bar Graph	Hexadecimal	0xFE 0x69 [ref] [value]	34
	Decimal	254 105 [ref] [value]	
	ASCII	254 "i" [ref] [value]	
Initializing a Strip Chart	Hexadecimal	0xFE 0x6A [refID] [x1] [y1] [x2] [y2]	34
	Decimal	254 106 [refID] [x1] [y1] [x2] [y2]	
	ASCII	254 "j" [refID] [x1] [y1] [x2] [y2]	
Shifting a Strip Chart	Hexadecimal	0xFE 0x6B [ref]	35
	Decimal	254 107 [ref]	
	ASCII	254 "k" [ref]	

# 14.6 Touchpad

Description	Syntax		Page
Set Touch Region	Hexadecimal	0xFE 0x84 [num] [x] [y] [w] [h] [keyDown	<u>1] [₿</u> øyUp]
-	Decimal	254 132 [num] [x] [y] [w] [h] [keyDown] [	keyUp]
Delete Touch Region	Hexadecimal	0xFE 0x85 [num]	37
-	Decimal	254 133 [num]	
Delete All Touch Regions	Hexadecimal	0xFE 0x86	37
-	Decimal	254 134	
Set Touch Mode	Hexadecimal	0xFE 0x87 [mode]	38
	Decimal	254 135 [mode]	
Set Region Reporting	Hexadecimal	0xFE 0x88 [mode]	38
Mode	Decimal	254 136 [mode]	
Set Dragging Threshold	Hexadecimal	0xFE 0x89 [threshold]	39
	Decimal	254 137 [threshold]	
Set Pressure Threshold	Hexadecimal	0xFE 0x8A [threshold]	39
	Decimal	254 138 [threshold]	
Run Touchpad	Hexadecimal	0xFE 0x8B	39
Calibration	Decimal	254 139	

# 14.7 Display Functions

Description	Syntax		Page
Clear Screen	Hexadecimal	0xFE 0x58	40
	Decimal	254 88	
	ASCII	254 "X"	
Display On	Hexadecimal	0xFE 0x42 [min]	40
	Decimal	254 66 [min]	
	ASCII	254 "B" [min]	
Display Off	Hexadecimal	0xFE 0x46	41
	Decimal	254 70	
	ASCII	254 "F"	
Set Brightness	Hexadecimal	0xFE 0x99 [brightness]	41
-	Decimal	254 153 [brightness]	
Set and Save Brightness	Hexadecimal	0xFE 0x98 [brightness]	41
	Decimal	254 152 [brightness]	
Set Contrast	Hexadecimal	0xFE 0x50 [contrast]	42
	Decimal	254 80 [contrast]	
	ASCII	254 "P" [contrast]	
Set and Save Contrast	Hexadecimal	0xFE 0x91 [contrast]	42
	Decimal	254 145 [contrast]	

# 14.8 Filesystem

Description	Syntax		Page
Wipe Filesystem	Hexadecimal	0xFE 0x21 0x59 0x21	45
	Decimal	254 33 89 33	
	ASCII	254 "!" "Y" "!"	
Deleting a File	Hexadecimal	0xFE 0xAD [type] [refID]	46
-	Decimal	254 173 [type] [refID]	
Get Filesystem Space	Hexadecimal	0xFE 0xAF	46
• •	Decimal	254 175	
Get Filesystem Directory	Hexadecimal	0xFE 0xB3	48
	Decimal	254 179	
Filesystem Upload	Hexadecimal	0xFE 0xB0 [Size] [Data]	48
• •	Decimal	254 176 [Size] [Data]	
Downloading a File	Hexadecimal	0xFE 0xB2 [Type] [refID]	48
	Decimal	254 178 [Type] [refID]	
Moving a File	Hexadecimal	0xFE 0xB4 [oldT] [oldID] [newT] [newID]	49
-	Decimal	254 180 [oldT] [oldID] [newT] [newID]	

# 14.9 Data Security

Description	Syntax		Page
Set Remember	Hexadecimal Decimal	0xFE 0x93 [switch] 254 147 [switch]	50

Description	Syntax		Page
Data Lock	Hexadecimal	0xFE 0xCA 0xF5 0xA0 [level]	50
	Decimal	254 202 245 160 [level]	
Set and Save Data Lock	Hexadecimal	0xFE 0xCB 0xF5 0xA0 [level]	52
	Decimal	254 203 245 160 [level]	
Dump the Filesystem	Hexadecimal	0xFE 0x30	52
1 V	Decimal	254 48	
	ASCII	254 "0"	
Write Customer Data	Hexadecimal	0xFE 0x34 [data]	52
	Decimal	254 52 [data]	
	ASCII	254 "4" [data]	
Read Customer Data	Hexadecimal	0xFE 0x35	52
	Decimal	254 53	
	ASCII	254 "5"	

# 14.10 Miscellaneous

Description	Syntax		Page
Read Version Number	Hexadecimal	0xFE 0x36	53
	Decimal	254 54	
	ASCII	254 "6"	
Read Module Type	Hexadecimal	0xFE 0x37	53
•••	Decimal	254 55	
	ASCII	254 "7"	

# 14.11 Command By Number

Comman	d Descrij	ption Page		
Hex	Dec	ASCII		
0x21	33	"!"	Wipe Filesystem	45
0x24	36	<b>''</b> \$''	Uploading a Font File	24
0x30	48	"0"	Dump the Filesystem	52
0x31	49	"1"	Setting the Current Font	24
0x32	50	"2"	Font Metrics	25
0x33	51	"3"	Changing the I <sup>2</sup> C Slave Address	19
0x34	52	"4"	Write Customer Data	52
0x35	53	"5"	Read Customer Data	52
0x36	54	"6"	Read Version Number	53
0x37	55	"7"	Read Module Type	53
0x39	57	"9"	Changing the Baud Rate	20
0x3A	58	·····	Turn Flow Control On	18
0x3B	59	····››	Turn Flow Control Off	19
0x42	66	"В"	Display On	40

Comman	d Descrip	tion Page		
Hex	Dec	ASCII		
0x46	70	"F"	Display Off	41
0x47	71	"G"	Setting the Cursor Position	27
0x48	72	"H"	Move Cursor Home	26
0x50	80	"P"	Set Contrast	42
0x51	81	"Q"	Auto Scroll On	27
0x52	82	"R"	Auto Scroll Off	28
0x58	88	"X"	Clear Screen	40
0x5E	94	···\››	Uploading a Bitmap File	28
0x62	98	"b"	Drawing a Bitmap from Memory	29
0x63	99	"c"	Set Drawing Color	30
0x64	100	"d"	Drawing a Bitmap Directly	30
0x65	101	"e"	Continue a Line	32
0x67	103	"g"	Initializing a Bar Graph	33
0x69	105	"i"	Drawing a Bar Graph	34
0x6A	106	"j"	Initializing a Strip Chart	34
0x6B	107	"k"	Shifting a Strip Chart	35
0x6C	108	··1''	Drawing a Line	31
0x70	112	"p"	Draw Pixel	31
0x72	114	"r"	Draw a Rectangle	32
0x78	120	"x"	Drawing a Solid Rectangle	32
0x79	121	"y"	Setting the Cursor Coordinate	27
0x84	132	-	Set Touch Region	37
0x85	133		Delete Touch Region	37
0x86	134		Delete All Touch Regions	37
0x87	135		Set Touch Mode	38
0x88	136		Set Region Reporting Mode	38
0x89	137		Set Dragging Threshold	39
0x8A	138		Set Pressure Threshold	39
0x8B	139		Run Touchpad Calibration	39
0x91	145		Set and Save Contrast	42
0x93	147		Set Remember	50
0x98	152		Set and Save Brightness	41
0x99	153		Set Brightness	41
0xA4	164		Setting a Non-Standard Baud Rate	21
0xAC	172		Set Box Space Mode	26
0xAD	173		Deleting a File	46
0xAF	175		Get Filesystem Space	46
0xB0	176		Filesystem Upload	48
0xB2	178		Downloading a File	48
0xB3	179		Get Filesystem Directory	48
0xB4	180		Moving a File	49

# 15 Appendix

### **15.1 Optical Characteristics**

ruore / or optical characteristics		
Pixel Layout (WxH)	240 x 128 pixels	
Display Area	107.95 x 57.55mm	
Dot Size	0.40 x 0.40mm	
Dot Pitch	0.45 x 0.45mm	
Viewing Angle (Vertical)	+35°/- 20° from Normal	
Viewing Angle (Horizontal)	+30°/- 30° from Normal	
LED Backlight Life(GW&WB)	10,000 hours typical	
LED Backlight Life(YG)	50,000 hours typical	
Backlight	white or yellow-green STN LED	

Table 76: Optical Characteristics

**NOTE** To prolong life, it is recommended that the backlight be turned off when the display is not in use.

### 15.2 Specifications

#### 15.2.1 Environmental

Table 77. Environmental Speemeations					
$0^{\circ}$ C to $+50^{\circ}$ C					
$-20^{\circ}$ C to $+70^{\circ}$ C					
60% max non-condensing					
4.9 m/s <sup>2</sup> XYZ directions					
19.6 m/s <sup>2</sup> XYZ directions					
29.4 m/s <sup>2</sup> XYZ directions					
490 m/s <sup>2</sup> XYZ directions					

Table 77: Environmental Specifications

Table 79: Touch Specifications
--------------------------------

<b>Required Operation Force</b>	10-100g
Tapping Durability	1,000,000 at 250g with 2mm diameter stylus
Sliding Durability	100,000 at 250g with 2mm diameter stylus

#### 15.2.2 Electrical

Table	78:	Electrical	S	pecifications
raore	70.	Licenieur		peemeutono

	Standard Wide Voltage (V) Wide Voltage with ESPS (V)			
Supply Voltage $+5$ Vdc $\pm 0.25$ V $+9$ V to $+15$ V		+9V to +35V		
Minimum Current	80mA typical			
Backlight ON (GW&WB)	add 90mA (170mA) typical			
Backlight ON (YG)	add 260mA (340mA) typical			



#### WARNINGS

- Do not apply any power with reversed polarization.Do not apply any voltage other than the specified voltage.

#### 15.2.3 Touch

## 15.3 Physical Layout



Figure 24: Physical Diagram

#### 15.4 Ordering Information

G	L	Т	240	128	-USB	-VPT	-YG
1	2	3	4	5	6	7	8

Table 80: Part Numbering Scheme

#	Description	Options			
1	Screen Type G: Graphic				
2	Display Technology L: Liquid Crystal Display				
3	Input Interface T: Touch Pad				
4	4 Width 240: pixel width count				
5	5 Height 128: pixel height count				
6	Communication Interface	NP: Standard RS232/TTL/I <sup>2</sup> C interface			
U		-USB: USB only interface			
	Input Voltage	NP: Standard voltage (4.75-5.25V)			
7		-V: Wide voltage (9.00-15.00V)			
		-VPT: Wide voltage with ESPS (9.00-35.00V)			
	Colour (Text/Background)	-YG: Grey/Yellow Green			
8		-GW: Grey/White			
		-WB: White/Blue			

Table 81: Part Options

#### 15.5 Definitions

**V** Wide Voltage (+9 to +15Vdc)

**VPT** Wide Voltage with Efficient Switching Power Supply (+9 to +35Vdc)

**GW** White Backlight (Grey text on White Background)

WB White Backlight (White text on Blue Background)

YG Yellow Green Backlight with Grey text

MSB Most Significant Byte

LSB Least Significant Byte

#### 15.6 Contacting Matrix Orbital

#### Telephone

Sales: 1(403)229-2737 Support: 1(403)204-3750

#### On The Web

Sales: http://www.MatrixOrbital.com Support: http://www.MatrixOrbital.ca Forums: http://www.lcdforums.com

### 15.7 Revision History

<b>Revision Number</b>	Description	Author
1.0	Initial Manual	Clark
1.1	Touch Specifications Added	Clark
1.2	Updated Backlight Life	Clark

Table 82: Revision History

# **Mouser Electronics**

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Matrix Orbital:

 GLT240128-USB
 GLT240128-USB-WB
 GLT240128-USB-FGW
 GLT240128-422
 GLT240128-422-FGW

 GLT240128-422-WB
 GLT240128-422-FGW-VPT
 GLT240128-422-VPT
 GLT240128-422-WB-VPT
 GLT240128-422-WB-VPT

 GLT240128-WB-VPT
 GLT240128-WB-VPT
 GLT240128-422-WB-VPT
 GLT240128-422-WB-VPT
 GLT240128-WB-VPT