Safety power system basis chip with CAN FD and LIN transceivers

Rev. 8 — 5 August 2024

Product data sheet



1 General description

The FS6500/FS4500 SMARTMOS devices are a multi-output, power supply, integrated circuit, including CAN Flexible Data (FD) and/or LIN transceivers, dedicated to the automotive market.

Multiple switching and linear voltage regulators, including low-power mode ($32 \mu A$) are available with various wake-up capabilities. An advanced power management scheme is implemented to maintain high efficiency over a wide range of input voltages (down to 2.7 V) and output current ranges (up to 2.2 A).

The FS6500/FS4500 includes configurable fail-safe/fail silent safety behavior and features, with two fail-safe outputs, becoming a full part of a safety oriented system partitioning, to reach a high integrity safety level (up to ASIL D).

The built-in CAN FD interface fulfills the ISO 11898-2⁽¹²⁾ and $-5^{(13)}$ standards. The LIN interface fulfills LIN protocol specifications 2.0, $2.1^{(22)}$, $2.2^{(23)}$, and SAE J2602-2⁽²⁴⁾.

High temperature capability up to T_A = 125 °C and T_J = 150 °C, compliant with AEC-Q100 Grade 1 automotive qualification.

2 Features and benefits

- Battery voltage sensing and MUX output pin
- Highly flexible SMPS pre-regulator, allowing two topologies: non-inverting buck-boost and standard buck
- Family of devices to supply MCU core from 1.0 V to 5.0 V, with SMPS (0.8 A, 1.5 A or 2.2 A, 1.5 A or 2.2 A) or LDO (0.5 A)
- Linear voltage regulator dedicated to auxiliary functions, or to sensor supply (V_{CCA} tracker or independent), 5.0 V, or 3.3 V
- Linear voltage regulator dedicated to MCU Analog/Digital (A/D) reference voltage or I/Os supply (V_{CCA}), 5.0 V, or 3.3 V
- 3.3 V keep alive memory supply available in low-power mode
- Long duration timer, counting up to 6 months with 1.0 s resolution
- Multiple wake-up sources in low-power mode: CAN, LIN, IOs, LDT
- Five configurable I/Os



Safety power system basis chip with CAN FD and LIN transceivers

3 Applications

- Drive Train Electrification (BMS, Hybrid EV and HEV, Inverter, DC-DC, Alterno Starter)
- Drive Train Chassis and Safety (Active Suspension, Steering, Safety Domain Gateway)
- Power Train (EMS, TCU, Gear Box)
- ADAS (LDW, Radar, Sensor Fusion Safety area)

4 Simplified application diagrams









FS6500-FS4500-ASILD Product data sheet

Ordering information 5

5.1 Part number definition

MC33FS <u>c</u> 5 <u>x</u> <u>y</u> <u>z</u> AE/R2

Table 1. Part number breakdown

Code	Option	Variable	Description
С	4 series	V _{CORE} type	Linear
	6 series		DC-DC
x	0	V _{CORE} current	0.5 A or 0.8 A
	1		1.5 A
	2		2.2 A
У	0	Functions	None
	1		FS1B
	2		LDT
	3		FS1B, LDT
	4		LDT, VKAM ON by default
z	N	Physical interface	None
	С		CAN FD
	L		CAN FD and LIN

5.2 Part numbers list

Table 2. Orderable part variations

Part Number	Temperature (T _A)	Package	FS1B	LDT	VCORE	VCORE type	VKAM on	CAN FD	LIN	Notes
MC33FS4500CAE			0	0	0.5 A	Linear	by SPI	1	0	
MC33FS4500LAE			0	0	0.5 A	Linear	by SPI	1	1	
MC33FS4500NAE			0	0	0.5 A	Linear	by SPI	0	0	
MC33FS4501CAE			1	0	0.5 A	Linear	by SPI	1	0	
MC33FS4501NAE			1	0	0.5 A	Linear	by SPI	0	0	
MC33FS4502CAE			0	1	0.5 A	Linear	by SPI	1	0	
MC33FS4502LAE	–40 °C		0	1	0.5 A	Linear	by SPI	1	1	
MC33FS4502NAE	to	48-pin LQFP	0	1	0.5 A	Linear	by SPI	0	0	[1] [2]
MC33FS4503CAE	125 °C		1	1	0.5 A	Linear	by SPI	1	0	
MC33FS4503NAE			1	1	0.5 A	Linear	by SPI	0	0	
MC33FS6500CAE			0	0	0.8 A	DC-DC	by SPI	1	0	
MC33FS6500LAE			0	0	0.8 A	DC-DC	by SPI	1	1	
MC33FS6500NAE			0	0	0.8 A	DC-DC	by SPI	0	0	
MC33FS6501CAE			1	0	0.8 A	DC-DC	by SPI	1	0	
MC33FS6501NAE			1	0	0.8 A	DC-DC	by SPI	0	0	

Safety power system basis chip with CAN FD and LIN transceivers

Part Number	Temperature (T _A)	Package	FS1B	LDT	VCORE	VCORE type	VKAM on	CAN FD	LIN	Notes
MC33FS6502CAE			0	1	0.8 A	DC-DC	by SPI	1	0	
MC33FS6502LAE			0	1	0.8 A	DC-DC	by SPI	1	1	
MC33FS6502NAE	-		0	1	0.8 A	DC-DC	by SPI	0	0	
MC33FS6503CAE			1	1	0.8 A	DC-DC	by SPI	1	0	
MC33FS6503NAE			1	1	0.8 A	DC-DC	by SPI	0	0	
MC33FS6504LAE			0	1	0.8 A	DC-DC	by default	1	1	
MC33FS6510CAE			0	0	1.5 A	DC-DC	by SPI	1	0	
MC33FS6510LAE			0	0	1.5 A	DC-DC	by SPI	1	1	
MC33FS6510NAE			0	0	1.5 A	DC-DC	by SPI	0	0	
MC33FS6511CAE			1	0	1.5 A	DC-DC	by SPI	1	0	
MC33FS6511NAE			1	0	1.5 A	DC-DC	by SPI	0	0	
MC33FS6512CAE			0	1	1.5 A	DC-DC	by SPI	1	0	
MC33FS6512LAE	-		0	1	1.5 A	DC-DC	by SPI	1	1	
MC33FS6512NAE			0	1	1.5 A	DC-DC	by SPI	0	0	
MC33FS6513CAE	-		1	1	1.5 A	DC-DC	by SPI	1	0	
MC33FS6513NAE	-		1	1	1.5 A	DC-DC	by SPI	0	0	
MC33FS6514LAE	-		0	1	1.5 A	DC-DC	by default	1	1	
MC33FS6520CAE	-		0	0	2.2 A	DC-DC	by SPI	1	0	
MC33FS6520LAE			0	0	2.2 A	DC-DC	by SPI	1	1	
MC33FS6520NAE	-		0	0	2.2 A	DC-DC	by SPI	0	0	
MC33FS6521CAE			1	0	2.2 A	DC-DC	by SPI	1	0	
MC33FS6521NAE	-		1	0	2.2 A	DC-DC	by SPI	0	0	
MC33FS6522CAE			0	1	2.2 A	DC-DC	by SPI	1	0	
MC33FS6522LAE	-		0	1	2.2 A	DC-DC	by SPI	1	1	
MC33FS6522NAE			0	1	2.2 A	DC-DC	by SPI	0	0	
MC33FS6523CAE			1	1	2.2 A	DC-DC	by SPI	1	0	
MC33FS6523NAE	1		1	1	2.2 A	DC-DC	by SPI	0	0	

Table 2. Orderable part variations...continued

[1] [2]

To order parts in tape and reel, add the R2 suffix to the part number. LIN and FS1B functions are exclusive. The differentiation is made by part numbers. When LIN is available, FS1B is not, and vice versa. VKAM on by default is available on certain part numbers only.

Safety power system basis chip with CAN FD and LIN transceivers

Block diagram 6





Safety power system basis chip with CAN FD and LIN transceivers

7 Pinning information

7.1 Pinning information





NXP Semiconductors

FS6500-FS4500-ASILD

Safety power system basis chip with CAN FD and LIN transceivers



FS6500-FS4500-ASILD Product data sheet

Safety power system basis chip with CAN FD and LIN transceivers

7.2 Pin description

A functional description of each pin can be found in <u>Section 11</u>.

Pin number	Pin name	Туре	Definition
1	VSUP1	A_IN	Power supply of the device. An external reverse battery protection diode in series is mandatory
2	VSUP2	A_IN	Second power supply. Protected by the external reverse battery protection diode used for VSUP1. VSUP1 and VSUP2 must be connected together externally.
3	VSENSE	A_IN	Sensing of the battery voltage. Must be connected prior to the reverse battery protection diode.
4	VSUP3	A_IN	Third power supply dedicated to the device supply. Protected by the external reverse battery protection diode used for VSUP1. Must be connected between the reverse protection diode and the input PI filter.
5	LIN	A_IN/OUT	LIN single-wire bus transmitter and receiver.
	or FS1B	D_OUT	Second output of the safety block (active low). The pin is asserted low at start-up and when a fault condition is detected, with a configurable delay or duration versus FS0B output terminal. Open drain structure.
	LIN and FS1E is not, and vio	B functions are ce versa. If nei	exclusive. The differentiation is made by part numbers. When LIN is available, FS1B ther LIN, nor FS1B functions are used, this pin must be left open.
6	GND_COM	GROUND	Dedicated ground for physical layers
7	CAN_5V	A_OUT	Output voltage for the embedded CAN FD interface
8	CANH	A_IN/OUT	CAN output high. If CAN function is not used, this pin must be left open.
9	CANL	A_IN/OUT	CAN output low. If CAN function is not used, this pin must be left open.
10	IO_4	D_IN A_OUT	Can be used as digital input (load dump proof) with wake-up capability or as an output gate driver Digital input : Pin status can be read through the SPI. Can be used to monitor error signals from another IC for safety purposes (when used with IO_5). Wake-up capability: Can be selectable to wake-up on edges or levels. Output gate driver: Can drive a logic level low-side NMOS transistor. Controlled by the SPI.
11	IO_5/VKAM	A_IN D_IN A_OUT	Can be used as digital input with wake-up capability or as an analog output providing keep alive memory supply in low-power mode. Analog input: Pin status can be read through the MUX output terminal Digital input: Pin status can be read through the SPI. Can be used to monitor error signals from another IC for safety purposes (when used with IO_4). Wake-up capability: Can be selectable to wake-up on edges or levels. Supply output: Provide keep alive memory supply in low-power mode
	VKAM can be	e enabled or di	sabled by default at power up. The differentiation is made by part numbers.
12	IO_0	A_IN D_IN	Can be used as analog or digital input (load dump proof) with wake-up capability (selectable) Analog input : Pin status can be read through the MUX output terminal Digital input : Pin status can be read through the SPI. Wake-up capability: Can be selectable to wake-up on edges or levels.
13	FCRBM	A_IN	Feedback core resistor bridge monitoring: For safety purposes, this pin is used to monitor the middle point of a redundant resistor bridge connected on V_{CORE} (in
FS6500-FS4500-	ASILD		All information provided in this document is subject to legal disclaimers. @ 2024 NXP R V All rights reserved

Table 3. FS6500/FS4500 pin definition

Safety power system basis chip with CAN FD and LIN transceivers

		_	
Pin number	Pin name	Туре	Definition
			parallel to the one used to set the V_{CORE} voltage). If not used, this pin must be connected directly to FB_CORE.
14	FS0B	D_OUT	First output of the safety block (active low). The pin is asserted low at start-up and when a fault condition is detected. Open drain structure.
15	DEBUG	D_IN	Debug mode entry input
16	AGND	GROUND	Analog ground connection
17	MUX_OUT	A_OUT	Multiplexed output to be connected to a MCU ADC. Selection of the analog parameter is available at MUX-OUT through the SPI.
18 19	IO_2:3	D_IN	Digital input pin with wake-up capability (logic level compatible) Digital input : Pin status can be read through the SPI. Can be used to monitor FCCU error signals from MCU for safety purposes. Wake-up capability: Can be selectable to wake-up on edges or levels.
20	TXD	D_IN	Transceiver input from the MCU which controls the state of the CAN-bus. Internal pull-up to VDDIO. If CAN function is not used, this pin must be left open.
21	RXD	D_OUT	Receiver output which reports the state of the CAN-bus to the MCU If CAN function is not used, this pin must be left open.
22	TXDL	D_IN	Transceiver input from the MCU controlling the state of the LIN bus. Internal pull-up to VDDIO.
	or VPU_FS	A_OUT	Pull-up output for FS1B function.
	LIN and FS1 is not, and vid If neither LIN	B functions are ce versa. , nor FS1B fun	e exclusive. The differentiation is made by part numbers. When LIN is available, FS1B
23	RXDL	D_OUT	Receiver output reporting the state of the LIN bus to the MCU. If LIN function is not used, this pin must be left open.
24	RSTB	D_OUT	This output is asserted low when the safety block reports a failure. The main function is to reset the MCU. Reset input voltage is also monitored in order to detect external reset and fault condition. Open drain structure.
25	MISO	D_OUT	SPI bus. primary input secondary output
26	MOSI	D_IN	SPI bus. primary output secondary input
27	SCLK	D_IN	SPI Bus. Serial clock
28	NCS	D_IN	Not chip select (active low)
29	INTB	D_OUT	This output pin generates a low pulse when an Interrupt condition occurs. Pulse duration is configurable. Internal pull-up to VDDIO.
30	VDDIO	A_IN	Input voltage for MISO output buffer. Allows voltage compatibility with MCU I/Os.
31	SELECT	D_IN	Hardware selection pin for VAUX and VCCA output voltages
32	FB_CORE	A_IN	VCORE voltage feedback. Input of the error amplifier.
33	COMP_ CORE	A_OUT	Compensation network. Output of the error amplifier. For FS4500 series, this pin must be left open (NC).
34	VCORE_ SNS	A_IN	VCORE input voltage sense

Table 3. FS6500/FS4500 pin definition...continued

Safety power system basis chip with CAN FD and LIN transceivers

Pin number	Pin name	Туре	Definition
35	SW_CORE	A_OUT	VCORE output switching point for FS6500 series
	or VCORE	A_OUT	VCORE output voltage for FS4500 series
36	BOOT_ CORE	A_IN/OUT	Bootstrap capacitor for VCORE internal NMOS gate drive For FS4500 series, this pin must be left open (NC).
37	VPRE	A_IN	VPRE input voltage sense
38	VAUX	A_OUT	VAUX output voltage. External PNP ballast transistor. Collector connection
39	VAUX_B	A_OUT	VAUX voltage regulator. External PNP ballast transistor. Base connection
40	VAUX_E	A_OUT	VAUX voltage regulator. External PNP ballast transistor. Emitter connection
41	VCCA_E	A_OUT	VCCA voltage regulator. External PNP ballast transistor. Emitter connection
42	VCCA_B	A_OUT	VCCA voltage regulator. External PNP ballast transistor. Base connection
43	VCCA	A_OUT	VCCA output voltage. External PNP ballast transistor. Collector connection
44	GATE_LS	A_OUT	Low-side MOSFET gate drive for non-inverting buck-boost configuration
45	DGND	GROUND	Digital ground connection
46	BOOT_PRE	A_IN/OUT	Bootstrap capacitor for the VPRE internal NMOS gate drive
47	SW_PRE2	A_OUT	Second pre-regulator output switching point
48	SW_PRE1	A_OUT	First pre-regulator output switching point

Table 3. FS6500/FS4500 pin definition...continued

8 Maximum ratings

Table 4. Maximum ratings

All voltages are with respect to ground, unless otherwise specified. Exceeding these ratings may cause a malfunction or permanent damage to the device.

Symbol	Ratings	Value	Unit	Notes			
Electrical rating	Electrical ratings						
V _{SUP1/2/3}	DC voltage at power supply pins	-1.0 to 40	V	[1]			
V _{SENSE}	DC voltage at battery sense pin (with ext R in series mandatory)	-14 to 40	V				
V _{SW1,2}	DC voltage at SW_PRE1 and SW_PRE2 Pins	-1.0 to 40	V				
V _{PRE}	DC voltage at VPRE Pin	–0.3 to 8	V				
V _{GATE_LS}	DC voltage at Gate_LS pin	-0.3 to 8	V				
V _{BOOT_PRE}	DC voltage at BOOT_PRE pin	-1.0 to 50	V				
V _{SW_CORE}	DC voltage at SW_CORE pin	-1.0 to 8	V				
V _{CORE_SNS}	DC voltage at VCORE_SNS pin	0.0 to 8	V				
V _{BOOT_CORE}	DC voltage at BOOT_CORE pin	0.0 to 15	V				
V _{FB_CORE}	DC voltage at FB_CORE pin	-0.3 to 2.5	V				
V _{COMP_CORE}	DC voltage at COMP_CORE pin	-0.3 to 2.5	V				
V _{FCRBM}	DC voltage at FCRBM pin	–0.3 to 8	V				
V _{AUX_B,E}	DC voltage at VAUX_B, VAUX_E pins	-0.3 to 40	V				
V _{AUX}	DC voltage at VAUX pin	-2.0 to 40	V				
V _{CCA_B,E}	DC voltage at VCCA_B, VCCA_E pins	–0.3 to 8	V				

Safety power system basis chip with CAN FD and LIN transceivers

Table 4. Maximum ratings ... continued

All voltages are with respect to ground, unless otherwise specified. Exceeding these ratings may cause a malfunction or permanent damage to the device.

Symbol	Ratings	Value	Unit	Notes
V _{CCA}	DC voltage at VCCA pin	-0.3 to 8	V	
V _{DDIO}	DC voltage at VDDIO pin	-0.3 to 8	V	
V _{CAN_5V}	DC voltage on CAN_5V pin	-0.3 to 8	V	
V _{PU_FS}	DC voltage at VPU_FS pin	-0.3 to 8	V	
V _{FSxB}	DC voltage at FS0B, FS1B pins (with ext R in series mandatory)	-0.3 to 40	V	
V _{DEBUG}	DC voltage at DEBUG pin	-0.3 to 40	V	
V _{IO_0,4}	DC voltage at IO_0, IO_4 pins (with ext R in series mandatory)	-0.3 to 40	V	
V _{IO_5}	DC voltage at IO_5 pin	-0.3 to 20	V	
V _{KAM}	DC voltage at VKAM pin	-0.3 to 8	V	
V _{DIG}	DC voltage at INTB, RSTB, MISO, MOSI, NCS, SCLK, MUX_OUT, RXD, TXD, RXDL, TXDL, IO_2, IO_3 pins	-0.3 to 8	V	
V _{SELECT}	DC voltage at SELECT pin	-0.3 to 8	V	
V _{BUS_CAN}	DC voltage on CANL, CANH pins	-27 to 40	V	
V _{BUS_LIN}	DC voltage on LIN pin	-18 to 40	V	
I_lsense	V _{SENSE} maximum current capability	-5.0 to 5.0	mA	
I_IO _{0, 4, 5}	IOs maximum current capability (IO_0, IO_4, IO_5)	-5.0 to 5.0	mA	
ESD voltage				
Human body m	nodel (JESD22/A114) ⁽¹⁹⁾ – 100 pF, 1.5 kΩ			
V _{ESD-HBM1}	All pins	±2.0	kV	[2]
V _{ESD-HBM2}	• VSUP1, 2, 3, VSENSE, VAUX, IO_0,4, FS0B, FS1B, DEBUG	±4.0	kV	
V _{ESD-HBM3}	CANH, CANL	±6.0	kV	
V _{ESD-HBM4}	• LIN	±8.0	kV	
Charge device	model (JESD22/C101) ⁽²⁰⁾ :			
V _{ESD-CDM1}	All pins	±500	V	
V _{ESD-CDM2}	Corner pins	±750	V	
System level E	SD (gun test)			
	• VSUP1, 2, 3, VSENSE, VAUX, IO_0, 4, 5, FS0B, FS1B			
V _{ESD-GUN1}	330 Ω/150 pF unpowered according to IEC 61000-4-2. (16)	±8.0	kV	
V _{ESD-GUN2}	330 Ω /150 pF unpowered according to OEM LIN, CAN, FlexRay Conformance	±8.0	kV	
V _{ESD-GUN3}	2.0 kΩ/150 pF unpowered according to ISO 10605 ⁽¹⁵⁾	±8.0	kV	
V _{ESD-GUN4}	2.0 kΩ/330 pF powered according to ISO 10605 ⁽¹⁵⁾	±8.0	kV	
	CANH, CANL			
V _{ESD-GUN5}	330 Ω /150 pF unpowered according to IEC 61000-4-2: ⁽¹⁶⁾	±15.0	kV	
V _{ESD-GUN6}	330 Ω/150 pF unpowered according to OEM LIN, CAN, FlexRay Conformance	±12.0	kV	
V _{ESD-GUN7}	2.0 kΩ/150 pF unpowered according to ISO 10605 ⁽¹⁵⁾	±15.0	kV	
V _{ESD-GUN8}	 2.0 kΩ/330 pF powered according to ISO 10605⁽¹⁵⁾ LIN 	±12.0	kV	
	• LIN			

FS6500-FS4500-ASILD Product data sheet

Safety power system basis chip with CAN FD and LIN transceivers

Table 4. Maximum ratings ... continued

All voltages are with respect to ground, unless otherwise specified. Exceeding these ratings may cause a malfunction or permanent damage to the device.

Symbol	Ratings	Value	Unit	Notes	
V _{ESD-GUN9}	330 Ω /150 pF unpowered according to IEC 61000-4-2. ⁽¹⁶⁾	±12.0	kV		
V _{ESD-GUN10}	330 Ω /150 pF unpowered according to OEM LIN, CAN, FlexRay conformance	±12.0	kV		
V _{ESD-GUN11}	2.0 k Ω /150 pF unpowered according to ISO 10605 ⁽¹⁵⁾	±12.0	kV		
V _{ESD-GUN12}	2.0 k Ω /330 pF powered according to ISO 10605 ⁽¹⁵⁾	±12.0	kV		
Thermal ratings					
T _A	Ambient temperature	-40 to 125	°C		
TJ	Junction temperature	-40 to 150	°C		
T _{STG}	Storage temperature	–55 to 150	°C		
Thermal resist	ance				
R _{θJA}	Thermal resistance junction to ambient	30	°C/W	[3]	
R _{0JCTOP}	Thermal resistance junction to case top	23.8	°C/W	[4]	
R _{0JCBOTTOM}	Thermal resistance junction to case bottom	0.9	°C/W	[5]	

All $V_{SUPS}\left(V_{SUP1/2/3}\right)$ must be connected to the same supply (Figure 73). Compared to AGND. [1]

[2] [3]

Per JEDEC JESD51- $6^{(17)}$ with the board (JESD51-7)⁽¹⁸⁾ horizontal.

[4] Thermal resistance between the die and the case top surface as measured by the cold plate method (MIL SPEC - 883 Method 1012.1)^[21].

Thermal resistance between the die and the solder pad on the bottom of the packaged based on simulation without any interface resistance. [5]

Static electrical characteristics 9

Table 5. Static electrical characteristics

 $T_A = -40$ °C to 125 °C, unless otherwise specified. $V_{SUP} = V_{SUP_UV_L}$ to 36 V, unless otherwise specified. All voltages referenced to ground. When 28 V < V_{SUP} < 36 V, thermal dissipation must be considered (see Figure 32).

Symbol	Parameter	Min.	Тур.	Max.	Unit	Notes
Power supply	•					
I _{SUP123}	Power supply current in normal mode	_	_	15.0	mA	
I _{SUP3}	Power supply current for VSUP3 in normal mode	_	3.5	5.0	mA	
I _{SUP_LPOFF1}	Power supply current in LPOFF (V _{SUP} = 14 V at T_A = 25 °C)	_	32	_	μΑ	[1]
I _{SUP_LPOFF2}	Power supply current in LPOFF (V_{SUP} = 18 V at T_A = 80 °C)	_	42	60	μΑ	
V _{SNS_UV}	Power supply undervoltage warning	7.0	8.0	9.0	V	
V _{SNS_UV_HYST}	Power supply undervoltage warning hysteresis	0.1	_	0.5	V	
V _{SUP_IPFF}	I _{PFF} input voltage detection	21	_	27	V	
V _{SUP_IPFF_HYST}	I _{PFF} input voltage hysteresis	0.2	_	_	V	
V _{SUP_UV_7}	Power supply undervoltage lockout (power up)	7.0	_	8.0	V	
V _{SUP_UV_5}	Power supply undervoltage lockout (power up)	_	_	5.6	V	
V _{SUP_UV_L}	Power supply undervoltage lockout (falling — boost configuration)	_		2.7	V	
V _{SUP_UV_L_B}	Power supply undervoltage lockout (falling — buck configuration)	_		4.5	V	[2]
V _{SUP_UV_LPOFF}	Power supply undervoltage lockout in LPOFF	—	—	4.5	V	[3]
V _{SUP_UV_HYST}	Power supply undervoltage lockout hysteresis	—	0.1	—	V	[4]

Safety power system basis chip with CAN FD and LIN transceivers

Table 5. Static electrical characteristics ... continued

Symbol	Parameter	Min.	Тур.	Max.	Unit	Notes					
V _{PRE} voltage pre	V _{PRE} voltage pre-regulator										
V _{PRE}	V _{PRE} output voltage										
	Buck mode (V _{SUP} > V _{SUP_UV_7})	6.25	_	6.75							
	• Buck mode ($V_{SUP}UV_7 \ge V_{SUP} \ge 4.5 V$)	V _{PRE} _ UV_4P3	V _{SUP} – R _{DS(on)_} PRE [*] IPRE	_							
	• Boost mode (V _{SUP} ≥ 2.7 V)	6.0	_	7.0							
I _{PRE}	V _{PRE} maximum output current capability				A	[4]					
	Buck or boost with V _{SUP} > V _{SUP_UV_7}	2.0	_	_							
	• Buck with $V_{SUP_UV_7} \ge V_{SUP} \ge 4.5 V$	0.5	2.0	_							
	• Boost with $V_{SUP_UV_7} \ge V_{SUP} \ge 6.0 V$	2.0	_	_							
	• Boost with 6.0 V \ge V _{SUP} \ge 4.0 V	1.0	_								
	• Boost with 4.0 V \ge V _{SUP} \ge 2.7 V	0.3	_	_							
I _{PRE_LIM1}	SW_PRE output current limitation in buck–boost mode (V _{SUP} \leq 28 V)	3.5	_		A						
I _{PRE_LIM2}	SW_PRE output current limitation in buck mode (V _{SUP} \leq 28 V)	2.5	—	_	А						
I _{PRE_OC}	SW_PRE overcurrent detection threshold in buck mode (V _{SUP} \leq 28 V)	4.5	_	—	A						
V _{PRE_UV}	V _{PRE} undervoltage detection threshold (falling)	5.5	—	6.0	V						
V _{PRE_UV_HYST}	V _{PRE} undervoltage hysteresis	0.05	_	0.15	V	[5]					
V _{PRE_UV_4P3}	V _{PRE} shut-off threshold (falling – buck and buck/boost)	4.1	—	4.5	V						
V _{PRE_UV_4P3_} HYST	V _{PRE} shut-off hysteresis	0.05	_	0.15	V	[5]					
R _{DSON_PRE}	V_{PRE} pass transistor on resistance with $V_{SUP} \le 28 \text{ V}$	—	—	200	mΩ						
L _{IR_VPRE}	V _{PRE} line regulation	—	20	_	mV	[5]					
LOR _{VPRE_BUCK}	 V_{PRE} load regulation for C_{OUT_VPRE} = 57 μF I_{PRE} from 50 mA to 2.0 A - buck mode 	_	100	_	mV	[5]					
LOR _{VPRE_BOOST}	 V_{PRE} load regulation for C_{OUT_VPRE} = 57 μF I_{PRE} from 50 mA to 2.0 A - boost mode 		500		mV	[5]					
V _{PRE_LL_H}	V _{PRE} pulse skipping thresholds	—	200	_	mV						
V _{PRE_LL_L}		—	180								
T _{WARN_PRE}	V _{PRE} thermal warning threshold	—	125		°C						
T _{SD_PRE}	V _{PRE} thermal shutdown threshold	160	_	—	°C	[6]					
T _{SD_PRE_HYST}	V _{PRE} thermal shutdown hysteresis	—	10	—	°C	[0]					
V _{G_LS_OH}	LS gate driver high output voltage (I _{OUT} = 50 mA)	V _{PRE} – 1	—	V _{PRE}	V						
V _{G_LS_OL}	LS gate driver low level (I _{OUT} = 50 mA)	—	—	0.5	V						
I _{G_LS}	LS gate driver current capability	_	300	<u> </u>	mA						
R _{G_SHORT}	GATE_LS pin short to GND resistance to detect buck mode only	_	_	10	Ω						

Safety power system basis chip with CAN FD and LIN transceivers

Table 5. Static electrical characteristics ... continued

 $T_A = -40$ °C to 125 °C, unless otherwise specified. $V_{SUP} = V_{SUP_UV_L}$ to 36 V, unless otherwise specified. All voltages referenced to ground. When 28 V < V_{SUP} < 36 V, thermal dissipation must be considered (see Figure 32).

Symbol	Parameter	Min.	Тур.	Max.	Unit	Notes				
V _{core} voltage regulator										
V _{CORE_FB}	V _{CORE} feedback input voltage	0.784	0.8	0.816	V					
I _{PD_CORE}	V_{CORE} internal pull-down current (active when $V_{\text{COR E}}$ is enabled)	5.0	12	25	mA					
I _{CORE}	V _{CORE} output current capability in normal mode • FS450x • FS650x • FS651x • FS652x	 		0.5 0.8 1.5 2.2	A					
ICORE_LIM	V _{CORE} output current limitation • FS450x • FS650x • FS651x • FS652x	0.55 1 1.8 2.5	 	1.7 2 2.8 3.5	A					
R _{DSON_CORE}	V _{CORE} pass transistor on resistance	—	—	200	mΩ					
FS65_ LOR _{VCORE_1.2}	V_{CORE} transient load regulation – 1.2 V range C_{OUT_VCORE} = 40 µF, I _{CORE} = 10 mA to 2.2 A, dI _{CORE} /dt ≤ 2.0 A/µs	-60	_	60	mV	[4]				
FS65_ LOR _{VCORE_3.3}	V_{CORE} transient load regulation – 3.3 V range C_{OUT_VCORE} = 40 μ F, I_{CORE} = 10 mA to 1.5 A, $dI_{CORE}/dt \le 2.0$ A/ μ s	-100		100	mV	[4]				
FS65_ LOR _{VCORE_5}	V_{CORE} transient load regulation – 5.0 V range C_{OUT_VCORE} = 20 μ F, I_{CORE} = 10 mA to 0.8 A, dI_{CORE}/dt ≤ 2.0 A/ μ s	-150		150	mV	[4]				
FS45_ LOR _{VCORE_1.2}	V_{CORE} transient load regulation – 1.2 V range C_{OUT_VCORE} = 20 µF, I _{CORE} = 10 mA to 0.2 A, dI _{CORE} /dt ≤ 0.5 A/µs	-60	_	60	mV	[4]				
FS45_ LOR _{VCORE_3.3}	V_{CORE} transient load regulation – 3.3 V range C_{OUT_VCORE} = 20 μ F, I_{CORE} = 10 mA to 0.35 A, $dI_{CORE}/dt \le 0.5$ A/ μ s	-100	_	100	mV	[4]				
FS45_ LOR _{VCORE_5}	V_{CORE} transient load regulation – 5 V range C_{OUT_VCORE} = 20 μ F, I_{CORE} = 10 mA to 0.5 A, $dI_{CORE}/dt \le 0.5$ A/ μ s	-150		150	mV	[4]				
V _{CORE_LL_H} V _{CORE_LL_L}	V _{CORE} pulse skipping thresholds	_	180 160		mV					
T _{WARN_CORE}	V _{CORE} thermal warning threshold	—	125	—	°C					
T _{SD_CORE}	V _{CORE} thermal shutdown threshold	160		_	°C					
T _{SD_CORE_HYST}	V _{CORE} thermal shutdown hysteresis	—	10	—	°C	[4]				
V _{CCA} voltage reg	julator									
V _{CCA}	V _{CCA} output voltage • 5.0 V configuration with Internal ballast at 100 mA • 5.0 V configuration with external ballast at 200 mA • 5.0 V configuration with external ballast at 300 mA • 3.3 V configuration with Internal ballast at 100 mA • 3.3 V configuration with external ballast at 200 mA • 3.3 V configuration with external ballast at 300 mA	4.95 4.9 4.85 3.267 3.234 3.201	5.0 5.0 3.3 3.3 3.3	5.05 5.1 5.15 3.333 3.366 3.399	V	[6]				
I _{CCA_IN}	V _{CCA} output current (int. MOSFET)	_	_	100	mA					

Safety power system basis chip with CAN FD and LIN transceivers

Table 5. Static electrical characteristics ... continued

 $T_A = -40$ °C to 125 °C, unless otherwise specified. $V_{SUP} = V_{SUP_UV_L}$ to 36 V, unless otherwise specified. All voltages referenced to ground. When 28 V < V_{SUP} < 36 V, thermal dissipation must be considered (see Figure 32).

Symbol	Parameter	Min.	Тур.	Max.	Unit	Notes
I _{CCA_OUT}	V _{CCA} output current (external PNP)		_	300	mA	
I _{CCA_LIM_INT}	V _{CCA} output current limitation (int. MOSFET)	100	_	675	mA	
I _{CCA_LIM_OUT}	V _{CCA} output current limitation (external PNP)	300	_	675	mA	
I _{CCA_LIM_FB}	V _{CCA} output current limitation foldback	60	_	240	mA	
V _{CCA_LIM_FB}	V _{CCA} output voltage foldback threshold	0.6	_	1.2	V	
V _{CCA_LIM_HYST}	V _{CCA} output voltage foldback hysteresis	0.03	_	0.3	V	
I _{CCA_BASE_SC} I _{CCA_BASE_SK}	V _{CCA} base current capability	 20	-20 65	_30 	mA	
T _{WARN_CCA}	V _{CCA} thermal warning threshold (int. MOSFET only)		125	_	°C	
TSD _{CCA}	V _{CCA} thermal shutdown threshold (int. MOSFET only)	160	_	_	°C	
TSD _{CCA_HYST}	V _{CCA} thermal shutdown hysteresis		10	_	°C	[5]
LOR _{VCCA}	V _{CCA} static load regulation • I _{CCA} = 10 mA to 100 mA (internal MOSFET) • I _{CCA} = 10 mA to 300 mA (external ballast)	_	15	_	mV	[5]
LORT _{VCCA}	V _{CCA} transient load regulation • I _{CCA} = 10 mA to 100 mA (internal MOSFET) • I _{CCA} = 10 mA to 300 mA (external ballast)	_	_	1.0	%	[5]
R _{PD_CCA}	V_{CCA} internal pull-down resistor (active when V_{CCA} is disabled)	50	_	170	Ω	
V _{AUX} voltage re	gulator			1		
V _{AUX_5}	V _{AUX} output voltage (5.0 V configuration)	4.85	5.0	5.15	V	
V _{AUX_33}	V _{AUX} output voltage (3.3 V configuration)	3.2	3.3	3.4	V	
V _{AUX_TRK}	V_{AUX} tracking error (V_{AUX_5} and V_{AUX_33})	-15	_	+15	mV	
I _{AUX_OUT}	V _{AUX} output current	_	_	400	mA	
I _{AUX_LIM}	V _{AUX} output current limitation	400	—	800	mA	
I _{AUX_LIM_FB}	V _{AUX} output current limitation foldback	60	—	240	mA	
V _{AUX_LIM_FB}	V _{AUX} output voltage foldback threshold	0.6	_	1.2	V	
V _{AUX_LIM_HYST}	V _{AUX} output voltage foldback hysteresis	0.03	_	0.3	V	
I _{AUX_BASE_SC} I _{AUX_BASE_SK}	V _{AUX} base current capability	— 7.0	-15 30	-7.0	mA	
TSD _{AUX}	V _{AUX} thermal shutdown threshold	160	_	_	°C	
TSD _{AUX_HYST}	V _{AUX} thermal shutdown hysteresis	_	10	_	°C	[5]
LOR _{VAUX}	V_{AUX} static load regulation ($I_{AUX_{OUT}}$ = 10 mA to 400 mA)	_	15	_	mV	[5]
LORT _{VAUX}	V _{AUX} transient load regulation • I _{AUX_OUT} = 10 mA to 400 mA	_	_	1.0	%	[5]
R _{PD_AUX}	V_{AUX} internal pull-down resistor (active when V_{AUX} is disabled)	50	_	170	Ω	
CAN_5V voltag	e regulator		1	_	-	
V _{CAN}	V_{CAN} output voltage $V_{SUP} > 6.0$ V in buck mode $V_{SUP} > V_{SUP_UV_L}$ in boost mode	4.8	5.0	5.2	V	
I _{CAN_OUT}	V _{CAN} output current	_	_	100	mA	
I _{CAN_LIM}	V _{CAN} output current limitation	100	_	250	mA	

Safety power system basis chip with CAN FD and LIN transceivers

Table 5. Static electrical characteristics ... continued

 $T_A = -40$ °C to 125 °C, unless otherwise specified. $V_{SUP} = V_{SUP_UV_L}$ to 36 V, unless otherwise specified. All voltages referenced to ground. When 28 V < V_{SUP} < 36 V, thermal dissipation must be considered (see Figure 32).

Symbol	Parameter	Min.	Тур.	Max.	Unit	Notes
TSD _{CAN}	V _{CAN} thermal shutdown threshold	160	-	_	°C	
TSD _{CAN_HYST}	V _{CAN} thermal shutdown hysteresis		10	_	°C	[5]
V _{CAN_UV}	V _{CAN} undervoltage detection threshold	4.25	_	4.8	V	
V _{CAN_UV_HYST}	V _{CAN} undervoltage hysteresis	0.07	_	0.22	V	
V _{CAN_OV}	V _{CAN} overvoltage detection threshold (rising)	5.2		5.85	V	
V _{CAN_OV_HYST}	V _{CAN} overvoltage hysteresis	0.07	_	0.22	V	
LOR _{VCAN}	V _{CAN} transient load regulation • I _{CAN_OUT} = 0 mA to 50 mA		100	_	mV	[5]
VKAM voltage	regulator	1			1	
V _{KAM}	V _{KAM} output voltage	3.0	3.5	4.0	V	
I _{KAM_OUT}	V _{KAM} output current		_	3.0	mA	
I _{KAM_LIM}	V _{KAM} output current limitation	4.0		10.0	mA	
I _{SUP_KAM}	$V_{KAM} \text{ current consumption from } V_{SUP3}$ • $I_{KAM_OUT} = 0 \text{ mA}$ • $I_{KAM_OUT} < 1.0 \text{ mA}$ • $1.0 \text{ mA} < I_{KAM_OUT} < 3.0 \text{ mA}$	_ _ _	-	25 150 2.15	μA μA mA	
Long duration	timer					
I _{LDT}	Timer current consumption (from V _{SUP3})	_	5.0	10	μA	
Fail-safe machi	ne voltage supervisor					
V _{PRE_OV}	V _{PRE} overvoltage detection threshold	7.2	_	8.0	V	
V _{PRE_OV_HYST}	V _{PRE} overvoltage hysteresis	_	0.1	_	V	[5]
V _{CORE_FB_UV}	V _{CORE} FB undervoltage detection threshold	0.67	_	0.773	V	-
V _{CORE_FB_UV_D}	V _{CORE} FB undervoltage detection threshold - degraded mode	0.45	_	0.58	V	
V _{CORE_FB_UV_} HYST	V _{CORE} FB undervoltage hysteresis	10	_	27	mV	[5]
V _{CORE_FB_OV}	V _{CORE} FB overvoltage detection threshold	0.84	_	0.905	V	
V _{CORE_FB_OV_} HYST	V _{CORE} FB overvoltage hysteresis	10	_	30	mV	[5]
V _{CORE_FB_DRIFT}	V _{CORE_FB} drift versus FCRBM	50	100	150	mV	
V _{CCA_UV_5}	V_{CCA} undervoltage detection threshold (5.0 V configuration)	4.5	—	4.75	V	
V _{CCA_UV_5D}	V_{CCA} undervoltage detection threshold (degraded 5.0 V)	3.0	—	3.2	V	
V _{CCA_UV_33}	V_{CCA} undervoltage detection threshold (3.3 V configuration)	3.0	_	3.2	V	
V _{CCA_OV_5}	V _{CCA} overvoltage detection threshold (5.0 V configuration)	5.25	_	5.5	V	
V _{CCA_OV_33}	V _{CCA} overvoltage detection threshold (3.3 V configuration)	3.4	_	3.6	V	
V _{CCA_5_HYST}	V _{CCA} undervoltage and overvoltage hysteresis (5.0 V configuration)		0.105	_	V	[5]
V _{CCA_33_HYST}	V_{CCA} undervoltage and overvoltage hysteresis (3.3 V configuration)	_	0.07	_	V	[5]
V _{AUX_UV_5}	V_{AUX} undervoltage detection threshold (5.0 V configuration)	4.5		4.75	V	
V _{AUX_UV_5D}	V_{AUX} undervoltage detection threshold (degraded 5.0 V)	3.0		3.2	V	
V _{AUX_UV_33}	V _{AUX} undervoltage detection threshold (3.3 V configuration)	3.0		3.2	V	

Safety power system basis chip with CAN FD and LIN transceivers

Table 5. Static electrical characteristics ... continued

Symbol	Parameter	Min.	Тур.	Max.	Unit	Notes
V _{AUX_OV_5}	V _{AUX} overvoltage detection threshold (5.0 V configuration)	5.25		5.5	V	
V _{AUX_OV_33}	V _{AUX} overvoltage detection threshold (3.3 V configuration)	3.4		3.6	V	
V _{AUX_5_HYST}	V _{AUX} undervoltage and overvoltage hysteresis (5.0 V configuration)	_	0.105	—	V	[5]
V _{AUX_33_HYST}	V _{AUX} undervoltage and overvoltage hysteresis (3.3 V configuration)	_	0.07	-	V	[5]
Fail-safe outputs	5		1			
V _{RSTB_OL}	Reset low output level (I_RSTB = 2.0 mA)	_	_	0.5	V	
I _{RSTB_LIM}	Reset output current limitation	12	_	25	mA	
V _{RSTB_IL}	Reset low level detection threshold (falling)	1.0	_	—	V	
V _{RSTB_IH}	Reset high level detection threshold (rising)	_	_	2.0	V	
V _{RSTB_HYST}	Reset hysteresis	200		_	mV	
RSTB _{PULL-DOWN}	RSTB pull-down resistor	_	1.0	_	MΩ	
V _{FS0B_OL}	FS0B low output level (I_FS0B = 2.0 mA)	_		0.5	V	
I _{FS0B_LIM}	FS0B output current limitation	4.0		16	mA	
V _{FS0B_IL}	FS0B low level detection threshold (falling)	1.0		_	V	
V _{FS0B_IH}	FS0B high level detection threshold (rising)	_	_	2.0	V	
V _{FS0B_HYST}	FS0B hysteresis	100		_	mV	
FS0B _{PULL-DOWN}	FS0B pull-down resistor	_	4.0	—	MΩ	
V _{FS1B_OL}	FS1B low output level (I_FS1B = 2.0 mA)	_		0.5	V	
I _{FS1B_LIM}	FS1B output current limitation	4.0	_	16	mA	
V _{FS1B_IL}	FS1B low level detection threshold (falling)	1.0	_	_	V	
V _{FS1B_IH}	FS1B high level detection threshold (rising)	_	_	2.0	V	
V _{FS1B_HYST}	FS1B hysteresis	100	_	—	mV	
FS1B _{PULL-DOWN}	FS1B pull-down resistor	_	4.0	_	MΩ	
Fail-safe pull-up		1				
I _{VPU_FS}	VPU_FS circuitry consumption	_	5.0	10	μA	
V _{VPU_FS_TH}	VPU_FS falling threshold to assert FS1B (FS1B_trig)	2.9	3.2	3.5	V	
R _{VPU_FS}	Resistor between VPRE and VPU_FS	—	1.0	1.5	kΩ	[5]
Digital input						
V _{IO_IH}	Digital high input voltage level (IO_0, IO_4, IO_5)	2.6	_	—	V	
V _{IO23_IH}	Digital high input voltage level (IO_2, IO_3)	2.0	_	—	V	
V _{IO_IL}	Digital low input voltage level (IO_0, IO_4, IO_5)	—	—	2.1	V	
V _{IO_HYST}	Input voltage hysteresis (IO_0, IO_4, IO_5)	50	120	500	mV	[5]
V _{IO23_IL}	Digital low input voltage level (IO_2, IO_3)	—	_	0.9	V	
V _{IO23_HYST}	Input voltage hysteresis (IO_2, IO_3)	200	450	700	mV	[5]
I _{IO_IN_2:4}	Input current for IO_2, IO_3 and IO_4	-5.0	_	5.0	μΑ	
IIO_IN_LPOFF	Input current for IO_0:5 in LPOFF	-1.0		1.0	μΑ	

Safety power system basis chip with CAN FD and LIN transceivers

Table 5. Static electrical characteristics ... continued

Symbol	Parameter	Min.	Тур.	Max.	Unit	Notes
Analog input - n	nulti-purpose IOs	11		1	1	
VIO_ANA_WD	Measurable input voltage (wide range)	3.0	_	19	V	
V _{IO_ANA_TG}	Measurable input voltage (tight range)	3.0	_	9.0	V	
I _{IO_IN_ANA}	Input current for IO_0 and IO_5	-5.0	_	100	μA	[7]
Output gate driv	ver (IO_4)	11		1	1	
V _{IO4_OH}	High output level at I _{IO4_OUT} = -2.0 mA	V _{PRE} – 1.5	_	V _{PRE}	V	
V _{IO4_OL}	Low output level at I _{IO4_OUT} = +2.0 mA	0.0	_	1.0	V	
V _{IO4_OUT_SK} V _{IO4_OUT_SC}	Output current capability	2.0	_	 2.0	mA	
Analog multiple	xer					
V _{AMUX_ACC}	Voltage sense accuracy (V_{SNS}, IO_0, IO_5) using 5.1 k Ω resistor	-5.0	_	5.0	%	[8]
V _{AMUX_WD_5}	Divider ratio (wide input voltage range) at V _{DDIO} = 5.0 V	_	5.0	_		[9]
V _{AMUX_WD_3P3}	Divider ratio (wide input voltage range) at V _{DDIO} = 3.3 V	_	7.0	_		20 ^[9]
V _{AMUX_TG_5}	Divider ratio (tight input voltage range) at V _{DDIO} = 5.0 V	_	2.0	_		
V _{AMUX_TG_3P3}	Divider ratio (tight input voltage range) at V _{DDIO} = 3.3 V	_	3.0	_		
VAMUX_REF1	Internal voltage Reference with 6.0 V < V _{SUP} < 19 V	2.475	2.5	2.525	V	
V _{AMUX_REF2}	Internal voltage reference with $V_{SUP} \le 6.0 \text{ V}$, or $V_{SUP} \ge 19 \text{ V}$	2.468	2.5	2.532	V	
V _{AMUX_TP_CO}	Internal temperature sensor coefficient	_	9.9	_	mV/°C	[5]
V _{AMUX_TP}	Temperature sensor MUX_OUT output voltage (at T_J = 165 °C)	2.08	2.15	2.22	V	
Interrupt		II		1	1	
V _{INTB_OL}	Low output level (I _{INT} = 2.5 mA)	—	—	0.5	V	
R _{PU_INT}	Internal pull-up resistor (connected to VDDIO)	_	10	_	ΚΩ	
I _{INT_LK}	Input leakage current	—	_	1.0	μA	
Digital interface		1			1	
MISO _H	High output level on MISO (I _{MISO} = 1.5 mA)	V _{DDIO} - 0.4	_	_	V	
MISOL	Low output level on MISO (I _{MISO} = 2.0 mA)	—	—	0.4	V	
I _{MISO}	Tri-state leakage current (V _{DDIO} = 5.0 V)	-5.0		5.0	μA	
V _{DDIO}	Supply voltage for MISO output buffer	3.0	—	5.5	V	
IV _{DDIO}	Current consumption on VDDIO	—	1.0	3.0	mA	
SPI _{LK}	SCLK, NCS, MOSI input current	-1.0	_	1.0	μA	
V _{SPI_IH}	SCLK, NCS, MOSI high input threshold	2.0	_	_	V	
V _{SPI_IL}	SCLK, NCS, MOSI low input threshold	_	_	0.8	V	
R _{SPI}	NCS, MOSI internal pull-up (pull-up to VDDIO)	200	400	800	ΚΩ	
Debug	·	I				
V _{DEBUG_IL}	Low input voltage threshold	2.1	2.35	2.8	V	
V _{DEBUG_IH}	High input voltage threshold	4.35	4.6	4.97	V	
I _{DEBUG_LK}	Input leakage current	-10	_	10	μA	

Safety power system basis chip with CAN FD and LIN transceivers

Table 5. Static electrical characteristics ... continued

Symbol	Parameter	Min.	Тур.	Max.	Unit	Notes
CAN transceiver	(FD 2.0 Mbit/s)	1	1			1
CAN logic input	pin (TXD)					
V _{TXD_IH}	TXD high input threshold	0.7 x V _{DDIO}	_	_	V	
V _{TXD_IL}	TXD low input threshold		_	0.3 x V _{DDIO}	V	
TXD _{PULL-UP}	TXD main device pull-up	20	33	50	ΚΩ	
TXD _{LK}	TXD input leakage current, V _{TXD} = V _{DDIO}	-1.0	—	1.0	μA	
CAN logic output	t pin (RXD)					
V _{RXD_OL1}	Low level output voltage (I _{RXD} = 250 µA)		—	0.4	V	
V _{RXD_OL2}	Low level output voltage (I _{RXD} = 1.5 mA)	_	—	0.9	V	
VOUT _{HIGH}	High level output voltage (I_{RXD} = -250 µA, V_{DDIO} = 3.0 V to 5.5 V)	V _{DDIO} - 0.4	_	_	V	
CAN output pins	(CANH, CANL)	1		1		1
V _{DIFF_COM_MODE}	Differential input comparator common mode range in normal mode	-20	_	20	V	
V _{IN_DIFF}	Differential input voltage threshold in normal mode	0.5	—	0.9	V	
V _{DIFF_COM_SLEEP}	Differential input comparator common mode range in sleep mode	-12	_	12	V	
VIN_DIFF_SLEEP	Differential input voltage threshold in sleep mode	0.4	—	1.1	V	
V _{IN_HYST}	Differential input hysteresis (in TX, RX mode)	50	_		mV	
R _{IN_CHCL}	CANH, CANL input resistance	5.0	—	50	kΩ	
R _{IN_DIFF}	CAN differential input resistance	10	—	100	kΩ	
R _{INSLEEP}	CANH, CANL input resistance device supplied and in CAN sleep mode	5.0	—	50	kΩ	
R _{IN_MATCH}	Input resistance matching	-3.0	_	3.0	%	
C _{IN_CM}	Common mode input capacitance	_	20	_	pF	[5]
C _{IN_DIFF}	Differential input capacitance		10	—	pF]
V _{CANH}	CANH output voltage (45 Ω < R _{BUS} < 65 Ω) • TX dominant state • TX recessive state	2.75 2.0	 2.5	4.5 3.0	V	
V _{CANL}	CANL output voltage (45 Ω < R _{BUS} < 65 Ω) • TX dominant state • TX recessive state	0.5 2.0	 2.5	2.25 3.0	v	
V _{CAN_SYM}	CAN dominant voltage symmetry (V _{CANL} + V _{CANH})	4.5	5.0	5.5	V	
V _{OH} -V _{OL}	Differential output voltage • TX dominant state (45 Ω < R _{BUS} < 65 Ω) • TX recessive state	1.5 –50	2.0 0.0	3.0 50	V mV	
I _{CANL-SK}	CANL sink current under short-circuit condition (V _{CANL} \leq 12 V, CANL driver ON, TXD low)	40	—	100	mA	
I _{CANH-SC}	CANH source current under short-circuit condition ($V_{CANH} = -2.0$ V, CANH driver ON, TXD low)	-100	_	-40	mA	

Safety power system basis chip with CAN FD and LIN transceivers

Table 5. Static electrical characteristics ... continued

 $T_A = -40$ °C to 125 °C, unless otherwise specified. $V_{SUP} = V_{SUP_UV_L}$ to 36 V, unless otherwise specified. All voltages referenced to ground. When 28 V < V_{SUP} < 36 V, thermal dissipation must be considered (see <u>Figure 32</u>).

Symbol	Parameter	Min.	Тур.	Max.	Unit	Notes
V _{CANLP}	CANL, CANH output voltage in sleep modes. No termination load.	-0.1	0.0	0.1	V	
I _{CAN}	CANH, CANL input current, device unsupplied, $(V_{CANH}, V_{CANL} = 5.0 \text{ V})$					[10]
	• V _{SUP} and V _{CAN} connected to GND	-10	_	10	μA	[10]
	+ V_{SUP} and V_{CAN} connected to GND via 47 $k\Omega$ resistor	-10	_	10	μA	
Т _{от}	Overtemperature detection	160	—	_	°C	
T _{HYST}	Overtemperature hysteresis	—	_	20	°C	
LIN transceiver	(when 7.0 V < V _{SUP} 1,2,3 < 18 V, unless otherwise specified)					
LIN logic input p	in (TXDL)					
V _{TXDL_IH}	TXDL high input threshold	2.0	_		V	
V _{TXDL_IL}	TXDL low input threshold	_	_	0.8	V	
TXDL _{PULL-UP}	TXDL internal pull-up (to VDDIO)	20	33	50	kΩ	
TXDL _{LK}	TXD input leakage current, V _{TXDL} = VDDIO	-1.0	_	1.0	μA	
LIN logic input p	bin (RXDL)					1
V _{RXDL_OL1}	Low level output voltage (I _{RXDL} = 250 µA)	_	_	0.4	V	
V _{RXDL_OL2}	Low level output voltage (I _{RXDL} = 1.5 mA)	_	_	0.9	V	
V _{RXDL_OUT_HIGH}	High level output voltage (I _{RXDL} = -250μ A, V _{DDIO} = 3.0 V to 5.5 V)	V _{DDIO} - 0.4	—	-	V	
LIN output pin	· ·				I	
IBUS_PAS_DOM	Input leakage current at the receiver. dominant state (Driver OFF, V_{BAT} = 12 V, V_{BUS} = 0 V)	-1.0	_	-	mA	[11]
I _{BUS_PAS_REC}	Input leakage current at the receiver. recessive state (Driver OFF, 8.0 V < V_{BAT} < 18 V, 8.0 V < V_{BUS} < 18 V, $V_{BUS} \ge V_{BAT}$)	_	_	20	μA	
V _{DRIVER_DOM}	Driver dominant voltage	_	_	0.251 × V _{SUP}	V	
V _{BUS_DOM}	Receiver dominant state	—	—	0.4 × V _{SUP}	V	
V _{BUS_REC}	Receiver recessive state	$0.6 \times V_{SUP}$	—	_	V	
V _{BUS_WU}	LIN wake-up detection threshold (7.0 V < V_{SUP} < 18 V)	0.4 × V _{SUP}	_	0.6 × V _{SUP}	V	
V _{LIN_UV}	V _{SUP} undervoltage threshold	—	_	7.0	V	
V _{SER_DIODE}	Series diode voltage drop ($D_{SER_COMMANDER}$ and D_{SER_INT} in pull-up path)	0.4	0.7	1.0	V	
I _{BUS_LIM}	Current limitation for driver dominant state (V _{BUS} = 18 V)	40	_	200	mA	[12]
R _{RESPONDER}	LIN pull-up resistor	20	_	60	kΩ	
V _{SHIFT_GND}	Ground shift ($V_{SHIFT_GND} = V_{GND_ECU} - V_{GND_BATTERY}$)	0.0	_	11.5 % V _{BAT}	V	
V _{SHIFT_BAT}	Battery voltage shift ($V_{SHIFT_BAT} = V_{BATTERY} - V_{SHIFT_GND} - V_{BAT}$)	0.0	—	11.5 % V _{BAT}	V	[13]
V _{SHIFT_DIF}	Difference between battery shift and ground shift	0.0	_	8.0 %	V	[14]
	(V _{SHIFT_DIF} = V _{SHIFT_BAT} - V _{SHIFT_GND})			V _{BAT}		-
V _{BUS_CNT}	V _{BUS_CNT} = (V _{TH_REC} + V _{TH_DOM})/2	0.475 × V _{SUP}	—	0.525 × V _{SUP}	V	[15]

FS6500-FS4500-ASILD Product data sheet

Safety power system basis chip with CAN FD and LIN transceivers

Table 5. Static electrical characteristics ... continued

T_A = -40 °C to 125 °C, unless otherwise specified. V_{SUP} = V_{SUP_UV_L} to 36 V, unless otherwise specified. All voltages referenced to ground. When 28 V < V_{SUP} < 36 V, thermal dissipation must be considered (see Figure 32).

Symbol	Parameter	Min.	Тур.	Max.	Unit	Notes
V _{HYST}	V _{HYST} = V _{TH_REC} - V _{TH_DOM}			0.175 × V _{SUP}	V	
I _{BUS_NO_GND}	Ground disconnection. GND = V_{SUP} 0 V < V_{BUS} < 18 V, V_{BAT} = 12 V. Loss of local GND does not affect communication in the remaining network	-1.0	_	1.0	mA	[16]
I _{BUS_NO_BAT}	VBAT disconnection. V_{SUP} = GND, 0 V < V_{BUS} < 18 V. Node sustains the current which can flow under this condition. BUS remains operational.	_	_	30	μΑ	
LIN _{TSD}	LIN thermal shutdown	150	175	_	°C	[5]
LIN _{TSD_HYST}	LIN thermal shutdown hysteresis		20		°C	
C _{LIN}	LIN internal capacitor	—	—	10	pF	[5]

Long duration timer and VKAM disable. [1]

[2] [3]

 $V_{SUP_{UV_LB}} = V_{PRE_UV_4P3} + R_{DSON_PRE} \times I_{PRE}$. V_{SUP} min to guarantee V_{KAM} and main logic supply in LPOFF.

[4] [5] Guaranteed by characterization.

Guaranteed by design.

[6] [7] External PNP gain within 150 to 450.

Valid for $V_{SUP3} \ge 10_5$.

If a higher resistor value than recommended is used, the accuracy degrades. [8] Wide range accuracy for input voltage from 9.0 V to 19 V.

[9]

[10] Guaranteed by design and characterization. V_{BAT} is the voltage at the input of the control unit. [11]

Current flowing inside the pin. A transceiver must be capable to sink at least 40 mA. [12]

V_{BAT}: voltage across the battery connectors of the vehicle. V_{GND ECU}: voltage on the local ECU ground connector with respect to battery ground of the [13] vehicle (V_{GND BATTERY}).

This constraint refers to duty cycle D1 and D2 only. [14]

[15] V_{TH DOM}: receiver threshold of the recessive to dominant LIN bus edge. V_{TH REC} receiver threshold of the dominant to recessive LIN bus edge.

[16] V_{SUP} is the voltage at the input of the device (different from V_{BAT} when a reverse current protection diode is implemented.

Dynamic electrical characteristics 10

Table 6. Dynamic electrical characteristics

T_A = -40 °C to 125 °C, unless otherwise specified. V_{SUP} = V_{SUP} UV L to 36 V, unless otherwise specified. All voltages referenced to ground. When 28 V < V_{SUP} < 36 V, thermal dissipation must be considered (see Figure 32).

Symbol	Parameter	Min.	Тур.	Max.	Unit	Notes	
Digital interface	Digital interface timing						
f _{SPI}	SPI operation frequency (50 % DC)	0.5	—	8.0	MHz		
t _{MISO_TRANS}	MISO transition speed, $20 - 80 \%$ • V _{DDIO} = 5.0 V, C _{LOAD} = 50 pF • V _{DDIO} = 5.0 V, C _{LOAD} = 150 pF	5.0 5.0	_	30 50	ns		
t _{CLH}	Minimum time SCLK = HIGH	62		_	ns		
t _{CLL}	Minimum time SCLK = LOW	62	—		ns		
t _{PCLD}	Propagation delay (SCLK to data at 10 % of MISO rising edge)	_	—	30	ns		
t _{CSDV}	NCS = low to data at MISO active	_	—	75	ns		
t _{SCLCH}	SCLK low before NCS low (setup time SCLK to NCS change H/ L)	75	_	_	ns		
t _{HCLCL}	SCLK change L/H after NCS = low	75	—	_	ns		
t _{SCLD}	SDI input setup time (SCLK change H/L after MOSI data valid)	40	_	_	ns		
t _{HCLD}	SDI input hold time (MOSI data hold after SCLK change H/L)	40	_	_	ns		

Safety power system basis chip with CAN FD and LIN transceivers

Table 6. Dynamic electrical characteristics ...continued

 $T_A = -40$ °C to 125 °C, unless otherwise specified. $V_{SUP} = V_{SUP_UV_L}$ to 36 V, unless otherwise specified. All voltages referenced to ground. When 28 V < V_{SUP} < 36 V, thermal dissipation must be considered (see <u>Figure 32</u>).

Symbol	Parameter	Min.	Тур.	Max.	Unit	Notes
t _{SCLCL}	SCLK low before NCS high	100	_	_	ns	
t _{HCLCH}	SCLK high after NCS high	100	_	_	ns	
t _{PCHD}	NCS L/H to MISO at high-impedance	_	_	75	ns	
t _{ONNCS}	NCS min. high time	500	_	_	ns	
t _{NCS_MIN}	NCS filter time	10	_	40	ns	
Functional state	machine					1
t _{WU_GEN}	General wake-up signal deglitch time (for any wake-up signal on IOs)	60	70	80	μs	
Fail-safe state m	nachine	-				
CLK _{FS}	Fail-safe oscillator	406	_	495	kHz	
CLK _{FS_MON}	Fail-safe oscillator monitoring	200	_	950	kHz	
t _{IC_ERR}	IO_4:5 Ext. IC filter time	4.0	_	20	μs	
t _{ACK_FS}	Acknowledgment counter (used for IC error handling IO_5)	7.0	_	9.7	ms	
t _{FCCU_ERR}	IO_2:3 FCCU filter time	4.0	_	8.0	us	
t _{DFS_RECOVERY}	IO_0 filter time to recover from deep reset and fail state	0.8	_	1.3	ms	
t _{CORE_DRIFT_MON}	FCRBM filter time	1.0	_	2.0	ms	
Fail-safe output		-	1	1	1	
t _{RSTB_FB}	RSTB feedback filter time	8.0	_	15	μs	
t _{FS0B_FB}	FS0B feedback filter time	8.0	_	15	μs	
t _{FS1B_FB}	FS1B feedback filter time	8.0	_	15	μs	
t _{RSTB_BLK}	RSTB feedback blanking time	180	_	320	μs	
t _{FS0B_BLK}	FS0B feedback blanking time	180	_	320	μs	
t _{FS1B_BLK}	FS1B feedback blanking time	180	_	320	μs	
t _{RSTB_POR}	Reset delay time (after a power-on reset or from LPOFF)	12.5	16.5	24.3	ms	[1]
t _{RSTB_LG}	Reset duration (long pulse)	8.0	_	10	ms	
t _{RSTB_ST}	Reset duration (short pulse)	1.0	_	1.3	ms	
t _{RSTB_IN}	External reset delay time	8.0	_	15	μs	
t _{DIAG_SC}	Fail-safe output diagnostic counter (RSTB, FS0B, FS1B)	500	_	800	μs	
V _{SENSE} voltage s	supply	-				
t _{VSNS_UV}	V _{SNS} undervoltage filtering time	1.0	_	3.0	μs	
V _{SUP} voltage su	pply					
t _{VSUP_IPFF}	I _{PFF} input voltage filtering time	1.0	_	5.0	μs	
C _{SUP}	Minimum capacitor on V _{SUP}	47	_	_	μF	
V _{PRE} voltage pre	-regulator					
f _{SW_PRE}	V _{PRE} switching frequency	412	437.5	463	kHz	
t _{SW_PRE}	V _{SW_PRE} on and off switching time		_	30	ns	[2]
t _{PRE_SOFT}	V_{PRE} soft start duration ($C_{OUT_VPRE} \le 100 \ \mu F$)	500	-	700	μs	
t _{PRE_BLK_LIM}	V _{PRE} current limitation blanking time	200	_	600	ns	
t _{IPRE_OC}	V _{PRE} overcurrent filtering time	30		120	ns	[2]

FS6500-FS4500-ASILD Product data sheet

Safety power system basis chip with CAN FD and LIN transceivers

Table 6. Dynamic electrical characteristics ... continued

 $T_A = -40$ °C to 125 °C, unless otherwise specified. $V_{SUP} = V_{SUP_UV_L}$ to 36 V, unless otherwise specified. All voltages referenced to ground. When 28 V < V_{SUP} < 36 V, thermal dissipation must be considered (see <u>Figure 32</u>).

Symbol	Parameter	Min.	Тур.	Max.	Unit	Notes			
t _{PRE_UV}	V _{PRE} undervoltage filtering time	20		40	μs				
t _{PRE_UV_4p3}	V _{PRE} shutoff filtering time	3.0		7.0	μs				
d _{IPRE/DT}	V _{PRE} load regulation variation	_	_	25	A/ms	[2]			
t _{PRE_WARN}	V _{PRE} thermal warning filtering time	30	_	40	μs				
t _{PRE_TSD}	V _{PRE} thermal detection filtering time	1.0	_	3.0	μs				
t _{LS_RISE/FALL}	LS gate voltage switching time (I _{OUT} = 300 mA)	_	_	50	ns				
t _{BBTO}	GATE_LS boost transistor timeout detection	_	120	_	us				
V _{core} voltage regulator									
t _{CORE_BLK_LIM}	V _{CORE} current limitation blanking time	20	_	40	ns				
f _{SW_CORE}	V _{CORE} switching frequency	2.2	2.34	2.48	MHz				
t _{SW_CORE}	V _{SW_CORE} on and off switching time	_	_	12	ns				
V _{CORE_SOFT}	V _{CORE} soft start (C _{OUT_VCORE} = 100 μF max)	_	_	10	V/ms				
t _{CORE_WARN}	V _{CORE} thermal warning filtering time	30	_	40	μs				
t _{CORE_TSD}	V _{CORE} thermal detection filtering time	1.0	_	3.0	μs				
V _{CCA} voltage reg	Julator				•				
t _{CCA_LIM}	V _{CCA} output current limitation filter time	1.0		3.0	μs				
t _{CCA_LIM_OFF1}	V _{CCA} output current limitation duration	10		15	ms				
^t CCA_LIM_OFF2		50		60					
t _{CCA_WARN}	V _{CCA} thermal warning filtering time (int. MOSFET)	30	_	40	μs				
t _{CCA_TSD}	V _{CCA} thermal detection filter time (int. MOSFET)	1.0		3.0	μs	[2]			
dl _{LOAD} /dt	V _{CCA} load transient	—	2.0	—	A/ms	[2]			
V _{CCA_SOFT}	V _{CCA} soft start (5.0 V and 3.3 V)			50	V/ms				
V _{AUX} voltage reg	Julator			1	1	1			
t _{AUX_LIM}	V _{AUX} output current limitation filter time	1.0	—	3.0	μs				
t _{AUX_LIM_OFF1}	V _{AUX} output current limitation duration	10	—	15	ms				
t	V thermal detection filter time	1.0		3.0	116				
dlum/dt		1.0	2.0	5.0	μs A/ms	[2]			
	V_{AUX} road transferr		2.0	50	V/ms				
CAN 5V voltage				50	V/113				
tonu un		2.0		4.0	118				
		1.0		3.0	μ3 e				
to AN LINK		4.0		7.0	μ3 e				
to an ex	V _{CAN} undervoltage filtering time	100		200	μ 3 με				
dlaw/dt	Very load transient	100	100	200	μ3 Δ/ms	[2]			
Fail-safe machin			100		7/115				
		128		234	116				
TRE_OV				314	но 116				
PRE_OV_R		4.0		10	<u>но</u>				
CORE_UV		4.0		10	μs				

Safety power system basis chip with CAN FD and LIN transceivers

Table 6. Dynamic electrical characteristics ... continued

Symbol	Parameter	Min.	Тур.	Max.	Unit	Notes
t _{CORE_UV_R}	V _{CORE} FB undervoltage reaction time	_	_	15	μs	
t _{CORE_OV}	V _{CORE} FB overvoltage filtering time	128	_	234	μs	
t _{CORE_OV_R}	V _{CORE} FB overvoltage reaction time	_	_	314	μs	
t _{CCA_UV}	V _{CCA} undervoltage filtering time	4.0	_	10	μs	
t _{CCA_UV_R}	V _{CCA} undervoltage reaction time	_	_	15	μs	
t _{CCA_OV}	V _{CCA} overvoltage filtering time	128	_	234	μs	
t _{CCA_OV_R}	V _{CCA} overvoltage reaction time	_	_	314	μs	
t _{AUX_UV}	V _{AUX} undervoltage filtering time	4.0	_	10	μs	
t _{AUX_UV_R}	V _{AUX} undervoltage reaction time	_	_	15	μs	
t _{AUX_OV}	V _{AUX} overvoltage filtering time	128	_	234	μs	
t _{AUX_OV_R}	V _{AUX} overvoltage reaction time	_	_	314	μs	
Digital input – m	ulti-purpose IOs					
F _{IO_IN}	Digital input frequency range	0.0	_	100	kHz	
Analog multiple	xer					
t _{MUX_READY}	SPI selection to data ready to be sampled on Mux_out					
	• V _{DDIO} = 5.0 V, C _{MUX_OUT} = 1.0 nF	—	_	10	μs	
Interrupt	T	1	1	1		,
t _{INTB_LG}	INTB pulse duration (long)	90	100	_	μs	
t _{INTB_ST}	INTB pulse duration (short)	20	25	_	μs	
Long duration ti	mer	-		1	1	
CLK _{LDT}	Long duration timer oscillator	31129	32768	34407	Hz	
CLK _{LDT_%}	Long duration timer oscillator accuracy					
	• from -40 °C to 125 °C • from -20 °C to 85 °C and calibration	-5.0		5.0	%	
CAN dynamic cl	hom -20 0 to 00 0 and cambration	-2.0		2.0		
ta our	TXD dominant state timeout	0.8		5.0	me	1
*DOUT	Pus deminant state timeout	0.0		5.0	- 1115 	
LDOM		0.0		5.0	1115	
LOOP	• R_{LOAD} = 120 Ω , C between CANH and CANL = 100 pF, C at RXD < 15 pF	_	_	255	ns	
t _{1PWU}	First pulse wake-up time	0.5	_	3.5	μs	
t _{3PWU}	Second and third pulse wake-up time	0.5	_	1.0	μs	
t _{3PTO1}	Multiple pulse wake-up timeout (short)	100	120	_	μs	
t _{3PTO2}	Multiple pulse wake-up timeout (long)	2400	2800	_	μs	
t _{CAN_READY}	Delay to enable CAN by SPI command (NCS rising edge) to CAN to transmit (device in normal mode and CAN interface in TX/RX mode)	-	_	100	μs	[3]
t _{BIT(BUS)}	Transmitted recessive bit width at 2.0 Mbit/s	435	-	530	ns	
t _{BIT(RXD)}	Received recessive bit width at 2.0 Mbit/s	400	-	550	ns	
t _{REC}	Receiver timing symmetry at 2.0 Mbit/s	-65	—	40	ns	

Safety power system basis chip with CAN FD and LIN transceivers

Table 6. Dynamic electrical characteristics ... continued

 $T_A = -40$ °C to 125 °C, unless otherwise specified. $V_{SUP} = V_{SUP_UV_L}$ to 36 V, unless otherwise specified. All voltages referenced to ground. When 28 V < V_{SUP} < 36 V, thermal dissipation must be considered (see Figure 32).

Symbol	Parameter	Min.	Тур.	Max.	Unit	Notes		
LIN dynamic characteristics (when 7.0 V < V _{SUP} 1, 2, 3 < 18 V, unless otherwise specified)								
t _{RX_PD}	Receiver propagation delay ($T_{RX_{PD}}$ = MAX ($t_{REC_{PDR}}$, $t_{REC_{PDF}}$))	_	_	6.0	μs			
t _{RX_SYM}	Symmetry of receiver propagation delay (T _{RX_SYM} = t _{REC_PDF} _ t_{REC_PDR})	-2.0	—	2.0	μs			
t _{BUS_WU}	BUS wake-up filter time	_	_	250	μs			
t _{XD_DOM}	TXD_L permanent dominant state detection	—	5.0	—	ms			
t _{LIN_SHORT_GND}	LIN Short-circuit to GND deglitcher	_	15	—	ms			
BD _{FAST}	Fast baud rate	—	_	100	KB/s			
D1	Duty cycle D1 TH _{REC} (max) = 0.744 x V _{SUP} , TH _{DOM} (max) = 0.581 x V _{SUP} V _{SUP} 7.0 V to 18 V, t _{BIT} = 50 μ s, D1 = t _{BUS} -rec(min)/(2t _{BIT})	0.396		_	%	[4]		
D2	Duty cycle D2 $TH_{REC}(min) = 0.422 \text{ x } V_{SUP}, TH_{DOM}(min) = 0.284 \text{ x } V_{SUP}$ $V_{SUP} 7.6 \text{ V to } 18 \text{ V}, t_{BIT} = 50 \mu\text{s}, D2 = t_{BUS}\text{-rec}(max)/(2t_{BIT})$	_		0.581	%	35 ^[4]		
D3	Duty cycle D3 TH _{REC} (max) = 0.778 x V _{SUP} , TH _{DOM} (max) = 0.616 x V _{SUP} V _{SUP} 7.0 V to 18 V, t _{BIT} = 96 μ s, D3 = t _{BUS} -rec(min)/(2t _{BIT})	0.417		_	%	35 ^[4]		
D4	Duty cycle D4 TH _{REC} (min) = 0.389 x V _{SUP} , TH _{DOM} (min) = 0.251 x V _{SUP} V _{SUP} 7.6 V to 18 V, t _{BIT} = 96 μ s, D4 = t _{BUS} -rec(max)/(2t _{BIT})	_		0.590	%	35 ^[4]		

[1] This timing is not guaranteed in case of fault during startup phase (after power-on reset of from LPOFF).

[2] [3] Guaranteed by characterization.

For proper CAN operation, TXD must be set to high level before CAN enable by the SPI, and must remain high for at least T_{CAN READY}.

[4] LIN Driver, bus load conditions (CBUS, RBUS): 1.0 nF; 1.0 k Ω / 6.8 nF; 660 Ω / 10 nF; 500 Ω .

NCS		<u> </u>					
			^t CLH				
SCLK		tre	D				
MISO	Tri-state tCSDV	Not used	X MSB		X_	LSB	→ -
				t _{HCLD}			
MOSI			X	MSB		LSB X	
							aaa-037738
Figure 9.	SPI timing of	diagram					

FS6500-FS4500-ASILD



11 Functional pin description

11.1 Introduction

The FS6500/FS4500 is the fourth generation of the system basis chip, combining:

- High efficiency switching voltage regulator for MCU, and linear voltage regulators for integrated CAN FD and LIN interfaces.
- External ICs such as sensors, accurate reference voltage for A to D converters, and keep alive memory supply in low-power mode for MCU static RAM.
- Built-in CAN flexible data interface at 2.0 Mbit/s (ISO 11898-2⁽¹²⁾ and -5⁽¹³⁾), and LIN interface (LIN up to Rev. 2.2^{(22), (23)}/SAEJ2602-2⁽²⁴⁾), with local and bus failure diagnostic, protection, and fail-safe operation mode.
- Low-power mode, with ultra low-current consumption.
- Various wake-up capabilities.
- Long duration timer available in normal and low-power mode.
- Enhanced safety features with multiple fail-safe outputs and a scheme to support ASIL D applications.

11.2 Power supplies (VSUP1, VSUP2, VSUP3)

VSUP1 and VSUP2 are the input pins for the internal supply dedicated to the SMPS regulators. VSUP3 is the input pin for internal voltage reference. VSUP1, 2, and 3 are robust against ISO 7637⁽¹⁴⁾ pulses. VSUP1, 2, and 3 must be connected to the same supply (Figure 73).

11.3 V_{SENSE} input (VSENSE)

This pin must be connected to the battery line (before the reverse battery protection diode), via a serial resistor. It incorporates a threshold detector to sense the battery voltage, and provide a battery early warning. It also includes a resistor divider to measure VSENSE voltage via the MUX-OUT pin. The VSENSE pin is robust against ISO 7637⁽¹⁴⁾ pulses.

11.4 Pre-regulator (VPRE)

A highly flexible SMPS pre-regulator is implemented in the FS6500/FS4500. It can be configured as a 'noninverting buck-boost converter' (Figure 34) or 'standard buck converter' (Figure 33), depending on the external configuration (connection of pin GATE_LS). The configuration is detected automatically during start-up sequence.

The SMPS pre-regulator is working in current mode control and the compensation network is fully integrated in the device. The high-side switching MOSFET is also integrated to make the current control easier. The pre-regulator delivers a typical output voltage of 6.5 V, which is used internally. Current limitation, overcurrent, overvoltage, and undervoltage detectors are provided. VPRE is enabled by default.

11.5 VCORE output (from 1.0 V to 5.0 V range)

The VCORE block of the FS6500 series is an SMPS regulator. The voltage regulator is a step down DC– DC converter operating in voltage control mode. The stability of the converter is done externally, by using the COMP_CORE pin. The VCORE block of the FS4500 series is a linear regulator. In this case, BOOT_CORE and COMP_CORE pins must be left open.

The output voltage of FS6500/FS4500 is configurable to any voltage from a 1.0 V to 5.0 V range using an external resistor divider connected between VCORE and the feedback pin (FB_CORE) (as example in Figure 1, or Figure 73). Current limitation, overvoltage, and undervoltage detectors are provided. VCORE can be turned on or off via a SPI command, however it is not recommended to turn off VCORE with the SPI when VCORE is configured safety critical (both overvoltage and undervoltage have an impact on fail-safe outputs). VCORE overvoltage information disables VCORE. Diagnostics are reported in the dedicated register and generate an Interrupt. VCORE is enabled by default. For safety purpose, a second resistor bridge (R3/R4 duplicated) connected to FCRBM should be used to detect an external resistor drift.

11.6 VCCA output, 5.0 V, or 3.3 V selectable

The VCCA voltage regulator is used to provide an accurate voltage output (5.0 V, 3.3 V) selectable through an external resistor connected to the SELECT pin.

The VCCA output voltage regulator can be configured using an internal transistor delivering very good accuracy (\pm 1.0 % for 5.0 V and 3.3 V configuration), with a limited current capability (100 mA) for an analog to digital converter, or with an external PNP transistor, giving higher current capability (up to 300 mA) with lower output voltage accuracy (\pm 3.0 % for 300 mA) when using a local ECU supply.

Current limitation, overvoltage, and undervoltage detectors are provided. VCCA can be turned on or off via a SPI command, however it is not recommended to turn off VCCA with the SPI when VCCA is configured safety critical (both overvoltage and undervoltage have an impact on fail-safe outputs). VCCA overcurrent (with the use of external PNP only) and overvoltage information disables VCCA. Diagnostics are reported in the dedicated register and generate an Interrupt. VCCA is enabled by default.

11.7 VAUX output, 5.0 V, or 3.3 V selectable

The VAUX pin provides an auxiliary output voltage (5.0 V, 3.3 V) selectable through an external resistor connected to SELECT pin. It uses an external PNP ballast transistor for flexibility and power dissipation constraints. The VAUX output voltage regulator can be used as 'auxiliary supply' (local ECU supply) or 'sensor supply' (external ECU supply) with the possibility to be configured as a tracking regulator following VCCA.

Current limitation, overvoltage, and undervoltage detectors are provided. VAUX can be turned on or off via a SPI command, however it is not recommended to turn off VAUX with the SPI when VAUX is configured safety critical (both overvoltage and undervoltage have an impact on fail-safe outputs). V_{AUX} overcurrent and overvoltage information disables VAUX, reported in the dedicated register, and generates an Interrupt. VAUX is enabled by default.

11.8 SELECT input pin

11.8.1 VCCA, VAUX voltage configuration

VCCA and VAUX output voltage configurations are set by connecting an external resistor between the SELECT pin and Ground or the SELECT pin and VPRE. According to the value of this resistor, the voltage of VCCA and VAUX are configured after each power-on reset, and after a wake-up event when the device is in LPOFF. Information latches until the next hardware configuration read. Regulator voltage values can be read on the dedicated register via the SPI. See Figure 75.

V _{CCA} (V)	V _{AUX} (V)	R select	Recommended value ^[1]				
3.3	3.3	<6.0 kΩ	5.1 kΩ ±5.0 %				
5.0	5.0	10.8 << 13.2 kΩ	12 kΩ ±5.0 %				
3.3	5.0	21.6 << 26.2 kΩ	24 kΩ ±5.0 %				
5.0	3.3	45.9 << 56.1 kΩ	51 kΩ ±5.0 %				

Table 7. V_{CCA}/V_{AUX} voltage selection

[1] If the SELECT pin is detected open, the VCCA and VAUX regulators start at their minimum output voltage 3.3 V.

11.8.2 Deep fail-safe configuration

Deep fail-safe function is enabled when the SELECT pin is connected to ground and disabled when the SELECT pin is connected to VPRE. The configuration is done after each power-on reset, and after a wake-up event when device is in LPOFF by both the main and the fail-safe logics. The Information is latched until the next hardware configuration read (Figure 11).



11.9 CAN_5V voltage regulator

The CAN_5V voltage regulator is a linear regulator dedicated to the internal CAN FD interface. An external capacitor is required. Current limitation, overvoltage, and undervoltage detectors are provided. If the internal CAN transceiver is not used, the CAN_5V regulator can supply an external load (see <u>Section 12.7.6</u>). CAN_5V is enabled by default.

11.10 Interrupt (INTB)

The INTB output pin generates a low pulse when an Interrupt condition occurs. The INTB behavior as well as the pulse duration are set through the SPI during INIT phase. INTB has an internal pull-up resistor connected to VDDIO.

11.11 CANH, CANL, TXD, RXD

These are the pins of the CAN FD physical interface. The CAN FD transceiver provides the physical interface between the CAN FD protocol controller of an MCU and the physical dual wires CAN-bus. The CAN FD interface is connected to the MCU via the RXD and TXD pins.

11.11.1 TXD

TXD is the device input pin to control the CAN-bus level. TXD is a digital input with an internal pull-up resistor connected to VDDIO. In the application, this pin is connected to the microcontroller transmit pin. In normal mode, when TXD is high or floating, the CANH and CANL drivers are off, setting the bus in a recessive state.

FS6500-FS4500-ASILD	

When TXD is low, the CANH and CANL drivers are activated and the bus is set to a dominant state. TXD has a built-in timing protection disabling the bus when TXD is dominant for more than t_{DOUT}. In LPOFF mode, VDDIO is off, pulling this pin to GND.

11.11.2 RXD

RXD is the bus output level report pin. In the application, this pin is connected to the microcontroller receive pin. In normal mode, RXD is a push-pull structure. When the bus is in a recessive state, RXD is high. When the bus is dominant, RXD is low. In LPOFF mode, this pin is in the high-impedance state.

11.11.3 CANH and CANL

These are the CAN-bus pins. CANL is a low-side driver to GND, and CANH is a high-side driver to CAN 5V. In normal mode and TXD high, the CANH and CANL drivers are off, and the voltage at CANH and CANL is approximately 2.5 V, provided by the internal bus biasing circuitry. When TXD is low, CANL is pulled to GND and CANH to CAN 5V, creating a differential voltage on the CAN-bus.

In LPOFF mode, the CANH and CANL drivers are off, and these pins are pulled to GND via the device RIN CHCL resistors. CANH and CANL have integrated ESD protection and extremely high robustness versus external disturbance, such as EMC and electrical transients. These pins have current limitation and thermal protection.

11.12 LIN, TXDL, RXDL

These are the pins of the LIN physical interface. The LIN transceivers provides the physical interface between the MCU and the physical single wire LIN bus. The LIN interface is connected to the MCU via the RXDL and TXDL pins.

11.12.1 TXDL

The TXDL input pin is the MCU interface to control the state of the LIN output. TXDL is a digital input with an internal pull-up resistor connected to VDDIO. In the application, this pin is connected to the microcontroller transmit pin.

In normal mode, when TXDL is high or floating, the LIN output transistor is OFF, setting the bus in recessive state. When TXDL is low, the LIN output transistor is on and the bus is set to a dominant state. TXDL has a built-in timing protection disabling the bus when TXDL is dominant for more than T_{XD DOM}. In LPOFF mode, VDDIO is off, pulling this pin to GND.

11.12.2 RXDL

RXDL is the bus output level report pin. In the application, this pin is connected to the microcontroller receive pin. In normal mode, RXD is a push-pull structure. When the bus is in a recessive state, RXD is high. When the bus is dominant, RXD is low. In LPOFF mode, this pin is in the high-impedance state.

11.12.3 LIN

This is the LIN bus pin. The LIN driver is a low-side MOSFET with internal overcurrent thermal shutdown. An internal pull-up resistor with a serial diode structure is integrated so no external pull-up components are required for the application in a responder node. An additional pull-up resistor of 1.0 k Ω must be added when the device is used in the commander node. In normal mode and TXDL high, the LIN transistor is off, and the voltage at LIN is approximately VSUP3, provided by the pull-up resistor with a serial diode structure. When TXD is low, LIN is pulled to GND.

The device has two selectable baud rates: 20 kbit/s for normal baud rate and 10 kbit/s for slow baud rate. An additional fast baud rate (100 kbit/s) is implemented. It can be used to flash the MCU or in the garage for

diagnostic. The LIN consortium specification does not specify electrical parameters for this baud rate. The communication only must be guaranteed. In LPOFF mode, the LIN transistor is off, and this pin is pulled up to VSUP3. LIN has integrated ESD protection and extremely high robustness versus external disturbance, such as EMC and electrical transients.

11.13 Multiplexer output MUX_OUT

The MUX_OUT pin (Figure 12) delivers analog voltage to the MCU ADC input. The voltage to be delivered to MUX_OUT is selected via the SPI, from one of the following parameters:

- VSENSE
- VIO_0
- VKAM
- Internal 2.5 V reference

Internal die temperature sensor T(°C) = (V_{AMUX} – V_{AMUX} TP)/V_{AMUX} TP CO + 165

Voltage range at MUX_OUT is from GND to VDDIO (3.3 V or 5.0 V)



11.14 I/O pins (I/O_0:I/O_5)

The FS6500/FS4500 includes five multi-purpose I/Os (I/O_0 to I/O_5). I/O_0 and I/O_4 are load dump proof and robust against ISO $7637^{(14)}$ pulses. An external serial resistor must be connected to those pins to limit the current during ISO pulses. I/O_2 and I/O_3 are not load dump proof. I/O_5 requires an external protection (resistor and Zener diode) to be load dump proof and robust against ISO $7637^{(14)}$ pulses.

I/O number	Digital input wake-up capability	Analog input	Output gate driver	VKAM	FCCU monitoring	Ext. IC monitoring
IO_0	Х	Х				
IO_2	Х				Х	
IO_3	Х				Х	
IO_4	Х		Х			Х

Table 8. I/Os configuration

FS6500-FS4500-ASILD Product data sheet

I/O number	Digital input wake-up capability	Analog input	Output gate driver	VKAM	FCCU monitoring	Ext. IC monitoring	
IO_5	Х	Х		Х		х	

Table 8. I/Os configuration...continued

• IO_0 is selectable as follows:

Analog input (load dump proof) sent to the MCU through the MUX_OUT pin. Wake-up input on the rising or falling edge or based on the previous state. Digital input (logic level) sent to the MCU through the SPI.

Safety purpose: IO_0 is the only wake-up input to resume from deep fail-safe mode.

• IO_2:3 are selectable as follows:

Digital input (logic level) sent to the MCU through the SPI. Wake-up input on the rising or falling edge or based on the previous state. **Safety purpose**: Digital input (logic level) to monitor MCU error signals (both IO_2 AND IO_3 are used if configured as safety inputs). Only bi-stable protocol is available.

When IO_2:3 are used as safety inputs to monitor FCCU error outputs from the NXP MCU, the monitoring is active only when the fail-safe sate machine is in 'normal WD' state (Figure 17) and all the phases except the 'normal phase' are considered as an error.



• IO_4 is selectable as follows:

Digital input (logic level) sent to the MCU through the SPI. Wake-up input (load dump proof) on rising or falling edge or based on previous state. Output gate driver (from V_{PRE}) for low-side logic level MOSFET.

• IO_5 is selectable as follows:

Analog input (20 V max.) sent to the MCU through the MUX_OUT pin. Digital input (logic level) sent to the MCU through the SPI. Wake-up input on rising or falling edge or based on previous state. VKAM output supply.

• IO_4:5 are selectable as follows:

Safety purpose: Digital input (logic level) to perform an IC error monitoring (both IO_4 AND IO_5 are used if configured as safety inputs, see Figure 14).



11.15 SAFE output pins (FS0B, FS1B, RSTB)

11.15.1 FS0B pin

FS0B pin is the primary safe output pin. FS0B is asserted low when a fault event occurs (see <u>Section 12.5.5</u>). The objective of this pin is to drive an electrical safe circuitry independent from MCU to deactivate the whole system and set the ECU in a protected and known state.

After each power-on reset or after each wake-up event (LPOFF), the FS0B pin is asserted low. The MCU can decide to release the FS0B pin, when the application is ready to start. An external pull-up circuitry is mandatory connected to VDDIO or VSUP3.

- If the pull-up is connected to VDDIO, the value recommended is 5.0 k Ω , there is no current in LPOFF since VDDIO is off in LPOFF mode.
- If the pull-up is connected to VSUP3, the value must be above 10 kΩ, there is a current in the pull-up resistor to consider at application level in LPOFF mode.

11.15.2 FS1B pin

FS1B pin is the secondary safe output pin. FS1B is asserted low with a configurable delay (t_{DELAY}) or duration (t_{DUR}) when FS0B is asserted low (see <u>Section 12.5.6</u>). This pin can be used to:

- Open the phases of a motor after a configurable delay starting when FS0B is asserted, to demagnetize the motor coils and reduce the inductive effect when the switch is open.
- Disable an external physical layer during a configurable duration starting when FS0B is asserted, to avoid miscommunication when the module is in fail mode.
- Be a redundant safe output pin to FS0B when t_{DELAY} = 0. In this case, FS1B is asserted at the same time than FS0B.
- Any other use case where a second safety pin is needed.

After each power-on reset or after each wake-up event (LPOFF), the FS1B pin is asserted low. Then the MCU can decide to release the FS1B pin, when the application is ready to start. An external pull-up circuitry is mandatory, connected to VPU_FS or VDDIO.

11.15.3 RSTB pin

The RSTB pin must be connected to MCU and is active low. An external pull-up resistor must be connected to VDDIO. In default configuration, the RST delay time has three possible values depending on the mode and product configuration:

- The longest one is used automatically following a power-on reset or when resulting from LPOFF mode (low-power off).
- The two reset durations are then available in the INIT_FSSM register, which are 1.0 ms and 10 ms. The configured duration is finally used in the normal operation when a fault occurs leading to a reset activation. The INIT_FSSM register is available (writing) in the INIT_FS phase.

11.16 VPU_FS (fail-safe pull-up)

This pin is intended to be the pull-up terminal of FS1B, internally attached to V_{PRE} through a reverse diode protection. When FS1B is used in t_{DELAY} configuration, a configurable external RC network provides a minimum backup delay, in case of a loss of the internal fail-safe oscillator or loss of supply. This independent pull-up (compared to FS0B pull-up) avoids common cause failures between the two safe outputs and guarantee FS1B activation with a delay compared to FS0B in all conditions. When FS1B is used with $t_{DELAY} = 0$ or in t_{DUR} configuration, a pull-up to V_{DDIO} is also possible, taking into account the common cause failure with the same pull-up as FS0B in the safety analysis.

11.17 DEBUG input (entering in debug mode)

The DEBUG pin allows the product to enter debug mode. To activate the debug mode, voltage applied to the DEBUG pin must be within the $V_{DEBUG_{IL}}$ and $V_{DEBUG_{IH}}$ range at start-up. If the voltage applied to DEBUG pin is out of these limits, during the SELECT pin configuration, the device settles into normal mode.

In debug mode, the watchdog window is fully open and no watchdog refresh is required. This allows an easy debug of the hardware and software routines (i.e. SPI commands). However, the whole watchdog functionality is kept on (seed, LFSR, WD refresh counter, WD error counter,...). WD errors are detected and counted with reaction according to WD_IMPACT bit configuration. When the debug mode is activated, the fail-safe outputs (FS0B, FS1B) are asserted low at start-up. The release procedure and the assertion conditions are the same than in normal mode. When the Debug mode is activated, there is no deep fail-safe state.

The CAN transceiver is set to normal operation mode by default allowing CAN communication without SPI configuration (FS1B_CAN_IMP bit = 0). To exit debug mode, the pin must be tied to ground through an external pull-down resistor and a power-on reset or wake-up from LPOFF occurs.

12 Functional device operation

12.1 Mode and state description of the main state machine

The device has several operation modes. The transition and conditions to enter or leave each mode are illustrated in the functional state diagram (Figure 16). Two state machines work in parallel. The main state machine controls the power management (VPRE, VCORE, VCCA, VAUX,...) and the fail-safe state machine controls all the safety aspects (WD, RSTB, FS0B, FS1B,...).

12.1.1 Buck or buck boost configuration

An external low-side logic level MOSFET (N-type) is required to operate in non-inverting buck-boost converter. The connection of the external MOSFET is detected automatically during the start-up phase (after a power-on reset or from LPOFF).

- If the external low-side MOSFET is **not** connected (GATE_LS pin connected to PGND), the product is configured as a standard buck converter.
- If the external low-side MOSFET is connected (GATE_LS pin connected to external MOSFET gate), the product is configured as a non-inverting buck-boost converter.

The automatic detection is done by pushing 300 μ A current on Gate_LS pin and monitoring the corresponding voltage generated. If a voltage >120 mV is detected before the 120 μ s timeout, the non-inverting buck-boost configuration is locked. Otherwise, the standard buck configuration is locked. The boost driver has a current capability of ±300 mA.

12.1.2 V_{PRE} on

Pre-regulator is an SMPS regulator. In this phase, the pre-regulator is switched on and a soft start with a specified duration t_{PRE SOFT} controls the VPRE output capacitor charge.

12.1.3 SELECT pin configuration

This phase detects the required voltage level on VAUX and VCCA, according to the resistor value connected between the SELECT pin and Ground or VPRE, and configures the deep fail-safe function.

12.1.4 $V_{CORE}/V_{AUX}/V_{CCA}$ on

In this stage, the three regulators VCORE, VAUX, VCCA are switched on at the same time with a specified soft start duration. The CAN_5V is also started at this time.

12.1.5 INIT main

This mode is automatically entered after the device is 'powered on'. When RSTB is released, initialization phase starts where the device can be configured via the SPI. During INIT phase, some registers can only be configured in this mode (see <u>Table 19</u> and <u>Table 20</u>). Other registers can be written in this mode, and also in normal mode.

Once the INIT registers configurations are complete, a last register called 'INIT_INT' must be configured to switch to normal mode. Writing data in this register (even same default values), automatically locks the INIT registers, and the product switches automatically to normal mode in the main state machine.

12.1.6 Normal

In this mode, all device functions are available. This mode is entered by a SPI command from the INIT phase by writing in the INIT_INT register. While in normal mode, the device can be set to low-power mode (LPOFF) using secured SPI command.

12.1.7 Low-power mode off

The main state machine has three LPOFF modes with different conditions to enter and exit each LPOFF mode, as described hereafter. After wake-up from LPOFF, all the regulators are enabled by default. In LPOFF, all the regulators are switched off, except VKAM. The register configuration and the ISO pulse requirement are valid for the three LPOFF modes.

12.1.7.1 LPOFF - sleep

Entering in low-power mode LPOFF - sleep is only available if the product is in normal mode by sending a secured SPI command. In this mode, all the regulators are turned off and the MCU connected to the V_{CORE} regulator is unsupplied. Only VKAM is available if VKAM is used (specific part number for VKAM on by default).

Once the FS6500/FS4500 is in LPOFF - sleep, the device monitors external events to wake-up and leave the low-power mode. The wake-up events can occur and depending on the device configuration from:

- Physical layer (CAN or LIN)
- I/O inputs
- Timer

When a wake-up event is detected, the device starts the main state machine again by detecting the VPRE configuration (buck or buck-boost), the wake-up source is reported to the dedicated SPI register, and the fail-safe state machine is also restarted.

12.1.7.2 LPOFF - auto WU

LPOFF - auto WU is entered when the device is in the INIT or normal mode and if the V_{PRE} voltage level is passing the $V_{PRE_UV_4P3}$ threshold (typ 4.3 V). It can be also entered by sending a secured SPI command if the product is in normal mode. It allows a POR and complete restart of the fail-safe state machine. After 1.0 ms, the device attempts to recover by switching on V_{PRE} again.

12.1.7.3 LPOFF - deep FS

LPOFF - deep FS is entered when the device is in deep fail-safe and if the key is off (IO_0 is low). To exit this mode, a transition to high level on IO_0 is required. IO_0 is usually connected to the key on key off signal (see <u>Section 12.3</u>).

12.1.7.4 Register configuration in LPOFF

In LPOFF, the register settings of the main state machine are kept because the internal 2.5 V main digital regulator is available for wake-up operation. However, the register settings of the fail-safe state machine are erased because the 2.5 V fail-safe digital regulator is not available in LPOFF. As a consequence, after a wake-up event, the configuration of the fail-safe registers must be done again during initialization phase (256 ms open window).

12.1.7.5 ISO pulse in LPOFF

If the application has to sustain ISO pulses on V_{BAT} in LPOFF mode, the connection of an external Zener diode and a serial resistor to the ground is mandatory (see <u>Figure 15</u>). During repetitive ISO pulses on V_{BAT} , the capacitors connected on V_{SUP} line are more and more charged and cannot be discharged due to the extremely low-current needed to maintain wake-up capabilities on IOs, CAN, and LIN. As a consequence, if a leakage path is not created artificially with those discrete components, the voltage on V_{SUP} line can exceed the absolute maximum rating supported by this pin.


12.2 Mode and state description of fail-safe state machine

12.2.1 LBIST

Included in the fail-safe machine, the logic built-in self-test (LBIST) verifies the correct functionality of the FSSM at start-up. The fail-safe state machine is fully checked. If an issue is reported, the SAFE output pins FS0B and FS1B stays low and a flag is reported, the RSTB pin is released to allow diagnostic by the MCU. LBIST is run at start-up and after each wake-up event when the device is in LPOFF mode.

LBIST fail does not gate the RSTB pin release, but prevents the FS0B and FS1B pins release. It allows the MCU diagnostic keeping the application in a safe sate.

12.2.2 Select pin configuration

This phase detects the required voltage level to apply on VAUX and VCCA according to the resistor value connected between the SELECT pin and Ground or VPRE, and the deep fail-safe configuration. This mode is the equivalent mode seen in the main state machine. In the fail-safe machine this detection is used to internally set the UV/OV threshold on VCCA and VAUX for the voltage supervision, and to enable/disable the deep fail-safe feature.

12.2.3 ABIST

Included in the fail-safe machine, the analog built-in self-test (ABIST) verifies the correct functionality of the analog part of the device like the overvoltage and undervoltage detections of the voltage supervisor and the fail-safe outputs feedback. ABIST fail does not gate the RSTB pin release, but prevents the FS0B and FS1B pins release. It allows the MCU diagnostic, keeping the application in safe sate.

12.2.3.1 ABIST1

The first ABIST1 (<u>Table 9</u>) is always run at start-up and after each wake-up event when device is in LPOFF mode.

Table et Regulatore alla fall	ballo pillo olloolloa aalilig / E		
Parameters	Overvoltage	Undervoltage	OK/NOK
VPRE	Х		
VCORE (including FCRBM)	Х	Х	

 Table 9. Regulators and fail-safe pins checked during ABIST1

FS6500-FS4500-ASILD Product data sheet

Parameters	Overvoltage	Undervoltage	OK/NOK
VCCA	Х	Х	
RSTB			Х
FS0B			Х

Table 9. Regulators and fail-safe pins checked during ABIST1...continued

12.2.3.2 ABIST2

The second ABIST2 (Table 10) is run on demand by a SPI command from the MCU. ABIST2 must be executed and pass for FS1B and VAUX, when VAUX is declared safety critical (overvoltage and/or undervoltage have an impact on fail-safe outputs) to release the FS0B pin. Consequently, ABIST2 must be executed at start-up and after each wake-up event when device is in LPOFF mode, to release the fail-safe pin FS0B.

 Table 10. Regulators and fail-safe pins checked during ABIST2

Parameters	Overvoltage	Undervoltage	OK/NOK
VAUX	Х	Х	
FS1B			Х

12.2.4 Release RSTB

In this state, the device releases the RSTB pin.

12.2.5 INIT_FS

This mode is automatically entered after the device is 'powered on' and the built-in self-tests (logic LBIST and analog ABIST1) have been executed. This INIT_FS mode starts as soon as RSTB is released.

In this mode, the device can be configured via the SPI within a maximum time of 256 ms, including first watchdog refresh. Some registers can only be configured in this mode and is locked when leaving INIT_FS mode (see <u>Table 19</u> and <u>Table 20</u>). It is recommended, to configure the device first before sending the first WD refresh. As soon as the first good watchdog refresh is sent by the MCU, the device leaves this mode and goes into normal WD mode.

12.2.6 Normal WD

In this mode, the device waits for a periodic watchdog refresh coming from the MCU, within a specific configured window timing. Configuration of the watchdog window period can be set during INIT_FS phase or in this mode. This mode is exited if a fault occurs leading to an RSTB activation (external reset request included).

12.2.7 Assert RSTB

When the reset pin is asserted low by the device, a delay runs, to release RSTB, if there are no faults present. The reset low duration time is configurable via the SPI in the INIT_FSSM register, which is accessible for writing only in the INIT_FS phase.

12.2.8 Assert FSxB and ABIST2

These functions are executed in parallel to INIT_FS or normal WD states of the fail-safe state machine.

12.3 Deep fail-safe state

When the deep fail-safe function is enabled, the fail-safe state machine monitors and counts the number of faults happening, in case of fault detection (see <u>Section 12.5.3</u>). As soon as either the fault error counter reaches its final value or the RESET pin remains asserted low for more than 8.0 s, the device moves to deep fail-safe state in the functional state diagram (<u>Figure 16</u>).

When the device is in deep fail-safe state, all the regulators are off (except VKAM if VKAM was on), RSTB, FS0B, and FS1B are activated. To exit this state, a key off/key on action is needed. IO_0 is usually connected to key signal. Key off (IO_0 low) moves the device to LPOFF-deep FS, and key on (IO_0 high) wakes up the device.

During power up phase, the 8.0 s timer starts when the fail-safe state machine enters in the 'Wait_V_{PRE}' state and stops when the RSTB pin is released. During 'INIT_FS' state, the 8.0 s timer can be disabled in the register INIT_FS_IMPACT. During 'normal WD' state, the 8.0 s timer is activated at each RSTB pin assertion.



12.4 Functional state diagram

Figure 16. Simplified state diagram

12.5 Fail-safe machine

To fulfill safety critical applications, the FS6500/FS4500 integrates a dedicated fail-safe machine (FSM). The FSM is composed of three main sub-blocks: the voltage supervisor (VS), the fail-safe state machine (FSSM), and the fail-safe output driver (FSO). The FSM is electrically independent from the rest of the circuitry, to avoid common cause failure.

For this reason, the FSM has its own voltage regulators (analog and digital), dedicated band gap, and its own oscillator. Three power supply pins (VSUP 1, 2, and 3) are used to overtake a pin lift issue. The internal voltage regulators are directly connected on VSUP (one bonding wire per pin is used). Additionally, the ground connection is redundant as well to avoid any loss of ground.

All the voltages generated in the device are monitored by the voltage supervisor (under and overvoltage) owing to a dedicated internal voltage reference (different from the one used for the voltage regulators). The result is reported to the MCU through the SPI and delivered to the fail-safe state machine (FSSM) for action, in case of a fault. All the safety relevant signals feed the FSSM, which handles the error handling and controls the fail-safe outputs.

There are three fail-safe outputs: RSTB (asserted low to reset the MCU), FS0B, and FS1B (asserted low to control any fail-safe circuitry). The fail-safe machine is in charge of bringing and maintaining the application in a fail-safe state.

Safety power system basis chip with CAN FD and LIN transceivers



12.5.1 Fail-safe machine state diagram

12.5.2 Watchdog operation

A windowed watchdog is implemented in the FS6500/FS4500 and is based on the "question/answer" principle (challenger). The watchdog must be continuously triggered by the MCU in the open watchdog window, otherwise an error is generated. The error handling and watchdog operations are managed by the fail-safe state machine. For debugging purpose, this functionality can be inhibited by setting the right voltage on the DEBUG pin at start-up.

The watchdog window duration is selectable through the SPI during the INIT_FS phase or in normal mode. The following values are available: 1.0 ms, 2.0 ms, 3.0 ms, 4.0 ms, 6.0 ms, 8.0 ms, 12 ms, 16.0 ms, 24 ms, 32 ms, 64 ms, 128 ms, 256 ms, 512 ms, and 1024 ms. The watchdog can also be inhibited through the SPI register in INIT_FS phase to allow "reprogramming" (i.e. at vehicle level thru CAN).

An 8-bit pseudo-random word is generated by implementing a linear feedback shift register in the FS6500/ FS4500. The MCU can send the seed of the LFSR or use the LFSR generated by the FS6500/FS4500 during the INIT phase and performs a pre-defined calculation. The result is sent through the SPI during the "open" watchdog window and verified by the FS6500/FS4500. When the result is right, a new LFSR is generated and the watchdog window is restarted. When the result is wrong, the WD error counter is incremented, the watchdog window is restarted, an INTB is generated, and the LFSR value is not changed. Any access to the WD register during the "closed" watchdog window is considered a wrong WD refresh.

12.5.2.1 Normal operation (first watchdog refresh)

At power up, when the RSTB is released as high (after around 16.5 ms), the INIT phase starts for a maximum duration of 256 ms, and this is considered as a fully open watchdog window. During this initialization phase the MCU sends the seed for the LFSR, or uses the default LFSR value generated by the FS6500/FS4500 (0xB2), available in the WD_LFSR register (<u>Table 90</u>). Using this LFSR, the MCU performs a simple calculation based on this formula. As an example, the result of this calculation based on LFSR default value (0xB2) is 0x4D.



The MCU sends the results in the WD_ANSWER register (<u>Table 92</u>). When the watchdog is properly refreshed during the open window, the 256 ms open window is stopped and the initialization phase is finished. A new LFSR is generated and available in the WD_LFSR register (<u>Table 90</u>). If the watchdog refresh is wrong or if the watchdog is not refreshed during this 256 ms open window (INIT_FS phase), the device asserts the RSTB, FS0B, and the fault error counter is incremented by '1'.

After a good watchdog refresh, the device enters the Normal WD refresh mode, where open and closed windows are defined either by the configuration made during initialization phase in the WD_WINDOW register (<u>Table 88</u>), or by the default value already present in this register (3.0 ms).

12.5.2.2 Normal watchdog refresh

The watchdog must be refreshed during every open window of the window period configured in the register WD_ANSWER. Any WD refresh restarts the window. This ensures the synchronization between MCU and FS6500/FS4500.

The duration of the 'window' is selectable through the SPI with no access restriction, meaning the window duration can be changed in the INIT phase or normal mode. Doing the change in normal operation allows the system integrator to configure the watchdog window duration on the fly:

1 30300-1 343	UU-AOIL	U
Product	data	sheet

- The new WD window duration (except after disable) is taken into account when a write in the WD_ANSWER register occurs (good or bad WD answer) or when the previous WD window is finished without any writing (WD timeout).
- The new WD window duration after disable is taken into account when the SPI command is validated.

The duty cycle of the window is set to 50 % ±10 % and is not modifiable.



12.5.2.3 Watchdog in debug mode

When the device is in debug mode (entered via the DEBUG pin), the watchdog continues to operate, but does not affect the device operation by asserting a reset of the fail-safe pins. For the user, operation appears without the watchdog. If needed and to debug the watchdog itself, the user can operate as in normal mode and check LFSR values, the watchdog refresh counter, the watchdog error counter, and the reset counter. This allows the user to debug their software and ensure a good watchdog strategy in the application.

12.5.2.4 Wrong watchdog refresh handling

Error counters and strategy are implemented in the device to manage wrong watchdog refreshes from the MCU. According to consecutive numbers of wrong watchdog refreshes, the device can decide to assert the RSTB and/or FS0B pin, depending on the safety configuration set during the INIT_FS phase (WD_IMPACT bit in INIT_SF_IMPACT register, <u>Table 86</u>).

12.5.2.5 Watchdog error counter

The watchdog error counter is implemented in the device to filter the incorrect watchdog refresh. Each time a watchdog failure occurs, the device increments this counter by 2. The WD error counter is decremented by 1 each time the watchdog is properly refreshed. This principle ensures a cyclic 'OK/NOK' behavior converges to a failure detection. To allow flexibility in the application, the maximum value of this counter is configurable in the INIT_WD_CNT register, but only when device is in INIT_FS mode.

Safety power system basis chip with CAN FD and LIN transceivers



12.5.2.6 Watchdog refresh counter

The watchdog refresh counter is used to decrement the fault error counter. Each time the watchdog is properly refreshed, the watchdog refresh counter is incremented by '1'. Each time the watchdog refresh counter reaches '6' and if next WD refresh is also good, the fault error counter is decremented by '1' (case with WD_CNT_RFR_1:0 configured at 6).

Whatever the position the watchdog refresh counter is in, each time there is a wrong refresh watchdog, the watchdog refresh counter is reset to '0'. To allow flexibility in the application, the maximum value of this watchdog refresh counter is configurable in the INIT_WD_CNT register, but only when device is in INIT_FS mode.

Safety power system basis chip with CAN FD and LIN transceivers



Table 11. Watchdog error table

		Window			
		CLOSED	OPEN		
	BAD key	WD_NOK	WD_NOK		
SPI	GOOD key	WD_NOK	WD_OK		
	None (timeout)	No_issue	WD_NOK		

Any access to the watchdog register during the 'closed' watchdog window is considered as a wrong watchdog refresh. Watchdog timeout, meaning no WD refresh during closed or open windows, is considered as a wrong WD refresh.

12.5.3 Fault error counter

The fault error counter manages and counts the number of faults occurring in the application. This counter is incremented not only for the fault linked to consecutive wrong refresh watchdogs, but also for other sources of fault (undervoltage, overvoltage, external reset....).

The fault error counter is incremented by 1, each time RSTB and/or FS0B pin is asserted. When FS0B is asserted, the fault error counter is incremented by 1, every time the watchdog error counter maximum value is reached. The fault error counter has two output values (intermediate and final).

- The intermediate value can be used to force the FS0B activation or to generate a RSTB pulse depending on the FLT_ERR_IMP_1:0 bit configuration in INIT_FAULT register.
- The final value is used to handle the transition to deep fail-safe when the SELECT pin is connected to Ground. If the SELECT pin is connected to VPRE, the main state machine remains in normal mode and the regulators remain on.

The intermediate value of the fault error counter is configurable to '1' or '3' using the FLT_ERR_FS bit in the INIT_FAULT register (Table 83). The final value of the fault error counter is based on the intermediate configuration. This configuration must be done during INIT_FS phase.

Safety power system basis chip with CAN FD and LIN transceivers

- FLT_ERR_FS = 0/Intermediate = 3; Final = 6 (Figure 22).
- FLT_ERR_FS = 1/Intermediate = 1; Final = 2 (Figure 23).

In any condition, if the RSTB pin is asserted low for a duration longer than eight seconds, the device goes to:

- Deep fail-safe if the DFS function is enabled (SELECT pin connected to ground)
- LPOFF-sleep if the DFS function is disabled (SELECT pin connected to VPRE) The following faults lead to an increment of the fault error counter and can be configured:
- Watchdog error counter = max value (6 by default)
- VCORE, VCCA, VAUX undervoltage
- VCORE, VCCA, VAUX overvoltage
- FCRBM follows VCORE configuration
- IO_45 error detection (external IC error)
- The following faults lead to an increment of the fault error counter and cannot be configured:
- VPRE overvoltage
- Watchdog refresh not OK or watchdog timeout during INIT phase
- SPI DED
- ABIST1, ABIST2 fail
- RSTB short to high (by cascaded effect of FS0B assertion)
- External reset (except reset extension by MCU after reset assertion by the device)
- IO_23 error detection (FCCU)



Safety power system basis chip with CAN FD and LIN transceivers



12.5.3.1 Fault error counter intermediate value

Figure 24 illustrates the fault error counter increment when the watchdog error counter maximum value is reached.



Figure 25 illustrates the RSTB and FS0B possible behavior at the fault error counter intermediate value depending on WD_IMPACT_1:0 and FLT_ERR_IMP_1:0 bits configurations:

- #1, WD_IMPACT_1:0 = '01' and FLT_ERR_IMP_1:0 = '01': WD impact on RSTB only and FS0B is asserted low if FLT_ERR_CNT ≥ intermediate value
- #2, WD_IMPACT_1:0 = '10' and FLT_ERR_IMP_1:0 = '10': WD impact on FS0B only and RSTB is asserted low if FLT_ERR_CNT ≥ intermediate value and WD error counter = WD_CNT_ERR[1:0]

NXP Semiconductors

FS6500-FS4500-ASILD

Safety power system basis chip with CAN FD and LIN transceivers



12.5.3.2 Fault error counter at start-up or resuming from LPOFF mode

At start-up or when resuming from LPOFF mode, the fault error counter starts at level 1 and FS0B is asserted low. To release FS0B, the fault error counter must go back to a '0' value due to several consecutive good watchdog refreshes. The right command is sent to the RELEASE_FSxB register (Figure 27). With the default watchdog refresh counter configuration (WD_RFR_CNT = 6), seven consecutive good watchdog refreshes decrease the fault error counter to 0 (Figure 26).



Safety power system basis chip with CAN FD and LIN transceivers

	# WD refresh cou consecutive W	nter max value + 1 /D answers OK	# V	VD refresh cou consecutive V	inter max v VD answers	alue + 1 s OK	WD error or WD not	counter = 6 OK INIT_FS	#	WD refresh cou consecutive V	nter max value + /D answers OK	1	
Cold reset (start-up)		FS_OUT write OK	WD error counter = 6	6	FS_O write (UT WD OK count	error ter = 6	WD error of or WD not (counter = 6 OK INIT_FS			FS_C write	OK
FLT_ERR_CNT_	1	0	Ť_	1	t t	0	1	2	3	2	1	0	
RSTB													
FS0B							1						—
												aaa-0)37756
Figure 27.	Fault erro	or counter an	nd FS0B	deactiv	ation	sequence	(FLT_E	RR_FS	= 0 and	WD_CN	T_ERR =	6)	

12.5.4 RESET (RSTB) activation

The activation of RSTB depends on the fail-safe state machine configuration performed during the INIT_FS phase.

The following faults impact on RSTB activation can be configured:

- Watchdog error counter = max value (6 by default)
- VCORE, VCCA, VAUX undervoltage
- VCORE, VCCA, VAUX overvoltage
- FCRBM follows VCORE configuration
- IO_23 error detection (FCCU)
- Fault error counter level

The following faults impact on RSTB activation cannot be configured:

- VPRE overvoltage
- Watchdog refresh not OK or watchdog timeout during INIT phase
- FS0B short to high
- RSTB pulse requested by SPI

12.5.5 Fail-safe output (FS0B) activation

The activation of FS0B depends on the fail-safe state machine configuration performed during the INIT_FS phase.

The following faults impact on FS0B activation can be configured:

- Watchdog error counter = max value (6 by default)
- VCORE, VCCA, VAUX undervoltage
- VCORE, VCCA, VAUX overvoltage
- FCRBM follows VCORE configuration
- IO_23 error detection (FCCU)
- IO_45 error detection (external IC error)
- Fault error counter level

The following faults impact on FS0B activation cannot be configured:

- VPRE overvoltage
- Watchdog refresh not OK or watchdog timeout during INIT phase
- LBIST, ABIST1/2 fail
- RSTB, FS1B short to high
- · FS0B low requested by SPI

Safety power system basis chip with CAN FD and LIN transceivers

SPI DED

12.5.6 Fail-safe output (FS1B) activation

The activation of FS1B follows the activation of FS0B with a configurable delay (t_{DELAY}) or for a configurable duration (t_{DUR}).



VPU_FS is internally connected to VPRE with a reverse diode protection and protected against short-circuit by R_{VPU} FS. The R_FS1B resistor is needed to be robust against ISO 7637⁽¹⁴⁾ pulses.

12.5.6.1 t_{DELAY} operation

In t_{DELAY} configuration, FS1B is asserted low with a delay after FS0B is activated, and remains asserted until it is released by the SPI.

The delay between FS0B and FS1B activation is configurable via the SPI from 0 ms to 3150 ms with the combination of FS1B_TIME_3:0 and FS1B_TIME_RANGE bits. This digital delay is generated by the fail-safe logic with an accuracy of ± 10 %. FS1B can be activated at the same time as FS0B if t_{DELAY} = 0 or after a programmable delay if t_{DELAY} > 0 (Figure 29).



To ensure the FS1B delay is guaranteed in all system failure cases, VPU_FS pin must be used as a FS1B pullup (Figure 28).

The R_{PD}/C_{PD} components at VPU_FS provide a configurable backup delay under system failure (loss of internal fail-safe oscillator or loss of power supply). VPU_FS circuit consumption is negligible (~1.0 µA). Consequently, the external components R_{PD}/C_{PD} can be easily calculated for the desired backup delay (Figure 30).



R_{PD}/C_{PD} calculation:

- $R_{TOT} = R_{INT} // R_{PD}$ with $R_{INT} = 1.0 \text{ M} \pm 50 \%$
- $V_{PU_FS} = [(V_{PRE} V_{DIODE}) \times R_{TOT}/(R_{TOT} + R_{VPU_FS})]$
- $V_{PU_{FS_{TH}}} = V_{PU_{FS}} \times e(-t_{DELAY}/R_{TOT}C_{PD})$
- $t_{\text{DELAY}} = -R_{\text{TOT}}C_{\text{PD}} \times \text{Ln} (V_{\text{PU}_{\text{FS}}\text{TH}}/V_{\text{PU}_{\text{FS}}})$

<u>R_{PD}/C_{PD} typical use case:</u>

- t_{DELAY} = 33 ms, V_{PU_FS_TH} = 3.2 V, V_{PU_FS} = 5.5 V
- R_{PD} = 16 KΩ, C_{PD} = 3.3 μF

The switch S1 is opened by default and must be closed by a SPI command, due to the FS1B_DLY_REQ bit in the SF_OUTPUT_REQUEST register, before releasing the FS1B pin. V_{PU_FS} rise time is limited by the time constant of $R_{VPU_FS} \times C_{PD}$ 95 % of V_{PU_FS} is reached after 3 x $R_{VPU_FS} \times C_{PD}$ = 15 ms. It is recommended to select high R_{PD} resistor value to be negligible versus R_{VPU_FS} and low C_{PD} capacitor value to reduce V_{PU_FS} rising time.

The external R_{PD}/C_{PD} components connected to VPU_FS are used to generate an FS1B backup delay. This backup delay can be verified at the application level to cover latent faults on these components, by opening the internal switch connecting VPRE to VPU_FS with the FS1B_DLY_REQ bit in the SF_OUPUT_REQ register (FS0B must be asserted first). The backup delay accuracy depends only on external component accuracy.

12.5.6.2 t_{DURATION} operation

In t_{DURATION} configuration, FS1B is asserted low at the same time as FS0B for a configurable duration, and is automatically released after t_{DURATION} timing (Figure 31). The FS1B activation duration is configurable via the SPI from 0 ms to 3150 ms with the combination of the FS1B_TIME_3:0 and FS1B_TIME_RANGE bits. This digital duration is generated by the fail-safe logic with an accuracy of ±10 %.



12.5.7 Fail-safe outputs (FS0B and FS1B) release

When the fail-safe outputs FS0B and consequently FS1B are asserted low by the device due to a fault, some conditions must be validated before allowing these pins to be released by the device. These conditions are:

- ABIST2_FS1B_OK=1 if part number with FS1B
- ABIST2_VAUX_OK=1 except if VAUX_FS_OV_1:0=VAUX_FS_UV_1:0="00"
- Fault is removed
- Fault error counter must be at '0'
- Close the S1 switch if FS1B backup delay was engaged (FS1B_DLY_DRV bit = 1)
- RELEASE_FSxB register must be filled with the right value

12.5.7.1 RELEASE_FSxB register

When a fault is removed and the fault error counter changes back to level '0', a right word must be filled in the RELEASE_FSxB register. The value depends on the current WD_LFSR. LSB, MSB must be swapped, and a negative operation per bit must be applied.

FS0B and FS1B can be released independently or at the same time, depending on the configuration of the first three bits of the RELEASE_FSxB register (<u>Table 12</u>). The RELEASE_FSxB write command should be done after a WD_LFSR read command. If FS0B and FS1B are released sequentially, the procedure must be done a first time for FS0B, and a second time for FS1B.

	WD_LFSR_7:0	b7	b6	b5	b4	b3	b2	b1	b0
Release FS0B	RELEASE_FSxB_7:0	0	1	1	b0	b1	b2	b3	b4
Release FS1B	RELEASE_FSxB_7:0	1	1	0	b3	b4	b5	b6	b7
Release FS0B and FS1B	RELEASE_FSxB_7:0	1	0	1	b0	b1	b2	b6	b7

Table 12. RELEASE_FSxB register based on LFSR value

12.5.8 SPI DED

Some SPI registers affect some safety critical aspects of the fail-safe functions, and therefore are required to be protected against SEU (single event upset). Only fail-safe registers are concerned. During INIT_FS mode, access to fail-safe registers for product configuration is open. Once the INIT_FS phase is over, the Hamming circuitry is activated to protect registers content.

At this stage, if there is one single bit flip, the detection is made due to Hamming code, the error is corrected automatically (fully transparent for the user), and a flag is sent. If there are two errors (DED - dual error detection), the detection is made due to Hamming code but detected errors cannot be corrected. The flag is sent and FS0B is activated.

12.6 Input voltage range

Due to the flexibility of the pre-regulator, the device can cover a wide battery input voltage range. However, a more standard voltage range can still be covered using only the buck configuration.



V_{SUP} > 28 V: Potential V_{PRE} thermal limitation

 $R_{DS(on)}$, Current limitation and overcurrent detection are specified for V_{SUP} < 28 V.

• V_{SUP} > 19 V: MUX_OUT limitation

 V_{SENSE} and IO_0 maximum analog input voltage range is 19 V. Internal 2.5 V reference voltage accuracy degraded.

• Buck only, V_{SUP} < V_{SUP_UV_7}:

CAN communication is guaranteed for $V_{SUP} > 6.0 \text{ V}$. LIN communication stopped when $V_{SUP} < 7.0 \text{ V}$ if LIN_J2602_DIS bit is not set. For V_{CCA} and V_{AUX} 5.0 V configuration, undervoltage triggers at low V_{SUP} (See <u>Section 9</u>, $V_{CCA_UV_5}$ and $V_{AUX_UV_5}$).

12.7 Power management operation

A thermal sensor is implemented as close as possible to the pass transistor of each regulator (V_{PRE} , V_{CORE} , V_{CCA} , V_{CAN}) and an associated individual thermal shutdown (T_{SD}) protects these regulators independently. When the T_{SD} threshold of a specific regulator is reached, this regulator only is switched off and the information

FS6500-FS45	00-ASIL	D
Product	data	sheet

is reported in the main state machine. The regulator restarts automatically when the junction temperature of the pass transistor decrease below the T_{SD} threshold.

12.7.1 VPRE voltage pre-regulator

A highly flexible SMPS pre-regulator is implemented in the FS6500/FS4500. Depending on the input voltage requirement, the device can be configured as 'non-inverting buck-boost converter' (Figure 34) or 'standard buck converter' (Figure 33). An external logic level MOSFET (N-type) is required to operate in 'non-inverting buck-boost converter'. The connection of the external MOSFET is detected automatically during the start-up phase.

The converter operates in current control mode in any configuration. The high-side switching MOSFET is integrated to make the current control easier. The PWM frequency is fixed at a typical 440 kHz. The compensation network is fully integrated. The V_{PRE} output voltage is regulated between 6.0 V and 7.0 V.

If the full current capability is not used for VCORE, VCCA, VAUX, and CAN_5V, an additional external LDO can be connected to VPRE to fulfill application needs, while the current load remains below the maximum current capability in all conditions.



Figure 33. Pre-regulator: buck configuration



When the converter is set up to work in boost mode at low V_{SUP} , the transition between buck and boost mode is automatically handled by the device at the $V_{SUP_UV_7}$ threshold. Transition between buck mode and boost mode is based on hysteresis (Figure 35).

- When VSUP > $V_{SUP_UV_7}$, the converter works in buck mode and the VPRE output is regulated at 6.5 V typ.
- When VSUP < V_{SUP_UV_7}, the converter works in boost mode and the VPRE output is regulated at 6.3 V typ.



12.7.1.1 Power up and power down sequence



Safety power system basis chip with CAN FD and LIN transceivers



12.7.1.2 Cranking management

When VPRE is set up to work in buck only mode, the application can work down to VSUP = $V_{SUP_UV_L_B}$ = 4.5 V with a minimum of 500 mA current guaranteed on VPRE.



When VPRE is set up to work in buck-boost mode, the application can work down to VSUP = $V_{SUP_UV_L}$ = 2.7 V with a minimum of 300 mA current guaranteed on VPRE. The buck-boost configuration helps to pass the LV124 specification requiring a minimum of 3.2 V on V_{BAT} supply during cold cranking conditions.



12.7.1.3 Light load condition

To improve the converter efficiency and avoid any unwanted output voltage increase, the VPRE voltage regulator operates in pulse skipping mode during light load conditions.

The transition between normal mode and pulse skipping mode is based on the comparison between the error amplifier output (EA_out) and pre-defined thresholds $V_{PRE_LL_H}$ and $V_{PRE_LL_L}$. When the error amplifier output reaches $V_{PRE_LL_L}$, the VPRE high-side transistor is switched off. When the error amplifier output reaches $V_{PRE_LL_L}$, the VPRE high-side transistor is switched on again for the next switching period (Figure 40).



12.7.1.4 Input power feed forward condition

To improve the converter efficiency during high input power conditions, the VPRE switching frequency is reduced from 440 kHz to 220 kHz, when VSUP > V_{SUP_IPFF} , to decrease the switching losses. The transition between the two frequencies is transparent for the application.



12.7.1.5 Overcurrent detection and current limitation

12.7.1.5.1 Overcurrent protection:

To ensure the integrity of the high-side MOSFET, an overcurrent detection is implemented. The regulator is switched off by the main state machine when the I_{PRE_OC} overcurrent detection threshold is reached three consecutive times. The overcurrent detection is blanked when the pass transistor is switched on during t_{PRE_OC} to avoid parasitic switch off of the high-side gate driver.

The VPRE output voltage decrease causes an undervoltage condition on one of the cascaded regulators (VCORE, VCCA, VAUX) and brings the device into fail-safe state. The overcurrent protects the regulator in case the SW_PRE pin is shorted to GND. The overcurrent works in buck mode only.

12.7.1.5.2 Current limitation:

A current limitation is also implemented to avoid uncontrolled power dissipation inside the device (duty cycle control) and limits the current. VPRE current limitation is automatically set based on the buck or buck-boost configuration. In buck only mode, the lowest current limitation I_{PRE_LIM2} is applied while in buck-boost mode, the highest current limitation I_{PRE_LIM1} is applied. The current limitation is blanked when the pass transistor is switched on during $t_{PRE_BLK_LIM1}$ to allow short-circuit detection on the SW_PRE pin.

When I_{PRE_LIM} threshold is reached during buck mode, the high-side integrated MOSFET is switched off. When the I_{PRE_LIM} threshold is reached during boost mode, the external low-side MOSFET is switched off. In both cases, the MOSFET is not switched on again before the next rising edge of the switching clock.

The current limitation induces a duty cycle reduction and leads to the VPRE output voltage gradually dropping, which may cause an undervoltage condition on one of the cascaded regulators (VCORE, VCCA, VAUX) and bring the device to the fail-safe state. The current limitation does not switch off the regulator. The current limitation protects the regulator when the VPRE pin is shorted to GND.

Safety power system basis chip with CAN FD and LIN transceivers



12.7.1.6 VPRE voltage monitoring

The overvoltage detection switches off the regulator. The undervoltage detector is disabled when the regulator is switched off, reporting an undervoltage. Diagnostic is reported in the dedicated register and generates an Interrupt. The undervoltage detection does not switch off the regulator. However, V_{PRE} decrease may induce an undervoltage on a regulator attached to V_{PRE} (VCORE, VCCA, VAUX, or CAN_5V), and bring the application in fail-safe state depending on the supervisor configuration (registers INIT_VCORE_OVUV_IMPACT, INIT_VCCA_OVUV_IMPACT, INIT_VAUX_OVUV_IMPACT).

12.7.1.7 VPRE efficiency

VPRE efficiency versus current load is given for information based on typical external component criteria described in Figure 43, close to the graph and at typical automotive V_{SUP} voltage(14 V). The efficiency is valid in buck mode only and above a 200 mA load on VPRE, to be in continuous mode on the 22 µH inductor. The efficiency is calculated and has to be verified by measurement at the application level.

Safety power system basis chip with CAN FD and LIN transceivers



12.7.2 VCORE voltage regulator

This voltage regulator is a step-down DC–DC converter in the FS6500 series and a linear regulator in the FS4500 series.

12.7.2.1 VCORE DC–DC converter

The FS6500 voltage regulator is a step-down DC–DC converter operating in voltage control mode. The highside switching MOSFET, connected to VPRE, is integrated in the device, and the PWM frequency is fixed at 2.4 MHz typical. The output voltage is configurable from a 1.0 V to 5.0 V range, and adjustable around these voltages with an external resistor divider (R3/R4) connected between VCORE and the feedback pin (FB_CORE) (Figure 44). V_{CORE} = V_{CORE FB} x ((R3 + R4)/R4).

The voltage accuracy is ± 2.0 % (without the external resistor bridge R3/R4 accuracy) and the max output current is 2.2 A. The stability of the overall converter is done by an external compensation network (R1/C1/R2/C2) connected to the pin COMP_CORE. It is recommended to use 1.0 % accuracy resistors and set R4 = 8.06 k Ω and adjust R3 to obtain the final V_{CORE} voltage needed for the MCU core supply.



12.7.2.2 Light load condition

To improve the converter efficiency and avoid any unwanted output voltage increase, the VCORE voltage regulator operates in pulse skipping mode during light load conditions. The principle is the same as the VPRE implementation described in detail in <u>Section 12.7.1.3</u>.

12.7.2.3 Current limitation

A current limitation is implemented to avoid uncontrolled power dissipation inside the device (duty cycle control) and limits the current below I_{CORE_LIM} . The current limitation is banked when the pass transistor is switched on during $t_{CORE_BLK_LIM}$ to avoid parasite detection. When the I_{CORE_LIM} threshold is reached, the high-side integrated MOSFET is switched off. The MOSFET is not switched on again before the next rising edge of the switching clock.

The current limitation induces a duty cycle reduction and leads to the VCORE output voltage to fall gradually and may cause an undervoltage condition, bringing the device into a fail-safe state. The current limitation does not switch off the regulator.

12.7.2.4 Voltage monitoring

The overvoltage detection switches off the regulator. The regulator remains on during an undervoltage detection. Diagnostic is reported in the dedicated register, generates an interrupt, and may bring the application into the fail-safe state, depending on the supervisor configuration (register INIT_VCORE_OVUV_IMPACT).

For safety purposes, the FCRBM pin monitors the external resistor bridge (R3/R4) used to set up the final V_{CORE} voltage through a second resistor bridge (R3b/R4b) to detect an external resistor drift or disconnection. The monitoring compares the FB_CORE and FCRBM pins (Figure 45) and triggers when FB_CORE – FCRBM > ±150 mV max.



If the second resistor bridge (R3b/R4b) is not mounted, FCRBM must be connected directly to FB_CORE to satisfy FB_CORE = FCRBM in all conditions.

12.7.2.5 V_{CORE} efficiency

 V_{CORE} efficiency versus current load is given for information based on typical external component criteria described in <u>Figure 46</u>, close to the graph and at three typical V_{CORE} voltages (5.0 V, 3.3 V, and 1.2 V), covering most of the MCU supply ranges. The efficiency is valid above a 200 mA load on V_{CORE} to be in continuous mode in the 2.2 µH inductor. The efficiency is calculated and has to be verified by measurement at the application level. One major contributor degrading the efficiency at V_{CORE} = 1.2 V is the external diode during the recirculation phase. The lower the diode forward voltage (V_E) is, the better the efficiency.



12.7.2.6 VCORE linear regulator

The FS4500 voltage regulator is a linear regulator. The pass device, connected to VPRE, is integrated. The output voltage range is configurable from 1.0 V to 5.0 V, and adjustable around these voltages with an external resistor divider (R3/R4) connected between V_{CORE} and the feedback pin (FB_CORE) (see Figure 47). $V_{CORE} = V_{CORE, FB} x$ ((R3 + R4)/R4).

The voltage accuracy is ±2.0 % (without the external resistor bridge R3/R4 accuracy) and the max. output current is 0.5 A. In this case, the BOOT_CORE and COMP_CORE pins (used in buck converter mode only)

FS6500-FS4500-ASILD	All information provided in this document is subject to legal disclaimers.
Product data sheet	Rev. 8 — 5 August 2024

must be left open. It is recommended to use 1.0 % accuracy resistors and set R4 = 8.06 k Ω and adjust R3 to obtain the final V_{CORE} voltage needed for the MCU core supply. When VCORE is used in linear mode, the power dissipation must be taken into account at low-voltage.



12.7.2.7 Current limitation

Similar to the buck converter mode, a current limitation is implemented to avoid uncontrolled power dissipation inside the device (see <u>Section 12.7.2.3</u>).

12.7.2.8 Voltage monitoring

The linear regulator has the same voltage monitoring than the DC–DC buck converter (see Section 12.7.2.4).

12.7.3 Charge pump and bootstrap

Both switching MOSFETs of VPRE and VCORE SMPS are driven by external bootstrap capacitors. Additionally, a charge pump is implemented to ensure 100 % duty cycle for both converters. Each converter uses a 100 nF external capacitor minimum to operate properly.

12.7.4 VCCA voltage regulator

VCCA is a linear voltage regulator mainly dedicated to supply the MCU I/Os, especially the ADC. The output voltage is selectable at 5.0 V, or 3.3 V. Since this output voltage can be used to supply MCU I/Os, the output voltage selection is done using an external resistor connected to the SELECT pin and ground or VPRE. When VCCA is used with the internal MOS transistor, the VCCA_E pin must be connected to VPRE. The voltage accuracy is ± 1.0 % for 5.0 V and 3.3 V configuration with an output current capability at 100 mA.

When VCCA is used with an external PNP transistor to boost the current capability up to 300 mA, the connection is detected automatically during the start-up sequence of the FS6500/FS4500. In such condition, the internal pass transistor is switched off and all the current is driven through the external PNP to reduce the internal power dissipation. The output voltage accuracy with an external PNP is reduced to ± 3.0 % at 300 mA current load. The VCCA output voltage is used as a reference for the auxiliary voltage supply (V_{AUX}) when VAUX is configured as a tracking regulator.

12.7.4.1 Current limitation

A current limitation is implemented to avoid uncontrolled power dissipation of the internal MOSFET or external PNP transistor. By default, the current limitation threshold is selected based on the auto detection of the external PNP during start-up phase.

- When the internal MOSFET transistor is used, the current is limited to I_{CCA LIM INT} and the regulator is kept on
- When the external PNP transistor is used, the current is limited to I_{CCA_LIM_OUT} and the regulator is switch off after a dedicated duration t_{CCA_LIM_OFF} under current limitation. A SPI command is needed to restart the regulator.

In case of an external PNP configuration only, the lowest current limitation threshold can be selected by the SPI in the register INIT_VREG instead of the highest one. A current limitation foldback scheme is implemented to reduce the current limitation to $I_{CCA_LIM_FB}$ when VCCA is below $V_{CCA_LIM_FB}$, limiting the power dissipation in the external PNP transistor during a short-circuit to GND of the VCCA pin.

12.7.4.2 Voltage monitoring

The overvoltage detection switches off the regulator. The regulator remains on if an undervoltage is detected. A diagnostic is reported in the dedicated register, generating an Interrupt and may bring the application into fail-safe state, depending on the supervisor configuration (register INIT_VCCA_OVUV_IMPACT).

12.7.5 VAUX voltage regulator

VAUX is a highly flexible linear voltage regulator, which can be used either as an auxiliary supply dedicated to additional device in the ECU or as a sensor supply (i.e. outside the ECU). An external PNP transistor must be used (no internal current capability).

If VAUX is not used in the application, the VAUX, VAUX_E, and VAUX_B pins must be left open. It is recommended to turn the V_{AUX} driver off and disable the V_{AUX} safety impact by the SPI (VAUX_EN=0 in REG_MODE register and all bits of INIT_VAUX_OVUV_IMPACT register at 0).

If VAUX is used as an auxiliary supply, the output voltage is selectable between 5.0 V and 3.3 V. Since this voltage rail can be used to supply MCU IOs, the selection is done with an external resistor connected between the SELECT pin and ground or VPRE. In such case, the voltage accuracy is ± 3.0 %, with a maximum output current capability of 400 mA.

If VAUX is used as a sensor supply rail, the output voltage is selectable between 5.0 V and 3.3 V. VCCA can be used as reference for the sensor supply used as tracker. In this case, the V_{AUX} voltage must match V_{CCA}, limiting the resistor configuration at the SELECT pin to 5.1 k Ω (V_{AUX} = V_{CCA} = 3.3 V) and 12 k Ω (V_{AUX} = V_{CCA} = 5.0 V). The tracker mode selection is done during the INIT phase and secured (bit VAUX_TRK_EN in the INIT_VREG register). The tracking accuracy is ±15 mV.

Safety power system basis chip with CAN FD and LIN transceivers



12.7.5.1 Current limitation

A current limitation is implemented to avoid uncontrolled power dissipation of the external PNP transistor. The current is limited to I_{AUX_LIM} and the regulator is switch off after a dedicated duration $t_{AUX_LIM_OFF}$ under current limitation. A SPI command is needed to restart the regulator. A current limitation foldback scheme is implemented to reduce the current limitation to $I_{AUX_LIM_FB}$ when V_{AUX} is below $V_{AUX_LIM_FB}$, limiting the power dissipation in the external PNP transistor during a short-circuit to GND of the VAUX pin.



12.7.5.2 Voltage monitoring

The overvoltage detection switches off the regulator. The regulator remains on if an undervoltage is detected. A diagnostic is reported in the dedicated register, generating an interrupt and may bring the application into the fail-safe state, depending on the supervisor configuration (register INIT_VAUX_OVUV_Impact).

12.7.6 CAN_5V voltage regulator

The CAN_5V voltage regulator is a linear regulator fully dedicated to the internal CAN interface. By default, the CAN_5V regulator and the undervoltage detector are enabled and the overvoltage detector is disabled. The overvoltage detector can be enabled by the SPI during INIT_MAIN state.

If the overvoltage detector is enabled, the CAN_5V regulator switches off when an overvoltage is detected. The undervoltage detector is disabled when the regulator is switched off reporting an undervoltage. A diagnostic is reported in the dedicated register, generating an Interrupt. The CAN_5V regulator is not a safety regulator. Consequently, the CAN_5V voltage monitoring (overvoltage, undervoltage) never asserts the RSTB or FS0B fail-safe pins.

If the FS6500/FS4500 internal CAN FD transceiver is not used in the application, the CAN_5V regulator can be used to supply an external standalone CAN or FLEX–RAY transceiver, provided the current load remains below the maximum current capability in all conditions. In this case, the internal CAN FD transceiver must be put into sleep mode without wake-up capability.

12.7.7 VKAM

The keep alive memory supply is shared with IO_5 pin. When VKAM is used, IO_5 is not available and vice versa. Depending on the part number selection (Section 5.2), VKAM can be on or off by default.

- If VKAM is on by default, VKAM starts as soon as VSUP3 is > 4.5 V. VKAM can still be turned off/on by the SPI.
- If VKAM is off by default, VKAM is turned on/off by the SPI.



Figure 50. VKAM start-up strategy

VKAM is the only supply available in low-power mode (LPOFF). VKAM can be used to supply the MCU static RAM or any other external IC which does not exceed the current capability. A current limitation is implemented. Neither voltage monitoring, nor thermal shutdown are implemented. VKAM can be selected at the MUX_OUT pin to be monitored by the MCU ADC. The VKAM supply is available down to $V_{SUP} = V_{SUP_UV_L} = 2.7 V$ when the device is in normal mode, and down to $V_{SUP} = 4.5 V$ when the device is in low-power mode off.

Safety power system basis chip with CAN FD and LIN transceivers

12.7.8 Power dissipation

The FS6500/FS4500 provides high performance SMPS and linear regulators to supply high end MCUs in automotive applications. Each regulator can deliver:

- V_{PRE} (6.5 V) up to 2.0 A
- V_{CORE} (from 1.0 V to 5.0 V range) up to 2.2 A
- V_{CCA} (3.3 V or 5.0 V) up to 100 mA (with internal MOS) or up to 300 mA (with external PNP)
- V_{AUX} (3.3 V or 5.0 V) up to 400 mA (with external PNP)
- V_{CAN} (5.0 V) up to 100 mA

A thermal dissipation analysis has to be performed based on the application use case to ensure the maximum silicon junction temperature does not exceed 150 °C.

Two use cases covering the two main V_{CORE} voltage configurations are provided in Figure 51.

- use case 1: V_{CORE} = 3.3 V, I_{CORE} = 0.7 A, V_{CCA} with int. MOS
- use case 2: V_{CORE} = 1.2 V, I_{CORE} = 1.4 A, V_{CCA} with ext. PNP

Both use cases have a total internal power dissipation below 0.9 W. A junction to ambient thermal resistivity of 30 °C/W allows the application to work up to an ambient temperature of 125 °C. A good soldering of the package expose pad is highly recommended to achieve such thermal performance.



FS6500-FS4500-ASILD Product data sheet

0.03

0.07

0.09

0 11

I_{CCA} (A) aaa-037781

The main contributors to the device power dissipation are the VPRE, VCORE, and VCCA (when used with an internal PMOS) regulators. In comparison, the power dissipation from the Internal IC, VAUX, and CAN transceiver are negligible. VPRE power dissipation is mainly induced by the loading of the regulators it is supplying, mainly V_{CORE}, V_{CCA}, and V_{AUX} which are application dependent. The total device power dissipation, depending on the variation of these three regulators, is detailed in Figure 52 with the environmental conditions in the associated table.



Figure 52. Power dissipation versus I_{CORE}, I_{CCA}, or I_{PRE}

06

08

10

12

14

I_{CORE} (A)

16

04

12.7.9 Start-up sequence

02

To provide a safe and well known start-up sequence, the FS6500/FS4500 includes an undervoltage lockout. This V_{SUP UV 5} undervoltage lockout applies when the device is under a power-on reset condition or released from LPOFF. All the different voltage rails start automatically as described in Figure 53.

FS6500-FS4500-ASILD

2.0

NXP Semiconductors

FS6500-FS4500-ASILD

Safety power system basis chip with CAN FD and LIN transceivers



Figure 53. Start-up scheme

The final value of V_{AUX} and V_{CCA} depends on the hardware configuration (resistor values at the SELECT pin). The typical start-up sequence takes around 16.5 ms to release RSTB. RSTB can be pulled low after those 16.5 ms by the MCU, if it is not ready to run after power up. See <u>Section 12.7.7</u> for the VKAM start-up sequence.

12.8 Long duration timer

The device includes a long duration timer, with an integrated oscillator. The timer is configurable by the SPI and can operate in normal mode and low-power mode. It provides several functions and offers a large range of counting periods, as well as a calibration mechanism, for internal oscillator compensation.

The timer is not part of the safety circuitry, and is not covered by LBIST (logic built in self-test). However it can be activated in normal mode, and all prescaler options can be selected, to allow timer circuitry verification. The timer is based on a 24-bit counter, with a 32768 Hz oscillator, allowing a 1.0 s timebase.



12.8.1 Timer characteristics

In normal operation, the timer can count up to 194 days, with 1 second resolution. In calibration mode, the prescaler 2 is bypassed and the timer can count up to 2.28 hours, with 488 μ s resolution. The calibration principle consists in activation of the counter for a dedicated and accurate duration, due to the MCU accurate clock and timing. The MCU then reads back the timer count, compares the count versus the accurate time of activation, then calculates a time offset. It is recommended to perform the calibration between -20 °C and +85 °C.

Table 1	13	long	duration	timer	characteristics
Ianic	13.	LONG	uuration	uniei	characteristics

	Osc freq	Osc period	Prescaler	Counter resolution	Max o	count
Operation	32768 Hz	30.52 µs	16 x 2048	1 s	4660 Hrs	194 days
Calibration	32768 Hz	30.52 µs	16	488 µs	8192 s	2.28 Hrs

12.8.2 Calibration procedure

The calibration procedure consists of activating the counter for a specific duration and comparing the result with the MCU's accurate clock and timing. Once the timer expires, the MCU reads back its final value to compare with its own accurate time of activation and to calculate a time offset. NXP recommends performing the calibration between -20 °C and 85 °C.

Calibration example:

- Select the timer function 1 and set the after run value to 65535 (~32 s).
- Start the counter.
- Read the counter when the MCU RTC reaches 20 s (must be less than 30 s with ±5.0 % oscillator accuracy).
- If the oscillator period is at exact typical value (absolutely no deviation error), expected reading is 40960.
- The exact reading calculates the error correction factor ECF = exact_reading/expected_reading.
- ECF < 1 if the oscillator is faster than the exact typical value.
- ECF > 1 if the oscillator is slower than the exact typical value.

• After calibration, the new after run or wake-up values to set the counter are "after run x ECF" and "wake-up x ECF".

12.8.3 Timer functions

- Function 1: In normal mode, count and generate a flag or an Interrupt when the counter reaches the after run value.
- Function 2: In normal mode, count until the counter reaches the after run value and enters into low-power mode.
- Function 3: In normal mode, count until the counter reaches the after run value and enters into low-power mode. Once in low-power mode, count until the counter reaches the wake-up value and wakes up.
- Function 4: In low-power mode, count until the counter reaches the wake-up value and wakes up.
- Function 5: In low-power mode, count and do not wake-up unless the counter overflow occurs, or if the device wakes up by another source (CAN, LIN, IO).

FUNCTIONS	NORMAL MODE	LOW-POWER MODE (LPOFF)
Function 1 SPI: configure timer function 1 SPI: write after run register SPI: write START INTB when after run value reached	timer counts / → → / After run value reached INTb	No entry in low-power mode controlled by LDT
Function 2 SPI: configure timer function 2 SPI: write after run register SPI: write START Entry in LPOFF after run value reached	timer counts After run value reached	Entry in low-power mode when after run value reached
Function 3 SPI: configure timer function 3 SPI: write after run register SPI: write wake-up register SPI: write START Entry in LPOFF after run value reached and wake-up when wake-up value reached	timer counts After run value reached Entry in init mode after wake-up by timer ←	I Entry in low-power mode when after run value reached timer counts Wake-up value reached Make-up value reached Make-up value reached Make-up value reached
Function 4 SPI: configure timer function 4 SPI: write wake-up register SPI: go to LPOFF Wake-up when wake-up value reached	Entry in init mode after wake-up by timer ←	Entry in low-power mode by SPI Wake-up timer counts value reached WAKE-UP
Function 5 SPI: configure timer function 5 SPI: go to LPOFF Wake-up when other wake-up event occurs (ex CAN)	Entry in init mode after CAN wake-up ↓ timer continues to count	Entry in low-power mode by SPI timer counts WAKE-UP (ex CAN)

Figure 55. Long duration timer functions

12.8.4 Timer operation

The timer is configured and operates with the LONG_DURATION_TIMER register. The 16-bit after-run value and the 24-bit wake-up value are configured and read in the corresponding registers.

<u>Figure 56</u> describes the independent state machine of long duration timer (LDT). After a POR of the device, the LDT is in idle mode waiting for configuration. The after-run timer function starts when the LDT_ENABLE bit is set by SPI. The wake-up timer function starts when the device enters in LPOFF mode.

- When function 1 is selected and the counter reaches the after run value (EOT), an interrupt is generated and the counter is stopped. The counter must be disabled (~ENABLE) before reading its value and enabled again.
- When function 2 is selected and the counter reaches the after run value (EOT), the device goes to LPOFF mode and the counter is stopped. The counter must be disabled (~ENABLE) before reading its value and enabled again.
- When function 3 is selected and the counter reaches the after run value (EOT), the device goes to LPOFF mode. The counter is reset and restart to count. When the counter reaches the wake-up value (EOT), the device wakes up and the counter is stopped. The counter must be disabled (~ENABLE) before reading its value and enabled again.
- When function 4 is selected and the counter reaches the wake-up value (EOT), the device wakes up and the counter is stopped. The counter must be disabled (~ENABLE) before reading its value and enabled again.
- When function 5 is selected and the counter overflows (OVRFLW), the device wakes up and the counter is stopped. The counter must be disabled (~ENABLE) before reading its value and enabled again. Overflow means counter max value is reached (all 24 bits at logic 1).
- When function 5 is selected and the devices wakes up by CAN, LIN, or IO, the counter is running. The counter must be disabled (~ENABLE) before reading its value and enabled again.



12.9 CAN transceiver

The CAN (controller area network) transceiver provides the physical interface between the CAN protocol controller of an MCU and the physical dual wires CAN-bus. The FS6500/FS4500 integrated CAN interface is compliant with flexible data standard at 2.0 Mbit/s. It offers excellent EMC and ESD performance, and meets the ISO 11898-2⁽¹²⁾ and ISO 11898-5⁽¹³⁾ standards.

FS6500-FS4500-ASILD Product data sheet
Safety power system basis chip with CAN FD and LIN transceivers



12.9.1 Operating modes

12.9.1.1 Normal mode

When the CAN mode bit configuration is '11' (CAN in normal operation), the device is able to transmit information from TXD to the bus and report the bus level to the RXD pin. When TXD is high, CANH and CANL drivers are off and the bus is in the recessive state (unless it is in an application where another device drives the bus to the dominant state). When TXD is low, the CANH and CANL drivers are on and the bus is in the dominant state. When the CAN mode bit configuration is '01' (CAN in listen only), the device is only able to report the bus level to the RXD pin. The TXD driver is off and the device is not able to transmit information from TXD to the bus. TXD is maintained high by an internal pull-up resistor TXD_{PULL-UP} connected to VDDIO.

Safety power system basis chip with CAN FD and LIN transceivers



12.9.1.2 Sleep mode

When the device is in LPOFF mode, the CAN transceiver is automatically set in sleep mode with or without wake-up capability, depending on the CAN mode bit configuration. In this case, the CANH and CANL pins are pulled down to GND via the internal R_{IN} resistor, the TXD and RXD pins are pulled to GND, and both driver and receiver are off. The CAN mode is automatically changed to sleep with wake-up capability if not configured to sleep without wake-up capability when the device enters is LPOFF. After LPOFF, the initial CAN mode prior to enter LPOFF is restored (Figure 59).

CAN sta	ate before entering LPOFF	CA	AN state after LPOFF	CAN state after entering LPOFF		
CAN_mode [1:0]	CAN state	CAN_mode [1:0]	CAN state	CAN_mode [1:0]	CAN state	
00	Sleep, no wake-up capability	00	Sleep, no wake-up capability	00	Sleep, no wake-up capability	
01	Listen only			01	Listen only	
10	Sleep, wake-up capability	10	Sleep, wake-up capability	10	Sleep, wake-up capability	
11	Normal			11	Normal	

Figure 59. CAN transition when device goes to LPOFF

12.9.2 Fault detection

12.9.2.1 TXD permanent dominant (timeout)

If TXD is set low for a time longer than t_{DOUT} , the CAN drivers are disabled and the CAN-bus returns to the recessive state. The CAN receiver continues to operate. This prevents the bus to be set in the dominant state permanently in case a failure sets the TXD input to a permanent low level.

The CAN_MODE MSB bit is set to 0 and the flag TXD_dominant is reported in the DIAG_CAN_1 register. The device recovers from this error detection after setting the CAN_MODE to normal operation and when a high level is detected on TXD. The TXD failure detection is operating when the CAN transceiver is in normal mode and listen only mode.

FS6500-FS4500-ASILD								
Product of	data sh	eet						



12.9.2.2 RXD permanent recessive

If RXD is detected high for seven consecutive receive/dominant cycles, the CAN drivers and receiver are disabled and the CAN-bus returns to the recessive state. This prevents a CAN protocol controller from starting a CAN message on the TXD pin, while RXD is shorted to a recessive level and seen from a CAN controller as a bus idle state.

The CAN_MODE MSB bit is set to 0 and the flag RXD_REC is reported in the DIAG_CAN_1 register. The device recovers from this error detection after setting the CAN_MODE to normal operation. The RXD failure detection is operating when the CAN transceiver is in normal mode and listen only mode.

12.9.2.3 CAN-bus short-circuits

CANL/CANH short to GND and CANL/CANH short to the battery are detected and reported to the device main logic. The CAN driver and receiver are not disabled. They are detected and reported to the device main logic.

CANL short to GND is detected when CANL is < 0.5 V, 500 ns after TXD is activated low, and five consecutive times, as illustrated for CANL short to GND on Figure 61. CANH short to the battery is detected when CANH is > 5.2 V, 500 ns after TXD is activated low, and five consecutive times. CANL short to the battery and CANH short to GND are detected when I_{CANL} or I_{CANH} > 75 mA (typ), 500 ns after TXD is activated low, and five consecutive times.



Figure 61. Illustration of CANL short to GND detection mechanism

If the CAN-bus is dominant for a time longer than t_{DOM}, due for instance to an external short-circuit from another CAN node, the flag CAN_DOM is reported in the DIAG_CAN_1 register. This failure does not disable the bus

FS6500-FS4500-ASILD Product data sheet

driver. The CAN-bus dominant failure detection is operating when the CAN transceiver is in normal mode and listen only mode.

12.9.2.4 CAN current limitation

The current flowing in and out of the CANH and CANL driver is limited to 100 mA, in case of a short-circuit (parameters $I_{CANL-SK}$ and $I_{CANH-SC}$).

12.9.2.5 CAN overtemperature

If the driver temperature exceeds the TSD (T_{OT}), the CAN drivers are disabled and the CAN-bus returns to the recessive state. The CAN receiver continues to operate. The CAN_MODE MSB bit is set to 0 and the flag CAN_OT is reported in the DIAG_CAN_LIN register.

A hysteresis is implemented in this protection feature. The device overtemperature and recovery conditions are shown in <u>Figure 62</u>. The CAN drivers remain disabled until the temperature has fallen below the OT threshold minus hysteresis. The device recovers from this error detection after setting the CAN_MODE to normal operation and when a high level is detected on TXD.



Event 1: overtemperature detection. CAN driver disable.

Event 2: temperature falls below 'overtemp. threshold minus hysteresis' => CAN driver remains disable.

Event 3: temperature below 'overtemp. threshold minus hysteresis' and TXD high to low transition ≥ CAN driver enable.

Event 4: temperature above 'overtemp. threshold minus hysteresis' and TXD high to low transition ≥ CAN driver remains disable.

Figure 62. Overtemperature behavior

12.9.2.6 Distinguish CAN diagnostics and CAN errors

The CAN errors can generate an interruption while the CAN diagnostics are reported in the digital for information only. The interruption generated by the CAN errors can be inhibited setting the INT_INH_CAN bit in the INIT_INH_INT register. The list of CAN diagnostic and CAN error bits is provided in <u>Table 14</u>.

Safety power system basis chip with CAN FD and LIN transceivers

Register	Bit	Flag type	Effect	
DIAG_CAN_FD	CANH_BATT	Diagnostic	No impact on CAN transceiver	
	CANH_GND	Diagnostic	No impact on CAN transceiver	
	CANL_BATT	Diagnostic	No impact on CAN transceiver	
	CANL_GND	Diagnostic	No impact on CAN transceiver	
	CAN_DOM	Error	Turn off CAN transceiver	
	RXD_REC	Error	Turn off CAN transceiver	
	TXD_DOM	Error	Turn off CAN transceiver	
DIAG_CAN_LIN	CAN_OT	Error	Turn off CAN transceiver	
	CAN_OC	Diagnostic	No impact on CAN transceiver	

Table 14. CAN diagnostic and CAN error bits

12.9.3 Wake-up mechanism

The device includes bus monitoring circuitry to detect and report bus wake-ups when the device is in LPOFF and when CAN mode configuration is different from sleep/no wake-up capability. Multiple dominant pulse wake-up detection is implemented. The event must occur within the t_{3PTOX} timeout. $t_{3PTOX} = t_{3PTO1}$ or t_{3PTO2} , depending on the SPI selection. The wake-up events are reported in the WU_SOURCE register.

12.9.3.1 Multiple pulse detection

To activate wake-up report, three events must occur on the CAN-bus:

- event 1: a dominant level longer than t_{1PWU} followed by
- event 2: a dominant level longer than t_{3PWU} followed by
- event 3: a dominant level longer than t_{3PWU}.

The three events and the timeout function avoiding a permanent dominant state on the bus generates permanent wake-up situation which would prevent system to enter in low-power mode.



12.10 LIN transceiver

The local interconnect network (LIN) is a serial communication protocol, designed to support automotive networks in conjunction with a controller area network (CAN). The LIN transceiver is operational from a V_{SUP} of 7.0 V to 18 V DC, and compatible with LIN protocol specification 2.0, $2.1^{(22)}$, $2.2^{(23)}$, and SAEJ2602- $2^{(24)}$.

FS6500-FS4500-ASILD Product data sheet

Safety power system basis chip with CAN FD and LIN transceivers

12.10.1 Simplified block diagram



12.10.2 Operating modes

12.10.2.1 Normal mode

When the LIN mode bit configuration is '11' (LIN in normal operation), the device is able to transmit information from TXDL to the bus and report the bus level to the RXDL pin. When TXDL is high, the LIN driver is off and the bus is in the recessive state (unless it is in an application where another device drives the bus to the dominant state). When TXDL is low, the LIN driver is on and the bus is in the dominant state.

When the LIN mode bit configuration is '01' (LIN in listen only), the device is only able to report the bus level to the RXDL pin. The TXDL driver is off and the device is not able to transmit information from TXDL to the bus. TXDL is maintained high by the internal pull-up resistor TXDL_{PULL-UP} connected to VDDIO.

12.10.2.2 Sleep mode

When the device is in LPOFF mode, the LIN transceiver is automatically set into sleep mode with or without wake-up capability, depending on the LIN mode bit configuration. In this case, the LIN pin is pulled up to V_{SUP} via the internal resistor and diode structure, the TXDL and RXDL pins are driven to GND.

12.10.3 Baud rate selection

The device has two selectable baud rates: 20 kB/s for normal baud rate and 10 kB/s for slow baud rate. An additional fast baud rate (100 kB/s) can be used to flash the MCU, or in the garage for diagnostic. The LIN consortium specification does not specify electrical parameters for this baud rate. The communication only

FS6500-FS4500-ASILD Product data sheet



is guaranteed. The baud rate selection is done by the SPI setting during the INIT phase of the main logic. Depending on the baud rate setting, the corresponding LIN slope control is automatically selected.





12.10.4 Fault detection

12.10.4.1 VSUP undervoltage

A V_{SUP} undervoltage (V_{LIN_UV}) detection is implemented to be compliant with SAEJ2602-2⁽²⁴⁾ standard. At low V_{SUP} voltage (V_{SUP}<V_{LIN_UV}), the LIN bus goes into recessive state to avoid wrong communication.

12.10.4.2 TXDL permanent dominant (timeout)

If TXDL is set low for a time longer than the t_{XD_DOM} parameter, the LIN driver is disabled and the LIN bus returns to the recessive state. This prevents the bus from being set in dominant state permanently, in case a failure sets the TXDL input permanently to a low level.

The LIN receiver continues to operate. The LIN_mode MSB bit is set to 0 and the TXDL_DOM flag is reported in the DIAG_CAN_LIN register. The device recovers from this error detection after setting the LIN_mode to normal operation, and when a high level is detected on TXDL. The TXDL failure detection is operating when the LIN transceiver is in normal mode and listen only mode.

12.10.4.3 RXDL permanent recessive

If RXDL is detected high for seven consecutive receive/dominant cycles, the LIN driver and receiver are disabled and the LIN bus returns to the recessive state. The LIN_mode MSB bit is set to 0 and the RXDL_REC flag is reported in the DIAG_CAN_LIN register. The device recovers from this error detection after setting the LIN_mode to normal operation, and after a LIN dominant transition. The RXDL failure detection is operating when the LIN transceiver is in normal mode and listen only mode.

12.10.4.4 LIN bus short-circuit

If the LIN bus is dominant for a time longer than $t_{\text{LIN}_S\text{HORT}_G\text{ND}}$, due for instance to an external short-circuit to GND, the detection is reported to the device main logic. The BUS bus failure detection is operating when the LIN transceiver is in normal mode and listen only mode.

12.10.4.5 LIN current limitation

In case of a LIN short-circuit to the battery, the current flowing out of the LIN driver is limited to 200 mA (I_{BUS_LIM}) , and the LIN driver is not shutdown. The LIN bus goes into the recessive state when the current limitation occurs and returns in the same functional mode as before the failure when the current fell below the current limitation value.

12.10.4.6 LIN overtemperature

If the driver temperature exceeds TSD (t_{LIN_SD}), the LIN driver is disabled and the LIN bus returns to the recessive state. The LIN receiver continues to operate. The LIN_mode MSB bit is set to 0 and the LIN_OT flag is reported in the DIAG_CAN_LIN register. A hysteresis is implemented in this protection feature. The LIN driver remains disabled until the temperature has fallen below the OT threshold minus hysteresis. The device recovers from this error detection after setting the LIN_mode to normal operation, and when a high level is detected on TXDL.

12.10.4.7 LIN errors

The interruption generated by the LIN errors can be inhibited setting INT_INH_LIN bit in INIT_INH_INT register. The list of LIN error bits is provided in <u>Table 15</u>.

Table 15. LIN error bits

Register	Bit	Flag type	Effect
	LIN_DOM	Error	No impact on LIN transceiver
	RXDL_REC	Error	Turn off LIN transceiver
	TXDL_DOM	Error	Turn off LIN transceiver
	LIN_OT	Error	Turn off LIN transceiver

12.10.5 Wake-up mechanism

The device can wake-up by a LIN dominant pulse longer than t_{BUS_WU} . Dominant pulse means: a recessive to dominant transition, wait for t > t_{BUS_WU} , then a dominant to recessive transition.



13 Serial peripheral interface

13.1 High-level overview

13.1.1 SPI

The device uses a 16-bit SPI, with the following arrangement:

MOSI, primary out, secondary in bits:

- Bit 15 read/write
- Bit 14 main or fail-safe register target
- bit 13 to 9 (A4 to A0) to select the register address. Bit 8 is a parity bit in write mode, next bit (=0) in read mode.
- bit7 to 0 (D7 to D0): control bits

MISO, primary in, secondary out bits:

- bits 15 to 8 (S15 to S8) are device status bits
- bits 7 to 0 (Do7 to Do0) are either extended device status bits, device internal control register content or device flags.

Figure 69 is an overview of the SPI implementation.

13.1.2 Parity bit 8 calculation

The parity bit 8 is used in write mode only (bit 15 = 1). It is calculated based on the number of logic ones contained in the bit 15-9, 7-0 sequence (this is the whole 16-bits of the write command except bit 8). In read mode, the parity bit should be set to 0.

Bit 8 must be set to 0 if the number of ones is odd.

Bit 8 must be set to 1 if the number of ones is even.

13.1.3 Device status on MISO

When a write operation is performed to store data or a control bit in the device, the MISO pin reports a 16-bit fixed device status composed of two bytes: device fixed status (bits 15 to 8) + extended device status (bits 7 to 0). In a read operation, MISO reports the fixed device status (bits 15 to 8), and the next eight bits are content of the selected register. A standard serial peripheral interface (SPI) is integrated to allow bidirectional communication between the FS6500/FS4500 and the MCU. The SPI is used for configuration and diagnostic purposes.



The device contains several registers. Their address is coded on 7 bits (bits 15 to 9). Each register controls or reports part of the device function. Data can be written to the register, to control the device operation or set default value or behavior. Every register can also be read back to ensure its content (default setting or value previously written) is correct.

13.1.4 Register description

Although the minimum time between two NCS low sequences is defined by t_{ONNCS} (Figure 9), two consecutive accesses to the fail-safe registers must be done with a 3.5 µs minimum NCS high time in between. Although the minimum time between two fail-safe registers accesses is 3.5 µs, some SPI accesses to the main registers can be done in between (Figure 10).

13.2 Detailed operation

13.2.1 SPI command organization



Safety power system basis chip with CAN FD and LIN transceivers

Table 1	6. I	MOSI	bits	description
---------	------	------	------	-------------

	Description	Set if it is a read or write command						
R/W	0	Read						
	1	Write						
	Description	Split the addresses between fail-safe state machine and main logic						
M/FS	0	Main						
	1	Fail-safe						
Description	Description	Set the address to read or write						
A4:0	0	See register menning						
	1							
	Description	Parity bit (only use in write mode). Set to 0 in read mode						
Р	0	Number of '1' (bit 15:9 and bit 7:0) is odd						
	1	Number of '1' (bit 15:9 and bit 7:0) is even						
	Description	Data in write mode. Must be set to 00h in read mode						
D7:0	0	See register dataile						
	1							

13.2.2 Main logic general diagnostic



Table 17. MISO bits description

	Description	Report an error in the SPI communication						
	0	No failure						
561_6	1	Failure						
	Reset condition	Power on reset/read						
	Description	Report a wake-up event. Logical OR of all wake-up sources						
WILL G ^[2]	0	No WU_G event						
W0_G	1	WU_G event						
	Reset condition	Power on reset/when initial event cleared on read						
	Description	Report a CAN event (diagnostic)						
CAN C ^[3]	0	No event						
CAN_G	1	CAN event						
	Reset Condition	Power on reset/when initial event cleared on read						

Safety power system basis chip with CAN FD and LIN transceivers

	Description	Report a LIN event (diagnostic)					
	0	No event					
	1	LIN event					
	Reset condition	Power on reset/when initial event cleared on read					
	Description	Report a change in IOs state					
IO C ^[5]	0	No IO transition					
10_0	1	IO transition					
	Reset condition	Power on reset/when initial event cleared on read					
	Description	Report an event from $V_{\text{PRE-REGULATOR}}$ and battery monitoring (status change or failure)					
VPRE_G ^[6]	0	No event					
	1	Event occurred					
	Reset condition	Power on reset/when initial event cleared on read					
	Description	Report an event from V _{CORE} regulator (status change or failure)					
VCORE C ^[7]	0	No event					
VCORE_G	1	Event occurred					
	Reset condition	Power on reset/when initial event cleared on read					
	Description	Report an event from V_{CCA} , V_{AUX} , or V_{CAN} regulators (status change or failure)					
	0	No event					
VOTTERS_G	1	Event occurred					
	Reset condition	Power on reset/when initial event cleared on read					

Table 17. MISO bits description...continued

SPI_G = SPI_ERR or SPI_CLK or SPI_REQ or SPI_PARITY or SPI_FS_ERR or SPI_FS_CLK or SPI_FS_REQ or SPI_FS_PARITY [1]

WU_G = IO_5_WU or IO_4_WU or IO_3_WU or IO_2_WU or IO_0_WU or PHY_WU [2]

[3] CAN_G = CANH_BATT or CANH_GND or CANL_BATT or CANL_GND or CAN_DOM or RXD_REC or TXD_DOM or CAN_OT or CAN_OC

[4] LIN_G = LIN_OT or RXDL_REC or TXDL_DOM or LIN_DOM

[5] $IO_{\overline{G}} = IO_{\overline{5}} \text{ or } IO_{4} \text{ or } IO_{3} \text{ or } IO_{2} \text{ or } IO_{0}$

[6]

VPRE_G = VSNS_UV or VSUP_UV_7 or IPFF or ILIM_PRE or TWARN_PRE or BOB or !VPRE_STATE or VPRE_OV or VPRE_UV VCORE_G = TWARN_CORE or !VCORE_STATE or VCORE_OV or VCORE_UV [7]

VOTHERS_G = ILIM_CCA or TWARN_CCA or TSD_CCA or ILIM_CCA_OFF or VCCA_UV or VCCA_OV or ILIM_AUX or TSD_AUX or ILIM_AUX_OFF [8] or VAUX_OV or VAUX_UV or ILIM_CAN or VCAN_UV or VCAN_OV or TSD_CAN

13.2.3 Fail-safe logic general diagnostic



FS6500-FS4500-ASILD

Safety power system basis chip with CAN FD and LIN transceivers

Table 18. MISO bits description

	Description	Secured SPI communication check, concerns fail-safe logic only.					
	0	No error					
SFI_FS_ERR	1	Error detected in the secured bits					
	Reset condition	Power on reset					
	Description	SCLK error detection, concerns internal error in fail-safe logic only and external errors (at pin level) for both main and fail-safe logics. Other errors flagged by SPI_CLK_bit					
SPI_FS_CLK	0	16 clock cycles during NCS low					
	1	Wrong number of clock cycles (<16 or >16)					
	Reset condition	Power on reset					
	Description	Invalid SPI access (wrong write or read, write to INIT registers in normal mode, wrong address), concerns fail-safe Logic only					
SPI_FS_REQ	0	No error					
	1	SPI violation					
	Reset condition	Power on reset					
	Description	SPI parity bit error detection, concerns fail-safe logic only					
	0	Parity bit OK					
SFI_FS_FARIT	1	Parity bit error					
	Reset condition	Power on reset					

13.2.4 Main logic register address table

Table 19 is a list of device registers and addresses coded in bits 13 to 9 in MOSI for main logic.

Table 19. Register mapping of main logic

Pagistor				Ado	Iress			Write description	Table ref
Register	FS/M	A4	A3	A2	A1	A0	Hex	write description	Table Tel.
INIT_VREG	0	0	0	0	0	1	#1(01h)	Write during INIT phase then read only	Table 22
INIT_WU1	0	0	0	0	1	0	#2(02h)	Write during INIT phase then read only	Table 24
INIT_WU2	0	0	0	0	1	1	#3(03h)	Write during INIT phase then read only	Table 26
INIT_INT	0	0	0	1	0	0	#4(04h)	Write during INIT phase then read only	Table 28
INIT_INH_INT	0	0	0	1	0	1	#5(05h)	Write during INIT phase then read only	Table 30
LONG_DURATION_TIMER	0	0	0	1	1	0	#6(06h)	Write during normal and read	Table 32
NOT USED	0	0	0	1	1	1	#7(07h)	N/A	N/A
HW_CONFIG	0	0	1	0	0	0	#8(08h)	Read only	Table 34
WU_SOURCE	0	0	1	0	0	1	#9(09h)	Read only	Table 36
DEVICE_ID	0	0	1	0	1	0	#10(0Ah)	Read only	Table 38
IO_INPUT	0	0	1	0	1	1	#11(0Bh)	Read only	Table 40
DIAG_VPRE	0	0	1	1	0	0	#12(0Ch)	Read only	Table 42
DIAG_VCORE	0	0	1	1	0	1	#13(0Dh)	Read only	Table 44
DIAG_VCCA	0	0	1	1	1	0	#14(0Eh)	Read only	Table 46
DIAG_VAUX	0	0	1	1	1	1	#15(0Fh)	Read only	Table 48
DIAG_VSUP_VCAN	0	1	0	0	0	0	#16(10h)	Read only	Table 50
DIAG_CAN_FD	0	1	0	0	0	1	#17(11h)	Read only	Table 52

FS6500-FS4500-ASILD Product data sheet

Safety power system basis chip with CAN FD and LIN transceivers

Deviator				Add	Iress				
Register FS	FS/M	A4	A3	A2	A1	A0	Hex	Write description	Table ret.
DIAG_CAN_LIN	0	1	0	0	1	0	#18(12h)	Read only	Table 54
DIAG_SPI	0	1	0	0	1	1	#19(13h)	Read only	Table 56
NOT USED	0	1	0	1	0	0	#20(14h)	N/A	N/A
MODE	0	1	0	1	0	1	#21(15h)	Write during normal and read	Table 58
REG_MODE	0	1	0	1	1	0	#22(16h)	Write during normal and read	Table 60
IO_OUT_AMUX	0	1	0	1	1	1	#23(17h)	Write during normal and read	Table 62
CAN_LIN_MODE	0	1	1	0	0	0	#24(18h)	Write during normal and read	Table 64
NOT USED	0	1	1	0	0	1	#25(19h)	N/A	N/A
LDT_AFTER_RUN_1	0	1	1	0	1	0	#26(1Ah)	Write during normal and read	Table 66
LDT_AFTER_RUN_2	0	1	1	0	1	1	#27(1Bh)	Write during normal and read	Table 68
LDT_WAKE_UP_1	0	1	1	1	0	0	#28(1Ch)	Write during normal and read	Table 70
LDT_WAKE_UP_2	0	1	1	1	0	1	#29(1Dh)	Write during normal and read	Table 72
LDT_WAKE_UP_3	0	1	1	1	1	0	#30(1Eh)	Write during normal and read	Table 74

Table 19. Register mapping of main logic ... continued

13.2.5 Fail-safe logic register address table

Table 20 is a list of device registers and addresses coded in bits 13 to 9 in MOSI for fail-safe logic

Register	Addres	ss						Write description	Table ref.
	FS/M	A4	A3	A2	A1	A0	Hex		
INIT_FS1B_TIMING	1	0	0	0	0	1	#33(21h)	Write during INIT phase then read only	Table 76
BIST	1	0	0	0	1	0	#34(22h)	Write (No restriction) and read	Table 78
INIT_SUPERVISOR	1	0	0	0	1	1	#35(23h)	Write during INIT phase then read only	Table 80
INIT_FAULT	1	0	0	1	0	0	#36(24h)	Write during INIT phase then read only	Table 82
INIT_FSSM	1	0	0	1	0	1	#37(25h)	Write during INIT phase then read only	Table 84
INIT_SF_IMPACT	1	0	0	1	1	0	#38(26h)	Write during INIT phase then read only	Table 86
WD_WINDOW	1	0	0	1	1	1	#39(27h)	Write (no restriction) and read	Table 88
WD_LFSR	1	0	1	0	0	0	#40(28h)	Write (no restriction) and read	<u>Table 90</u>
WD_ANSWER	1	0	1	0	0	1	#41(29h)	Write (no restriction) and read	Table 92
RELEASE_FSxB	1	0	1	0	1	0	#42(2Ah)	Write (no restriction) and read	Table 94
SF_OUTPUT_REQUEST	1	0	1	0	1	1	#43(2Bh)	Write (no restriction) and read	Table 96
INIT_WD_CNT	1	0	1	1	0	0	#44(2Ch)	Write during INIT phase then read only	Table 98
DIAG_SF_IOs	1	0	1	1	0	1	#45(2Dh)	Read only	Table 100
WD_COUNTER	1	0	1	1	1	0	#46(2Eh)	Read only	<u>Table 102</u>
DIAG_SF_ERR	1	0	1	1	1	1	#47(2Fh)	Read only	<u>Table 104</u>
NOT USED	1	1	0	0	0	0	#48(30h)	N/A	N/A
INIT_VCORE_OVUV_IMPACT	1	1	0	0	0	1	#49(31h)	Write during INIT phase then read only	Table 106
INIT_VCCA_OVUV_IMPACT	1	1	0	0	1	0	#50(32h)	Write during INIT phase then read only	Table 108
INIT_VAUX_OVUV_IMPACT	1	1	0	0	1	1	#51(33h)	Write during INIT phase then read only	Table 110
DEVICE_ID_FS	1	1	0	1	0	0	#52(34h)	Read only	Table 112

Table 20. Register mapping of fail-safe logic

13.2.6 Secured SPI command

Some SPI commands must be secured to avoid unwanted change of the critical bits. The secured bits in the fail-safe machine and the main state machine are calculated from the data bits sent as follows:

Table 21. Secured SPI

Bit7	Bit6	Bit5	Bit4	Bit3	Bit2	Bit1	Bit0
Data 3	Data 2	Data 1	Data 0	Secure 3	Secure2	Secure 1	Secure 0

• Secure 3 = NOT(Bit5)

- Secure 2 = NOT(Bit4)
- Secure 1 = Bit7
- Secure 0 = Bit6

13.3 Detail of main logic register mapping

13.3.1 INIT_VREG

Table 22. INIT_VREG register description

Write																
	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
MOSI	1	0	0	0	0	0	1	Р	ICCA_LIM	TCCA_ LIM_OFF	IPFF_DIS	VCAN_ OV_MON	0	TAUX_ LIM_OFF	VAUX_ TRK_EN	0
MISO	SPI_G	WU_G	CAN_G	LIN_G	IO_G	VPRE _G	VCORE _G	VOTHERS G	ICCA_LIM	TCCA_ LIM_OFF	IPFF_DIS	VCAN_ OV_MON	RES ERVED	TAUX_ LIM_OFF	VAUX_ TRK_EN	BAT_FAIL
Deed																

	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
MOSI	0	0	0	0	0	0	1	0	0	0	0	0	0	0	0	0
MISO	SPI_G	WU_G	CAN_G	LIN_G	IO_G	VPRE _G	VCORE _G	VOTHERS G	ICCA_LIM	TCCA_ LIM_OFF	IPFF_DIS	VCAN_ OV_MON	RES ERVED	TAUX_ LIM_OFF	VAUX_ TRK_EN	BAT_FAIL

Table 23. INIT_VREG description and configuration of the bits (default value in bold)

	Description	Configure the current limitation threshold for VCCA. Only available for external PNP.
ICCA_LIM	0	ICCA_LIM_OUT
	1	ICCA_LIM_INT
	Reset condition	Power on reset
	Description	Configure the current limitation duration before VCCA is switched off. Only available for external PNP.
TCCA_LIM_OFF	0	10 ms
	1	50 ms
	Reset condition	Power on reset
	Description	DISABLE the input power feed forward (IPFF) function of V_{PRE}
	0	Enabled
	1	Disabled
	Reset condition	Power on reset

Safety power system basis chip with CAN FD and LIN transceivers

Table 23. INIT	_VREG dea	scription and	configuratio	on of the bits	(default valu	e in bold)continued

	Description	CAN_5V overvoltage monitoring
VCAN OV MON	0	Off. V _{CAN OV} is not monitored. Flag is ignored.
VCAN_OV_MON	1	On. $V_{CAN OV}$ is monitored. If OV the CAN_5V regulator is switched off.
	Reset condition	Power on reset
	Description	Configure the current limitation duration before VAUX is switched off.
	0	10 ms
	1	50 ms
	Reset condition	Power on reset
	Description	Configure VAUX regulator as a tracker of VCCA
VALLY TRK EN	0	NO tracking.
VAUX_INK_EN	1	Tracking mode enabled and latched
	Reset condition	Power on reset
	Description	Report a battery disconnection (POR of the main logic)
	0	NO POR
BAT_FAIL ^[1]	1	POR occurred
	Reset condition	Power on reset
	Clear condition	Read

[1] BAT_FAIL = POR_M or V_{SUP_UV_L} or BG_OK (reset sources of main logic). BAT_FAIL bit is cleared by a SPI read.

13.3.2 INIT_WU1

Table 24. INIT_WU1 register description

vvrite																
	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
MOSI	1	0	0	0	0	1	0	Р	WU_ IO0_1	WU_ IO0_0	WU_ IO2_1	WU_ IO2_0	WU_ IO3_1	WU_ IO3_0	WU_ IO4_1	WU_ IO4_0
MISO	SPI_G	WU_G	CAN_G	LIN_G	IO_G	VPRE _G	VCORE _G	VOTHERS_ G	WU_ IO0_1	WU_ IO0_0	WU_ IO2_1	WU_ IO2_0	WU_ IO3_1	WU_ IO3_0	WU_ IO4_1	WU_ IO4_0
Read																
	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0

	DILIS	DIL 14	DILIS	DILIZ	DICT	DILTO	DILD	DILO	DIL	Dito	5115	DIL4	511.5	0112	DILI	DILU
MOSI	0	0	0	0	0	1	0	0	0	0	0	0	0	0	0	0
MISO	SPI_G	WU_G	CAN_G	LIN_G	IO_G	VPRE _G	VCORE _G	VOTHERS_ G	WU_ IO0_1	WU_ IO0_0	WU_ IO2_1	WU_ IO2_0	WU_ IO3_1	WU_ IO3_0	WU_ IO4_1	WU_ IO4_0

Table 25. INIT_WU1 description and configuration of the bits (default value in bold)

	Description	IO_0 wake-up configuration
	00	NO wake-up capability
	01	Wake-up on rising edge - or high level
100_100_1.0	10	Wake-up on falling edge - or low level
	11	Wake-up on any edge
	Reset condition	Power on reset

Safety power system basis chip with CAN FD and LIN transceivers

Table 25. INIT_WU1 description and configuration of the bits (default value in bold)...continued

	Description	IO_2 wake-up configuration					
	00	NO wake-up capability					
	01	Wake-up on rising edge - or high level					
102_1.0	10	Wake-up on falling edge - or low level					
	11	Wake-up on any edge					
	Reset condition	Power on reset					
	Description	IO_3 wake-up configuration					
	00	NO wake-up capability					
WILLO3 1.0	01	Wake-up on rising edge - or high level					
W0_103_1.0	10	Wake-up on falling edge - or low level					
	11	Wake-up on any edge					
	Reset condition	Power on reset					
	Description	IO_4 wake-up configuration					
	00	NO wake-up capability					
	01	Wake-up on rising edge - or high level					
104_104	10	Wake-up on falling edge - or low level					
	11	Wake-up on any edge					
	Reset condition	Power on reset					

13.3.3 INIT_WU2

Table 26. INIT_WU2 register description

Write																
	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
MOSI	1	0	0	0	0	1	1	Ρ	WU_IO5_ 1	WU_IO5_ 0	CAN_ DIS_CFG	CAN_ WU_TO	0	LIN_ J2602_ DIS	LIN_SR_1	LIN_SR_0
MISO	SPI_G	WU_G	CAN_G	LIN_G	10_G	VPRE _G	VCORE _G	VOTHERS_ G	WU_IO5_ 1	WU_IO5_ 0	CAN_ DIS_CFG	CAN_ WU_TO	RES ERVED	LIN_ J2602_ DIS	LIN_SR_1	LIN_SR_0
Read																
	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
MOSI	0	0	0	0	0	1	1	0	0	0	0	0	0	0	0	0
MISO	SPI_G	WU_G	CAN_G	LIN_G	10_G	VPRE _G	VCORE _G	VOTHERS_ G	WU_IO5_ 1	WU_IO5_ 0	CAN_ DIS_CFG	CAN_ WU_TO	RES ERVED	LIN_ J2602_ DIS	LIN_SR_1	LIN_SR_0

Safety power system basis chip with CAN FD and LIN transceivers

Table 27. INIT_WU2 description and configuration of the bits (default value in bold)

	Description	IO_5 wake-up configuration
	00	NO wake-up capability
WILLIO5 1:0	01	Wake-up on rising edge - or high level
W0_105_1.0	10	Wake-up on falling edge - or low level
	11	Wake-up on any edge
	Reset condition	Power on reset
	Description	Define CAN behavior when FS1B is asserted low
CAN_DIS_CFG	0	CAN in RX only mode (when FS1B_CAN_ IMPACT = 1 in INIT_FAULT register)
	1	CAN in sleep mode (when FS1B_CAN_ IMPACT = 1 in INIT_FAULT register)
	Reset condition	Power on reset
	Description	Define the CAN wake-up timeout
	0	120 µs
	1	2.8 ms
	Reset condition	Power on reset
	Description	To comply with J2602 standard. Recessive mode when VSUP < 7.0 V
LIN 12602 dis	0	Compliant with J2602 standard
	1	Not compliant with J2602 standard
	Reset condition	Power on reset
	Description	Configure the LIN slew rate
	00	20 kbit/s
LIN_SR_1:0	01	10 kbit/s
	1X	Fast baud rate (Max: 100 kbit/s)
	Reset condition	Power on reset

13.3.4 INIT_INT

Table 28. INIT_INT register description

Write																
	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
MOSI	1	0	0	0	1	0	0	Ρ	INT_ DURATION	INT_INH_ LIN	INT_INH_ ALL	INT_INH_ VSNS	INT_INH_ VPRE	INT_INH_ VCORE	INT_INH_ VOTHER	INT_INH_ CAN
MISO	SPI_G	WU_G	CAN_G	LIN_G	IO_G	VPRE _G	VCORE _G	VOTHERS G	INT_ DURATION	INT_INH_ LIN	INT_INH_ ALL	INT_INH_ VSNS	INT_INH_ VPRE	INT_INH_ VCORE	INT_INH_ VOTHER	INT_INH_ CAN
Read																
	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
MOSI	0	0	0	0	1	0	0	0	0	0	0	0	0	0	0	0

Read																
	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
MISO	SPI_G	WU_G	CAN_G	LIN_G	IO_G	VPRE _G	VCORE _G	VOTHERS G	INT_ DURATION	INT_INH_ LIN	INT_INH_ ALL	INT_INH_ VSNS	INT_INH_ VPRE	INT_INH_ VCORE	INT_INH_ VOTHER	INT_INH_ CAN

Table 29. INIT_INT description and configuration of the bits (default value in bold)

	Description	Define the duration of the interrupt pulse					
	0	100 µs					
	1	25 μs					
	Reset condition	Power on reset					
	Description	Inhibit the interrupt for LIN error bits					
	0	All INT sources					
	1	LIN error bits change INHIBITED					
	Reset condition	Power on reset					
	Description	Inhibit ALL the interrupt					
	0	All INT sources					
	1	All INT inhibited					
	Reset condition	Power on reset					
	Description	Inhibit the interrupt for V _{SNS_UV}					
INT INU VENE	0	All INT sources					
	1	V _{SNS_UV} INT inhibited					
	Reset condition	Power on reset					
	Description	Inhibit the interrupt for V _{PRE} status event					
	0	All INT sources					
	1	V _{PRE} status change inhibited					
	Reset condition	Power on reset					
	Description	Inhibit the interrupt for V _{CORE} status event					
	0	All INT sources					
	1	V _{CORE} status change inhibited					
	Reset condition	Power on reset					
	Description	Inhibit the interrupt for V_{CCA}/V_{AUX} and V_{CAN} status event					
	0	All INT sources					
	1	V _{CCA} /V _{AUX} /V _{CAN} status change inhibited					
	Reset condition	Power on reset					
	Description	Inhibit the interrupt for CAN error bits					
	0	All INT sources					
	1	CAN error bits change inhibited					
	Reset condition	Power on reset					

13.3.5 INIT_INH_INT

Table 30. INIT_INH_INT register description

Write																
	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
MOSI	1	0	0	0	1	0	1	Р	0	0	0	INT_INH_ 5	INT_INH_ 4	INT_INH_ 3	INT_INH_ 2	INT_INH_ 0
MISO	SPI_G	WU_G	CAN_G	LIN_G	IO_G	VPRE _G	VCORE _G	VOTHERS_ G	RES ERVED	RES ERVED	RES ERVED	INT_INH_ 5	INT_INH_ 4	INT_INH_ 3	INT_INH_ 2	INT_INH_ 0
Read																
	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
MOSI	0	0	0	0	1	0	1	0	0	0	0	0	0	0	0	0
MISO	SPI_G	WU_G	CAN_G	LIN_G	IO_G	VPRE _G	VCORE _G	VOTHERS G	RES ERVED	RES ERVED	RES ERVED	INT_INH_ 5	INT_INH_ 4	INT_INH_ 3	INT_INH_ 2	INT_INH_ 0

Table 31. INIT IO_WU2 description and configuration of the bits (default value in bold)

Description	Inhibit the interrupt pulse for IO_5 (masked in IO_G)						
0	INT not masked						
1	INT masked						
Reset condition	Power on reset						
Description	Inhibit the interrupt pulse for IO_4 (masked in IO_G)						
0	INT not masked						
1	INT masked						
Reset condition	Power on reset						
Description	Inhibit the interrupt pulse for IO_3 (masked in IO_G)						
0	INT not masked						
1	INT masked						
Reset condition	Power on reset						
Description	Inhibit the interrupt pulse for IO_2 (masked in IO_G)						
0	INT not masked						
1	INT masked						
Reset condition	Power on reset						
Description	Inhibit the interrupt pulse for IO_0 (masked in IO_G)						
0	INT not masked						
1	INT masked						
Reset condition	Power on reset						

13.3.6 LONG_DURATION_TIMER

Table 32. LONG_DURATION_TIMER register description

Write																
	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
MOSI	1	0	0	0	1	1	0	Ρ	F2	F1	F0	REG_SE	0	MODE	LDT_ ENABLE	0
MISO	SPI_G	WU_G	CAN_G	LIN_G	10_G	VPRE _G	VCORE _G	VOTHERS G	F2	F1	F0	REG_SE	LDT_ RUNNING	MODE	LDT_ ENABLE	LDT_INT
Read																
	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
MOSI	0	0	0	0	1	1	0	0	0	0	0	0	0	0	0	0
MISO	SPI_G	WU_G	CAN_G	LIN_G	IO_G	VPRE	VCORE	VOTHERS	F2	F1	F0	REG_SE	LDT_ RUNNING	MODE	LDT_ ENABLE	LDT_INT
						_0	_0									1

Table 33. LONG_DURATION_TIMER description and configuration of the bits (default value in bold)

	Description	Select timer operating function					
	000	Function 1: in normal mode count and generate flag or INT when counter reaches the after run value.					
	001	Function 2: in normal mode count until after run value is reached, then enters in LPOFF.					
F2:F0	010	Function 3: in normal mode count until after run value is reached, then enters in LPOFF. Once in LPOFF, count until wake-up value is reached and wake-up.					
	011	Function 4: in LPOFF, count until wake-up value is reached and wake-up.					
	100	Function 5: in LPOFF, count and do not wake-up. Counter value is stored in wake-up register.					
	101 111	N/A					
	Reset condition	Power on reset					
	Description	Counter register selection					
	0	Read programmed wake-up register					
REG_SE	1	Read real time counter into wake-up register (after counter is stopped with LDT_ENABLE bit)					
	Reset condition	Power on reset					
	Description	Operating mode selection					
MODE	0	Calibration mode (488 µs resolution)					
MODE	1	Normal mode (1 s resolution)					
	Reset condition	Power on reset					
	Description	LDT counter control					
	0	LDT counter stop					
	1	LDT counter start					
	Reset condition	Power on reset					

Safety power system basis chip with CAN FD and LIN transceivers

Table 33. LONG_DURATION_TIMER description and configuration of the bits (default value in bold)...continued

Description	Counter status
0	Counter not running
1	Counter running
Reset condition	Power on reset
Description	Counter interrupt generation when function 1 is selected
0	No INT generated
1	INT generated when counter reach after run value
Reset condition	Power on reset/read

13.3.7 HW_CONFIG

Table 34. HW_CONFIG register description

Read																
	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
MOSI	0	0	0	1	0	0	0	0	0	0	0	0	0	0	0	0
MISO	SPI_G	WU_G	CAN_G	LIN_G	IO_G	VPRE _G	VCORE _G	VOTHERS G	LS_ DETECT	RES ERVED	VCCA_ PNP_DET	VCCA_HW	VAUX_HW	1	DFS_HW1	DBG_HW

Table 35. HW_CONFIG description and configuration of the bits (default value in bold)

	Description	Report the hardware configuration of V _{PRE}
	0	Buck-boost
LS_DETECT	1	Buck only
	Reset condition	Power on reset/refresh after LPOFF
	Description	Report the connection of an external PNP on V_{CCA}
	0	External PNP connected
VCCA_FINF_DET	1	Internal MOSFET
	Reset condition	Power on reset/refresh after LPOFF
	Description	Report the hardware configuration for V _{CCA}
	0	3.3 V
	1	5.0 V
	Reset condition	Power on reset/refresh after LPOFF
	Description	Report the hardware configuration for V _{AUX}
	0	5.0 V
	1	3.3 V
	Reset condition	Power on reset/refresh after LPOFF
	Description	Report the deep fail-safe hardware configuration (main logic)
	0	Deep fail-safe disable
	1	Deep fail-safe enable
	Reset condition	Power on reset/refresh after LPOFF

Safety power system basis chip with CAN FD and LIN transceivers

Table 35. HW_CONFIG description and configuration of the bits (default value in bold)...continued

Description	Report the configuration of the DEBUG mode
0	Normal operation
1	Debug mode selected
Reset condition	Power on reset/refresh after LPOFF

13.3.8 WU_SOURCE

Table 36.	WU	SOURCE	register	description
-----------	----	--------	----------	-------------

Read																
	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
MOSI	0	0	0	1	0	0	1	0	0	0	0	0	0	0	0	0
MISO	SPI_G	WU_G	CAN_G	LIN_G	IO_G	VPRE _G	VCORE _G	VOTHERS G	IO_5_WU	IO_4_WU	IO_3_WU	IO_2_WU	10_0_WU	AUTO_WU	LDT_WU	PHY_WU

Table 37. WU_SOURCE description and configuration of the bits (default value in bold)

	Description	Report a wake-up event from IO_5
	0	No wake-up
10_3_000	1	Wake-up event detected
	Reset condition	Power on reset/read
	Description	Report a wake-up event from IO_4
	0	No wake-up
10_4_00	1	Wake-up event detected
	Reset condition	Power on reset/read
	Description	Report a wake-up event from IO_3
	0	No wake-up
10_3_00	1	Wake-up event detected
	Reset condition	Power on reset/read
	Description	Report a wake-up event from IO_2
	0	No wake-up
10_2_00	1	Wake-up event detected
	Reset condition	Power on reset/read
	Description	Report a wake-up event from IO_0
	0	No wake-up
10_0_00	1	Wake-up event detected
	Reset condition	Power on reset/read
	Description	Report an automatic wake-up event
	0	No wake-up
A010_W0	1	Wake-up event detected
	Reset condition	Power on reset/read

Safety power system basis chip with CAN FD and LIN transceivers

Table 37. WU_SOURCE description and configuration of the bits (default value in bold)...continued

Description	Report a wake-up event from long duration timer
0	No wake-up
1	Wake-up event detected
Reset condition	Power on reset/read
Description	Report a wake-up event from CAN or LIN
0	No wake-up
1	Wake-up event detected
Reset condition	Power on reset/read CAN_WU or/and LIN_WU

13.3.9 DEVICE _ID

Table 38. DEVICE_ID register description

Read																
	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
MOSI	0	0	0	1	0	1	0	0	0	0	0	0	0	0	0	0
MISO	SPI_G	WU_G	CAN_G	LIN_G	IO_G	VPRE _G	VCORE _G	VOTHERS G	VCORE_1	VCORE_0	PHY_1	PHY_0	VKAM	DEV_ REV_2	DEV_ REV_1	DEV_ REV_0

Table 39. DEVICE_ID description and configuration of the bits (default value in bold)

	Description	VCORE current capability
	00	1.5 A
VCORE 1.0	01	0.8 A
VCONE_1.0	10	0.5 A
	11	2.2 A
	Reset condition	Power on reset
	Description	CAN or LIN physical layer
	00	No CAN/no LIN
	01	CAN only
1111_1.0	10	LIN only
	11	CAN and LIN
	Reset condition	Power on reset
	Description	VKAM supply
	0	VKAM off by default
VICANI	1	VKAM on by default
	Reset condition	Power on reset

Safety power system basis chip with CAN FD and LIN transceivers

Table 39. DEVICE_ID description and configuration of the bits (default value in bold)...continued

	Description	Device silicon revision
	000	Silicon Rev. xxx
DEV_REV_2:0		- For ASIL D devices, DEV_REV_2:0 = 010 For ASIL B devices, DEV_REV_2:0 = 111;
	111	
	Reset condition	Power on reset

13.3.10 IO_INPUT

Table 40. IO_INPUT register description

Read																
	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
MOSI	0	0	0	1	0	1	1	0	0	0	0	0	0	0	0	0
MISO	SPI_G	WU_G	CAN_G	LIN_G	IO_G	VPRE _G	VCORE _G	VOTHERS G	IO_5	IO_4	0	IO_3	IO_2	0	0	10_0

Table 41. IO_INPUT description and configuration of the bits

	Description	Report IO_5 digital state in normal mode. No update in LPOFF mode since wake-up features available
IO_5	0	Low
	1	High
	Reset condition	Power on reset/read
	Description	Report IO_4 digital state in normal mode. No update in LPOFF mode since wake-up features available
IO_4	0	Low
	1	High
	Reset condition	Power on reset/read
	Description	Report IO_3 digital state in normal mode. No update in LPOFF mode since wake-up features available
IO_3	0	Low
	1	High
	Reset condition	Power on reset/read
	Description	Report IO_2 digital state in normal mode. No update in LPOFF mode since wake-up features available
IO_2	0	Low
	1	High
	Reset condition	Power on reset/read
	Description	Report IO_0 digital state in normal mode. No update in LPOFF mode since wake-up features available
IO_0	0	Low
	1	High
	Reset condition	Power on reset/read

Product data sheet

13.3.11 DIAG_VPRE

Table 42. DIAG_VPRE register description

Read																
	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
MOSI	0	0	0	1	1	0	0	0	0	0	0	0	0	0	0	0
MISO	SPI_G	WU_G	CAN_G	LIN_G	IO_G	VPRE _G	VCORE _G	VOTHER G	S <u>B</u> oB	VPRE_ STATE	TWARN_ PRE	TSD_PRE	VPRE_OV	VPRE_UV	ILIM_ PRE	0

Table 43. DIAG_VPRE description and configuration of the bits (default value in bold)

	Description	Report a running mode of V _{PRE}					
RoR	0	Buck					
bob	1	Boost					
	Reset condition	Power on reset					
	Description	Report the activation state of V _{PRE} SMPS					
	0	SMPS off					
VFRE_STATE	1	SMPS on					
	Reset condition	Power on reset					
	Description	Report a thermal warning from V _{PRE}					
	0	No thermal warning (T _J < T _{WARN_PRE})					
IWARN_FRE	1	Thermal warning (T _J > T _{WARN_PRE})					
	Reset condition	Power on reset/read					
	Description	Thermal shutdown of V _{PRE}					
	0	No TSD (T _J < T _{SD_PRE})					
ISD_FRE	1	TSD occurred (T _J > T _{SD_PRE})					
	Reset condition	Power on reset/read					
	Description	V _{PRE} overvoltage detection					
	0	No overvoltage (V _{PRE} < V _{PRE_OV})					
	1	Overvoltage detected (V _{PRE} > V _{PRE_OV})					
	Reset condition	Power on reset/read					
	Description	V _{PRE} undervoltage detection					
	0	No undervoltage (V _{PRE} > V _{PRE_UV})					
	1	Undervoltage detected (V _{PRE} < V _{PRE_UV})					
	Reset condition	Power on reset/read					
	Description	Report a current limitation condition on V _{PRE}					
	0	No current limitation (I _{PRE_PK} < I _{PRE_LIM})					
	1	Current limitation (I _{PRE_PK} > I _{PRE_LIM})					
	Reset condition	Power on reset/read					

13.3.12 DIAG_VCORE

Table 44. DIAG_VCORE register description

Read																
	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
MOSI	0	0	0	1	1	0	1	0	0	0	0	0	0	0	0	0
MISO	SPI_G	WU_G	CAN_G	LIN_G	IO_G	VPRE _G	VCORE _G	VOTHERS G	0	VCORE_ STATE	TWARN_ CORE	TSD_ CORE	VCORE_ FB_OV	VCORE_ FB_UV	0	0

Table 45. DIAG_VCORE description and configuration of the bits (default value in bold)

	Description	Report the activation state of V _{CORE} SMPS						
	0	SMPS off						
VOORE_STATE	1	SMPS on						
	Reset condition	Power on reset						
	Description	Report a thermal warning from V _{CORE}						
	0	No thermal warning (T _J < T _{WARN_CORE})						
	1	Thermal warning (T _J > T _{WARN_CORE})						
	Reset condition	Power on reset/read						
	Description	Thermal shutdown of V _{CORE}						
	0	No TSD (T _J < T _{SD_CORE})						
ISD_CORE	1	TSD occurred (T _J > T _{SD_CORE})						
	Reset condition	Power on reset/read						
	Description	V _{CORE} overvoltage detection						
VCORE ER OV	0	No overvoltage (V _{CORE_FB} < V _{CORE_FB_OV})						
VCORE_FB_OV	1	Overvoltage detected (V _{CORE_FB} > V _{CORE_FB_OV})						
	Reset condition	Power on reset/read						
	Description	V _{CORE} undervoltage detection						
VCORE EB LIV	0	No undervoltage (V _{CORE_FB} > V _{CORE_FB_UV})						
	1	Undervoltage (V _{CORE_FB} < V _{CORE_FB_UV})						
	Reset condition	Power on reset/read						

13.3.13 DIAG_VCCA

Table 46. DIAG_VCCA register description

Read																
	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
MOSI	0	0	0	1	1	1	0	0	0	0	0	0	0	0	0	0
MISO	SPI_G	WU_G	CAN_G	LIN_G	IO_G	VPRE _G	VCORE _G	VOTHERS_ G	0	0	TWARN_ CCA	TSD_CCA	VCCA_OV	VCCA_UV	ILIM_CCA	ILIM_CCA_ OFF

Safety power system basis chip with CAN FD and LIN transceivers

	Description	Report a thermal warning from V_{CCA} . Available only for internal pass MOSFET					
TWARN_CCA	0	No thermal warning (T _J < T _{WARN_CCA})					
	1	Thermal warning (T _J > T _{WARN_CCA})					
	Reset condition	Power on reset/read					
	Description	Thermal shutdown of V _{CCA}					
	0	NO TSD (T _J < $T_{SD_{CCA}}$)					
	1	TSD occurred ($T_J > T_{SD_CCA}$)					
	Reset condition	Power on reset/read					
	Description	V _{CCA} overvoltage detection					
	0	No overvoltage (V _{CCA} < V _{CCA_OV})					
VCCA_OV	1	Overvoltage detected ($V_{CCA} > V_{CCA_{OV}}$)					
	Reset condition	Power on reset/read					
	Description	V _{CCA} undervoltage detection					
	0	No undervoltage (V _{CCA} > V _{CCA_UV})					
VCCA_UV	1	Undervoltage detected (V _{CCA} < V _{CCA_UV})					
	Reset condition	Power on reset/read					
	Description	Report a current limitation condition on V _{CCA}					
	0	No current limitation (I _{CCA} < I _{CCA_LIM})					
	1	Current limitation ($I_{CCA} > I_{CCA_LIM}$)					
	Reset condition	Power on reset/read					
	Description	Maximum current limitation duration. Available only when an external PNP is connected					
ILIM_CCA_OFF	0	T_LIMITATION < T _{CCA_LIM_OFF}					
	1	T_LIMITATION >T_CCA_LIM_OFF					
	Reset condition	Power on reset/read					

Table 47. DIAG_VCCA description and configuration of the bits (default value in bold)

13.3.14 DIAG_VAUX

Table 48. DIAG_VAUX register description

	Read																
		bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
	MOSI	0	0	0	1	1	1	1	0	0	0	0	0	0	0	0	0
	MISO	SPI_G	WU_G	CAN_G	LIN_G	10_G	VPRE G	VCORE G	VOTHERS_ G	0	0	0	TSD_AUX	VAUX_OV	VAUX_UV	ILIM_AUX	ILIM_AUX_ OFF
L							-	-									

Safety power system basis chip with CAN FD and LIN transceivers

	Description	Thermal shutdown of V _{AUX}
	0	No TSD (T _J < T _{SD_AUX})
ISD_AOX	1	TSD occurred ($T_J > T_{SD_AUX}$)
	Reset condition	Power on reset/read
	Description	V _{AUX} overvoltage detection
	0	No overvoltage (V _{AUX} < V _{AUX_OV})
VAUX_UV	1	Overvoltage detected ($V_{AUX} > V_{AUX_{OV}}$)
	Reset condition	Power on reset/read
	Description	V _{AUX} undervoltage detection
	0	No undervoltage (V _{AUX} > V _{AUX_UV})
	1	Undervoltage detected (V _{AUX} < V _{AUX_UV})
WOX_0V	1 Reset condition	Undervoltage detected (V _{AUX} < V _{AUX_UV}) Power on reset/read
	1 Reset condition Description	Undervoltage detected (V _{AUX} < V _{AUX_UV}) Power on reset/read Report a current limitation condition on V _{AUX}
	1 Reset condition Description 0	Undervoltage detected (V _{AUX} < V _{AUX_UV}) Power on reset/read Report a current limitation condition on V _{AUX} No current limitation (I _{AUX} < I _{AUX_LIM})
ILIM_AUX	1 Reset condition Description 0 1	Undervoltage detected (V _{AUX} < V _{AUX_UV}) Power on reset/read Report a current limitation condition on V _{AUX} No current limitation (I _{AUX} < I _{AUX_LIM}) Current limitation (I _{AUX} > I _{AUX_LIM})
ILIM_AUX	1Reset conditionDescription01Reset condition	Undervoltage detected (V _{AUX} < V _{AUX_UV}) Power on reset/read Report a current limitation condition on V _{AUX} No current limitation (I _{AUX} < I _{AUX_LIM}) Current limitation (I _{AUX} > I _{AUX_LIM}) Power on reset/read
ILIM_AUX	1Reset conditionDescription01Reset conditionDescription	Undervoltage detected (V _{AUX} < V _{AUX_UV}) Power on reset/read Report a current limitation condition on V _{AUX} No current limitation (I _{AUX} < I _{AUX_LIM}) Current limitation (I _{AUX} > I _{AUX_LIM}) Power on reset/read Maximum current limitation duration
	1 Reset condition Description 0 1 Reset condition Description 0	Undervoltage detected (V _{AUX} < V _{AUX_UV}) Power on reset/read Report a current limitation condition on V _{AUX} No current limitation (I _{AUX} < I _{AUX_LIM}) Current limitation (I _{AUX} > I _{AUX_LIM}) Power on reset/read Maximum current limitation duration T_LIMITATION < T _{AUX_LIM_OFF}
ILIM_AUX ILIM_AUX_OFF	1Reset conditionDescription01Reset conditionDescription01	Undervoltage detected (V _{AUX} < V _{AUX_UV}) Power on reset/read Report a current limitation condition on V _{AUX} No current limitation (I _{AUX} < I _{AUX_LIM}) Current limitation (I _{AUX} > I _{AUX_LIM}) Power on reset/read Maximum current limitation duration T_LIMITATION < T _{AUX_LIM_OFF} T_LIMITATION > T _{AUX_LIM_OFF}

Table 49. DIAG_VAUX description and configuration of the bits (default value in bold)

13.3.15 DIAG_VSUP_VCAN

Table 50. DIAG_VSUP_VCAN register description

Read																
	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
MOSI	0	0	1	0	0	0	0	0	0	0	0	0	0	0	0	0
MISO	SPI_G	WU_G	CAN_G	LIN_G	IO_G	VPRE _G	VCORE _G	VOTHERS_ G	VSNS_UV	VSUP_ UV_7	IPFF	TSD_CAN	VCAN_OV	VCAN_UV	ILIM_CAN	0

Table 51. DIAG_VSUP_VCAN description and configuration of the bits (default value in bold)

	Description	Detection of battery voltage below V _{SNS_UV}
VONG LIV	0	V _{BAT} > V _{SNS_UV}
0110_01	1	V _{BAT} < V _{SNS_UV}
	Reset condition	Power on reset/read
	Description	Detection of V _{SUP} below V _{SUP_UV_7}
	0	$V_{SUP} > V_{SUP_UV_7}$
	1	$\mathbf{V}_{SUP} < V_{SUP_{UV_{7}}}$
	Reset condition	Power on reset/read

Safety power system basis chip with CAN FD and LIN transceivers

Table 51. DIAG_VSUP_VCAN description and configuration of the bits (default value in bold)...continued

	Description	Input power feed forward (IPFF)					
IDEE	0	Normal operation					
	1	IPFF mode activated					
	Reset condition	Power on reset/read					
	Description	Thermal shutdown of V _{CAN}					
TSD CAN	0	NO TSD (T _J < T _{SD_CAN})					
	1	TSD occurred ($T_J > T_{SD_CAN}$)					
	Reset condition	Power on reset/read					
	Description	V _{CAN} overvoltage detection					
	0	No overvoltage (V _{CAN} < V _{CAN_OV})					
	1	Overvoltage detected ($V_{CAN} > V_{CAN_OV}$)					
	Reset condition	Power on reset/read					
	Description	V _{CAN} undervoltage detection					
	0	No undervoltage (V _{CAN} > V _{CAN_UV})					
VCAN_UV	1	Undervoltage detected (V _{CAN} < V _{CAN_UV})					
	Reset condition	Power on reset/read					
	Description	Report a current limitation condition on V _{CAN}					
	0	No current limitation (I _{CAN} < I _{CAN_LIM})					
	1	Current limitation (I _{CAN} > I _{CAN _LIM})					
	Reset condition	Power on reset/read					

13.3.16 DIAG_CAN_FD

Table 52. DIAG_CAN_FD register description

Read																
	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
MOSI	0	0	1	0	0	0	1	0	0	0	0	0	0	0	0	0
MISO	SPI_G	WU_G	CAN_G	LIN_G	IO_G	VPRE _G	VCORE _G	VOTHERS_ G	CANH_ BATT	CANH_ GND	CANL_ BATT	CANL_ GND	CAN_DOM	0	RXD_REC	TXD_DOM

Table 53. DIAG_CAN_FD description and configuration of the bits (default value in bold)

Description	CANH short-circuit to battery detection
0	No failure
1	Failure detected
Reset condition	Power on reset/read
Description	CANH short-circuit to GND detection
0	No failure
1	Failure detected
Reset condition	Power on reset/read

Safety power system basis chip with CAN FD and LIN transceivers

Table 53. DIAG_CAN_FD description and configuration of the bits (default value in bold)...continued

	Description	CANL short-circuit to battery detection					
	0	No failure					
CANL_DATT	1	Failure detected					
	Reset condition	Power on reset/read					
	Description	CANL short-circuit to GND detection					
	0	No failure					
CANL_GND	1	Failure detected					
	Reset condition	Power on reset/read					
	Description	CAN-bus dominant clamping detection					
	0	No failure					
	1	Failure detected					
	Reset condition	Power on reset/read					
	Description	RXD recessive clamping detection (short-circuit to 5.0 V)					
	0	No failure					
IND_NEC	1	Failure detected					
	Reset condition	Power on reset/read					
	Description	TXD dominant clamping detection (short-circuit to GND)					
	0	No failure					
	1	Failure detected					
	Reset condition	Power on reset/read					

13.3.17 DIAG_CAN_LIN

Table 54. DIAG_CAN_LIN register description

Read																
	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
MOSI	0	0	1	0	0	1	0	0	0	0	0	0	0	0	0	0
MISO	SPI_G	WU_G	CAN_G	LIN_G	IO_G	VPRE _G	VCORE _G	VOTHERS_ G	LIN_DOM	TXDL_ DOM	0	RXDL_ REC	LIN_OT	0	CAN_OT	CAN_OC

Table 55. DIAG_CAN_LIN description and configuration of the bits (default value in bold)

Description	LIN bus dominant clamping detection
0	No failure
1	Failure detected
Reset condition	Power on reset/read
Description	LIN TXD dominant clamping detection (short-circuit to GND)
0	No failure
1	Failure detected
Reset condition	Power on reset/read

Safety power system basis chip with CAN FD and LIN transceivers

Table 55.	DIAG	CAN_	LIN	description	and	configuration	of the b	oits ((default value in bold)continued

	Description	LIN RXD recessive clamping detection (short-circuit to 5.0 V)
	0	No failure
KADL_REC	1	Failure detected
	Reset condition	Power on reset/read
	Description	LIN overtemperature detection
	0	No failure
	1	Failure detected
	Reset condition	Power on reset/read
	Description	CAN overtemperature detection
CAN OT	0	No failure
	1	Failure detected
	Reset condition	Power on reset/read
	Description	CAN overcurrent detection
CAN OC	0	No failure
	1	Failure detected
	Reset condition	Power on reset/read

13.3.18 DIAG_SPI

Table 56. DIAG_SPI register description

Read																
	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
MOSI	0	0	1	0	0	1	1	0	0	0	0	0	0	0	0	0
MISO	SPI_G	WU_G	CAN_G	LIN_G	IO_G	VPRE _G	VCORE _G	VOTHERS G	SPI_ERR	0	SPI_CLK	0	SPI_REQ	0	SPI_ PARITY	0

Table 57. DIAG_SPI description and configuration of the bits (default value in blue)

	Description	Secured SPI communication check
	0	No error
	1	Error detected in the secured bits
	Reset condition	Power on reset/read
	Description	SCLK error detection
	0	16 clock cycles during NCS low
	1	Wrong number of clock cycles (<16 or > 16)
	Reset condition	Power on reset/read
	Description	Invalid SPI access (wrong write or read, write to INIT registers in normal mode, wrong address)
SPI_REQ	0	No error
	1	SPI violation
	Reset condition	Power on reset/read

Safety power system basis chip with CAN FD and LIN transceivers

Table 57. DIAG_SPI description and configuration of the bits (default value in blue)...continued

	Description	SPI parity bit error detection
	0	Parity bit OK
SFI_FARIT	1	Parity bit error
	Reset condition	Power on reset/read

13.3.19 Mode

Table	58.	Mode	register	description
-------	-----	------	----------	-------------

Write																
	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
MOSI	1	0	1	0	1	0	1	Ρ	VKAM_EN	LPOFF_ AUTO_WU	GO_ LPOFF	INT_REQ	Secure_3	Secure_2	Secure_1	Secure_0
MISO	SPI_G	WU_G	CAN_G	LIN_G	IO_G	VPRE _G	VCORE _G	VOTHERS_ G	VKAM_EN	RESERVED	RES ERVED	RES ERVED	INIT	NORMAL	DFS	LPOFF
Read																
	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
MOSI	0	0	1	0	1	0	1	0	0	0	0	0	0	0	0	0
MISO	SPI_G	WU_G	CAN_G	LIN_G	IO_G	VPRE _G	VCORE _G	VOTHERS_ G	VKAM_EN	RESERVED	RES ERVED	RES ERVED	INIT	NORMAL	DFS	LPOFF

Table 59. Mode description and configuration of the bits (default value in bold)

	Description	V _{KAM} control (default state depends on part number)
	0	DISABLED
	1	ENABLED
	Reset condition	Power on reset
	Description	Configure the device in LPOFF_AUTO_WU
	0	No action
LFOFF_AUTO_WO	1	Go to LPOFF mode and wake-up automatically after 1.0 ms
	Reset condition	Power on reset/refresh after LPOFF
	Description	Configure the device in LPOFF–SLEEP
	0	No action
GO_LFOFF	1	Go to LPOFF mode and wait for wake-up event
	Reset condition	Power on reset/refresh after LPOFF
	Description	Request for an INT pulse
INT REO	0	No Request
	1	Request for an INT pulse
	Reset condition	Power on reset
	Description	Report if INIT mode of the main logic state machine is entered
	0	Not in INIT mode
	1	INIT mode
	Reset condition	Power on reset

Safety power system basis chip with CAN FD and LIN transceivers

	Description	Report if normal mode of the main logic state machine is entered
	0	Not in normal mode
NORMAL	1	Normal mode
	Reset condition	Power on reset
	Description	Report if the device resumes from deep fail-safe mode
DES	0	Not in deep fail-safe
	1	Resume from deep fail-safe
	Reset condition	Power on reset/read
	Description	Report if the device resumes from LPOFF-sleep or LPOFF_AUTO_WU mode
	0	Not in LPOFF
	1	Resume from LPOFF
	Reset condition	Power on reset/read
	Description	Secured bits based on write bits
Secure 3:0		Secured_3 = NOT(bit5) Secured_2 = NOT(bit4) Secured_1 = bit7 Secured_0 = bit6

Table 59. Mode description and configuration of the bits (default value in bold)...continued

13.3.20 REG_MODE

Table 60. REG_MODE register description

Write																
	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
MOSI	1	0	1	0	1	1	0	Ρ	VCORE_ EN	VCCA_EN	VAUX_EN	VCAN_EN	Secure_3	Secure_2	Secure_1	Secure_0
MISO	SPI_G	WU_G	CAN_G	LIN_G	10_G	VPRE _G	VCORE _G	VOTHERS G	RES ERVED	RES ERVED	RES ERVED	RES ERVED	VCORE_ EN	VCCA_EN	VAUX_EN	VCAN_EN
Read																
	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
MOSI	0	0	1	0	1	1	0	0	0	0	0	0	0	0	0	0
MISO	SPI_G	WU_G	CAN_G	LIN_G	IO_G	VPRE _G	VCORE _G	VOTHERS G	RES ERVED	RES ERVED	RES ERVED	RES ERVED	VCORE_ EN	VCCA_EN	VAUX_EN	VCAN_EN

Table 61. REG_MODE description and configuration of the bits (default value in bold)

	Description	V_{CORE} control (switch off not recommended if V_{CORE} is safety critical)
VCORE_EN	0	Disabled
	1	Enabled
	Reset condition	Power on reset
	Description	V_{CCA} control (switch off not recommended if V_{CCA} is safety critical)
	0	Disabled
	1	Enabled
	Reset condition	Power on reset

FS6500-FS4500-ASILD Product data sheet

Safety power system basis chip with CAN FD and LIN transceivers

Table 61. REG_MODE description and configuration of the bits (default value in bold)...continued

	Description	V_{AUX} control (switch off not recommended if V_{AUX} is safety critical)
	0	Disabled
VAUX_EN	1	Enabled
	Reset condition	Power on reset
	Description	V _{CAN} control
VCAN EN	0	Disabled
VCAN_EN	1	Enabled
	Reset condition	Power on reset
	Description	Secured bits based on write bits
Secure 3:0		Secured_3 = NOT(bit5) Secured_2 = NOT(bit4) Secured_1 = bit7 Secured_0 = bit6

13.3.21 IO_OUT_AMUX

Table 62. IO_OUT_AMUX register description

Write																
	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
MOSI	1	0	1	0	1	1	1	Ρ	IO_OUT_ 4_EN	IO_OUT_4	0	0	0	AMUX_2	AMUX_1	AMUX_0
MISO	SPI_G	WU_G	CAN_G	LIN_G	IO_G	VPRE _G	VCORE _G	VOTHERS_ G	IO_OUT_ 4_EN	IO_OUT_4	RES ERVED	RES ERVED	RES ERVED	AMUX_2	AMUX_1	AMUX_0
Read																
	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
MOSI	0	0	1	0	1	1	1	0	0	0	0	0	0	0	0	0
MISO	SPI_G	WU_G	CAN_G	LIN_G	IO_G	VPRE _G	VCORE _G	VOTHERS_ G	IO_OUT_ 4_EN	IO_OUT_4	RES ERVED	RES ERVED	RES ERVED	AMUX_2	AMUX_1	AMUX_0

Table 63. IO_OUT_AMUX description and configuration of the bits (default value in bold)

	Description	Enable the output gate driver capability for IO_4
	0	High-impedance (IO_4 configured as input)
10_001_4_EN	1	Enabled (IO_4 configured as output gate driver)
	Reset condition	Power on reset
	Description	Configure IO_4 output gate driver state
	0	Low
10_001_4	1	High
	Reset condition	Power on reset
Safety power system basis chip with CAN FD and LIN transceivers

Table 63. IO_OUT_AMUX description and configuration of the bits (default value in bold)...continued

	Description	Select AMUX output
	000	V _{REF}
	001	V _{SNS} wide range
	010	IO_0 wide range
AMUX 2:0	011	IO_5 wide range
AMOA_2.0	100	V _{SNS} tight range
	101	IO_0 tight range
	110	IO_5 tight range/VKAM
	111	Die Temperature Sensor
	Reset condition	Power on reset

13.3.22 CAN_LIN_MODE

Table 64. CAN_LIN_MODE register description

Write																
	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
MOSI	1	0	1	1	0	0	0	Ρ	CAN_ MODE_1	CAN_ MODE_0	CAN_ AUTO_ DIS	LIN_ MODE_1	LIN_ MODE_0	LIN_ AUTO_ DIS	0	0
MISO	SPI_G	WU_G	CAN_G	LIN_G	10_G	VPRE _G	VCORE _G	VOTHERS G	CAN_ MODE_1	CAN_ MODE_0	CAN_ AUTO_ DIS	LIN_ MODE_1	LIN_ MODE_0	LIN_ AUTO_ DIS	CAN_WU	LIN_WU
Read																
	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
MOSI	0	0	1	1	0	0	0	0	0	0	0	0	0	0	0	0
MISO	SPI_G	WU_G	CAN_G	LIN_G	10_G	VPRE _G	VCORE _G	VOTHERS G	CAN_ MODE_1	CAN_ MODE_0	CAN_ AUTO_ DIS	LIN_ MODE_1	LIN_ MODE_0	LIN_ AUTO_ DIS	CAN_WU	LIN_WU

Table 65. CAN_LIN_MODE description and configuration of the bits (default value in bold)

	Description	Configure the CAN mode
	00	Sleep/no wake-up capability
CAN MODE 1:0 ^[1]	01	Listen only
CAN_WODE_1.0	10	Sleep/wake-up capability
	11	Normal operation mode
	Reset condition	Power on reset
	Description	Automatic CAN TX disable
	0	NO auto disable
CAN_AUTO_DIS	1	Reset CAN_MODE from '11' to '01' on CAN_OT or TXD_DOM or RXD_REC event
	Reset condition	Power on reset

Safety power system basis chip with CAN FD and LIN transceivers

Table 65. CAN_LIN_MODE description and configuration of the bits (default value in bold)...continued

	Description	Configure the LIN mode
	00	Sleep/no wake-up capability
LIN MODE 1:0	01	Listen only
	10	Sleep/wake-up capability
	11	Normal operation mode
	Reset condition	Power on reset
	Description	Automatic LIN mode disable
	0	No auto disable
LIN_AUTO_DIS	1	Reset LIN_mode from '11' to '01' on LIN_OT or TXDL_DOM or RXDL_ REC event
	Reset condition	Power on reset
	Description	Penert a wake up event from the CAN
	Description	Report a wake-up event from the CAN
	0	No wake-up
CAN_WU	0 1	No wake-up Wake-up detected
CAN_WU	0 1 Reset condition	No wake-up Wake-up detected Power on reset/read
CAN_WU	0 1 Reset condition Description	No wake-up Wake-up detected Power on reset/read Report a wake-up event from the LIN
	0 1 Reset condition Description 0	No wake-up Wake-up detected Power on reset/read Report a wake-up event from the LIN No wake-up
CAN_WU	0 1 Reset condition Description 0 1	No wake-up Wake-up detected Power on reset/read Report a wake-up event from the LIN No wake-up Wake-up detected

[1] CAN mode is automatically configured to 'sleep + wake-up capability[10]' if CAN mode was different than 'sleep + no wake-up capability [00]' before the device enters in LPOFF. After LPOFF, the initial CAN mode prior to enter LPOFF is restored.

13.3.23 LDT_AFTER_RUN_1

Table 66. LDT_AFTER_RUN_1 register description

Write																
	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
MOSI	1	0	1	1	0	1	0	Р	B15	B14	B13	B12	B11	B10	B9	B8
MISO	SPI_G	WU_G	CAN_G	LIN_G	IO_G	VPRE _G	VCORE _G	VOTHERS G	B15	B14	B13	B12	B11	B10	B9	B8
Read																
	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
MOSI	0	0	1	1	0	1	0	0	0	0	0	0	0	0	0	0
MISO	SPI_G	WU_G	CAN_G	LIN_G	IO_G	VPRE	VCORE	VOTHERS	B15	B14	B13	B12	B11	B10	B9	B8

Table 67. LDT_AFTER_RUN_1 description and configuration of the bits (default value in bold)

	Description	Long duration timer - after run value
B15:8	00 to FF	After run value (8 most significant bits)
	Reset condition	Power on reset

13.3.24 LDT_AFTER_RUN_2

Table 68. LDT_AFTER_RUN_2 register description

bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
1	0	1	1	0	1	1	Р	B7	B6	B5	B4	B3	B2	B1	B0
SPI_G	WU_G	CAN_G	LIN_G	10_G	VPRE _G	VCORE _G	VOTHERS G	B7	B6	B5	B4	В3	B2	B1	B0
bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
0	0	1	1	0	1	1	0	0	0	0	0	0	0	0	0
SPI_G	WU_G	CAN_G	LIN_G	IO_G	VPRE _G	VCORE _G	VOTHERS G	B7	B6	B5	B4	В3	B2	B1	B0
	bit15 1 SPI_G bit15 0 SPI_G SPI_G	bit15 bit14 1 0 SPI_G WU_G bit15 bit14 0 0 SPI_G WU_G	bit15 bit14 bit13 1 0 1 SPI_G WU_G CAN_G bit15 bit14 bit13 0 0 1 SPI_G WU_G CAN_G	bit15 bit14 bit13 bit12 1 0 1 1 SPI_G WU_G CAN_G LIN_G bit15 bit14 bit13 bit12 0 0 1 1 SPI_G WU_G CAN_G LIN_G Bit15 bit14 bit13 bit12 0 0 1 1 SPI_G WU_G CAN_G LIN_G	bit15 bit14 bit13 bit12 bit11 1 0 1 1 0 SPI_G WU_G CAN_G LIN_G IO_G bit15 bit14 bit13 bit12 bit11 0 0 1 1 0 G SPI_G WU_G CAN_G LIN_G IO_G III1 0 0 1 1 0 G	bit15 bit14 bit13 bit12 bit11 bit10 1 0 1 1 0 1 SPI_G WU_G CAN_G LIN_G IO_G VPRE _G bit15 bit14 bit13 bit12 bit11 bit10 0 0 1 1 0 1 SPI_G WU_G CAN_G LIN_G IO_G VPRE _G SPI_G WU_G CAN_G LIN_G IO_G VPRE _G	bit15 bit14 bit13 bit12 bit11 bit10 bit19 1 0 1 1 0 1 1 SPI_G WU_G CAN_G LIN_G IO_G VPRE _G VCORE _G bit15 bit14 bit13 bit12 bit11 bit10 bit9 0 0 1 1 0 1 1 SPI_G WU_G CAN_G LIN_G IO_G VPRE _G VCORE _G	bit15 bit14 bit13 bit12 bit11 bit10 bit9 bit8 1 0 1 1 0 1 1 P SPI_G WU_G CAN_G LIN_G IO_G VPRE _G VCORE _G VOTHERS _G bit15 bit14 bit13 bit12 bit11 bit10 bit9 bit8 0 0 1 1 0 1 1 0 SPI_G WU_G CAN_G LIN_G IO_G VPRE _G VCORE _G VOTHERS _G	bit15 bit14 bit13 bit12 bit11 bit10 bit9 bit8 bit7 1 0 1 1 0 1 1 P B7 SPI_G WU_G CAN_G LIN_G IO_G VPRE _G VCORE _G VOTHERS G B7 bit15 bit14 bit13 bit12 bit11 bit10 bit9 bit8 bit7 0 1 1 0 1 0 0 SPI_G WU_G CAN_G LIN_G IO_G VPRE _G VCORE _G VOTHERS D SPI_G WU_G CAN_G LIN_G IO_G VPRE _G VCORE _G VOTHERS_B7	bit15 bit14 bit13 bit12 bit11 bit10 bit9 bit8 bit7 bit6 1 0 1 1 0 1 1 P B7 B6 SPI_G WU_G CAN_G LIN_G IO_G VPRE _G VCORE _G VOTHERS G B7 B6 SPI_G WU_G CAN_G LIN_G IO_G VPRE _G VCORE _G VOTHERS_ B10 B7 B6 SPI_G WU_G CAN_G LIN_G IO_G VPRE _G VCORE _G VOTHERS_ B10 B11 B110 B18 B17 B166 SPI_G WU_G CAN_G LIN_G IO_G VPRE _G VCORE _G VOTHERS_ B7 B6	bit15 bit14 bit13 bit12 bit11 bit10 bit9 bit8 bit7 bit6 bit5 1 0 1 1 0 1 1 P B7 B6 B5 SPI_G WU_G CAN_G LIN_G IO_G VPRE _G VCORE _G VOTHERS_ G B7 B6 B5 SPI_G WU_G CAN_G LIN_G IO_G VPRE _G VCORE _G VOTHERS_ B7 B6 B5 SPI_G bit14 bit13 bit12 bit11 bit10 bit9 bit8 bit7 bit6 bit5 0 0 1 1 0 1 0 0 0 0 SPI_G WU_G CAN_G LIN_G IO_G VPRE _G VCORE _G VOTHERS_B7 B7 B6 B5	bit15 bit14 bit13 bit12 bit11 bit10 bit9 bit8 bit7 bit6 bit5 bit4 1 0 1 1 0 1 1 P B7 B6 B5 B4 SPI_G WU_G CAN_G LIN_G IO_G VPRE _G VCORE _G VOTHERS B7 B6 B5 B4 SPI_G WU_G CAN_G LIN_G IO_G VPRE _G VCORE _G VOTHERS B7 B6 B5 B4 SPI_G bit14 bit13 bit12 bit11 bit10 bit9 bit8 bit7 bit6 bit5 bit4 0 0 1 0 1 0 0 0 0 0 SPI_G WU_G CAN_G LIN_G IO_G VPRE _G VCORE _G VOTHERS B7 B6 B5 B4	bit15 bit14 bit12 bit11 bit10 bit9 bit8 bit7 bit6 bit5 bit4 bit3 1 0 1 1 0 1 1 P B7 B6 B5 B4 B3 SPI_G WU_G CAN_G LIN_G IO_G VPRE _G VCORE _G VOTHERS G B7 B6 B5 B4 B3 SPI_G WU_G CAN_G LIN_G IO_G VPRE _G VCORE _G VOTHERS G B7 B6 B5 B4 B3 bit14 bit13 bit12 bit11 bit10 bit8 bit7 bit6 bit5 bit4 bit3 0 0 1 0 bit8 bit7 bit6 bit5 bit4 bit3 0 0 1 0 1 0 0 0 0 0 0 0 0 0 0 0 0	bit15 bit14 bit13 bit12 bit11 bit10 bit3 bit8 bit7 bit6 bit6 bit4 bit3 bit2 1 0 1 1 0 1 1 P B7 B6 B5 B4 B3 B2 SPI_G WU_G CAN_G LIN_G IO_G VPRE _G VCORE _G VOTHERS _G B7 B6 B5 B4 B3 B2 SPI_G WU_G CAN_G LIN_G IO_G VPRE _G VCORE _G VOTHERS _G B7 B6 B5 B4 B3 B2 SPI_G WU_G CAN_G LIN_G IO_G VPRE _G VCORE _G VOTHERS _G B7 B6 B5 B4 B3 b12 SPI_G bit4 bit3 bit10 bit8 bit7 bit6 bit6 bit4 bit3 bit2 0 0 1 0	bit15 bit14 bit13 bit12 bit11 bit10 bit9 bit8 bit7 bit6 bit5 bit4 bit3 bit2 bit1 1 0 1 1 0 1 1 P B7 B6 B5 B4 B3 B2 B1 SPI_G WU_G CAN_G LIN_G IO_G VPRE _G VCORE _G VOTHERS _G B7 B6 B5 B4 B3 B2 B1 SPI_G WU_G CAN_G LIN_G IO_G VPRE _G VCORE _G VOTHERS _G B7 B6 B5 B4 B3 B2 B1 SPI_G WU_G CAN_G LIN_G IO_G VPRE _G VCORE _G VOTHERS _G B7 B6 bit5 bit4 bit3 bit2 bit11 0 0 1 0 1 0 0 0 0 0 0 0 <

Table 69. LDT_AFTER_RUN_2 description and configuration of the bits (default value in bold)

	Description	Long duration timer - after run value
B7:0	00 to FF	After run value (8 least significant bits)
	Reset condition	Power on reset

13.3.25 LDT_WAKE_UP_1

Table 70. LDT_WAKE_UP_1 register description

Write																
	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
MOSI	1	0	1	1	1	0	0	Р	B23	B22	B21	B20	B19	B18	B17	B16
MISO	SPI_G	WU_G	CAN_G	LIN_G	IO_G	VPRE _G	VCORE _G	VOTHERS G	B23	B22	B21	B20	B19	B18	B17	B16
Read																
	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
MOSI	0	0	1	1	1	0	0	0	0	0	0	0	0	0	0	0
MISO	SPI_G	WU_G	CAN_G	LIN_G	IO_G	VPRE _G	VCORE _G	VOTHERS G	B23	B22	B21	B20	B19	B18	B17	B16

Table 71. LDT_WAKE_UP_1 description and configuration of the bits (default value in bold)

	Description	Long duration timer – wake-up value
B23:16	00 to FF	Wake-up value (8 most significant bits)
	Reset condition	Power on reset

13.3.26 LDT_WAKE_UP_2

Table 72. LDT_WAKE_UP_2 register description

vvrite																
	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
MOSI	1	0	1	1	1	0	1	Р	B15	B14	B13	B12	B11	B10	B9	B8
MISO	SPI_G	WU_G	CAN_G	LIN_G	IO_G	VPRE _G	VCORE _G	VOTHERS G	B15	B14	B13	B12	B11	B10	В9	B8

Read																
	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
MOSI	0	0	1	1	1	0	1	0	0	0	0	0	0	0	0	0
MISO	SPI_G	WU_G	CAN_G	LIN_G	IO_G	VPRE _G	VCORE _G	VOTHERS G	B15	B14	B13	B12	B11	B10	B9	B8

Table 73. LDT_WAKE_UP_2 description and configuration of the bits (default value in bold)

	Description	Long duration timer – wake-up value
B15:8	00 to FF	Wake-up value (8 intermediate bits)
	Reset condition	Power on reset

13.3.27 LDT_WAKE_UP_3

Table 74. LDT_WAKE_UP_3 register description

Write																
	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
MOSI	1	0	1	1	1	1	0	Р	B7	B6	B5	B4	B3	B2	B1	B0
MISO	SPI_G	WU_G	CAN_G	LIN_G	IO_G	VPRE _G	VCORE _G	VOTHERS G	B7	B6	B5	B4	B3	B2	B1	B0
Read																
	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
MOSI	0	0	1	1	1	1	0	0	0	0	0	0	0	0	0	0
MISO	SPI_G	WU_G	CAN_G	LIN_G	IO_G	VPRE _G	VCORE _G	VOTHERS G	B7	B6	B5	B4	B3	B2	B1	B0

Table 75. LDT_WAKE_UP_3 description and configuration of the bits (default value in bold)

	Description	Long duration timer – wake-up value
B7:0	00 to FF	Wake-up value (8 least significant bits)
	Reset condition	Power on reset

13.4 Detail of fail-safe logic register mapping

13.4.1 INIT_FS1B_TIMING

Table 76. INIT_FS1B_TIMING register description

write																
	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
MOSI	1	1	0	0	0	0	1	p	FS1B_ TIME_3	FS1B_ TIME_2	FS1B_ TIME_1	FS1B_ TIME_0	SECURE_ 3	SECURE_ 2	SECURE_ 1	SECURE_ 0
MISO	SPI_G	WU_G	CAN_G	LIN_G	IO_G	VPRE _G	VCORE _G	VOTHERS G	SPI_FS_ ERR	SPI_FS_ CLK	SPI_FS_ REQ	SPI_FS_ PARITY	FS1B_ TIME_3	FS1B_ TIME_2	FS1B_ TIME_1	FS1B_ TIME_0

Read																
	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
MOSI	0	1	0	0	0	0	1	0	0	0	0	0	0	0	0	0
MISO	SPI_G	WU_G	CAN_G	LIN_G	10_G	VPRE _G	VCORE _G	VOTHERS G	SPI_FS_ ERR	SPI_FS_ CLK	SPI_FS_ REQ	SPI_FS_ PARITY	FS1B_ TIME_3	FS1B_ TIME_2	FS1B_ TIME_1	FS1B_ TIME_0

FS6500-FS4500-ASILD

All information provided in this document is subject to legal disclaimers.

Safety power system basis chip with CAN FD and LIN transceivers

	Description	FS1B timing range factor x1 (FS1B_TIME_RANGE bit = 0)	FS1B timing range factor x8 (FS1B_TIME_RANGE bit = 1)				
	0000	0	0				
	0001	10 ms	80 ms				
	0010	13 ms	104 ms				
	0011	17 ms	135 ms				
	0100	22 ms	176 ms				
	0101	29 ms	228 ms				
ES1B TIME 3.0	0110	37 ms	297 ms				
(timing made with	0111	48 ms	386 ms				
fail-safe oscillator)	1000	63 ms	502 ms				
	1001	82 ms	653 ms				
	1010	106 ms	848 ms				
	1011	138 ms	1103 ms				
	1100	179 ms	1434 ms				
	1101	233 ms	1864 ms				
	1110	303 ms	2423 ms				
	1111	394 ms	3150 ms				
	Reset condition	Power on reset					
	Description	Secured bits based on write bits					
Secure3:0		Secured_3 = NOT(bit5) Secured_2 = NOT(bit4) Secured_1 = bit7 Secured_0 = bit6					

Table 77. INIT_FS1B_TIMING. Description and configuration of the bits (Default value in bold)

13.4.2 BIST

Table 78. BIST register description

Write																
	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
MOSI	1	1	0	0	0	1	0	Ρ	0	ABIST2_ FS1B	ABIST2_ VAUX	0	Secure_3	Secure_2	Secure_1	Secure_0
MISO	SPI_G	WU_G	CAN_G	LIN_G	10_G	VPRE _G	VCORE _G	VOTHERS G	SPI_FS_ ERR	SPI_FS_ CLK	SPI_FS_ REQ	SPI_FS_ PARITY	LBIST_ OK	ABIST2_ FS1B_OK	ABIST2_ VAUX_OK	ABIST1_ OK
Read																
	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
MOSI	0	1	0	0	0	1	0	0	0	0	0	0	0	0	0	0
MISO	SPI_G	WU_G	CAN_G	LIN_G	IO_G	VPRE _G	VCORE _G	VOTHERS G	SPI_FS_ ERR	SPI_FS_ CLK	SPI_FS_ REQ	SPI_FS_ PARITY	LBIST_ OK	ABIST2_ FS1B_OK	ABIST2_ VAUX_OK	ABIST1_ OK

Safety power system basis chip with CAN FD and LIN transceivers

Table 79. BIST description and configuration of the bits (default value in bold)

	Description	Request ABIST execution on FS1B
ARIST2 ES1R	0	No action
	1	Launch ABIST on FS1B
	Reset condition	Fail-safe power-on-reset
	Description	Request ABIST execution on VAUX
ARIST2 VALLY	0	No action
	1	Launch ABIST on VAUX
	Reset condition	Fail-safe power-on-reset
	Description	Secured bits based on write bits
Secure3:0		Secured_3 = NOT(bit5) Secured_2 = NOT(bit4) Secured_1 = bit7 Secured_0 = bit6
	Description	Diagnostic of fail-safe logic BIST (automatically executed)
	0	LBIST fail
	1	LBIST pass
	Reset condition	Fail-safe power-on-reset
	Description	Diagnostic of FS1B Analog BIST2 (executed on demand)
ABIST2 ES1B OK	0	FS1B ABIST fail or not executed
	1	FS1B ABIST pass
	Reset condition	Fail-safe power-on-reset
	Description	Diagnostic of VAUX Analog BIST2 (executed on demand)
ABIST2 VALLY OK	0	VAUX ABIST fail or not executed
	1	VAUX ABIST pass
	Reset condition	Fail-safe power-on-reset
	Description	Diagnostic of analog BIST1 (automatically executed)
ABIST1 OK	0	ABIST1 fail
ABIST1_OK	1	ABIST1 pass
	Reset condition	Fail-safe power-on-reset

13.4.3 INIT_SUPERVISOR

Table 80.	INIT	SUPERVISOR	register	description
-----------	------	------------	----------	-------------

Write																
	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
MOSI	1	1	0	0	0	1	1	P	VCORE_ 5D	VCCA_5D	VAUX_5D	FS1B_TIME_ RANGE	Secure_3	Secure_2	Secure_1	Secure_0
MISO	SPI_G	WU_G	CAN_G	LIN_G	IO_G	VPRE _G	VCORE _G	VOTHERS G	SPI_FS_ ERR	SPI_FS_ CLK	SPI_FS_ REQ	SPI_FS_ PARITY	VCORE_ 5D	VCCA_5D	VAUX_5D	FS1B_TIME_ RANGE

Read																
	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
MOSI	0	1	0	0	0	1	1	0	0	0	0	0	0	0	0	0
MISO	SPI_G	WU_G	CAN_G	LIN_G	IO_G	VPRE _G	VCORE _G	VOTHERS G	SPI_FS_ ERR	SPI_FS_ CLK	SPI_FS_ REQ	SPI_FS_ PARITY	VCORE_ 5D	VCCA_5D	VAUX_5D	FS1B_TIME_ RANGE

Table 81. INIT_SUPERVISOR description and configuration of the bits (default value in bold)

	Description	Configure the V_{CORE} undervoltage in degraded mode. Only valid for 5.0 V
	0	Normal 5.0 V undervoltage detection threshold (V _{CORE_FB_UV})
VCORE_5D	1	Degraded mode, lower undervoltage detection threshold applied (V_{CORE_FB_ UV_D})
	Reset condition	Power on reset
	Description	Configure the $V_{\mbox{\scriptsize CCA}}$ undervoltage in degraded mode. Only valid for 5.0 V
	0	Normal 5.0 V undervoltage detection threshold (V _{CCA_UV_5})
	1	Degraded mode, lower undervoltage detection threshold applied (V _{CCA_UV_D})
	Reset condition	Power on reset
	Description	Configure the V_{AUX} undervoltage in degraded mode. Only valid for 5.0 V
	0	Normal 5.0 V undervoltage detection threshold (V _{AUX_UV_5})
VAUX_3D	1	Degraded mode; lower undervoltage detection threshold applied (V _{AUX_UV_5D})
	Reset condition	Power on reset
	Description	Configure the FS1B timing range factor x1 or x8
ES1R TIME DANCE	0	x1 timing range factor
FOID_TIME_NANGE	1	x8 timing range factor
	Reset condition	Power on reset
	Description	Secured bits based on write bits
Secure3:0		Secured_3 = NOT(bit5) Secured_2= NOT(bit4) Secured_1=bit7 Secured_0=bit6

13.4.4 INIT_FAULT

Table 82.	INIT	FAULT	register	description
-----------	------	-------	----------	-------------

Write																
	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
MOSI	1	1	0	0	1	0	0	Ρ	FLT_ ERR_FS	FS1B_CAN_ IMPACT	FLT_ERR_ IMP_1	FLT_ERR_ IMP_0	Secure_3	Secure_2	Secure_1	Secure_0
MISO	SPI_G	WU_G	CAN_G	LIN_G	IO_G	VPRE _G	VCORE _G	VOTHERS G	SPI_FS_ ERR	SPI_FS_CLK	SPI_FS_ REQ	SPI_FS_ PARITY	FLT_ ERR_FS	FS1B_CAN_ IMPACT	FLT_ERR_ IMP_1	FLT_ERR_ IMP_0
Read																
	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
MOSI	0	1	0	0	1	0	0	0	0	0	0	0	0	0	0	0
MISO	SPI_G	WU_G	CAN_G	LIN_G	IO_G	VPRE _G	VCORE _G	VOTHERS G	SPI_FS_ ERR	SPI_FS_CLK	SPI_FS_ REQ	SPI_FS_ PARITY	FLT_ ERR_FS	FS1B_CAN_ IMPACT	FLT_ERR_ IMP_1	FLT_ERR_ IMP_0
FS6500-FS	4500-ASILD					All info	rmation prov	ided in this d	ocument is s	ubject to legal dis	sclaimers.			© 2024	NXP B.V. All ri	ghts reserved.

Safety power system basis chip with CAN FD and LIN transceivers

	Description	Configure the values of the fault error counter
	0	intermediate = 3; final = 6
	1	intermediate = 1; final = 2
	Reset condition	Power on reset
	Description	Configure CAN behavior when FS1B is asserted low
	0	No effect
FS1B_CAN_IMPACT	1	CAN in RX only or sleep mode when FS1B is asserted (depends on CAN_DIS_CFG bit in INIT_WU2 register)
	Reset condition	Power on reset
	Description	Configure RSTB and FS0B behavior when fault error counter ≥ intermediate value
	00	No effect on RSTB and FS0B
	01	FS0B is asserted low if FLT_ERR_CNT ≥ intermediate value
FLT_ERR_IMP_1:0	10	RSTB is asserted low if FLT_ERR_CNT ≥ intermediate value and WD error counter = WD_CNT_ERR[1:0]
	11	FS0B is asserted low if FLT_ERR_CNT ≥ intermediate value RSTB is asserted low if FLT_ERR_CNT ≥ intermediate value and WD error counter = WD_CNT_ERR[1:0]
	Reset condition	Power on reset
	Description	Secured bits based on write bits
Secure3:0		Secured_3 = NOT(bit5) Secured_2 = NOT(bit4) Secured_1 = bit7 Secured_0 = bit6

Table 83. INIT_FAULT description and configuration of the bits (default value in bold)

13.4.5 INIT_FSSM

Table 84. INIT_FSSM register description

Write																
	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
MOSI	1	1	0	0	1	0	1	Ρ	IO_45_FS	IO_23_FS	PS	RSTB_ DURATION	Secure_3	Secure_2	Secure_1	Secure_0
MISO	SPI_G	WU_G	CAN_G	LIN_G	IO_G	VPRE _G	VCORE _G	VOTHERS_ G	SPI_FS_ ERR	SPI_FS_ CLK	SPI_FS_ REQ	SPI_FS_ PARITY	IO_45_FS	IO_23_FS	PS	RSTB_ DURATION
Read																
	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
MOSI	0	1	0	0	1	0	1	0	0	0	0	0	0	0	0	0
MISO	SPI_G	WU_G	CAN_G	LIN_G	IO_G	VPRE _G	VCORE _G	VOTHERS_ G	SPI_FS_ ERR	SPI_FS_ CLK	SPI_FS_ REQ	SPI_FS_ PARITY	IO_45_FS	IO_23_FS	PS	RSTB_ DURATION

Safety power system basis chip with CAN FD and LIN transceivers

	Description	Configure the couple of IO_4:5 as safety inputs for external IC error monitoring
IO_45_FS	0	Not safety
	1	Safety critical
	Reset condition	Power on reset
	Description	Configure the couple of IO_3:2 as safety inputs for FCCU monitoring
10 22 58	0	Not safety
10_23_F3	1	Safety critical
	Reset condition	Power on reset
	Description	Configure the F _{CCU} polarity
De	0	Fccu_eaout_1:0 active high
r5	1	Fccu_eaout_1:0 active low
	Reset condition	Power on reset
	Description	Configure the RSTB low duration time
	0	10 ms
KSTB_DORATION	1	1.0 ms
	Reset condition	Power on reset
	Description	Secured bits based on write bits
Secure3:0		Secured_3 = NOT(bit5) Secured_2 = NOT(bit4) Secured_1 = bit7 Secured_0 = bit6

Table 85. INIT_FSSM description and configuration of the bits (default value in bold)

13.4.6 INIT_SF_IMPACT

lable	able 86. INIT_SF_IMPACT register description															
Write																
	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
MOSI	1	1	0	0	1	1	0	Ρ	TDLY_ TDUR	DIS_8S	WD_ IMPACT_1	WD_ IMPACT_0	Secure_3	Secure_2	Secure_1	Secure_0
MISO	SPI_G	WU_G	CAN_G	LIN_G	IO_G	VPRE _G	VCORE _G	VOTHERS G	SPI_FS_ ERR	SPI_FS_ CLK	SPI_FS_ REQ	SPI_FS_ PARITY	TDLY_ TDUR	DIS_8S	WD_ IMPACT_1	WD_ IMPACT_0
Read																
	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
MOSI	0	1	0	0	1	1	0	0	0	0	0	0	0	0	0	0
MISO	SPI_G	WU_G	CAN_G	LIN_G	IO_G	VPRE _G	VCORE _G	VOTHERS G	SPI_FS_ ERR	SPI_FS_ CLK	SPI_FS_ REQ	SPI_FS_ PARITY	TDLY_ TDUR	DIS_8S	WD_ IMPACT_1	WD_ IMPACT_0

Table 86. INIT_SF_IMPACT register description

Safety power system basis chip with CAN FD and LIN transceivers

	Description	FS1B delay or FS1B duration mode selection
	0	FS1B t _{DELAY} mode
	1	FS1B t _{DURATION} mode
	Reset condition	Power on reset
	Description	Disable the 8.0 s timer used to enter deep fail-safe mode
	0	Enabled
013_03	1	Disabled
	Reset condition	Power on reset
	Description	Watchdog impact on RSTB and/or FS0B assertion
	00	No effect on RSTB and FS0B if WD error counter = WD_CNT_ERR[1:0]
	01	RSTB only is asserted low if WD error counter = WD_CNT_ERR[1:0]
WD_INFACT_1.0	10	FS0B only is asserted low if WD error counter = WD_CNT_ERR[1:0]
	11	RSTB and FS0B are asserted low if WD error counter = WD_CNT_ERR[1:0]
	Reset condition	Power on reset
	Description	Secured bits based on write bits
Secure3:0		Secured_3 = NOT(bit5) Secured_2 = NOT(bit4) Secured_1 = bit7 Secured_0 = bit6

Table 87. INIT_SF_IMPACT description and configuration of the bits (default value in bold)

13.4.7 WD_WINDOW

Table 88. WD_WINDOW register description

write.																
	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
MOSI	1	1	0	0	1	1	1	Ρ	WD_ WINDOW_ 3	WD_ WINDOW_ 2	WD_ WINDOW_ 1	WD_ WINDOW_ 0	Secure_3	Secure_2	Secure_1	Secure_0
MISO	SPI_G	WU_G	CAN_G	LIN_G	IO_G	VPRE _G	VCORE _G	VOTHERS G	SPI_FS_ ERR	SPI_FS_ CLK	SPI_FS_ REQ	SPI_FS_ PARITY	WD_ WINDOW_ 3	WD_ WINDOW_ 2	WD_ WINDOW_ 1	WD_ WINDOW_ 0
Read																
	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
MOSI	0	1	0	0	1	1	1	0	0	0	0	0	0	0	0	0
MISO	SPI_G	WU_G	CAN_G	LIN_G	IO_G	VPRE _G	VCORE _G	VOTHERS G	SPI_FS_ ERR	SPI_FS_ CLK	SPI_FS_ REQ	SPI_FS_ PARITY	WD_ WINDOW_ 3	WD_ WINDOW_ 2	WD_ WINDOW_ 1	WD_ WINDOW_ 0

[1] Any write command to the WD_WINDOW register in the normal mode should be followed by a read command to verify the correct change of the WD window duration.

Safety power system basis chip with CAN FD and LIN transceivers

	Description	Configure the watchdog window duration. Duty cycle if set to 50 %
	0000	Disable (in INIT phase only)
	0001	1.0 ms
	0010	2.0 ms
	0011	3.0 ms
	0100	4.0 ms
	0101	6.0 ms
	0110	8.0 ms
	0111	12 ms
	1000	16 ms
	1001	24 ms
	1010	32 ms
	1011	64 ms
	1100	128 ms
	1101	256 ms
	1110	512 ms
	1111	1024 ms
	Reset condition	Power on reset
	Description	Secured bits based on write bits
Secure3:0		Secured_3 = NOT(bit5) Secured_2 = NOT(bit4) Secured_1 = bit7
		Secured_0 = bit6

Table 89. WD_WINDOW description and configuration of the bits (default value in bold)

13.4.8 WD_LFSR

Table 90. WD_LFSR register description

Write																
	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
MOSI	1	1	0	1	0	0	0	Р	WD_LFSR_	WD_LFSR_	6WD_LFSR_	SWD_LFSR_	4WD_LFSR_	3WD_LFSR_	2WD_LFSR_	1WD_LFSR_0
MISO	SPI_G	WU_G	CAN_G	LIN_G	IO_G	VPRE _G	VCORE _G	VOTHERS_ G	WD_LFSR_	WD_LFSR_	6WD_LFSR_	SWD_LFSR_	4WD_LFSR_	3WD_FSR_2	WD_LFSR_	1WD_LFSR_0
						-					-					
Read																
	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
MOSI	0	1	0	1	0	0	0	0	0	0	0	0	0	0	0	0
MISO	SPI_G	WU_G	CAN_G	LIN_G	10_G	VPRE _G	VCORE _G	VOTHERS G	WD_LFSR_	WD_LFSR_	6WD_LFSR_	SWD_LFSR_	4WD_LFSR_	3WD_LFSR_	2WD_LFSR_	1WD_LFSR_0

NXP Semiconductors

FS6500-FS4500-ASILD

Safety power system basis chip with CAN FD and LIN transceivers

Table 91. WD_LFSR description and configuration of the bits (default value in bold)

	Description	WD 8 bits LFSR value. Used to write the seed at any time
	0	bit7:bit0: 10110010 default value at start-up or after a power-on-reset: 0xB2 ^{[1],}
WD_LF3K_7.0	1	
	Reset condition	Power on reset

[1] Value Bit7:Bit0: 1111 1111 is prohibited.

[2] During a write command, MISO reports the previous register content.

13.4.9 WD_ANSWER

Table 92. WD_ANSWER register description

bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
1	1	0	1	0	0	1	Ρ	WD_ ANSWER_ 7	WD_ ANSWER_ 6	WD_ ANSWER_ 5	WD_ ANSWER_ 4	WD_ ANSWER_ 3	WD_ ANSWER_ 2	WD_ ANSWER_ 1	WD_ ANSWER_ 0
SPI_G	WU_G	CAN_G	LIN_G	IO_G	VPRE _G	VCORE _G	VOTHERS G	RSTB	FSxB	WD_BAD_ DATA	FSO_G	IO_FS_G	WD_BAD_ TIMING	ERR_INT_ HW	ERR_INT_ SW
bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
0	1	0	1	0	0	1	0	0	0	0	0	0	0	0	0
SPI_G	WU_G	CAN_G	LIN_G	IO_G	VPRE _G	VCORE _G	VOTHERS G	RSTB	FSxB	WD_BAD_ DATA	FSO_G	IO_FS_G	WD_BAD_ TIMING	ER_INT_ HW	ER_INT_ SW
	bit15 1 SPI_G bit15 0 SPI_G SPI_G	bit15 bit14 1 1 SPI_G WU_G bit15 bit14 0 1 SPI_G WU_G	bit15 bit14 bit13 1 1 0 SPI_G WU_G CAN_G bit15 bit14 bit13 0 1 0 SPI_G WU_G CAN_G	bit15 bit14 bit13 bit12 1 1 0 1 SPI_G WU_G CAN_G LIN_G bit15 bit14 bit13 bit12 0 1 0 1 SPI_G WU_G CAN_G LIN_G SPI_G WU_G CAN_G LIN_G	bit15 bit14 bit13 bit12 bit11 1 1 0 1 0 SPI_G WU_G CAN_G LIN_G IO_G bit15 bit14 bit13 bit12 bit11 0 1 0 1 0_G sepi_G WU_G CAN_G LIN_G IO_G sepi_G WU_G CAN_G LIN_G IO_G	bit15 bit14 bit13 bit12 bit11 bit10 1 1 0 1 0 0 SPI_G WU_G CAN_G LIN_G IO_G VPRE _G bit15 bit14 bit13 bit12 bit11 bit10 0 1 0 1 0 0 SPI_G WU_G CAN_G LIN_G IO_G VPRE _G SPI_G WU_G CAN_G LIN_G IO_G VPRE _G	bit15 bit14 bit13 bit12 bit11 bit10 bit9 1 1 0 1 0 0 1 SPI_G WU_G CAN_G LIN_G IO_G VPRE _G VCORE _G bit15 bit14 bit13 bit12 bit11 bit10 bit9 0 1 0 1 0 0 1 SPI_G WU_G CAN_G LIN_G IO_G VPRE _G VCORE _G	bit15 bit14 bit13 bit12 bit11 bit10 bit9 bit8 1 1 0 1 0 0 1 P SPI_G WU_G CAN_G LIN_G IO_G VPRE _G VCORE _G VOTHERS _G bit15 bit14 bit13 bit12 bit11 bit10 bit9 bit8 0 1 0 1 0 1 0 SPI_G WU_G CAN_G LIN_G IO_G VPRE _G VCORE _G VOTHERS _G	bit15 bit14 bit13 bit12 bit11 bit10 bit9 bit8 bit7 1 1 0 1 0 0 1 P WD_ANSWER_7 SPI_G WU_G CAN_G LIN_G IO_G VPRE VCORE VOTHERS RSTB bit15 bit14 bit13 bit12 bit11 bit10 bit9 bit8 bit7 0 1 0 1 0 1 0 1 SPI_G WU_G CAN_G LIN_G IO_G VPRE VCORE VOTHERS RSTB SPI_G WU_G CAN_G LIN_G IO_G VPRE VCORE VOTHERS RSTB SPI_G WU_G CAN_G LIN_G IO_G VPRE VCORE VOTHERS RSTB	bit15 bit14 bit13 bit12 bit11 bit10 bit9 bit8 bit7 bit6 1 1 0 1 0 0 1 P WD_ANSWER_ 7 WD_ANSWER_ 6 WD_ANSWER_ 6 WD_ANSWER_ 6 WD_ANSWER_ 6 NSWER_ 6 WD_ANSWER_ 6 NSWER_ 6 NSWER_ 6	bit15 bit14 bit13 bit12 bit11 bit10 bit9 bit8 bit7 bit6 bit5 1 1 0 1 0 0 1 P WD_ANSWER_ 7 WD_ANSWER_ 6 WD_ANSWER_ 5 MSWER_ 5 MSWER_ 6 MSWER_ 6 MSWER_ 5 MSWER_ 6 MSWER_ 5 MSWER_ 6 MSWER_ 6 MSWER_ 5 MSWER_ 6 MSWER_ 6 MSWER_ 5 MSWER_ 6 MSWER_ 5 MSWER_ 6 MSWER_ 6 MSWER_ 6 MSWER_ 5 MSWER_ 6 MSWER_	bit15 bit14 bit13 bit12 bit11 bit10 bit9 bit8 bit7 bit6 bit6 bit4 1 1 0 1 0 0 1 P WD_ANSWER_7 WD_ANSWER_6 MSWER_4 NSWER_4 NSWER_4 NSWER_4 NSWER_5 SSWER_4 NSWER_5 SSWER_4 NSWER_5 SSWER_5 SSWER_4 NSWER_5 SSWER_5 SSWER_4 NSWER_5 SSWER_5 SWER_5	bit15 bit14 bit13 bit12 bit11 bit10 bit9 bit8 bit7 bit6 bit5 bit4 bit3 1 1 0 1 0 0 1 P MD_ANSWER_7 MD_ANSWER_6 MD_ANSWER_6 MD_ANSWER_7 ANSWER_6 NSWER_4 ANSWER_ANSWER_3 SPI_G WU_G CAN_G LIN_G IO_G VPRE_G VCORE_G VOTHERS RSTB FSx8 WD_BAD_1 FSO_G IO_FS_G bit15 bit14 bit12 bit11 bit10 bit9 bit8 bit7 bit6 bit5 bit4 bit3 0 1 0 1 bit10 bit9 bit8 bit7 bit6 bit4 bit3 0 1 0 1 0 0 0 0 0 0 0 SPI_G WU_G CAN_G LIN_G IO_G VPRE_G VCORE_G VOTHERS RSTB FSxB WD_BAD_	bit15 bit14 bit13 bit12 bit10 bit3 bit3	bit13 bit13 bit12 bit11 bit10 bit9 bit8 bit7 bit6 bit3 bit4 bit3 bit2 bit1 1 1 0 1 0 1 0 1 P WD_ANSWER_7 WD_ANSWER_6 WD_ANSWER_5 WD_ANSWER_4 MNSWER_ANSWER_3 MNSWER_2 MNSWER_2 MNSWER_2 MNSWER_4 MNSWER_3 MNSWER_4 MNSWER_3 MNSWER_2 MNSWER_4 MNSWER_3 MNSWER_4 MNSWER_3 MNSWER_4 MNSWER_3 MNSWER_2 MNSWER_4 MNSWER_3 MNSWER_4 MNSWER_4 MNSWER_3 MNSWER_4 MNSWER_4

Table 93. WD_ANSWER description and configuration of the bits (default value in bold)

	Description	WD answer from the MCU							
	0	Answer = (NOT(((LFSR x 4)+6)-4))/4							
WD_ANSWER_7.0	1								
	Reset condition	Power on reset/RSTB low							
	Description	Report a reset event							
PSTR	0	No reset							
NOTD	1	Reset occurred							
	Reset condition	Power on reset/read							
	Description	Report a fail-safe event							
	0	No fail-safe							
FSxB	1	Fail-safe event occurred (default state at power up and after LPOFF as FS0B/FS1B are asserted low)							
	Reset condition	Power on reset/read							
	Description	Report a watchdog data refresh error							
	0	WD data refresh OK							
	1	Wrong WD data refresh							
	Reset condition	Power on reset/read							

Safety power system basis chip with CAN FD and LIN transceivers

Table 93.	WD_	ANSWER	description a	and o	configuration of the	ne bits	(default	value in	bold)c	ontinued

	Description	Report a fail-safe output failure							
ESO 0 ^[1]	0	No failure							
-30_6	1	Failure							
	Reset condition	Power on reset/read							
	Description	Report an IO monitoring error							
IO ES C ^[2]	0	No error							
10_F3_6	1	Error detected							
	Reset condition	Power on reset/read							
	Description	Report a watchdog timing refresh error							
	0	WD timing refresh OK							
	1	Wrong WD timing refresh							
	Reset condition	Power on reset/read							
	Description	Report an error from an internal redundant structure of the fail-safe state machine							
ERR_INT_HW	0	No error							
	1	Error detected							
	Reset condition	Power on reset/read							
	Description	Report an error from the EDC of the fail-safe state machine (error detection correction)							
ERR_INT_SW	0	No error							
	1	Error detected							
	Reset condition	Power on reset/read							

[1] **FSO_G** = RSTB_short_high or FS0B_short_high or FS0B_short_low or FS1B_short_high or FS1B_short_low

[2] **IO_FS_G** = IO_23_fail or IO_45_fail

Values of the two registers WD_COUNTER and DIAG_SF_ERR are updated at the end of any SPI access to one of the three registers WD_ANSWER, WD_COUNTER, and DIAG_SF_ERR. To always get up to date values, it is recommended to make two consecutive SPI accesses to WD_COUNTER and DIAG_SF_ERR registers or access (read or write) WD_ANSWER register first.

Example1: read or write WD_ANSWER to update the registers, read WD_COUNTER and DIAG_SF_ERR to report the latest information

Example2: read WD_COUNTER to update the register, read again WD_COUNTER to report the latest information

13.4.10 RELEASE_FSxB

Table 94.	RELEASE	_FSxB	register	description
-----------	---------	-------	----------	-------------

Write																
	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
MOSI	1	1	0	1	0	1	0	Ρ	RELEASE_ FSxB_7	RELEASE_ FSxB_6	RELEASE_ FSxB_5	RELEASE_ FSxB_4	RELEASE_ FSxB_3	RELEASE_ FSxB_2	RELEASE_ FSxB_1	RELEASE_ FSxB_0
MISO	SPI_G	WU_G	CAN_G	LIN_G	IO_G	VPRE _G	VCORE _G	VOTHERS G	SPI_FS_ ERR	SPI_FS_ CLK	SPI_FS_ REQ	SPI_FS_ PARITY	RES ERVED	FS1B_ SNS	FS0B_ SNS	RSTB_ SNS

Read																
	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
MOSI	0	1	0	1	0	1	0	0	0	0	0	0	0	0	0	0
MISO	SPI_G	WU_G	CAN_G	LIN_G	IO_G	VPRE _G	VCORE _G	VOTHERS G	SPI_FS_ ERR	SPI_FS_ CLK	SPI_FS_ REQ	SPI_FS_ PARITY	RES ERVED	FS1B_ SNS	FS0B_ SNS	RSTB_ SNS

Table 95. RELEASE_FSxB description and configuration of the bits (default value in bold)

	Description	Secured 8 bits word to release the FS0B and FS1B pins
DELEASE ESVR 7.0	0	Depends on LFSR_out value and calculation
RELEASE_FOXD_7.0	1	
	Reset condition	Power on reset -> default = 00h
	Description	Sense of FS1B pad
	0	FS1B pad sense low
	1	FS1B pad sense high
	Reset condition	Power on reset
	Description	Sense of FS0B pad
ESOR SNS	0	FS0B pad sense low
	1	FS0B pad sense high
	Reset condition	Power on reset
	Description	Sense of RSTB pad
DOTE ONO	0	RSTB pad sense low
1010_010	1	RSTB pad sense high
	Reset condition	Power on reset

13.4.11 SF_OUTPUT_REQUEST

Table 96. SF_OUTPUT_REQUEST register description

Write																
	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
MOSI	1	1	0	1	0	1	1	Р	FS1B_ REQ	FS1B_ DLY_REQ	FS0B_ REQ	RSTB_ REQ	Secure_3	Secure_2	Secure_1	Secure_0
MISO	SPI_G	WU_G	CAN_G	LIN_G	IO_G	VPRE _G	VCORE _G	VOTHERS G	SPI_FS_ ERR	SPI_FS_ CLK	SPI_FS_ REQ	SPI_FS_ PARITY	FS1B_ DRV	FS1B_ DLY_DRV	FS0B_ DRV	RSTB_ DRV
Read																
	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
MOSI	0	1	0	1	0	1	1	0	0	0	0	0	0	0	0	0
MISO	SPI_G	WU_G	CAN_G	LIN_G	IO_G	VPRE _G	VCORE _G	VOTHERS G	SPI_FS_ ERR	SPI_FS_ CLK	SPI_FS_ REQ	SPI_FS_ PARITY	FS1B_ DRV	FS1B_ DLY_DRV	FS0B_ DRV	RSTB_ DRV

Safety power system basis chip with CAN FD and LIN transceivers

Table 97. SF_OUTPUT_REQUEST description and configuration of the bits (default value in bold)

	Description	Request FS1B to be asserted low
ES1B REO	0	No request
	1	Request FS1B assertion with immediate assertion, no delay
	Reset condition	Power on reset
	Description	Request activation of FS1B internal pull-up (open/close switch S1)
	0	Close S1
	1	Open S1
	Reset condition	Power on reset
	Description	Request FS0B to be asserted low
ESOB REO	0	No request
	1	Request FS0B assertion
	Reset condition	Power On reset
	Description	Request a RSTB low pulse
RSTB REO	0	No request
	1	Request a RSTB low pulse
	Reset condition	Power on reset
	Description	Secured bits based on write bits
Secure3:0		Secured_3 = NOT(bit5) Secured_2 = NOT(bit4) Secured_1 = bit7 Secured_0 = bit6
	Description	Sense of FS1B driver command from fail-safe logic (digital)
	0	FS1B digital driver sense low
FSIB_DRV	1	FS1B digital driver sense high
	Reset condition	Power on reset
	Description	Sense of FS1B driver command from internal pull-up (analog)
	0	FS1B analog driver sense low
	1	FS1B analog driver sense high
	Reset condition	Power on reset
	Description	Sense of FS0B driver command from fail-safe logic
	0	FS0B driver sense low
	1	FS0B driver sense high
	Reset condition	Power on reset
	Description	Sense of RSTB driver command from fail-safe logic
	0	RSTB driver sense low
	1	RSTB driver sense high
	Reset condition	Power on reset

13.4.12 INIT_WD_CNT

Table 98. INIT_WD_CNT register description

144.0															
1115	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
	1	0	1	1	0	0	Ρ	WD_CNT_ ERR_1	WD_CNT_ ERR_0	WD_CNT_ RFR_1	WD_CNT_ RFR_0	Secure_3	Secure_2	Secure_1	Secure_0
iPI_G	WU_G	CAN_G	LIN_G	IO_G	VPRE _G	VCORE _G	VOTHERS G	_SPI_FS_ ERR	SPI_FS_ CLK	SPI_FS_ REQ	SPI_FS_ PARITY	WD_CNT_ ERR_1	WD_CNT_ ERR_0	WD_CNT_ RFR_1	WD_CNT_ RFR_0
it15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
	1	0	1	1	0	0	0	0	0	0	0	0	0	0	0
iPI_G	WU_G	CAN_G	LIN_G	IO_G	VPRE _G	VCORE _G	VOTHERS G	_SPI_FS_ ERR	SPI_FS_ CLK	SPI_FS_ REQ	SPI_FS_ PARITY	WD_CNT_ ERR_1	WD_CNT_ ERR_0	WD_CNT_ RFR_1	WD_CNT_ RFR_0
it1	_G	1 _G WU_G 15 bit14 1 _G WU_G	1 0 _G WU_G CAN_G 1 0 0	1 0 1 _G WU_G CAN_G LIN_G	1 0 1 1 _G WU_G CAN_G LIN_G IO_G 1 bit13 bit12 bit11 1 0 1 1 _G WU_G CAN_G LIN_G IO_G	1 0 1 1 0 _G WU_G CAN_G LIN_G IO_G VPRE _G 15 bit14 bit13 bit12 bit11 bit10 1 0 1 1 0 _G WU_G CAN_G LIN_G IO_G VPRE _G	1 0 1 1 0 0 _G WU_G CAN_G LIN_G IO_G VPRE _G VCORE _G 15 bit14 bit13 bit12 bit11 bit10 bit9 1 0 1 1 0 0 _G WU_G CAN_G LIN_G IO_G VPRE _G VCORE _G	1 0 1 1 0 0 P _G WU_G CAN_G LIN_G IO_G VPRE _G VCORE _G VOTHERS _G 15 bit14 bit13 bit12 bit11 bit10 bit9 bit8 1 0 1 1 0 0 0 _G WU_G CAN_G LIN_G IO_G VPRE _G VCORE _G VOTHERS	1 0 1 1 0 0 P WD_CNT_ ERR_1 _G WU_G CAN_G LIN_G IO_G VPRE _G VCORE _G VOTHERS G SPI_FS_ ERR 15 bit14 bit13 bit12 bit11 bit10 bit9 bit8 bit7 1 0 1 1 0 0 0 0 _G WU_G CAN_G LIN_G IO_G VPRE _G VCORE _G VOTHERS_SPI_FS_ _ERR	1 0 1 1 0 0 P WD_CNT_ ERR_1 WD_CNT_ ERR_0 _G WU_G CAN_G LIN_G IO_G VPRE _G VCORE _G VOTHERS G SPI_FS_ ERR SPI_FS_ CLK 15 bit14 bit13 bit12 bit11 bit10 bit9 bit8 bit7 bit6 1 0 1 1 0 0 0 0 0 _G WU_G CAN_G LIN_G IO_G VPRE _G VCORE _G VOTHERS _G SPI_FS_ _ERR SPI_FS_ _CLK	1 0 1 1 0 0 P WD_CNT_ ERR_1 WD_CNT_ ERR_2 WD_CNT_2 WD_CNT_	1 0 1 1 0 0 P WD_CNT_ ERR_1 WD_CNT_ RFR_2 WD_CNT_ RFR_1 WD_CNT_ RFR_1 WD_CNT_ RFR_1 WD_CNT_ RFR_2 WD_CNT_ RFR_1 WD_CNT_ RFR_2 WD_CNT_ RFR_1 WD_CNT_ RFR	1 0 1 1 0 0 P WD_CNT_ ERR_1 WD_CNT_ ERR_2 WD_CNT_ RFR_1 WD_CNT_ RFR_1 WD_CNT_ RFR_2 Secure_3	1 0 1 1 0 0 P WD_CNT_ ERR_1 WD_CNT_ ERR_0 WD_CNT_ RFR_1 WD_CNT_ RFR_1 WD_CNT_ RFR_0 Secure_3 Secure_2	1 0 1 1 0 0 P WD_CNT_ ERR_1 WD_CNT_ ERR_0 WD_CNT_ RFR_1 WD_CNT_ RFR_1 WD_CNT_ RFR_0 Secure_3 Secure_2 Secure_1

Table 99. INIT_WD_CNT description and configuration of the bits (default value in bold)

	Description	Configure the maximum value of the WD error counter
	00	6
	01	6
	10	4
	11	2
	Reset condition	Power on reset
	Description	Configure the maximum value of the WD refresh counter
	00	6
WD CNT REP 1.0	01	4
	10	2
	11	1
	Reset condition	Power on reset
	Description	Secured bits based on write bits
Secure3:0		Secured_3 = NOT(bit5) Secured_2 = NOT(bit4) Secured_1 = bit7 Secured_0 = bit6

13.4.13 DIAG_SF_IOs

Table 100. DIAG_SF_IOs register description

Read																
	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
MOSI	0	1	0	1	1	0	1	0	0	0	0	0	0	0	0	0
MISO	SPI_G	WU_G	CAN_G	LIN_G	IO_G	VPRE _G	VCORE _G	VOTHERS G	RSTB_ EXT	RSTB_ DIAG	FS0B_ DIAG_1	FS0B_ DIAG_0	FS1B_ DIAG_1	FS1B_ DIAG_0	IO_23_ FAIL	lo_45_ FAIL

Safety power system basis chip with CAN FD and LIN transceivers

Table 101. DIAG_SF_IOs description and configuration of the bits (default value in bold)

	Description	Report an external RSTB								
PSTR FYT	0	No external RSTB								
RSTB_EXT	1	External RSTB								
	Reset condition	Power on reset/read								
	Description	Report a RSTB short-circuit to high								
	0	No Failure								
	1	Short-circuit high								
	Reset condition	Power on reset/read								
	Description	Report a failure on FS0B								
	00	No Failure								
FS0B_DIAG_1:0	01	Short-circuit low/open load								
	1X	Short-circuit high								
	Reset condition	Power on reset/read								
	Description	Report a failure on FS1B								
	00	No Failure								
FS1B_DIAG_1:0	01	Short-circuit low/open load								
	1X	Short-circuit high								
	Reset condition	Power on reset/read								
	Description	Report an error in the FCCU protocol								
IO 23 FAII	0	No error								
	1	Error detected								
	Reset condition	Power on reset/read								
	Description	Report an error in the IO_45 protocol								
	0	No error								
	1	Error detected								
	Reset condition	Power on reset/read								

13.4.14 WD_COUNTER

٦	Fable	102.	WD_	COUNTER	register	description
Г						

Read																
	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
MOSI	0	1	0	1	1	1	0	0	0	0	0	0	0	0	0	0
MISO	SPI_G	WU_G	CAN_G	LIN_G	IO_G	VPRE _G	VCORE _G	VOTHERS_ G	WD_ ERR_2	WD_ ERR_1	WD_ ERR_0	RES ERVED	WD_RFR_ 2	WD_RFR_ 1	WD_RFR_ 0	RES ERVED

FS6500-FS4500-ASILD Product data sheet

Safety power system basis chip with CAN FD and LIN transceivers

Table 103. WD_COUNTER description and configuration of the bits (default value in bold)

	Description	Report the value of the watchdog error counter
	000	From 0 to 5 (6 generate an increase of the FLT_ERR_CNT and this counter is
	to 110	reset to 0)
	Reset condition	Power on reset
	Description	Report the value of the watchdog refresh counter
	000	From 0 to 6 (7 generate a decrease of the FLT_ERR_CNT and this counter is
VVD_NFN_2.0	to 111	reset to 0)
	Reset condition	Power on reset

13.4.15 DIAG_SF_ERR

Table 104	. DIAG	SF	ERR	register	description

Read																
	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
MOSI	0	1	0	1	1	1	1	0	0	0	0	0	0	0	0	0
MISO	SPI_G	WU_G	CAN_G	LIN_G	IO_G	VPRE _G	VCORE _G	VOTHERS G	FLT_ ERR_2	FLT_ ERR_1	FLT_ ERR_0	RES ERVED	V2P5_M_ A_OV	V2P5_M_ D_OV	FCRBM_ OV	FCRBM_ UV

Table 105. DIAG_SF_ERR description and configuration of the bits (default value in bold)

	Description	Report the value of the fault error counter
	000	Error counter is set to 1 by default
FLT_ERR_2:0		
	110	
	Reset condition	Power on reset
	Description	Report an overvoltage on V2P5 main analog regulator
	0	No overvoltage (V _{2P5_M_A} < V _{2P5_M_A_OV})
V2I 0_INI_A_OV	1	Overvoltage detected ($V_{2P5}M_A > V_{2P5}M_AOV$)
	Reset condition	Power on reset/read
	Description	Report an overvoltage on V2P5 main digital regulator
	0	No overvoltage (V _{2P5_M_D} < V _{2P5_M_D} _OV)
V2I 0_IN_D_0V	1	Overvoltage detected ($V_{2P5_M_D} > V_{2P5_M_D_OV}$)
	Reset condition	Power on reset/read
	Description	Report an overvoltage on FCRBM
	0	No overvoltage (FB_Core – FCRBM < 150 mV)
	1	Overvoltage detected (FB_Core – FCRBM > 150 mV)
	Reset condition	Power on reset/read

Safety power system basis chip with CAN FD and LIN transceivers

Table 105. DIAG_SF_ERR description and configuration of the bits (default value in bold)...continued

Description	Report an undervoltage on FCRBM
0	No undervoltage (FB_Core – FCRBM > –150 mV)
1	Undervoltage detected (FB_Core – FCRBM < –150 mV)
Reset condition	Power on reset/read

13.4.16 INIT_VCORE_OVUV_IMPACT

Table	106. I		CORE	ονυ	/_IMPA	ACT re	gister	descrij	otion							
Write							-									
	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
MOSI	1	1	1	0	0	0	1	Р	VCORE_ FS_OV_1	VCORE_ FS_OV_0	VCORE_ FS_UV_1	VCORE_ FS_UV_0	Secure_3	Secure_2	Secure_1	Secure_0
MISO	SPI_G	WU_G	CAN_G	LIN_G	IO_G	VPRE _G	VCORE _G	VOTHERS G	_SPI_FS_ ERR	SPI_FS_ CLK	SPI_FS_ REQ	SPI_FS_ PARITY	VCORE_ FS_OV_1	VCORE_ FS_OV_0	VCORE_ FS_UV_1	VCORE_ FS_UV_0
Read																
	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
MOSI	0	1	1	0	0	0	1	0	0	0	0	0	0	0	0	0
MISO	SPI_G	WU_G	CAN_G	LIN_G	IO_G	VPRE _G	VCORE _G	VOTHERS G	SPI_FS_ ERR	SPI_FS_ CLK	SPI_FS_ REQ	SPI_FS_ PARITY	VCORE_ FS_OV_1	VCORE_ FS_OV_0	VCORE_ FS_UV_1	VCORE_ FS_UV_0

Table 107. INIT_VCORE_OVUV_IMPACT description and configuration of the bits (default value in bold)

	Description	V _{CORE_FB} overvoltage safety impact
	00	No effect of V _{CORE_FB_OV} on RSTB and FS0B
	01	V _{CORE_FB_OV} does have an impact on RSTB only
VCORE_F3_0V_1.0	10	V _{CORE_FB_OV} does have an impact on FS0B only
	11	V _{CORE_FB_OV} does have an impact on RSTB and FS0B
	Reset condition	Power on reset
	Description	V _{CORE_FB} undervoltage safety impact
	00	No effect of V _{CORE_FB_UV} on RSTB and FS0B
VCORE ES LIV 1.0	01	V _{CORE_FB_UV} does have an impact on RSTB only
	10	V _{CORE_FB_UV} does have an impact on FS0B only
	11	V _{CORE_FB_UV} does have an impact on RSTB and FS0B
	Reset condition	Power on reset
	Description	Secured bits based on write bits
Soouro2:0		Secured_3 = NOT(bit5)
Secures.0		Secured_2 = NOT(bit4)
		Secured $0 = bit6$
	1	

13.4.17 INIT_VCCA_OVUV_IMPACT

Table 108. INIT_VCCA_OVUV_IMPACT register description

bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
1	1	1	0	0	1	0	Ρ	VCCA_FS_ OV_1	VCCA_FS_ OV_0	VCCA_FS_ UV_1	VCCA_FS_ UV_0	Secure_3	Secure_2	Secure_1	Secure_0
SPI_G	WU_G	CAN_G	LIN_G	IO_G	VPRE _G	VCORE _G	VOTHERS G	_SPI_FS_ ERR	SPI_FS_ CLK	SPI_FS_ REQ	SPI_FS_ PARITY	VCCA_FS_ OV_1	VCCA_FS_ OV_0	VCCA_FS_ UV_1	VCCA_FS_ UV_0
bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
0	1	1	0	0	1	0	0	0	0	0	0	0	0	0	0
SPI_G	WU_G	CAN_G	LIN_G	IO_G	VPRE _G	VCORE _G	VOTHERS G	_SPI_FS_ ERR	SPI_FS_ CLK	SPI_FS_ REQ	SPI_FS_ PARITY	VCCA_FS_ OV_1	VCCA_FS_ OV_0	VCCA_FS_ UV_1	VCCA_FS_ UV_0
	bit15 1 SPI_G bit15 0 SPI_G SPI_G	bit15 bit14 1 1 SPI_G WU_G bit15 bit14 0 1 SPI_G WU_G	bit15 bit14 bit13 1 1 1 SPI_G WU_G CAN_G bit15 bit14 bit13 0 1 1 SPI_G WU_G CAN_G	bit15 bit14 bit13 bit12 1 1 1 0 SPI_G WU_G CAN_G LIN_G bit15 bit14 bit13 bit12 0 1 1 0 SPI_G WU_G CAN_G LIN_G Bit15 bit14 bit13 bit12 0 1 1 0 SPI_G WU_G CAN_G LIN_G	bit15 bit14 bit13 bit12 bit11 1 1 0 0 SPI_G WU_G CAN_G LIN_G IO_G bit15 bit14 bit13 bit12 bit11 0 1 1 0 0 SPI_G WU_G CAN_G LIN_G IO_G set15 bit14 bit13 bit12 bit11 0 1 1 0 0 SPI_G WU_G CAN_G LIN_G IO_G	bit15 bit14 bit13 bit12 bit11 bit10 1 1 1 0 0 1 SPI_G WU_G CAN_G LIN_G IO_G VPRE _G bit15 bit14 bit13 bit12 bit11 bit10 0 1 1 0 0 1 SPI_G WU_G CAN_G LIN_G IO_G VPRE _G SPI_G WU_G CAN_G LIN_G IO_G VPRE _G	bit15 bit14 bit13 bit12 bit11 bit10 bit9 1 1 1 0 0 1 0 SPI_G WU_G CAN_G LIN_G IO_G VPRE _G VCORE _G bit15 bit14 bit13 bit12 bit11 bit10 bit9 0 1 1 0 0 1 0 SPI_G WU_G CAN_G LIN_G IO_G VPRE _G VCORE _G	bit15 bit14 bit13 bit12 bit11 bit10 bit9 bit8 1 1 1 0 0 1 0 P SPI_G WU_G CAN_G LIN_G IO_G VPRE _G VCORE _G VOTHERS G bit15 bit14 bit13 bit12 bit11 bit10 bit9 bit8 0 1 1 0 0 1 0 0 SPI_G WU_G CAN_G LIN_G IO_G VPRE _G VCORE _G VOTHERS SPI_G WU_G CAN_G LIN_G IO_G VPRE _G VCORE _G VOTHERS	bit15 bit14 bit13 bit12 bit11 bit10 bit9 bit8 bit7 1 1 1 0 0 1 0 P VCCA_FS_OV_1^- SPI_G WU_G CAN_G LIN_G IO_G VPRE_G VCORE_G VOTHERS SPI_FS_ERR bit15 bit14 bit13 bit12 bit11 bit10 bit9 bit8 bit7 0 1 1 0 0 1 0 0 0 SPI_G WU_G CAN_G LIN_G IO_G VPRE_G VCORE_G VOTHERS SPI_FS_G SPI_G WU_G CAN_G LIN_G IO_G VPRE_G VCORE_G VOTHERS SPI_FS_G	bit15 bit14 bit13 bit12 bit11 bit10 bit3 bit8 bit7 bit6 1 1 1 0 0 1 0 P VCCA_FS_ OV_1^FS_ VCCA_FS_ OV_0^FS_ SPI_G WU_G CAN_G LIN_G IO_G VPRE _G VCORE _G VOTHERS SPI_FS_ ERR SPI_FS_ CLK bit15 bit14 bit13 bit12 bit11 bit10 bit9 bit8 bit7 bit6 0 1 1 0 0 1 0 0 0 SPI_G WU_G CAN_G LIN_G IO_G VPRE _G VCORE _G VOTHERS SPI_FS_ _CLK	bit15 bit13 bit12 bit11 bit10 bit3 bit8 bit7 bit6 bit5 bit5 1 1 1 0 0 1 0 P VCCA_FS_ OV_1^S VCCA_FS_ UV_1^S VCCA_FS_ UV_1^S VCCA_FS_ UV_1^S SPI_G WU_G CAN_G LIN_G IO_G VPRE _G VCORE _G VOTHERS SPI_FS_ ERR SPI_FS_ CLK SPI_FS_ REQ bit15 bit14 bit12 bit11 bit10 bit9 bit8 bit7 bit6 bit5 0 1 0 0 1 0 0 0 0 SPI_G WU_G CAN_G LIN_G IO_G VPRE _G VCORE _G VOTHERS SPI_FS_ _G SPI_FS_ _G SPI_FS_ _G SPI_FS_ _G SPI_FS_ _G SPI_FS_ _G SPI_FS_ _CLK SPI_FS_ _REQ	bit15 bit13 bit12 bit11 bit10 bit3 bit3 bit7 bit6 bit5 bit4 1 1 1 0 0 1 0 P VCCA_FS_ OV_1 VCCA_FS_ UV_1 VCCA_FS_ UV_1 VCCA_FS_ UV_1 VCCA_FS_ UV_0 VCCA_FS_ ERR SPI_FS_ CLK SPI_FS_ BARITY SPI_FS_ PARITY bit15 bit14 bit12 bit10 bit9 bit8 bit7 bit6 bit4 bit4 0 1 0 0 1 0 0 0 0 0 SPI_FG _G _G _G _G _G _G _G _G _G _	bit15 bit13 bit12 bit11 bit10 bit3 bit3	bit15 bit13 bit12 bit11 bit10 bit3 bit3	bit15 bit13 bit12 bit10 bit3 bit3

Table 109. INIT_VCCA_OVUV_IMPACT description and configuration of the bits (default value in bold)

	Description	V _{CCA} overvoltage safety impact
	00	No effect of V _{CCA_OV} on RSTB and FS0B
	01	V _{CCA_OV} does have an impact on RSTB only
VCCA_F3_OV_1.0	10	V _{CCA_OV} does have an impact on FS0B only
	11	$\mathbf{V}_{CCA_{OV}}$ does have an impact on RSTB and FS0B
	Reset Condition	Power on reset
	Description	V _{CCA} undervoltage safety impact
	00	No effect of V _{CCA_UV} on RSTB and FS0B
	01	V _{CCA_UV} does have an impact on RSTB only
VCCA_F3_0V_1.0	10	V _{CCA_UV} does have an impact on FS0B only
	11	V _{CCA_UV} does have an impact on RSTB and FS0B
	Reset Condition	Power on reset
	Description	Secured bits based on write bits
Secure3:0		Secured_3 = NOT(bit5) Secured_2 = NOT(bit4) Secured_1 = bit7 Secured_0 = bit6

13.4.18 INIT_VAUX_OVUV_IMPACT

Table 110. INIT_VAUX_OVUV_IMPACT register description

Write																
	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
MOSI	1	1	1	0	0	1	1	P	VAUX_FS_ OV_1	VAUX_FS_ OV_0	VAUX_FS_ UV_1	VAUX_FS_ UV_0	Secure_3	Secure_2	Secure_1	Secure_0
MISO	SPI_G	WU_G	CAN_G	LIN_G	IO_G	VPRE _G	VCORE _G	VOTHERS G	SPI_FS_ ERR	SPI_FS_ CLK	SPI_FS_ REQ	SPI_FS_ PARITY	VAUX_FS_ OV_1	VAUX_FS_ OV_0	VAUX_FS_ UV_1	VAUX_FS_ UV_0

Read																
	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
MOSI	0	1	1	0	0	1	1	0	0	0	0	0	0	0	0	0
MISO	SPI_G	WU_G	CAN_G	LIN_G	IO_G	VPRE _G	VCORE _G	VOTHERS G	SPI_FS_ ERR	SPI_FS_ CLK	SPI_FS_ REQ	SPI_FS_ PARITY	VAUX_FS_ OV_1	VAUX_FS_ OV_0	VAUX_FS_ UV_1	VAUX_FS_ UV_0

Table 111. INIT_VAUX_OVUV_IMPACT description and configuration of the bits (default value in bold)

	Description	V _{AUX} overvoltage safety impact			
	00	No effect of V _{AUX_OV} on RSTB and FS0B			
VALLY ES OV 1.0	01	V _{AUX_OV} does have an impact on RSTB only			
VAOA_1 3_0V_1.0	10	V _{AUX_OV} does have an impact on FS0B only			
	11	V _{AUX_OV} does have an impact on RSTB and FS0B			
	Reset condition	Power on reset			
	Description	V _{AUX} undervoltage safety impact			
	00	No effect of V _{AUX_UV} on RSTB and FS0B			
VALLY ES LIV 1.0	01	V _{AUX_UV} does have an impact on RSTB only			
VAUX_13_0V_1.0	10	V _{AUX_UV} does have an impact on FS0B only			
	11	V _{AUX_UV} does have an impact on RSTB and FS0B			
	Reset condition	Power on reset			
	Description	Secured bits based on write bits			
		Secured_3 = NOT(bit5)			
Secure3:0		Secured_2 = NOT(bit4)			
		Secured_1 = bit7			
		Secured_0 = bit6			

13.4.19 DEVICE_ID_FS

Table 112. DEVICE_ID_FS register description

Read																
	bit15	bit14	bit13	bit12	bit11	bit10	bit9	bit8	bit7	bit6	bit5	bit4	bit3	bit2	bit1	bit0
MOSI	0	1	1	0	1	0	0	0	0	0	0	0	0	0	0	0
MISO	SPI_G	WU_G	CAN_G	LIN_G	IO_G	VPRE _G	VCORE _G	VOTHERS G	RES ERVED	RES ERVED	RES ERVED	RES ERVED	RES ERVED	RES ERVED	DFS_HW2	FS1

Table 113. DEVICE_ID_FS description and configuration of the bits (default value in bold)

Description	Report the deep fail-safe hardware configuration (fail-safe logic)
0	Deep fail-safe disable
1	Deep fail-safe enable
Reset condition	Power on reset

	Description	Report the FS1B function availability (depends on part number)
EQ1	0	Disabled
-51	1	Enabled
	Reset condition	Power on reset

Table 113. DEVICE_ID_FS description and configuration of the bits (default value in bold)...continued

14 List of interruptions and description

The INTB output pin generates a low pulse when an Interrupt condition occurs. The INTB behavior as well as the pulse duration are set through the SPI during INIT phase. It is possible to mask some Interruption source (see <u>Section 13.3</u>).

Event	Description
V _{SNS_UV}	Detection of V _{BATTERY} below 8.5 V
V _{SUP_UV_7}	Detection of V _{SUP} below 7.0 V (after reverse current protection diode)
I _{PFF}	Input power feed forward. Based on V _{SUP} and I _{PRE_PEAK}
I _{LIM_PRE}	Pre-regulator current limitation
T _{WARN_PRE}	Temperature warning on the pass transistor
ВоВ	Return the running state of V _{PRE} converter (buck or boost mode)
V _{PRE_STATE} (V _{PRE_} smps_en)	Return the activation state of V _{PRE} DC-DC converter
V _{PRE} OV	Report a V _{PRE} overvoltage detection
V _{PRE} UV	Report a V _{PRE} undervoltage detection
T _{WARN_CORE}	Temperature warning on the pass transistor
V _{CORE_STATE} (V _{CORE_} SMPS_EN)	Return the activation state of V _{CORE} DC-DC converter
V _{CORE} OV	Report a V _{CORE} overvoltage detection
V _{CORE} UV	Report a V _{CORE} undervoltage detection
I _{LIM_CCA}	V _{CCA} current limitation
I _{LIM_CCA_OFF}	Current limitation maximum duration expiration. Only used when external PNP connected.
T _{WARN_CCA}	Temperature warning on the pass transistor (internal pass transistor only)
TSD _{VCCA}	Temperature shutdown of the VCCA
V _{CCA} OV	Report a V _{CCA} overvoltage detection
V _{CCA} UV	Report a V _{CCA} undervoltage detection
I _{LIM_AUX}	V _{AUX} current limitation
I _{LIM_AUX_OFF}	Current limitation maximum duration expiration. Only used when external PNP connected.
TSD _{VAUX}	Temperature shutdown of the VAUX
V _{AUX} OV	Report a V _{AUX} overvoltage detection
V _{AUX} UV	Report a V _{AUX} undervoltage detection
I _{LIM_CAN}	V _{CAN} current limitation

Table 114. Interruptions list

FS6500-FS4500-ASILD Product data sheet

Safety power system basis chip with CAN FD and LIN transceivers

Event	Description
V _{CAN} OV	Report a V _{CAN} overvoltage detection
TSD _{CAN}	Temperature shutdown on the pass transistor. Auto restart when $T_J < (TSD_{CAN} - TSD_{CAN}_{HYST})$.
V _{CAN} UV	Report a V _{CAN} undervoltage detection
IO_0	Report IO_0 digital state change
IO_2	Report IO_2 digital state change
IO_3	Report IO_3 digital state change
IO_4	Report IO_4 digital state change
IO_5	Report IO_5 digital state change
IO_0_WU	Report IO_0 wake-up event
IO_2_WU	Report IO_2 wake-up event
IO_3_WU	Report IO_3 wake-up event
IO_4_WU	Report IO_4 wake-up event
IO_5_WU	Report IO_5 wake-up event
CAN_WU	Report a CAN wake-up event
CAN_OT	CAN overtemperature detection
RXD_REC	CAN RXD recessive clamping detection (short-circuit to 5.0 V)
TXD_DOM	CAN TXD dominant clamping detection (short-circuit to GND)
CAN_DOM	CAN-bus dominant clamping detection
LIN_WU	Report a LIN wake-up event
LIN_OT	LIN overtemperature detection
RXDL_REC	LIN RXDL recessive clamping detection (short to high)
TXDL_DOM	LIN TXDL dominant clamping detection (short to GND)
LIN_DOM	LIN bus dominant clamping detection
INT_REQ	MCU request for an interrupt pulse
LDT_F1	Long duration timer configured in function 1 and after run value is reach
SPI_ERR	Secured SPI communication check
SPI_CLK	Report a wrong number of CLK pulse different than 16 during the NCS low pulse in main state machine
SPI_REQ	Invalid SPI access (wrong write or read, write to INIT registers in normal mode, wrong address)
SPI_PARITY	Report a parity error in main state machine

Table 114. Interruptions list...continued

15 Typical applications



Safety power system basis chip with CAN FD and LIN transceivers







Safety power system basis chip with CAN FD and LIN transceivers











16 Packaging

16.1 Package mechanical dimensions

Package dimensions are provided in package drawings. To find the most current package outline drawing, go to www.nxp.com and perform a keyword search for the drawing's document number.

 Table 115. Package mechanical dimensions

Package	Suffix	Package outline drawing number
7.0 × 7.0, 48–Pin LQFP exposed pad, with 0.5 mm pitch, and a 4.5 × 4.5 exposed pad	AE	98ASA00173D

Safety power system basis chip with CAN FD and LIN transceivers

16.2 Package outline



FS6500-FS4500-ASILD Product data sheet

Safety power system basis chip with CAN FD and LIN transceivers



Safety power system basis chip with CAN FD and LIN transceivers

NOTES:

② NMP SEMICONDUCTORS N.V. ALL RIGHTS RESERVED DATE: 14 DEC 2017 ③ NMP SEMICONDUCTORS N.V. ALL RIGHTS RESERVED DATE: 14 DEC 2017 Ø NMP SEMICONDUCTORS N.V. ALL RIGHTS RESERVED DATE: 14 DEC 2017	1. DIMENSIONS ARE IN MILLIMETE	<u>-</u> RS.		
 [®] NN 1 FEATURE SHAPE, SIZE AND LOCATION MAY VARY. A DATUMS A, B AND D TO BE DETERMINED AT DATUM PLANE H. DIMENSION TO BE DETERMINED AT SEATING PLANE C. THIS DIMENSION DOES NOT INCLUDE DAMBAR PROTRUSION, ALLOWABLE DAMBAR PROTRUSION SHALL NOT CAUSE THE LEAD WIDTH TO EXCEED THE UPPER LIMIT BY MORE THAN 0.008M AT MAXIMUM MATERIAL CONDITION. DAMBAR CANNOT BE LOCATED ON THE LOWER RADIUS OR THE FOOT. MINIMUM SPACE BETWEEN PROTRUSION AND ADJACENT LEAD SHALL NOT BE LESS THAN 0.07MM. THIS DIMENSION DOES NOT INCLUDE MOLD PROTRUSION, ALLOWABLE PROTRUSION IS 0.25MM PER SIDE. THIS DIMENSION IS MAXIMUM PLASTIC BODY SIZE DIMENSION INCLUDING MOLD MISMATCH. A THIS DIMENSION DOES NOT INCLUDE MOLD FOR POTRUSION, ALLOWABLE PROTRUSION INCLUDING MOLD MISMATCH. A EXACT SHAPE OF EACH CORNER IS OPTIONAL. A HATCHED AREA TO BE KEEP OUT ZONE FOR PCB ROUTING. MATCHED AREA TO BE KEEP OUT ZONE FOR PCB ROUTING. DATE: 14 DEC 2017 MECHANICAL OUTLINE STANDARD: MECHANICAL OUTLINE STANDARD: MECHANICAL OUTLINE DEDEC MS-026 BEC SOTI571-1	2. DIMENSIONING AND TOLERANC	CING PER ASME Y14.5M-	1994.	
A. DATUMS A, B AND D TO BE DETERMINED AT DATUM PLANE H. ADIMENSION TO BE DETERMINED AT SEATING PLANE C. THIS DIMENSION DOES NOT INCLUDE DAMBAR PROTRUSION. ALLOWABLE DAMBAR PROTRUSION SHALL NOT CAUSE THE LEAD WIDTH TO EXCEED THE UPPER LIMIT BY MORE THAN 0.08MM AT MAXIMUM MATERIAL CONDITION. DAMBAR CANNOT BE LOCATED ON THE LOWER RADIUS OR THE FOOT. MINIMUM SPACE BETWEEN PROTRUSION AND ADJACENT LEAD SHALL NOT BE LESS THAN 0.07MM. THIS DIMENSION DOES NOT INCLUDE MOLD PROTRUSION. ALLOWABLE PROTRUSION IS 0.25MM PER SIDE. THIS DIMENSION IS MAXIMUM PLASTIC BODY SIZE DIMENSION INCLUDING MOLD MISMATCH. A EXACT SHAPE OF EACH CORNER IS OPTIONAL. HATCHED AREA TO BE KEEP OUT ZONE FOR PCB ROUTING. DATE: 14 DEC 2017 MECHANICAL OUTLINE STANDARD: DATE: 14 DEC 2017 MECHANICAL OUTLINE JEDEC MS-026 BEC SOTISTI-1 F	A PIN 1 FEATURE SHAPE, SIZE	AND LOCATION MAY VAR	RY.	
 ▲ DIMENSION TO BE DETERMINED AT SEATING PLANE C. ▲ THIS DIMENSION DOES NOT INCLUDE DAMBAR PROTRUSION. ALLOWABLE DAMBAR PROTRUSION SHALL NOT CAUSE THE LEAD WIDTH TO EXCEED THE UPPER LIMIT BY MORE THAN 0.08MM AT MAXIMUM MATERIAL CONDITION. DAMBAR CANNOT BE LOCATED ON THE LOWER REDUKES OR THE FOOT. MINIMUM SPACE BETWEEN PROTRUSION AND ADJACENT LEAD SHALL NOT BE LESS THAN 0.07MM. ▲ THIS DIMENSION DOES NOT INCLUDE MOLD PROTRUSION. ALLOWABLE PROTRUSION IS 0.25MM PER SIDE. THIS DIMENSION IS MAXIMUM PLASTIC BODY SIZE DIMENSION INCLUDING MOLD MISMATCH. ▲ EXACT SHAPE OF EACH CORNER IS OPTIONAL. ▲ HATCHED AREA TO BE KEEP OUT ZONE FOR PCB ROUTING. 	4. DATUMS A, B AND D TO BE	DETERMINED AT DATUM	PLANE H.	
	A DIMENSION TO BE DETERMINE	D AT SEATING PLANE C.		
A THIS DIMENSION DOES NOT INCLUDE MOLD PROTRUSION. ALLOWABLE PROTRUSION IS 0.25MM PER SIDE. THIS DIMENSION IS MAXIMUM PLASTIC BODY SIZE DIMENSION INCLUDING MOLD MISMATCH. A EXACT SHAPE OF EACH CORNER IS OPTIONAL. A HATCHED AREA TO BE KEEP OUT ZONE FOR PCB ROUTING. HATCHED AREA TO BE KEEP OUT ZONE FOR PCB ROUTING. A HATCHED AREA TO BE KEEP OUT ZONE FOR PCB ROUTING. DATE: 14 DEC 2017 MECHANICAL OUTLINE STANDARD: DRAWING NUMBER: REVSION: A STITEZEL A REVISION NOT TO SCALE JEDEC MS-026 BBC SOTIS71-1 F	A THIS DIMENSION DOES NOT IN PROTRUSION SHALL NOT CAU BY MORE THAN 0.08MM AT LOCATED ON THE LOWER RA PROTRUSION AND ADJACENT	ICLUDE DAMBAR PROTRU JSE THE LEAD WIDTH TO MAXIMUM MATERIAL CONI DIUS OR THE FOOT. MINI LEAD SHALL NOT BE LE	SION. ALLOWABLE EXCEED THE UPF DITION. DAMBAR C MUM SPACE BETW SS THAN 0.07MM.	DAMBAR PER LIMIT ANNOT BE ÆEN
© NXP SEMICONDUCTORS N.V. ALL RIGHTS RESERVED DATE: 14 DEC 2017 MECHANICAL OUTLINE STANDARD: DEAWING NUMBER: REVISION: PRINT VERSION NOT TO SCALE JEDEC MS-026 BBC SOT1571-1 F	THIS DIMENSION DOES NOT IN IS 0.25MM PER SIDE. THIS D INCLUDING MOLD MISMATCH.	NCLUDE MOLD PROTRUSIO NIMENSION IS MAXIMUM PI	DN. ALLOWABLE PF LASTIC BODY SIZE	ROTRUSION
AATCHED AREA TO BE KEEP OUT ZONE FOR PCB ROUTING. ONYP SEMICONDUCTORS N.V. ALL RIGHTS RESERVED DATE: 14 DEC 2017 MECHANICAL OUTLINE STANDARD: DRAWING NUMBER: REVISION: PRINT VERSION NOT TO SCALE JEDEC MS-026 BBC SOT1571-1 F	A EXACT SHAPE OF EACH COR	NER IS OPTIONAL.		
© NXP SEMICONDUCTORS N.V. ALL RIGHTS RESERVED DATE: 14 DEC 2017 MECHANICAL OUTLINE STANDARD: DRAWING NUMBER: REVISION: PRINT VERSION NOT TO SCALE JEDEC MS-026 BBC SOT1571-1 F	A HATCHED AREA TO BE KEEP	OUT ZONE FOR PCB RO	UTING.	
© NXP SEMICONDUCTORS N.V. ALL RIGHTS RESERVED DATE: 14 DEC 2017 MECHANICAL OUTLINE STANDARD: DRAWING NUMBER: REVISION: PRINT VERSION NOT TO SCALE JEDEC MS-026 BBC SOT1571-1 F 81 SOT1571-1 Poy E Notos				
MECHANICAL OUTLINE STANDARD: DRAWING NUMBER: REVISION: PRINT VERSION NOT TO SCALE JEDEC MS-026 BBC SOT1571-1 F	© NXP SEMICONDUC	TORS N.V. ALL RIGHTS RESE	ERVED	DATE: 14 DEC 20
81 SOT1571-1 Pov E Notos	MECHANICAL OUTLINE PRINT VERSION NOT TO SCALE	standard: JEDEC MS-026 BBC	drawing number: SOT1571-1	F
	81 SOT1571-1 Pov E Notos			11

Safety power system basis chip with CAN FD and LIN transceivers

17 Soldering



Safety power system basis chip with CAN FD and LIN transceivers



Safety power system basis chip with CAN FD and LIN transceivers



18 References

Obtain additional information on related NXP products and application solutions through the documents and URLs listed below.

- (1) **AN5238** FS6500 and FS4500 Safe System Basis Chip Hardware Design and Product Guidelines Application Note <u>https://www.nxp.com/AN5238-DOWNLOAD</u>
- (2) AN4388 Quad Flat Package (QFP) https://www.nxp.com/files/analog/doc/app_note/AN4388.pdf
- (3) **FS6500-FS4500PDTCALC** Power dissipation tool (Excel File) <u>https://www.nxp.com/files/analog/software_tools/FS6500-FS4500-power-dissipation-calculator.xlsx</u>
- (4) **V**_{CORE} compensation network simulation tool (CNC)^[1]
- (5) **FMEDA** FS6500/FS4500 FMEDA^[1]
- (6) **FS6500-FS4500SMUG** FS6500/FS4500 Safety manual user guide https://www.docstore.nxp.com/products/product-hierarchy?query=Sm5509
- (7) KITFS6507LAEEVM FS6507, System Basis Chip, ASIL B, DC-DC 0.8 A Vcore, LDT, CAN, LIN <u>https://www.nxp.com/KITFS6507LAEEVM</u>
- (8) KITFS4508CAEEVM FS4508, System Basis Chip, ASIL B, Linear 0.5 A Vcore, FS1b, LDT, CAN <u>https://www.nxp.com/KITFS4508CAEEVM</u>
- (9) FS6500 product summary page https://www.nxp.com/FS6500
- (10) FS4500 product summary page https://www.nxp.com/FS4500
- (11) Analog power management homepage https://www.nxp.com/products/power-management
- (12) **ISO 11898-2:2003** Road vehicles Controller area network (CAN) Part 2: High-speed medium access unit https://www.iso.org/standard/33423.html
- (13) ISO 11898-5:2007 Road vehicles Controller area network (CAN) Part 5: High-speed medium access unit with low-power mode https://www.iso.org/contents/data/standard/04/12/41284.html
- (14) ISO 7637-2:2011 Road vehicles Electrical disturbances from conduction and coupling Part 2: Electrical transient conduction along supply lines only <u>https://www.iso.org/standard/50925.html</u>
- (15) **ISO 10605:2008** Road vehicles Test methods for electrical disturbances from electrostatic discharge <u>https://www.iso.org/standard/41937.html</u>
- (16) IEC 61000-4-2:2008 Electromagnetic compatibility (EMC) Part 4-2: Testing and measurement techniques -Electrostatic discharge immunity test <u>https://webstore.iec.ch/publication/4189</u>
- (17) **JESD51- 6** INTEGRATED CIRCUIT THERMAL TEST METHOD ENVIRONMENTAL CONDITIONS FORCED CON VECTION (MOVING AIR)
- (18) **JESD51-7** HIGH EFFECTIVE THERMAL CONDUCTIVITY TEST BOARD FOR LEADED SURFACE MOUNT PAC KAGES
- (19) JESD22-A114F ELECTROSTATIC DISCHARGE (ESD) SENSITIVITY TESTING HUMAN BODY MODEL (HBM)
- (20) **JESD22-C101F** FIELD-INDUCED CHARGED-DEVICE MODEL TEST METHOD FOR ELECTROSTATIC DIS CHARGE WITHSTAND THRESHOLDS OF MICROELECTRONIC COMPONENTS

Safety power system basis chip with CAN FD and LIN transceivers

- (21) MIL-STD-883-1, Method 1012.1 TEST METHOD STANDARD MICROCIRCUITS
- (22) LIN Specification Package Revision 2.1:2006 https://www.lin-cia.org/fileadmin/microsites/lin-cia.org/resources/documents/LIN-Spec_Pac2_1.pdf
- (23) LIN Specification Package Revision 2.2A:2010 https://www.lin-cia.org/fileadmin/microsites/lin-cia.org/resources/documents/LIN_2.2A.pdf
- (24) SAE J2602-2:201211 LIN Network for Vehicle Applications Conformance Test https://www.sae.org/standards/content/j2602/2_201211/

[1] Available upon request.

19 Revision history

Table 117. Revision history

Document ID	Release date	Description
F\$6500-F\$4500-A\$ILD v.8	05 August 2024	 Product data sheet CIN 2024070251 Supercedes FS6500-FS4500 v.7.0 Updated status from confidential to public Updated document title from "FS6500, FS4500" to "FS6500-FS4500-ASILD" Updated Revision history to reflect new NXP standard Section 11.6: changed "(±1.0 % for 5.0 V configuration and ±1.5 % for 3.3 V configuration)," to (±1.0 % for 5.0 V and 3.3 V configuration)," in the second paragraph. Section 12.7.4: changed last sentence of first paragraph from "The voltage accuracy is ±1.0 % for 5.0 V configuration and ±1.5 % for 3.3 V configuration" to "The voltage accuracy is ±1.0 % for 5.0 V and 3.3 V configuration" Changed "master" to "primary" and "slave" to "secondary" throughout, except for LIN topics Section 9 and Section 11.12.3, where "master" was changed to "commander" and "slave" to "responder" Revised Figure 4 In Section 12.5.2,5, changed INIT_WD to INIT_WD_CNT Revised Section 12.8.2 Updated Figure 16 Revised Figure 17 Revised Figure 64 Revised Section 13.1.2 In Section 13.1.4, Corrected Figure 72 Updated description of bit field DEV_REV_2:0 in Table 39 Revised Figure 73

Safety power system basis chip with CAN FD and LIN transceivers

Table 117. Revision history...continued

Document ID	Release date	Description
FS6500-FS4500 v.7.0	11 November 2020	 Product data sheet Updated as per CIN 202011012I The format of this data sheet has been redesigned to comply with the new identity guidelines of NXP Semiconductors, N.V. Legal texts have been adapted to the new company name where appropriate. Changed product status from "Advance information" to "Product data sheet". Global: Performed minor grammar, punctuation, and typographical changes throughout the document. Revised all images in Figures 1 through 78. Section 1, added new paragraph beginning with "High temperature capability" Section 8, Table 4, added footnote on V_{ESD_HBI1}, "Compared to AGND." Section 9, Table 5, revised as follows: V_{DRIVER_DOM}, V_{BUS_DOM} and V_{HYST}: added multiplication operand between the coefficient and V_{SUP} in the Max column. V_{BUS_REC}: added multiplication operand between the coefficient and V_{SUP} in the Min column. V_{BUS_WU} V_{BUS_CNT}: added multiplication operand between the coefficient and V_{SUP} in the Min and Max columns. Section 12.5.7.1, revised the second paragraph Section 16.2, updated the package outline images and created separate figures for each drawing in Figure 79, Figure 80, and Figure 81 Section 17, added new Soldering section and Figure 82, Figure 83, and Figure 84. Section 18, Updated reference to FS6500-FS4500SMUG - FS6500/FS4500 Safety Manual – user guide and added industry standard documents referenced in the narrative.
FS6500-FS4500 v.6.0	October 2017	 Advance Information Updated as per CIN 201709027I Updated pinout diagrams (Figure 5, Figure 6, Figure 7, and Figure 8) Reduced max. value for V_{CCA_OV_5} from 5.6 V to 5.5 V and V_{CCA_OV_33} from 3.7 V to 3.6 V in Table 5 Reduced max. value for V_{AUX_OV_5} from 5.6 V to 5.5 V and V_{AUX_OV_33} from 3.7 V to 3.6 V in Table 5 Reduced max. value for t_{1PWU} from 5.0 µs to 3.5 µs in Table 6 Updated Section 12.5.8 Updated the effect for LIN_DOM bit in Table 15 Updated package drawings
FS6500-FS4500 v.5.0	January 2017	 Advance Information Added C_{IN_CM} and C_{IN_DIFF} parameters in <u>Table 5</u> Reduced I_{BUS_NO_BAT} high limit from 100 μA to 30 μA in <u>Table 5</u> Added Figure 77 Applies for silicon revision DEV_REV_2:0 = "010" in DEVICE_ID register
FS6500-FS4500 v.4.0	January 2017	 Advance Information Corrected R_{0JCTOP} value in <u>Table 4</u> Updated <u>Section 12.5.7</u> Updated <u>Figure 22</u> and <u>Figure 23</u> Corrected typos Applies for silicon revision DEV_REV_2:0 = "010" in DEVICE_ID register
FS6500-FS4500 v.3.0	June 2016	Advance Information
FS6500-FS4500-ASILD	All information provided in	n this document is subject to legal disclaimers. © 2024 NXP B.V. All rights reserved.
Safety power system basis chip with CAN FD and LIN transceivers

Table 11	7. Rev	vision hi	istorycontinue	d
----------	--------	-----------	----------------	---

Document ID	Release date	Description
		 Corrected LIN parameters (V_{BUS_CNT}, D2, D3) in <u>Table 5</u> and <u>Table 6</u> to be compliant with LIN standard Applies for silicon revision DEV_REV_2:0 = "010" in DEVICE_ID register
FS6500-FS4500 v.2.0	June 2016	 Advance Information PPAP release Applies for silicon revision DEV_REV_2:0 = "010" in DEVICE_ID register
FS6500-FS4500 v.1.0	September 2015	 Product preview Initial release Applies for silicon revision DEV_REV_2:0 = "001" in DEVICE_ID register

Safety power system basis chip with CAN FD and LIN transceivers

Legal information

Data sheet status

Document status ^{[1][2]}	Product status ^[3]	Definition
Objective [short] data sheet	Development	This document contains data from the objective specification for product development.
Preliminary [short] data sheet	Qualification	This document contains data from the preliminary specification.
Product [short] data sheet	Production	This document contains the product specification.

[1] Please consult the most recently issued document before initiating or completing a design.

[2] The term 'short data sheet' is explained in section "Definitions".

[3] The product status of device(s) described in this document may have changed since this document was published and may differ in case of multiple devices. The latest product status information is available on the Internet at URL <u>https://www.nxp.com</u>.

Definitions

Draft — A draft status on a document indicates that the content is still under internal review and subject to formal approval, which may result in modifications or additions. NXP Semiconductors does not give any representations or warranties as to the accuracy or completeness of information included in a draft version of a document and shall have no liability for the consequences of use of such information.

Short data sheet — A short data sheet is an extract from a full data sheet with the same product type number(s) and title. A short data sheet is intended for quick reference only and should not be relied upon to contain detailed and full information. For detailed and full information see the relevant full data sheet, which is available on request via the local NXP Semiconductors sales office. In case of any inconsistency or conflict with the short data sheet, the full data sheet shall prevail.

Product specification — The information and data provided in a Product data sheet shall define the specification of the product as agreed between NXP Semiconductors and its customer, unless NXP Semiconductors and customer have explicitly agreed otherwise in writing. In no event however, shall an agreement be valid in which the NXP Semiconductors product is deemed to offer functions and qualities beyond those described in the Product data sheet.

Disclaimers

Limited warranty and liability — Information in this document is believed to be accurate and reliable. However, NXP Semiconductors does not give any representations or warranties, expressed or implied, as to the accuracy or completeness of such information and shall have no liability for the consequences of use of such information. NXP Semiconductors takes no responsibility for the content in this document if provided by an information source outside of NXP Semiconductors.

In no event shall NXP Semiconductors be liable for any indirect, incidental, punitive, special or consequential damages (including - without limitation - lost profits, lost savings, business interruption, costs related to the removal or replacement of any products or rework charges) whether or not such damages are based on tort (including negligence), warranty, breach of contract or any other legal theory.

Notwithstanding any damages that customer might incur for any reason whatsoever, NXP Semiconductors' aggregate and cumulative liability towards customer for the products described herein shall be limited in accordance with the Terms and conditions of commercial sale of NXP Semiconductors.

Right to make changes — NXP Semiconductors reserves the right to make changes to information published in this document, including without limitation specifications and product descriptions, at any time and without notice. This document supersedes and replaces all information supplied prior to the publication hereof.

Applications — Applications that are described herein for any of these products are for illustrative purposes only. NXP Semiconductors makes no representation or warranty that such applications will be suitable for the specified use without further testing or modification.

Customers are responsible for the design and operation of their applications and products using NXP Semiconductors products, and NXP Semiconductors accepts no liability for any assistance with applications or customer product design. It is customer's sole responsibility to determine whether the NXP Semiconductors product is suitable and fit for the customer's applications and products planned, as well as for the planned application and use of customer's third party customer(s). Customers should provide appropriate design and operating safeguards to minimize the risks associated with their applications and products.

NXP Semiconductors does not accept any liability related to any default, damage, costs or problem which is based on any weakness or default in the customer's applications or products, or the application or use by customer's third party customer(s). Customer is responsible for doing all necessary testing for the customer's applications and products using NXP Semiconductors products in order to avoid a default of the applications and the products or of the application or use by customer's third party customer(s). NXP does not accept any liability in this respect.

Limiting values — Stress above one or more limiting values (as defined in the Absolute Maximum Ratings System of IEC 60134) will cause permanent damage to the device. Limiting values are stress ratings only and (proper) operation of the device at these or any other conditions above those given in the Recommended operating conditions section (if present) or the Characteristics sections of this document is not warranted. Constant or repeated exposure to limiting values will permanently and irreversibly affect the quality and reliability of the device.

Terms and conditions of commercial sale — NXP Semiconductors products are sold subject to the general terms and conditions of commercial sale, as published at https://www.nxp.com/profile/terms, unless otherwise agreed in a valid written individual agreement. In case an individual agreement is concluded only the terms and conditions of the respective agreement shall apply. NXP Semiconductors hereby expressly objects to applying the customer's general terms and conditions with regard to the purchase of NXP Semiconductors products by customer.

No offer to sell or license — Nothing in this document may be interpreted or construed as an offer to sell products that is open for acceptance or the grant, conveyance or implication of any license under any copyrights, patents or other industrial or intellectual property rights.

Quick reference data — The Quick reference data is an extract of the product data given in the Limiting values and Characteristics sections of this document, and as such is not complete, exhaustive or legally binding.

Export control — This document as well as the item(s) described herein may be subject to export control regulations. Export might require a prior authorization from competent authorities.

FS6500-FS4500-ASILD

Safety power system basis chip with CAN FD and LIN transceivers

Translations — A non-English (translated) version of a document, including the legal information in that document, is for reference only. The English version shall prevail in case of any discrepancy between the translated and English versions.

Security — Customer understands that all NXP products may be subject to unidentified vulnerabilities or may support established security standards or specifications with known limitations. Customer is responsible for the design and operation of its applications and products throughout their lifecycles to reduce the effect of these vulnerabilities on customer's applications and products. Customer's responsibility also extends to other open and/or proprietary technologies supported by NXP products for use in customer's applications. NXP accepts no liability for any vulnerability. Customer should regularly check security updates from NXP and follow up appropriately. Customer shall select products with security features that best meet rules, regulations, and standards of the intended application and make the ultimate design decisions regarding its products and is solely responsible for compliance with all legal, regulatory, and security related requirements concerning its products, regardless of any information or support that may be provided by NXP.

NXP has a Product Security Incident Response Team (PSIRT) (reachable at <u>PSIRT@nxp.com</u>) that manages the investigation, reporting, and solution release to security vulnerabilities of NXP products.

Suitability for use in automotive applications (functional safety) -This NXP product has been qualified for use in automotive applications. It has been developed in accordance with ISO 26262, and has been ASIL classified accordingly. If this product is used by customer in the development of, or for incorporation into, products or services (a) used in safety critical applications or (b) in which failure could lead to death, personal injury, or severe physical or environmental damage (such products and services hereinafter referred to as "Critical Applications"), then customer makes the ultimate design decisions regarding its products and is solely responsible for compliance with all legal, regulatory, safety, and security related requirements concerning its products, regardless of any information or support that may be provided by NXP. As such, customer assumes all risk related to use of any products in Critical Applications and NXP and its suppliers shall not be liable for any such use by customer. Accordingly, customer will indemnify and hold NXP harmless from any claims, liabilities, damages and associated costs and expenses (including attorneys' fees) that NXP may incur related to customer's incorporation of any product in a Critical Application.

 $\ensuremath{\mathsf{NXP}}\xspace \mathsf{B.V.}$ — NXP B.V. is not an operating company and it does not distribute or sell products.

Trademarks

Notice: All referenced brands, product names, service names, and trademarks are the property of their respective owners. **NXP** — wordmark and logo are trademarks of NXP B.V. **SafeAssure** — is a trademark of NXP B.V.

FS6500-FS4500-ASILD

Safety power system basis chip with CAN FD and LIN transceivers

Tables

Tab. 1.	Part number breakdown4
Tab. 2.	Orderable part variations4
Tab. 3.	FS6500/FS4500 pin definition9
Tab. 4.	Maximum ratings11
Tab. 5.	Static electrical characteristics
Tab. 6.	Dynamic electrical characteristics
Tab. 7.	VCCA/VAUX voltage selection
Tab. 8.	I/Os configuration
Tab. 9.	Regulators and fail-safe pins checked
	during ABIST137
Tab. 10.	Regulators and fail-safe pins checked
	during ABIST2
Tab. 11.	Watchdog error table45
Tab. 12.	RELEASE_FSxB register based on LFSR
	value
Tab. 13.	Long duration timer characteristics
Tab. 14.	CAN diagnostic and CAN error bits77
Tab. 15.	LIN error bits81
Tab. 16.	MOSI bits description84
Tab. 17.	MISO bits description84
Tab. 18.	MISO bits description86
Tab. 19.	Register mapping of main logic86
Tab. 20.	Register mapping of fail-safe logic
Tab. 21.	Secured SPI
Tab. 22.	INIT_VREG register description
Tab. 23.	INIT_VREG description and configuration
	of the bits (default value in bold)88
Tab. 24.	INIT_WU1 register description 89
Tab. 25.	INIT_WU1 description and configuration of
	the bits (default value in bold)89
Tab. 26.	INIT_WU2 register description
Tab. 27.	INIT_WU2 description and configuration of
	the bits (default value in bold)91
Tab. 28.	INIT_INT register description
Tab. 29.	INIT_INT description and configuration of
	the bits (default value in bold)92
Tab. 30.	INIT_INH_INT register description
Tab. 31.	INIT IO_WU2 description and configuration
	of the bits (default value in bold)93
Tab. 32.	LONG_DURATION_TIMER register
	description94
Tab. 33.	LONG_DURATION_TIMER description and
	configuration of the bits (default value in
	bold)
Tab. 34.	HW_CONFIG register description
Tab. 35.	HW_CONFIG description and configuration
	of the bits (default value in bold)95
Tab. 36.	WU_SOURCE register description96
Tab. 37.	WU_SOURCE description and
	configuration of the bits (default value in
	bold)
Tab. 38.	DEVICE_ID register description97
Tab. 39.	DEVICE_ID description and configuration
	of the bits (default value in bold)97
Tab. 40.	IO_INPUT register description

Tab. 41.	IO_INPUT description and configuration of
	the bits
Tab. 42.	DIAG_VPRE register description
Tab. 43.	DIAG_VPRE description and configuration
	of the bits (default value in bold)99
Tab. 44.	DIAG_VCORE register description100
Tab. 45.	DIAG_VCORE description and
	configuration of the bits (default value in
	bold) 100
Tab. 46.	DIAG_VCCA register description 100
lab. 47.	DIAG_VCCA description and configuration
	of the bits (default value in bold)
Tab. 48.	DIAG_VAUX register description
lab. 49.	DIAG_VAUX description and configuration
	of the bits (default value in bold)
Tab. 50.	DIAG_VSUP_VCAN register description 102
lab. 51.	DIAG_VSUP_VCAN description and
	configuration of the bits (default value in
T 1 50	bold)
Tab. 52.	DIAG_CAN_FD register description
Tab. 53.	DIAG_CAN_FD description and
	configuration of the bits (default value in
T 1 - 4	bold)
lab. 54.	DIAG_CAN_LIN register description 104
lab. 55.	DIAG_CAN_LIN description and
	configuration of the bits (default value in
T 1 F 0	bold)
Tab. 56.	DIAG_SPI register description 105
lab. 57.	DIAG_SPI description and configuration of
T 1 50	the bits (default value in blue)
Tab. 58.	Mode register description
Tap. 59.	Mode description and configuration of the
T-1- 00	Dits (default value in bold)
Tab. 60.	REG_MODE register description107
Tap. 61.	REG_MODE description and conliguration
T-1- 00	of the bits (default value in bold)
Tab. 62.	IO_OUT_AMUX register description
Tap. 63.	IO_OUT_AMUX description and
Tab CA	DOID)
Tab. 64.	CAN_LIN_MODE register description
Tab. 65.	CAN_LIN_MODE description and
	configuration of the bits (default value in
T-6 00	DOID)
Tab. 00.	LDT_AFTER_RUN_T register description 110
Tab. 67.	LDI_AFIER_RUN_I description and
	configuration of the bits (default value in
T-6 CO	DOID)
Tab. 68.	LDI_AFTER_RUN_2 register description 111
Tap. 69.	LDI_AFIER_RUN_2 description and
	configuration of the bits (default value in
Tab 70	DUIU)
120.70. Tob 71	LDI_WARE_UP_I register description
iau. / I.	LDI_WARE_UP_I description and
	computation of the bits (default value in
	DOID)

Safety power system basis chip with CAN FD and LIN transceivers

Tab. 72.	LDT_WAKE_UP_2 register description 111
Tab. 73.	LDT_WAKE_UP_2 description and
	configuration of the bits (default value in
	bold) 112
Tab. 74.	LDT WAKE UP 3 register description 112
Tab. 75.	LDT WAKE UP 3 description and
	configuration of the bits (default value in
	bold) 112
Tab. 76.	INIT FS1B TIMING register description 112
Tab. 77.	INIT FS1B TIMING. Description and
	configuration of the bits (Default value in
	bold) 113
Tab 78	BIST register description 113
Tab 79	BIST description and configuration of the
140.10.	bits (default value in bold) 114
Tab 80	INIT_SUPERVISOR register description 114
Tab. 81	INIT_SUPERVISOR description and
140.01.	configuration of the bits (default value in
	bold) 115
Tab 82	INIT FALL Tregister description 115
Tab. 02.	INIT_FAULT description and configuration
Tab. 05.	of the hits (default value in hold) 116
Tab 81	INIT ESSM register description 116
Tab. 04.	INIT_FSSM description and configuration
Tab. 05.	of the hits (default value in hold)
Tab 06	INIT SE IMPACT register description 117
Tab. 00.	INIT_SF_IMPACT description and
Tap. 07.	INIT_SF_IMFACT description and
Tab 00	MD MINDOW register description 119
Tab. 00.	WD_WINDOW register description
Tap. 69.	vvD_vviNDOvv description and
T-1 00	DOID)
Tab. 90.	WD_LFSR register description
Tap. 91.	the hite (default value in held)
T-1- 00	the bits (default value in bold)
Tab. 92.	WD_ANSWER register description 120
Tab. 93.	VVD_ANSVER description and
	configuration of the bits (default value in
	Dold)
1ab. 94.	RELEASE_FSXB register description
Iab. 95.	RELEASE_FSXB description and
	configuration of the bits (default value in
	bold) 122

Figures

FS6500C simplified application diagram - buck boost configuration - FS1B
FS6500L simplified application diagram -
buck configuration - LIN - VCCA = 100 mA3
FS4500C simplified application diagram -
buck boost configuration - FS1B3
FS6500/FS4500 with CAN and LIN
simplified internal block diagram6
FS6500 pinout with CAN and FS1B7
FS6500 pinout with CAN and LIN7
FS6500 pinout without CAN, without LIN8

Tab. 96.	SF_OUTPUT_REQUEST register	
	description	. 122
Tab. 97.	SF_OUTPUT_REQUEST description and	
	configuration of the bits (default value in	
	bold)	. 123
Tab. 98.	INIT WD CNT register description	. 124
Tab. 99.	INIT WD CNT description and	
	configuration of the bits (default value in	
	bold)	. 124
Tab. 100.	DIAG SF IOs register description	. 124
Tab. 101.	DIAG SF IOs description and	
	configuration of the bits (default value in	
	bold)	. 125
Tab. 102.	WD COUNTER register description	. 125
Tab. 103.	WD COUNTER description and	
	configuration of the bits (default value in	
	bold)	. 126
Tab. 104.	DIAG SF ERR register description	. 126
Tab. 105.	DIAG SF ERR description and	
	configuration of the bits (default value in	
	bold)	. 126
Tab. 106.	INIT VCORE OVUV IMPACT register	
	description	. 127
Tab. 107.	INIT VCORE OVUV IMPACT description	
	and configuration of the bits (default value	
	in bold)	. 127
Tab. 108.	INIT VCCA OVUV IMPACT register	
	description	. 128
Tab. 109.	INIT VCCA OVUV IMPACT description	
	and configuration of the bits (default value	
	in bold)	. 128
Tab. 110.	INIT VAUX OVUV IMPACT register	
	description	. 128
Tab. 111.	INIT VAUX OVUV IMPACT description	
	and configuration of the bits (default value	
	in bold)	. 129
Tab. 112.	DEVICE ID FS register description	129
Tab. 113.	DEVICE ID FS description and	
	configuration of the bits (default value in	
	bold)	. 129
Tab. 114.	Interruptions list	.130
Tab. 115.	Package mechanical dimensions	. 135
Tab. 116.	Revision history	.143
Tab. 117.	Revision history	.143

Fig. 8.	FS4500 pinout with CAN and FS1B	8
Fig. 9.	SPI timing diagram	26
Fig. 10.	Register access restriction	27
Fig. 11.	Deep fail-safe enable/disable	29
Fig. 12.	Simplified analog multiplexer block diagram	31
Fig. 13.	IO_2:3 MCU error monitoring: bi-stable	
	protocol	32
Fig. 14.	External error signal handling	33
Fig. 15.	Components involved under ISO pulse in	
	LPOFF	37
Fig. 16.	Simplified state diagram	39
-		

Safety power system basis chip with CAN FD and LIN transceivers

Fig. 17.	Detailed fail-safe state diagram41
Fig. 18.	Watchdog answer calculation42
Fig. 19.	Windowed watchdog with FS clock
	accuracy
Fig. 20.	Watchdog error counter configuration
0	(INIT WD CNT register, Bits WD CNT
	FRR 1:0) 44
Fig 21	Watchdog refresh counter configuration
119.21.	(INIT_WD_CNT register_WD_CNT_PEP
Fig. 00	1.0)
Fig. 22.	Fault error counter ($FLI_ERR_FS = 0$,
	WD_CN1_RFR = 6)46
Fig. 23.	Fault error counter (FLT_ERR_FS = 1,
	WD_CNT_RFR = 6)47
Fig. 24.	Example of WD operation generating a
	reset (WD_CNT_ERR = 6)47
Fig. 25.	Example of RTSB and FS0B behavior
C C	when FLT_ERR_CNT ≥ intermediate value48
Fia. 26.	Example of WD operation leading a
0	decrement of the fault error counter (WD
	CNT RFR = 6) 48
Fig 27	Fault error counter and ES0B deactivation
i ig. 27.	soquence (ELT_EDP_ES = 0 and WD
	$CNT_ERR = 0$
Fig. 28.	FSTB simplified architecture
Fig. 29.	tDELAY operation50
Fig. 30.	Backup delay operation51
Fig. 31.	tDURATION operation52
Fig. 32.	Input voltage range53
Fig. 33.	Pre-regulator: buck configuration
Fig. 34.	Pre-regulator: buck boost configuration54
Fig. 35.	Transition between buck and boost55
Fig. 36.	Buck configuration power up and power
U	down
Fig. 37.	Buck boost configuration power up and
	power down 56
Fig. 38	Rehavior during cranking (buck
i ig. 66.	configuration) 56
Eig 30	Rehavior during cranking (buck boost
Fig. 59.	configuration) 57
Fig. 40	Configuration)
Fig. 40.	Description of light load conditions
Fig. 41.	Input power feed forward principle
Fig. 42.	Overcurrent and current limitation scheme59
Fig. 43.	VPRE efficiency60
Fig. 44.	VCORE buck regulator61
Fig. 45.	Feedback core resistor bridge monitoring
	(FCRBM)
Fig. 46.	VCORE efficiency62
Fig. 47.	VCORE linear regulator
Fig. 48	Example of VAUX used in tracker mode 65
Fig. 49	VAUX current limitation scheme with
	foldback mechanism 65

Fig. 50.	VKAM start-up strategy	66
Fig. 51.	Power dissipation use case	67
Fig. 52.	Power dissipation versus ICORE, ICCA, or	60
Fig 53	Start un scheme	00
Fig. 53.	Long duration timer block diagram	70
Fig. 55	Long duration timer functions	70
Fig. 56.	I ong duration timer state machine	
Fig. 57.	CAN simplified block diagram	73
Fig. 58.	CAN timing diagram	74
Fig. 59.	CAN transition when device goes to	
U	LPOFF	74
Fig. 60.	TXD dominant timeout detection	75
Fig. 61.	Illustration of CANL short to GND detection	
	mechanism	75
Fig. 62.	Overtemperature behavior	76
Fig. 63.	Multiple pulse wake-up pattern illustration	77
Fig. 64.	LIN simplified block diagram	78
Fig. 65.	LIN timings for normal baud rate (20 kB/s)	79
Fig. 66.	LIN timings for slow baud rate (10 kB/s)	79
Fig. 67.	LIN receiver timings	80
Fig. 68.	LIN wake-up pattern illustration	81
Fig. 69.	SPI overview: SPI waveform and signals	
- : - 0	polarity	83
Fig. 70.	MOSI /MISO SPI command organization	83
Fig. 71.	MISO SPI bits 15:8	84
Fig. 72.	MISU SPI bits 7:4	85
Fig. 73.	FS6500 simplified application schematic	
	with CAN, FSTB, VKAW, DUCK/DOOSI VPRE	122
Fig 74	E4500 simplified application schematic	. 152
Fly. 74.	with CAN LIN IO 5 buck only V/PRE	
	configuration	133
Fig 75	VALIX/VCCA connection deep fail-safe	. 100
1 ig. 70.	enabled	133
Fig 76	VAUX not used VCCA configuration up to	
g e.	100 mA, deep fail-safe disabled	134
Fia. 77.	VCCA connection. VAUX not used, deep	
	fail-safe disabled	. 134
Fig. 78.	VCCA connection, VAUX not used, deep	
U	fail-safe enabled	134
Fig. 79.	SOT1571-1 Rev F	136
Fig. 80.	SOT1571-1 Rev. F Detail View	. 137
Fig. 81.	SOT1571-1 Rev F Notes	. 138
Fig. 82.	SOT1571-1 Rev. F - PCB design guidelines	
	- solder mask opening pattern	139
Fig. 83.	SOT1571-1 Rev. F - PCB design guidelines	
	- I/O pads and solderable area	. 140
Fig. 84.	SOT1571-1 Rev. F - PCB design guidelines	
	- solder paste stencil	141

Safety power system basis chip with CAN FD and LIN transceivers

Contents

1	General description	1	12.1.7.4	Reaiste	
2	Features and benefits	1	12.1.7.5	ISO pu	
3	Applications	2	12.2	Mode a	
4	Simplified application diagrams	2		machin	
5	Ordering information	4	1221	IBIST	
51	Part number definition	4	12.2.2	Select	
5.2	Part numbers list	1 	12.2.2	ARIST	
6	Block diagram	 6	12.2.0		
7	Pinning information	0	12.2.0.1	ABIST	
71	Pinning information	7	12.2.0.2	Release	
7.1	Pin description	<i>i</i>	12.2.4		
0 0	Maximum ratings		12.2.0	Normal	
0	Static electrical characteristics	12	12.2.0	Accort	
9 10	Dynamic electrical characteristics	13	12.2.7	Assent	
10	Europianic electrical characteristics	22	12.2.0	Doon f	
11 1	Introduction		12.3	Eupotio	
11.1		21	12.4		
11.2	VOENCE input (VOENCE)		12.5	Fail-sai	
11.3	VSENSE INPUL (VSENSE)	21	12.5.1	Fall-Sal	
11.4	VOODE systematic (VPRE)		12.5.2	vvalcho	
11.5	VCORE output (from 1.0 v to 5.0 v range)	28	12.5.2.1	Normal	
11.6	VCCA output, 5.0 V, or 3.3 V selectable	28	12.5.2.2	Normal	
11.7	VAUX output, 5.0 V, or 3.3 V selectable	28	12.5.2.3	Watchd	
11.8	SELECT input pin	28	12.5.2.4	Wrong	
11.8.1	VCCA, VAUX voltage configuration	28	12.5.2.5	Watchd	
11.8.2	Deep fail-safe configuration	29	12.5.2.6	Watchd	
11.9	CAN_5V voltage regulator	29	12.5.3	Fault e	
11.10	Interrupt (INTB)	29	12.5.3.1	Fault er	
11.11	CANH, CANL, TXD, RXD	29	12.5.3.2	Fault er	
11.11.1	TXD	29		from LF	
11.11.2	RXD	30	12.5.4	RESET	
11.11.3	CANH and CANL	30	12.5.5	Fail-saf	
11.12	LIN, TXDL, RXDL	30	12.5.6	Fail-saf	
11.12.1	TXDL	30	12.5.6.1	tDELAY	
11.12.2	RXDL	30	12.5.6.2	tDURA	
11.12.3	LIN	30	12.5.7	Fail-saf	
11.13	Multiplexer output MUX_OUT	31	12.5.7.1	RELEA	
11.14	I/O pins (I/O_0:I/O_5)	31	12.5.8	SPI DE	
11.15	SAFE output pins (FS0B, FS1B, RSTB)	33	12.6	Input v	
11.15.1	FS0B pin	33	12.7	Power	
11.15.2	FS1B pin	33	12.7.1	VPRE	
11.15.3	RSTB pin	34	12.7.1.1	Power	
11.16	VPU FS (fail-safe pull-up)	34	12.7.1.2	Crankir	
11.17	DEBUG input (entering in debug mode)	34	12.7.1.3	Light lo	
12	Functional device operation	34	12.7.1.4	Input p	
12.1	Mode and state description of the main		12.7.1.5	Overcu	
	state machine	34	12.7.1.6	VPRE	
12.1.1	Buck or buck boost configuration	35	12.7.1.7	VPRE (
12.1.2	VPRF on	35	12.7.2	VCORF	
12.1.2	SELECT pin configuration		12721	VCORE	
12.1.0		35	12.7.2.1	Light Io	
12 1 5	INIT main		12723	Current	
12.1.0	Normal	35	12721	Voltana	
12.1.0	Low-power mode off	35	12.7.2.4	VCOP	
12171	LPOFF - cleen	36	12776		
12.1.7.1	L OFF - SIECP	26	10707	Curront	
12.1.7.2		26	12.1.2.1	Voltogo	
12.1.1.3			12.1.2.0	voltage	
FS6500-FS4500-	S6500-FS4500-ASILD All information provided in this document is subject to legal disclaimers.				

		-
12.1.7.4	Register configuration in LPOFF	5
12175	ISO pulse in LPOFE 36	
12.2	Mode and state description of fail-safe state	
	machine	,
12.2.1	LBIST	,
12.2.2	Select pin configuration	,
12.2.3	ABIST	,
12231	ABIST1 37	,
12.2.3.2	ABIST2 38	5
1224	Release RSTB 38	
12.2.5	INIT ES 38	
12.2.6	Normal WD 38	
12.2.0	Assert RSTB 38	į
12.2.1	Assert FSxB and ABIST2 38	
12.2.0	Deen fail-safe state	Ì
12.0	Functional state diagram	
12.7	Fail-safe machine	
12.5	Fail safe machine state diagram	
12.3.1	Watchdog operation	,
12.5.2	Normal operation (first watchdog refresh) 42	,
12.0.2.1	Normal wetchdog refresh	
12.0.2.2	Wetebdeg in debug mede	
12.3.2.3	Watchdog in debug mode43	
12.5.2.4	Wrong watchdog refresh handling	2
12.5.2.5	Watchdog error counter	•
12.5.2.0	Watchdog refresh counter	
12.5.3	Fault error counter45	,
12.5.3.1	Fault error counter intermediate value	
12.5.3.2	Fault error counter at start-up or resuming	
40 - 4	from LPOFF mode48	,
12.5.4	RESET (RSTB) activation 49	ł
12.5.5	Fail-safe output (FS0B) activation	ł
12.5.6	Fail-safe output (FS1B) activation	1
12.5.6.1	tDELAY operation	1
12.5.6.2	tDURATION operation	
12.5.7	Fail-safe outputs (FS0B and FS1B) release 52	
12.5.7.1	RELEASE_FSxB register	÷
12.5.8	SPI DED	
12.6	Input voltage range53	,
12.7	Power management operation53	,
12.7.1	VPRE voltage pre-regulator54	
12.7.1.1	Power up and power down sequence55)
12.7.1.2	Cranking management 56	Ì
12.7.1.3	Light load condition 57	
12.7.1.4	Input power feed forward condition58	;
12.7.1.5	Overcurrent detection and current limitation 58	6
12.7.1.6	VPRE voltage monitoring 59	
12.7.1.7	VPRE efficiency59)
12.7.2	VCORE voltage regulator60)
12.7.2.1	VCORE DC-DC converter 60)
12.7.2.2	Light load condition 61	
12.7.2.3	Current limitation 61	
12.7.2.4	Voltage monitoring61	
12.7.2.5	VCORE efficiency	
12.7.2.6	VCORE linear regulator62	2
12.7.2.7	Current limitation	5
12.7.2.8	Voltage monitoring63	5

Safety power system basis chip with CAN FD and LIN transceivers

40 7 0		00
12.7.3	Charge pump and bootstrap	63
12.7.4	VCCA voltage regulator	63
12.7.4.1	Current limitation	64
127/2	Voltage monitoring	6/
12.7.4.2		04
12.7.5	VAUX voltage regulator	04
12.7.5.1	Current limitation	65
12.7.5.2	Voltage monitoring	66
12.7.6	CAN 5V voltage regulator	66
1277	VKAM	66
12.7.7	Dower dissinction	67
12.7.0		07
12.7.9	Start-up sequence	68
12.8	Long duration timer	69
12.8.1	Timer characteristics	70
1282	Calibration procedure	70
12.0.2	Timer functions	70
12.0.3		/ 1
12.8.4	limer operation	72
12.9	CAN transceiver	72
12.9.1	Operating modes	73
12911	Normal mode	73
12.0.1.1	Clean made	74
12.9.1.2		74
12.9.2	Fault detection	74
12.9.2.1	TXD permanent dominant (timeout)	74
12.9.2.2	RXD permanent recessive	75
12923	CAN-bus short-circuits	75
12.3.2.3	CAN example the iteritation	
12.9.2.4		70
12.9.2.5	CAN overtemperature	76
12.9.2.6	Distinguish CAN diagnostics and CAN	
	errors	76
1203	Wake-up mechanism	77
12.0.0 1	Multiple pulse detection	
12.9.3.1		
12.10	LIN transceiver	/ /
12.10.1	Simplified block diagram	78
12.10.2	Operating modes	78
12 10 2 1	Normal mode	78
12.10.2.1	Sloop modo	70
12.10.2.2		70
12.10.3	Baud rate selection	/8
12.10.4	Fault detection	80
12.10.4.1	VSUP undervoltage	80
12 10 4 2	TXDL permanent dominant (timeout)	80
12 10 / 3	PXDL permanent recessive	80
12.10.4.3	IN hus short singuit	00
12.10.4.4	LIN bus snort-circuit	80
12.10.4.5	LIN current limitation	80
12.10.4.6	LIN overtemperature	81
12.10.4.7	LIN errors	
12 10 5	Wake-up mechanism	81
12.10.0	Carial narinharal interface	00
13	Serial peripheral interface	02
13.1	High-level overview	82
13.1.1	SPI	82
13.1.2	Parity bit 8 calculation	82
1313	Device status on MISO	82
12 1 4	Period status on whoo	2 02
13.1.4		03
13.2	Detailed operation	83
13.2.1	SPI command organization	83
13.2.2	Main logic general diagnostic	84
1323	Fail-safe logic general diagnostic	85
12.2.4	Main logic register address table	00 96
13.2.4		00
13.2.5	Fail-sate logic register address table	87
13.2.6	Secured SPI command	87
13.3	Detail of main logic register mapping	88

13.3.1	INIT VREG	88
13.3.2	INIT_WU1	89
13.3.3	INIT_WU2	90
13.3.4		91
13.3.5	INIT INH INT	93
13.3.6	LONG DURATION TIMER	94
13.3.7	HW CONFIG	
13.3.8	WU SOURCE	96
13.3.9		97
13.3.10		98
13.3.11	DIAG VPRF	99
13.3.12		100
13 3 13		100
13.3.14		
13.3.15	DIAG VSUP VCAN	. 102
13.3.16	DIAG CAN FD	103
13.3.17	DIAG CAN LIN	. 104
13.3.18	DIAG SPI	105
13.3.19	Mode	. 106
13 3 20	REG MODE	107
13.3.21		108
13.3.22	CAN LIN MODE	109
13 3 23	LDT AFTER RUN 1	110
13.3.24	IDT AFTER RUN 2	
13.3.25	LDT WAKE UP 1	
13.3.26	LDT WAKE UP 2	
13.3.27		112
13.4	Detail of fail-safe logic register mapping	112
13.4.1	INIT FS1B TIMING	112
13.4.2	BIST	113
13.4.3	INIT SUPERVISOR	114
13.4.4	INIT FAULT	. 115
13.4.5	INIT FSSM	116
13.4.6	INIT SF IMPACT	. 117
13.4.7	WD_WINDOW	. 118
13.4.8	WD_LFSR	119
13.4.9	WD_ANSWER	. 120
13.4.10	RELEASE_FSxB	121
13.4.11	SF OUTPUT REQUEST	. 122
13.4.12	INIT_WD_CNT	124
13.4.13	DIAG_SF_IOs	124
13.4.14	WD_COUNTER	. 125
13.4.15	DIAG_SF_ERR	126
13.4.16	INIT_VCORE_OVUV_IMPACT	127
13.4.17	INIT_VCCA_OVUV_IMPACT	128
13.4.18	INIT_VAUX_OVUV_IMPACT	. 128
13.4.19	DEVICE_ID_FS	. 129
14	List of interruptions and description	. 130
15	Typical applications	132
16	Packaging	135
16.1	Package mechanical dimensions	135
16.2	Package outline	136
17	Soldering	. 139
18	References	142
19	Revision history	143
	Legal information	146

Safety power system basis chip with CAN FD and LIN transceivers

Please be aware that important notices concerning this document and the product(s) described herein, have been included in section 'Legal information'.

© 2024 NXP B.V.

All rights reserved.

For more information, please visit: https://www.nxp.com

Document feedback Date of release: 5 August 2024 Document identifier: FS6500-FS4500-ASILD

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

NXP:

MC33FS6523CAE MC33FS6523CAER2 MC33FS6513CAE MC33FS6511CAE MC33FS6512NAER2 MC33FS6522CAE MC33FS6521CAER2 MC33FS6512LAE MC33FS6520NAER2 MC33FS4502CAE MC33FS6510CAE MC33FS4501NAER2 MC33FS6520LAE MC33FS6520CAER2 MC33FS6511CAER2 MC33FS6511NAER2 MC33FS6522LAER2 MC33FS6514LAE MC33FS6510CAER2 MC33FS6513CAER2 MC33FS6501CAE MC33FS6502LAER2 MC33FS4500CAE MC33FS6522CAER2 MC33FS6521NAE MC33FS6521NAER2 MC33FS6502LAE MC33FS6523NAE MC33FS4503NAER2 MC33FS6520LAER2 MC33FS6500CAE MC33FS6514LAER2 MC33FS6503NAER2 MC33FS6502CAE MC33FS6512LAER2 MC33FS6503CAE MC33FS4500LAE MC33FS6510LAER2 MC33FS4502LAE MC33FS4502CAER2 MC33FS6522NAE MC33FS4500LAER2 MC33FS6520CAE MC33FS6503CAER2 MC33FS6500LAE MC33FS6501NAER2 MC33FS6512CAER2 MC33FS6512CAE MC33FS4503NAE MC33FS6520NAE MC33FS6502NAE MC33FS6502CAER2 MC33FS4501CAER2 MC33FS6500NAE MC33FS4501NAE MC33FS6502NAER2 MC33FS6500NAER2 MC33FS6511NAE MC33FS6513NAE MC33FS4500CAER2 MC33FS6521CAE MC33FS6510LAE MC33FS4501CAE MC33FS6512NAE MC33FS6523NAER2 MC33FS6500LAER2 MC33FS4502NAER2 MC33FS4503CAE MC33FS6504LAE MC33FS6500CAER2 MC33FS4500NAE MC33FS6501CAER2 MC33FS4500NAER2 MC33FS6503NAE MC33FS6510NAER2 MC33FS4502LAER2 MC33FS4503CAER2 MC33FS6504LAER2 MC33FS4502NAE MC33FS6522NAER2 MC33FS6510NAE MC33FS6513NAER2 MC33FS6501NAE MC33FS6522LAE