


SCHEMATIC  
VIEW FROM BASE END  
FUSE RECOMMENDED BUT NOT SUPPLIED

SPECIFICATIONS											
WIRING	INPUT		OUTPUT					SHAFT ROTATION TO INCREASE VOLTAGE	TERMINAL CONNECTIONS		
	VOLTS	HERTZ	VOLTS	CONSTANT CURRENT LOAD		CONSTANT IMPEDANCE LOAD			FOR INCREASING VOLTAGE AS VIEWED FROM BASE END		
				MAX. AMPS	MAX. KVA	MAX. AMPS	MAX. KVA		INPUT	JUMPER	OUTPUT
SINGLE PHASE	120	50/60	0-120	10	1.2	13	1.56	CW	1-4	—	4-3
			0-140	10	1.4	—	—	CCW	1-4	—	1-3
								CW	4-5	—	4-3
								CCW	1-2	—	1-3
UNLESS OTHERWISE SPECIFIED, TOLERANCE IS ±			TITLE: SPEC. CONTROL DRAWING VARIABLE TRANSFORMER MODEL: 1010BCT								
DECIMALS .XX .0005											
HOLES .002											
ANGLES 1°			DRAFT 1-1/2°			UNITS IN [mm]			 A Components Corporation of America Company 303 Gladis Boulevard Dayton, Ohio 45403 USA		
MATERIAL			ALL DIMENSIONS APPLY AFTER PLATING								
The information and design disclosed herein was originated by and is the property of STACO ENERGY PRODUCTS CO., which reserves all patent, proprietary, design, manufacturing, reproduction, use and sale rights thereto, and to any article disclosed therein except to the extent rights are expressly granted to others. The foregoing does not apply to vendor proprietary parts.											
DRAWN BY S.A. SMITH			DATE 9/17/97		FIRST USED ON			DO NOT SCALE DWG.		DWG. NO. 031-1655	
CHECKER			DATE		WEIGHT APPROX. 10.25 LBS			CAGE CODE 83008			
ENGINEER			DATE		SCALE 1=1			SHEET 1 OF 1			



# Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Staco:

1010BCT