



SCHEMATIC
VIEW FROM BASE END
FUSE RECOMMENDED BUT NOT SUPPLIED

SPECIFICATIONS															
WIRING	INPUT		VOLTS	OUTPUT				SHAFT ROTATION TO INCREASE VOLTAGE	TERMINAL CONNECTIONS						
	VOLTS	HERTZ		CONSTANT CURRENT LOAD		CONSTANT IMPEDANCE LOAD			FOR INCREASING VOLTAGE AS VIEWED FROM BASE END						
				MAX. AMPS	MAX. KVA	MAX. AMPS	MAX. KVA		INPUT	JUMPER	OUTPUT				
SINGLE PHASE	120	60	0-120	12	1.44	15	1.80	CW	1-4	—	4-3				
								CCW	1-4	—	1-3				
UNLESS OTHERWISE SPECIFIED, TOLERANCE IS ± DECIMALS .06 ANGLES 1° DRAFT 1-1/2° .XX .0005 XXX .005				TITLES				SPEC. CONTROL DRAWING VARIABLE TRANSFORMER MODEL: 1210BCT							
MATERIAL				UNITS IN [mm]				<div>STACO ENERGY PRODUCTS CO. <small>A Components Corporation of America Company 302 Gadsden Boulevard Dayton, Ohio 45403 USA</small></div>							
				ALL DIMENSIONS APPLY AFTER PLATING											
<p>The information and design disclosed herein was originated by and is the property of STACO ENERGY PRODUCTS CO., which reserves all patent, proprietary, design, manufacturing, reproduction, use and sale rights thereto, and to any article disclosed therein notwithstanding to the extent rights are expressly granted to others. The foregoing does not apply to vendor proprietary parts.</p>								DRAWN BY S.A. SMITH		DATE 9/24/97		FIRST USED ON		DO NOT SCALE DWG.	
								CHECKER		DATE		WEIGHT APPROX. 10.5 LBS		CAGE CODE 83008	
								ENGINEER		DATE		SCALE 1 = 1		SHEET 1 OF 1	
												DWG. NO. 031-3006		DWG. SIZE D	



Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Staco:

1210BCT