

KIT_XMC_PLT2GO_XMC4400 Evaluation Board guide

About this document

Scope and purpose

This document explains about the KIT_XMC_PLT2GO_XMC4400 Evaluation board: kit operation, out-of-the-box example and its operation, and the hardware details of the board.

Intended audience

This document is intended for all embedded developers using the KIT_XMC_PLT2GO_XMC4400 Evaluation board.

Evaluation board

This board is to be used during the design-in process for evaluating and measuring characteristic curves, and for checking datasheet specifications.

Note: *PCB and auxiliary circuits are NOT optimized for final customer design.*

Important notice**Important notice**

“Evaluation Boards and Reference Boards” shall mean products embedded on a printed circuit board (PCB) for demonstration and/or evaluation purposes, which include, without limitation, demonstration, reference and evaluation boards, kits and design (collectively referred to as “Reference Board”).

Environmental conditions have been considered in the design of the Evaluation Boards and Reference Boards provided by Infineon Technologies. The design of the Evaluation Boards and Reference Boards has been tested by Infineon Technologies only as described in this document. The design is not qualified in terms of safety requirements, manufacturing and operation over the entire operating temperature range or lifetime.

The Evaluation Boards and Reference Boards provided by Infineon Technologies are subject to functional testing only under typical load conditions. Evaluation Boards and Reference Boards are not subject to the same procedures as regular products regarding returned material analysis (RMA), process change notification (PCN) and product discontinuation (PD).

Evaluation Boards and Reference Boards are not commercialized products, and are solely intended for evaluation and testing purposes. In particular, they shall not be used for reliability testing or production. The Evaluation Boards and Reference Boards may therefore not comply with CE or similar standards (including but not limited to the EMC Directive 2004/EC/108 and the EMC Act) and may not fulfill other requirements of the country in which they are operated by the customer. The customer shall ensure that all Evaluation Boards and Reference Boards will be handled in a way which is compliant with the relevant requirements and standards of the country in which they are operated.

The Evaluation Boards and Reference Boards as well as the information provided in this document are addressed only to qualified and skilled technical staff, for laboratory usage, and shall be used and managed according to the terms and conditions set forth in this document and in other related documentation supplied with the respective Evaluation Board or Reference Board.

It is the responsibility of the customer’s technical departments to evaluate the suitability of the Evaluation Boards and Reference Boards for the intended application, and to evaluate the completeness and correctness of the information provided in this document with respect to such application.

The customer is obliged to ensure that the use of the Evaluation Boards and Reference Boards does not cause any harm to persons or third party property.

The Evaluation Boards and Reference Boards and any information in this document is provided "as is" and Infineon Technologies disclaims any warranties, express or implied, including but not limited to warranties of non-infringement of third party rights and implied warranties of fitness for any purpose, or for merchantability.

Infineon Technologies shall not be responsible for any damages resulting from the use of the Evaluation Boards and Reference Boards and/or from any information provided in this document. The customer is obliged to defend, indemnify and hold Infineon Technologies harmless from and against any claims or damages arising out of or resulting from any use thereof.

Infineon Technologies reserves the right to modify this document and/or any information provided herein at any time without further notice.

Safety precautions

Safety precautions

Note: Please note the following warnings regarding the hazards associated with development systems.

Table 1 **Safety precautions**

	Warning: The DC link potential of this board is up to 1000 V or more. When measuring voltage waveforms by oscilloscope, high voltage differential probes must be used. Failure to do so may result in personal injury or death.
	Warning: The evaluation or reference board contains DC bus capacitors which take time to discharge after removal of the main supply. Before working on the drive system, wait five minutes for capacitors to discharge to safe voltage levels. Failure to do so may result in personal injury or death. Darkened display LEDs are not an indication that capacitors have discharged to safe voltage levels.
	Warning: The evaluation or reference board is connected to the grid input during testing. Hence, high-voltage differential probes must be used when measuring voltage waveforms by oscilloscope. Failure to do so may result in personal injury or death. Darkened display LEDs are not an indication that capacitors have discharged to safe voltage levels.
	Caution: Only personnel familiar with the drive, power electronics and associated machinery should plan, install, commission and subsequently service the system. Failure to comply may result in personal injury and/or equipment damage.
	Caution: The evaluation or reference board contains parts and assemblies sensitive to electrostatic discharge (ESD). Electrostatic control precautions are required when installing, testing, servicing or repairing the assembly. Component damage may result if ESD control procedures are not followed. If you are not familiar with electrostatic control procedures, refer to the applicable ESD protection handbooks and guidelines.

Table of contents
Table of contents

	About this document	1
	Important notice	2
	Safety precautions	3
	Table of contents	4
1	Introduction	5
1.1	Key Features	6
1.2	Block Diagram	8
2	Hardware Description	9
2.1	Power Supply	12
2.2	Pin Header X1 and X2	13
2.3	Pin Header for Microbus and Shield2Go Connector 1 and 2	14
2.4	Solderable 0 Ohm Pin Bridges	15
2.5	Arduino Compatible Connector	15
2.6	User Push Buttons and User LEDs	16
2.7	On-board Debug Probe	17
2.8	UART Communication for XMC4200	18
2.9	Cortex™ Debug Connector (10-pin)	18
2.10	Reset	18
2.11	CAN Transceiver	19
2.12	Serial Flash Memory	19
2.13	Ethernet	20
2.14	Boot Option	20
3	Production Data	21
3.1	Schematics	21
3.2	List of Material	27
	Revision history	34
	Disclaimer	35

1 Introduction

1 Introduction

This document describes the features and hardware details of the XMC4400 Platform2Go Series-V1.1 equipped with an ARM® Cortex®-M4 based XMC™ Microcontroller from Infineon Technologies AG.

It can be used with a wide range of development tools including Infineon's free of charge Eclipse based IDE [ModusToolbox™](#). The XMC4400 Platform2Go Series-V1.1 are designed to evaluate the capabilities of the XMC4400 Microcontroller. [Table 2](#) shows its specification.

Table 2 Kit Specification

Processor	Infineon's ARM® Cortex®-M4 XMC4400 Microcontroller in PG-LQFP-100 package (order number XMC4400-F100F512 BA)
Flash Memory	512 kB Flash
Data Memory	80 kB
Dimensions	66 x 136 mm
Clock Crystals	12 MHz and 32.768 kHz crystal for CPU 25 MHz crystal for Ethernet Phy
Power	5V external powering - Micro-AB USB Connector interface or - On-Board Debugger USB interface
Connectors	- Arduino compatible connectors for 3.3V/5V - Two Shield2Go connectors - All relevant XMC™ pins available on expansion pads (X1, X2) - mikroBUS™ connector - Ethernet interface via RJ45 jack - microUSB - Serial Wire Debug interface (2x5, 50 mil pitch) to XMC™ (on board debugger can be overridden by externally connected debugger)
Debugger	On-Board J-Link Debug Probe via USB supporting - Serial Wire Debug (SWD) - UART-to-USB bridge (virtual COM)
Others	- On-board debug probe, based on XMC4200 Microcontroller - Ethernet Phy - CAN transceiver connected to X3 32 Mbit Quad-SPI Flash Memory 2 user push-buttons, 2 user LEDs - Reset push-button - Potentiometer (10kOhm) for variable analog input

The XMC4400 Platform2Go Series-V1.1 are available in four different assembly versions differentiating in features:

- XMC4400 Platform2Go for 3.3V Shields
- XMC4400 Platform2Go for 5V Shields
- XMC4400 Platform2Go Lite for 3.3V Shields
- XMC4400 Platform2Go Lite for 5V Shields

1 Introduction

The **XMC4400 Platform2Go** features an Ethernet-enabled communication option. You can control the XMC4400 Platform2Go via the web browser on your PC.

Additional voltage level shifters and Arduino connection header on the XMC4400 Platform2Go allow the usage of **Arduino shields with 3.3V or 5V** logic level.

The Ethernet-communication is not supported by the **XMC4400 Platform2Go Lite Kit**, because some components e.g. for Ethernet are not assembled.

All boards are marked with "Platform2Go XMC4400-V1.1" and can be distinguished by the assembled devices (see pictures in [Chapter 2](#)). These boards are neither cost nor size optimized and do not serve as a reference design.

1.1 Key Features

[Table 3](#) summarizes the features of the different assembly versions of the XMC4400 Platform2Go Series-V1.1.

Table 3 Kit Features of Assembly Versions

Feature	XMC4400 Platform2Go 3.3V	XMC4400 Platform2Go 3.3V Lite	XMC4400 Platform2Go 5V	XMC4400 Platform2Go 5V Lite
XMC4400 Microcontroller	✓	✓	✓	✓
On-board Debug Probe with USB interface supporting SWD + SWO	✓	✓	✓	✓
Virtual COM Port via Debug Probe	✓	✓	✓	✓
2 x User Push-Buttons and 2 x User LED and 1 x Reset Push-Button 1 x Potentiometer	✓	✓	✓	✓
Voltage Regulator 5 V -> 3.3 V	✓	✓	✓	✓
USB (Micro USB Plug)	✓	✓	✓	✓
12 MHz Crystal	✓	✓	✓	✓
32.768 kHz RTC Crystal	✓		✓	✓
Arduino compatible connector 3.3 V/5 V Arduino shields	✓	✓	✓	✓
0 Ohm Bridges Array for 3.3 V Arduino shields	✓	✓		✓

(table continues...)

1 Introduction

Table 3 (continued) Kit Features of Assembly Versions

Feature	XMC4400 Platform2Go 3.3V	XMC4400 Platform2Go 3.3V Lite	XMC4400 Platform2Go 5V	XMC4400 Platform2Go 5V Lite
Voltage level shifter for 5 V Arduino			✓	✓
Ethernet PHY and RJ45 Jack	✓		✓	
32 Mbit Quad-SPI Flash Memory	✓		✓	
CAN Transceiver	✓		✓	

1 Introduction

1.2 Block Diagram

The block diagram in [Figure 1](#) shows the main components of the XMC4400 Platform2Go and their interconnections. There are following main building blocks:

- XMC4400 Microcontroller in a LQFP100 package
- On-board USB debug probe based on XMC4200 for SWD, SWV and Virtual COM Port support
- Ethernet Phy with RJ45 Plug
- Two 40-pin header X1 and X2
- Connection Header for Arduino
- mikroBus™ connector
- Two Infineon Shield2Go connectors (at the bottom of the board)
- Potentiometer (10kOhm)
- On-board power generation
- 2 User Push-Buttons, 2 User LEDs, Reset Push-Button
- Micro-AB USB Plug
- CAN Transceiver connected to X3 Pinheader
- 32 Mbit Quad SPI Flash




Figure 1 Block Diagram of the XMC4400 Platform2Go Series-V1

2 Hardware Description

2 Hardware Description

The following chapters give a detailed description of the board hardware and how it can be used. The different assembly versions of the kits series are shown in [Figure 2](#), [Figure 3](#), [Figure 4](#) and [Figure 5](#).




Figure 2 XMC4400 Platform2Go 3.3V

2 Hardware Description




Figure 3 XMC4400 Platform2Go 5V




Figure 4 XMC4400 Platform2Go 3.3V Lite

2 Hardware Description




Figure 5 XMC4400 Platform2Go 5V Lite

2 Hardware Description

2.1 Power Supply

The XMC4400 Platform2Go Series-V1.1 must be supplied by an external 5 Volt DC power supply connected to any of the micro USB plugs (X100, X101). The green Power LED (VDD3.3) indicates the presence of the generated 3.3 V supply voltage.

On-board reverse current protection diodes will ensure safe operation in case power is provided through both USB plugs at the same time. These protection diodes allows to use the on-board debug probe connected with a PC/Notebook via X101 and a second host PC/Laptop connected with the XMC4400 via X100.

If the board is powered via a USB plug, it's not recommended to apply an additional 5 Volt power supply to one of the 5 Volt power pins (VDD5, 5 V) on the pin headers X1 or X2 or the Arduino Power header, because there is no protection against reverse current into the external power supply. These power pins can be used to power an external circuit. But care must be taken not to draw more current than USB can deliver. A PC as USB host typically can deliver up to 500 mA current. If higher currents are required and in order to avoid damages on the USB host the use of an external USB power supply unit which is able to deliver higher currents than 500 mA is strongly recommended.




Figure 6 Power Supply Concept

2 Hardware Description

2.2 Pin Header X1 and X2

The pin headers X1 and X2 can be used to extend the evaluation board or to perform measurements on the XMC4400. [Figure 7](#) shows the available GPIOs/signals at these pin headers. The pin table is also printed onto the bottom side of the PCB in bottom view.

Pin Header X2					Pin Header X1						
	GND	2	1	P0.7	LED2	RESET#	2	1	GND		
QSPI_CLK	P0.8*	4	3	P3.5	CS_2GO_1	UART_RX	P2.15	4	3	P2.14	UART_TX
INT_1, PWM_0	P3.6	6	5	P3.3	PWM_1	IO2	P4.1	6	5	P4.0	RST/GPIO2_2GO_2
PWM_2	P3.4	8	7	P0.11	PWM3	SPI_CS_2GO_2	P1.7	8	7	P1.6	IO_0
CS_MB	P0.12	10	9	P0.5	PC_TXD	SPI_MOSI/PWM5	P1.9	10	9	P1.8	SPI_CLK
LED1	P0.6	12	11	P0.3	INT/GPIO3_2GO_2	GPIO1_2GO_2	P1.1	12	11	P1.0	INT_0
ETH_TXEN	P0.4*	14	13	P0.1	INT	QSPI_IO2	P1.3*	14	13	P1.2*	QSPI_IO3
SPI_CS, PWM_4	P0.2	16	15	P0.10	INT/GPIO3_2GO_1	QSPI_IO0	P1.5*	16	15	P1.4*	QSPI_IO1
SPI_MISO	P0.0	18	17	P3.2*	BUTTON2	QSPI_CS	P1.11*	18	17	P1.10	RST/GPIO2_2GO_1
PWM/GPIO4_2GO_1	P0.9	20	19	P3.0	SCL, ADC_5	CAN_RX	P1.13*	20	19	P1.12*	CAN_TX
BUTTON1	P3.1*	22	21	P14.14	AN	PC_RXD	P1.15	22	21	P1.14	IO_1
SDA, ADC_4	P14.4	24	23	P14.12	AN1_2GO_2	ETH_INT	P5.1	24	23	P5.0	GPIO1_2GO_1
AN2_2GO_2	P14.13	26	25	P14.6	AN1_2GO_1	PWM	P5.7	26	25	P5.2	RST/P5.2
AN2_2GO_1	P14.7	28	27	P15.9*	ETH_CRS	ETH_MDC	P2.7*	28	27	P2.6	PWM/GPIO4_2GO_2
SCL, ADC_5	P14.5	30	29	P14.15		SWV	P2.1	30	29	P2.0*	ETH_MDIO
	P14.3	32	31	P15.2		ETH_RXD1	P2.3*	32	31	P2.2*	ETH_RXD0
ADC_3	P15.3	34	33	P14.8	DAC.OUT_0	SDA, ADC_4	P2.5	34	33	P2.4*	ETH_RXER
DAC.OUT_1	P14.9	36	35	HIB_IO_0		ETH_TXD1	P2.9*	36	35	P2.8*	ETH_TXD0
VARREF		38	37	HIB_IO_1		ETH_CLK	P15.8*	38	37	P2.10	ETH_LED
VDD3.3		40	39	#VBAT		VDD5		40	39	VDD3.3	

(Top View)

*Note: These pins have solderable 0 Ohm pin bridges. See section 2.4 and Table 3.

Figure 7 Signal mapping of the pin headers X1 and X2

2 Hardware Description

2.3 Pin Header for Microbus and Shield2Go Connector 1 and 2

The pin header for Microbus and Shield2Go Connector 1 and 2 can be used to extend the evaluation board or to perform measurements on the XMC4400. [Figure 8](#) shows the available signals at these pin headers. The **Shield2Go pin header is mounted on the bottom**. The pin table is also printed onto the top and bottom side of the PCB in each view.




Figure 8 Signal mapping of the pin headers for Microbus and Shield2Go Connector 1 and 2

2 Hardware Description

2.4 Solderable 0 Ohm Pin Bridges

The 0 Ohm (0805) pin bridges enable/disable the signal pins in [Table 4](#) (enabled by default).

To disable the signals, their resistor has to be removed. The XMC4400 pins are then usable for other usages.

Table 4 Signal mapping of the 0 Ohm Pin Bridges

Resistor	XMC Pin	Signal
R3	P0.8	QSPI_CLK
R4	P1.2	QSPI_IO3
R5	P1.3	QSPI_IO2
R6	P1.4	QSPI_IO1
R7	P1.5	QSPI_IO0
R8	P1.11	QSPI_CS
R9	P1.12	CAN_TX
R10	P1.13	CAN_RX
R11	P0.4	ETH_TXEN
R12	P2.0	ETH_MDIO
R13	P2.2	ETH_RXD0
R14	P2.3	ETH_RXD1
R15	P2.4	ETH_RXER
R16	P2.7	ETH_MDC
R17	P2.8	ETH_TXD0
R18	P2.9	ETH_TXD1
R19	R3.1	BUTTON1
R20	R3.2	BUTTON2
R21	P15.8	ETH_CLK
R22	P15.9	ETH_CRS
R24	P14.0/ADC0	Potentiometer

2.5 Arduino Compatible Connector

The mapping of GPIOs and XMC™ pin functions to Arduino compatible functions can be found in [Figure 9](#). The Arduino compatible connector supports

- SPI interface (SPI_xxx)
- I2C interface (I2C_xxx)
- UART interface (UART_xxx)
- PWM signal outputs (PWM0-4)
- ADC input (ADC0-5)
- Interrupt input (INT0-1)

2 Hardware Description




Figure 9 Mapping of Arduino Functions to XMC Pin Functions

The **XMC4400 Platform2Go 5V** features bi-directional voltage level shifter and therefore supports 5 V Arduino shields. Jumper JP300 (IOREF) determines whether the Arduino shield is driven with 5 V or 3.3 V.

Analog input signals ADC0-5 are limited to 3.3 V input voltage. Primarily ADC0 to ADC3 should be used as analog input, because there is no additional circuit connected to these pins, whereas ADC4 and ADC5 have additional circuitry and require an input signal with lower input impedance. ADC0 is also connected to the Potentiometer for a variable value of the analog input (optional see [Table 6](#)).

Note: Parallel operation of I2C and ADC4/ADC5 is not possible, because they share the same Arduino pins.

2.6 User Push Buttons and User LEDs

The XMC4400 Platform2Go Series-V1.1 provides two user push buttons, two LEDs and one potentiometer. The port pins used can be found in [Table 5](#) and [Table 6](#).

Table 5 XMC4400 Pin Mapping for User LEDs

LED	XMC Pin	Resistor
LED1	P0.6	R112 (680 Ohm)
LED2	P0.7	R113 (680 Ohm)

Table 6 XMC4400 Pin Mapping for User Push Buttons and Potentiometer

Button	XMC Pin	Resistor
BUTTON1 ¹⁾	P3.1	R19

(table continues...)

2 Hardware Description

Table 6 (continued) XMC4400 Pin Mapping for User Push Buttons and Potentiometer

Button	XMC Pin	Resistor
BUTTON2 ¹⁾	P3.2	R20
Potentiometer ¹⁾	P14.0	R24

1) Each push Buttons, the potentiometer and the LEDs can be disabled by removing their resistor.

Also see [Table 4](#).

Debugging and UART-to-USB Communication

The XMC4400 Platform2Go Series-V1.1 supports debugging via 2 different channels:

- On-board debug probe
- 10-pin Cortex™ Debug Connector (not assembled)

2.7 On-board Debug Probe

The on-board debug probe supports Serial Wire Debug (SWD) and UART communication. Both require the installation of Segger's J-Link Driver which is part of the ModusToolbox™ installation. ModusToolbox™ is a highly efficient development platform for the XMC microcontroller families to simplify and shorten SW development. It can be downloaded at [ModusToolbox™](#) webpage. The latest Segger J-Link Driver can be downloaded at <http://www.segger.com/jlink-software.html>. [Table 7](#) shows the pin assignment of the XMC4400 used for debugging and UART communication.

2 Hardware Description

2.8 UART Communication for XMC4200

To enable* the optional UART communication between the XMC4400 and the XMC4200 Debugger, R1 and R2 have to be assembled with 0 Ohm, 0805 resistor.

Table 7 XMC4400 Pins Mapping for Debugging and UART-Communication

Pin Function	Input/Output	XMC Pin
Data pin for Debugging via SWD	I/O	TMS
Clock pin for Debugging via SWD	O	TCK
Transmit pin for UART communication (PC_RX)	O	XMC4200 Debugger P1.15 (TDX_U1C0.DOUT0)
Receive pin for UART communication (PC_TX)	I	XMC4200 Debugger P0.5 (RDX_U1C0.DX0B)
Optional* Transmit pin for UART(UART_RX)	O	XMC4400 P2.15(RXD_U1C0.DX0C)
Optional* Receive pin for UART(UART_TX)	I	XMC4400 P2.14(TXD_U1C0.DOUT0)

2.9 Cortex™ Debug Connector (10-pin)

The 10-pin Cortex™ Debug Connector supports Serial Wire Debug (SWD) and Serial Wire Viewer (SWV). The pin assignment of the Cortex™ Debug Connector is shown in [Table 8](#).

Table 8 Pin Assignment of the Cortex™ Debug Connector (X102)

Pin No.	Signal Name	Description
1	VCC	+3.3 V
2	TMS	Serial Wire Data I/O
3	GND	Ground
4	TCK	Serial Wire Clock
5	GND	Ground
6	SWV	Serial Wire Viewer (Trace Data Out)
7	NC	Not connected
8	NC	Not connected
9	GND_Detect	Ground detect
10	RESET	Rest (active low)

2.10 Reset

The reset pin (PORST#) of the XMC4400 is a bi-directional pin in open drain mode. An internal pull-up resistor keeps the PORST# pin high during normal operation. A low level at this pin will force a hardware reset. In case of a MCU internal reset the PORST# pin will drive a low signal.

A reset signal can be issued by

- the on-board Reset Button (“RESET”)

2 Hardware Description

- the on-board debug probe (IC101.47)
- the external debugger connected to the 10-pin Cortex™ Debug probe connector (X102)
- the Arduino Power Header (X302.3, “RESET#”)
- the pin header X1 (X1.2, “RESET#”)

An XMC™ internal circuit always ensures a save Power-on-Reset. XMC™ does not require any additional external components to generate a reset signal during power-up.

2.11 CAN Transceiver

The XMC4400 Platform2Go provides a CAN interface via the X3 connector. Infineon's high speed CAN transceiver IFX1051LE for industrial application supports 3.3V I/O logic and is suitable for 12V and 24V bus systems with an excellent EMC performance. The CAN bus (signals CANH, CANL) is not terminated by a 120Ohm and needs to be terminated externally. To use the CAN pins otherwise see also [Table 4](#).

Table 9 CAN Signals and XMC4400 Pin Mapping

Signal Name	Pin No. at Pin Header X1	XMC Pin, XMC Function	Pin No. at Pinheader X3
CANH	-	-	X3.1
CANL	-	-	X3.2
CAN_TX	X1.19	P1.12, CAN_TX	-
CAN_RX	X1.20	P1.13, CAN_RX	-

2.12 Serial Flash Memory

The XMC4400 Platform2Go provides a 32 Mbit serial flash memory from Microchip Technology (type: SST26VF032BT-104I/SM) interfaced to XMC4400 through a SPI interface. The SPI interface can be configured as single, dual or quad SPI. To use the Serial Flash Memory pins otherwise see also [Table 4](#).

Table 10 XMC4400 Pins Mapping for Serial Flash Memory

XMC Pin	Function in qSPI Mode, XMC Function	Function in SPI Mode, XMC Function
P0.8	Clock, U0C0.SCLKOUT	Clock, U0C0.SCLKOUT
P1.11	Chip Select, U0C0.SELO0	Chip Select, U0C0.SELO0
P1.5	Data Line 0 I/O, U0C0.DOUT0	Master Out Slave In (MOSI, MTSR), U0C0.DOUT0
P1.4	Data Line 1, U0C0.DOUT1	Master In Slave Out (MISO, MRST), U0C0.DOUT1
P1.3	Data Line 2, U0C0.DOUT2	HOLD (low active)
P1.2	Data Line 3, U0C0.DOUT3	Write Protection (low active)

2 Hardware Description

2.13 Ethernet

The XMC4400 Platform2Go provides an Ethernet Phy and RJ45 plug.

Table 11 XMC4400 Pins used for Ethernet

XMC Pin	Ethernet Function	XMC Function
P15.9	Carrier Sense/Receive Data Valid	ETH0.CRS_DVC
P15.8	Clock Input	ETH0.CLK_RMIIC
P5.1	Interrupt (disabled ¹⁾ by default; Enabled via solder resistor R401)	GPIO P5.1
P2.10	LED	GPIO P2.10
P2.9	Transmit Data Line 1	ETH0.TXD1
P2.8	Transmit Data Line 0	ETH0.TXD0
P2.7	Management Data Clock	ETH0.MDC
P2.4	Receive Error	ETH0.RXERA
P2.3	Receive Data Line 1	ETH0.RXD1A
P2.2	Receive Data Line 0	ETH0.RXD0A
P2.0	Management Data In/Out	ETH0.MDO/MDIB
P0.4	Transmit Enable	ETH0.TX_EN

1) Interrupt can be enabled by soldering R401 with 0805 resistor.

2.14 Boot Option

During power-on-reset the XMC4400 latches the signal level at the pins TMS and TCK. Based on the logic levels latched at these pins after reset the XMC4400 starts booting in different modes. TMS and TCK pins are used for debugging and by default program execution is always starting from on-chip flash (normal mode).

The XMC4400 Platform2Go Series-V1.1 does not support the selection of the boot options by switches directly. In case of no external debug probe is used the boot mode can be influenced by applying 1 kOhm pull-up- or pull-down resistors to TMS and TCK pins. These pins are available at the 10-pin debug connector X102.

Table 12 Boot Mode Selection with external Pull Resistors

Logic Level at TMS during Reset	Logic Level at TCK during Reset	Boot Mode
High	Low	Normal Mode (boot from on-chip flash) (DEFAULT)
Low	Low	ASC BSL Mode (boot from UART)
High	High	BMI Customized Boot Mode
Low	High	CAN BSL Mode (boot from CAN)

3 Production Data

3 Production Data

This chapter covers schematics, board dimensions, component placement and the list of material.

3.1 Schematics

In the following figures shows the schematics of the XMC4400 Platform2Go Series-V1.1 in.

3 Production Data




Figure 10 Connectors Schematic: Pin header, Pin Bridges, Level Shifter, Microbus, Shield2Go Connector, Arduino Level Jumper, UART Bridges

Debug Micro-USB Connector	On-board Debugger	Caps of XMC4200
LED	Clock	Cortex Debug
Debug Micro-USB Connector	On-board Debugger	On-board Debugger
LED	Clock	Caps of XMC4200

Figure 11 XMC_4200_Debug Schematic: OBD Probe, Ethernet, Quad-SPI Memory

3 Production Data




Figure 12

XMC4400 Schematic: USB connector, Microcontroller pins and power, Potentiometer Buttons and LEDs

3 Production Data




Figure 13 ICs and Power Schematic: Can Transceiver, RTC Battery, Power

3 Production Data




Figure 14 Geometry

3 Production Data

3.2 List of Material

The list of material is valid for the Platform2Go XMC4400 Lite/3.3V/5V.

Table 13 List of Material

Description	Designator	Package Reference	Value	Quantity	Not fitted in ¹⁾
Micro Miniature Pushbutton Switch	BUTTON1 P3.1, BUTTON2 P3.2, RESET		FSM2JSMA	3	
Solid Tantalum Surface Mount Chip Capacitor	C1	7451/2920	220uF	1	
Surface Mount Multilayer Ceramic Chip Capacitor	C100, C109, C110, C111, C112, C114, C115, C118, C119	0402/1005	100nF	9	
Surface Mount Multilayer Ceramic Chip Capacitor	C300, C301, C302, C303	0402/1005	100nF	4	A,C
Surface Mount Multilayer Ceramic Chip Capacitor	C304	0402/1005	100nF	1	
Chip Monolithic Ceramic Capacitor	C101, C102, C103, C104, C126	0603/1608	10uF	5	
Multilayer Ceramic Chip Capacitor	C105, C106, C107, C108	0402/1005	100nF	4	
Chip Multilayer Ceramic Capacitor	C113, C127, C132, C133	0603/1608	10uF	4	
Chip Monolithic Ceramic Capacitor	C116, C117	0402/1005	15pF	2	
Chip Monolithic Ceramic Capacitor	C120	0402/1005	10nF	1	
Chip Monolithic Ceramic Capacitor	C121, C122	0402/1005	15pF	2	
Chip Monolithic Ceramic Capacitor	C123, C124, C128, C129, C130, C131	0402/1005	100nF	6	

(table continues...)

3 Production Data

Table 13 (continued) List of Material

Description	Designator	Package Reference	Value	Quantity	Not fitted in ¹⁾
Chip Monolithic Ceramic Capacitor	C125	0805/2012	4.7uF	1	
Chip Monolithic Ceramic Capacitor	C400, C401	0402/1005	15pF	2	C,D
Chip Monolithic Ceramic Capacitor	C402	0603/1608	22uF	1	C,D
Chip Monolithic Ceramic Capacitor	C403, C406, C408, C411, C412, C413	0402/1005	100nF	6	C,D
Multilayer Ceramic Capacitor (High dielectric type)	C404	0805/2012	10uF	1	C,D
Chip Monolithic Ceramic Capacitor	C405	0402/1005	2.2uF	1	C,D
Multilayer Ceramic Chip Capacitor	C407	0805/2012	22uF	1	C,D
Chip Monolithic Ceramic Capacitor	C409, C410	0402/1005	22pF	2	C,D
PICOLED, Yellowish Green	COM, DEBUG		LED-SMD-SMLP13BC8T	2	
Overvoltage Diode	D1	SOT23	BAV70	1	
TVS Diode, Bi-directional Low Capacitance	D100, D102		PGB102ST23WR	2	
Medium Power AF Schottky Diode	D101, D103		BAS3010A-03W	2	
Silicon Schottky Diode	D400, D401		BAT64-02V	2	C,D

(table continues...)

3 Production Data

Table 13 (continued) List of Material

Description	Designator	Package Reference	Value	Quantity	Not fitted in ¹⁾
Performance of the ARM Cortex-M4 Core with Powerful On-Chip Peripheral Subsystems, Temp Range(-40Â°C to 125Â°C)	IC101		IFX_XMC4200Q48K256ABXUMA1	1	
Voltage Regulator, 3.3 V Output	IC102		IFX1117ME V33	1	
8-Bit Bidirectional Voltage-Level Translator for Open-Drain and Push-Pull Applications	IC300, IC301		TXS0108EPWR	2	A,C
10Base-T/100Base-TX PHY with RMII with 25MHz crystal/clock input and 50MHz RMII REF_CLK output, Industrial Temperature	IC400		KSZ8081RNAIA	1	C,D
Serial NOR Flash Memory, 32Mb, 2.7-3.6V, Multiple I/O, 108MHZ Speed	IC401		SST26VF032BT-104I/SM	1	C,D
Industrial High Speed CAN-FD Transceiver	IC402		IFX1051LE	1	C,D
Through hole .025" SQ Post Header, 2.54mm pitch, 3 pins, vertical, Single Row	JP300		TSW-103-05-L-S	1	C,D
For Power Lines; For General	L100, L101, L102, L103	0603/1608	60R	4	

(table continues...)

3 Production Data

Table 13 (continued) List of Material

Description	Designator	Package Reference	Value	Quantity	Not fitted in ¹⁾
For Power Lines; For General	L400, L401	0603/1608	60R	2	C,D
	LED1 P0.6, LED2 P0.7		Red	2	
mikroBUS Host Socket	MIKROBUS			2	
9 Pin of the Socket	Headers		'S2G-1P, S2G-1P-2	2	
8 Pin of the Socket	Headers		'S2G-1P, S2G-1P-3	2	
SMD Crystal Unit for Automotive Application, 12.000MHz	Q100, Q101		12MHz	2	
SMD, 32.768kHz ± 20 PPM, 12.5pF Crystal Unit	Q400		32.77kHz	1	C,D
SMD Crystal Unit for Automotive Application, 25.000MHz	Q401		25MHz	1	C,D
Standard Thick Film Chip Resistor, 0R/50V	R1, R2, R401	0805/2012	0R	3	N
General Purpose Chip Resistor	R3 - R22, R24	0805/2012	0R	20	
Standard Thick Film Chip Resistor	R100, R101, R102, R103, R104, R105	0402/1005	100R	6	
Standard Thick Film Chip Resistor	R106, R125	0402/1005	1MEG	2	
Standard Thick Film Chip Resistor	R107, R108, R120 ¹⁾ , R12 ¹⁾ 1	0402/1005	22R	4	
Standard Thick Film Chip Resistor, 0R/50V	R110	0402/1005	0R	1	

(table continues...)

3 Production Data

Table 13 (continued) List of Material

Description	Designator	Package Reference	Value	Quantity	Not fitted in ¹⁾
Standard Thick Film Chip Resistor, 0R/50V	R109, R301, R303	0402/1005	0R	4	N
Surface Mount Single Turn Trimmer, Model 23A - J Hook	R23 POTI P14, 15		10k	1	
Standard Thick Film Chip Resistor	R111, R118, R122 ¹⁾	0402/1005	510R	3	
Standard Thick Film Chip Resistor	R112, R113, R130	0603/1608	680R	3	
Standard Thick Film Chip Resistor	R114, R115, R116, R119, R127	0402/1005	10k	5	
Standard Thick Film Chip Resistor	R403, R407, R408, R409	0402/1005	10k	4	C,D
Standard Thick Film Chip Resistor	R300, R302	0402/1005	10k	2	A,C
Automotive Grade Thick Film Chip Resistor	R123, R124	0603/1608	680R	2	
Standard Thick Film Chip Resistor	R126	0402/1005	4.7k	1	
Standard Thick Film Chip Resistor	R400, R402	0402/1005	1k	2	C,D
Standard Thick Film Chip Resistor	R404, R405	0603/1608	120R	2	C,D
Standard Thick Film Chip Resistor	R406	0402/1005	6.49k	1	C,D
Chip Resistor Array, Temp Range (-55 to 125Â°C)	RA200, RA300		0R	2	B,D

(table continues...)

3 Production Data

Table 13 (continued) List of Material

Description	Designator	Package Reference	Value	Quantity	Not fitted in ¹⁾
XMC4000 Family Microcontroller for Industrial Applications, Arm® Cortex®-M4, 32-bit processor core, Flash 512 Kbytes, SRAM 80 Kbytes (Temperature Range -40°C to 125°C)	U1		IFX_XMC4400-F100	1	
Surface Mount LED, Green, 570nm	VDD3.3		Green	1	
2.54mm PC/104 Connector, Stackthrough	X1, X2		M20-6102045	2	N
Micro-USB 2.0 Standard, Type AB, Bottom Mount, Shell SMT	X100, X101		ZX62-AB-5PA(31)	2	
THT Micro Header, 1.27mm pitch, 10 pin, vertical, double row, keying shroud, DAP	X102		FTSH-105-01-L-D-K	1	N
Through hole .025" SQ Post Header, 2.54mm pitch, 5 pin, vertical, single row	X103		TSW-105-07-L-S	1	N
Through hole .025" SQ Post Header, 2.54mm pitch, 2 pin, vertical, double row	X3		HTSW-102-07-L-S	1	

(table continues...)

3 Production Data

Table 13 (continued) List of Material

Description	Designator	Package Reference	Value	Quantity	Not fitted in ¹⁾
Through hole .025" SQ Post Header, 2.54mm pitch, 6 pin, vertical, double row	X300		Header 3X2A	1	
Through hole .025" SQ Post Header, 2.54mm pitch, 6 pin, vertical, single row	X301		TSW-106-07-L-S	1	
Through hole .025" SQ Post Header, 2.54mm pitch, 8 pin, vertical, single row	X302		TSW-108-23-F-S	1	
Through hole .025" SQ Post Header, 2.54mm pitch, 8 pin, vertical, single row	X303		TSW-108-07-L-S	1	
Through hole .025" SQ Post Header, 2.54mm pitch, 10 pin, vertical, single row	X304		TSW-110-07-L-S	1	
RJ45 Connector with Integrated Transformer, 8 positions, 8 contacts, 2 LEDs (green, yellow), Shielded	X400		7499010211A	1	C,D

1) Agenda:

A: XMC4400 Platform2Go for 3.3V Shields

B: XMC4400 Platform2Go for 5V Shields

C: XMC4400 Platform2Go Lite for 3.3V Shields

D: XMC4400 Platform2Go Lite for 5V Shields

N: Not assembled in all Versions

Revision history**Revision history**

Document revision	Date	Description of changes
1.0	2019-08-30	Initial version
1.1	2025-01-23	Template update. Replaced DAVE™ with ModusToolbox™.

Trademarks

All referenced product or service names and trademarks are the property of their respective owners.

Edition 2025-01-23

Published by

Infineon Technologies AG
81726 Munich, Germany

© 2025 Infineon Technologies AG
All Rights Reserved.

Do you have a question about any aspect of this document?

Email: erratum@infineon.com

Document reference
IFX-oqp1724855718922

For further information on the product, technology, delivery terms and conditions and prices please contact your nearest Infineon Technologies office (www.infineon.com)

Warnings

Due to technical requirements products may contain dangerous substances. For information on the types in question please contact your nearest Infineon Technologies office.

Except as otherwise explicitly approved by Infineon Technologies in a written document signed by authorized representatives of Infineon Technologies, Infineon Technologies' products may not be used in any applications where a failure of the product or any consequences of the use thereof can reasonably be expected to result in personal injury.