

50Ω DC to 50 MHz

The Big Deal


- Low Insertion loss, 1.5dB Typ.
- High rejection, > 40dB
- Sharp insertion loss roll-off
- Good VSWR
- · Ultra miniature surface mount package

Product Overview

The ULP-50+ is a lowpass filter in a top hat package (size of 0.25" x 0.25") fabricated using SMT technology. Covering DC to 50 MHz band width, these units offer good matching within the passband and high rejection. This model uses a miniature high Q capacitors and chip inductors for high reliability. In addition it has repeatable performance across production lots and consistent performance across temperature.

Key Features

Feature	Advantages					
Low passband insertion loss	Passband insertion loss 1.5dB typical ensures low signal loss throughout the passband					
Excellent stopband rejection	Rejection of 40 dB ensures unwanted spurious are eliminated					
Excellent return loss at DC-50 MHz	This makes signal transmission with very less reflections and well-matched with the adjacent com- ponent used in the system					
Small size, 0.25" x 0.25"	The Ultra miniature surface mount package enables the ULP-50+ to be used in compact designs.					



ULP-50+

CASE STYLE: QA2224

A Performance and quality attributes and conditions not expressly stated in this specification document are intended to be excluded and do not form a part of this specification document. B. Electrical specifications and performance data contained in this specification document are based on Mini-Circuit's applicable established test performance criteria and measurement instructions. G. The parts covered by this specification document are subject to Mini-Circuits trandard limited warranty and terms and conditions (collectively, "Standard Terms"); Purchasers of this part are entitled to the rights and benefits contained therein. For a full statement of the Standard Terms and the exclusive rights and remedies thereunder, please visit Mini-Circuits' website at www.minicircuits.com/MCLStore/terms.jsp



www.minicircuits.com P.O. Box 350166, Brooklyn, NY 11235-0003 (718) 934-4500 sales@minicircuits.com

Surface Mount Low Pass Filter

50Ω DC to 50 MHz

ULP-50+



CASE STYLE: QA2224


Features

- · High rejection
- · Sharp insertion loss roll-off
- Good VSWR, 1.2:1 typ at passband
- Ultra miniature surface mount package


Applications

- Wireless communications
- Receivers / Transformers
- Lab use

Functional Schematic



Typical Frequency Response



+RoHS Compliant The +Suffix identifies RoHS Compliance. See our web site for RoHS Compliance methodologies and qualifications


· · · · · · · · · · · · · · · · · · ·								
Pa	rameter	F#	Frequency (MHz)	Min.	Тур.	Max.	Unit	
	Insertion Loss	DC-F1	DC-50	_	1.5	2.0	dB	
Pass Band	Freq. Cut-Off	F2	59	_	3.0	—	dB	
	VSWR	DC-F1	DC-50	—	1.2	—	:1	
		F3-F4	78-91	20	27	—	dB	
Oton Dand	Rejection Loss	F4-F5	91-700	40	47	—	dB	
Stop Band		F5-F6	700-3000	_	20	—	dB	
	VSWR	F3-F6	78-3000	_	20	—	:1	


Electrical Specifications at 25°C


Maximum Ratings						
Operating Temperature	-40°C to 85°C					
Storage Temperature	-55°C to 100°C					
RF Power Input	0.10W max.					

Permanent damage may occur if any of these limits are exceeded.

Typical Performance Data at 25°C Insertion Loss (dB) VSWR (:1) Frequency (MHz) Frequency (MHz) **Group Delay** (nsec) 12.75 1 0.71 1.16 1 5 0.72 1.18 5 12.39 10 50 0.74 1.56 1.21 1.10 8 10 12.46 12.52 58 3.02 1.67 12 12.61 59 65 3.61 2.00 15 18 12.78 11.24 6.63 13.02 70 19.66 11.32 20 22 25 29 30 35 38 40 42 13.21 77 78 31.08 15.96 13.41 32.71 16.49 13.76 90 91 56.48 22.46 14.30 59.58 22.93 14.46 100 58.25 27.08 15.40 250 67.99 102.82 16.16 700 90.03 348.20 16.78 1000 54.03 343.25 17.50 43 45 1500 67 35 249.91 17 91 2000 64.47 164.07 18.81 48 2500 68.18 120.38 20.49 3000 67.62 99.61 50 21.98







(su)

DELAY

SROUP

A Performance and quality attributes and conditions not expressly stated in this specification document are intended to be excluded and do not form a part of this specification document. B. Electrical specifications and performance data contained in this specification document are based on Mini-Circuit's applicable established test performance criteria and measurement instructions. C. The parts covered by this specification document are subject to Mini-Circuits standard limited warranty and terms and conditions (collectively, "Standard Terms"); Purchasers of this part are entitled to the rights and benefits contained therein. For a full statement of the Standard Terms and the exclusive rights and remedies thereunder, please visit Mini-Circuits' website at www.minicircuits.com/MCLStore/terms.jsp

∭Mini-Circuits

www.minicircuits.com P.O. Box 350166, Brooklyn, NY 11235-0003 (718) 934-4500 sales@minicircuits.com

REV OR M156162 ULP-50+ EDU2382 URJ 170530 Page 2 of 3




Pad Connections

INPUT	1
OUTPUT	3
GROUND	2,4,5,6


Demo Board MCL P/N: TB-894+ Suggested PCB Layout (PL-484)






NOTES:

TRACE WIDTH IS SHOWN FOR ROGERS (R04350B) WITH DIELECTRIC THICKNESS .020°±.0015". COPPER: 1/2 0Z. EACH SIDE. FOR OTHER MATERIALS TRACE WIDTH MAY NEED TO BE MODIFIED.
BOTTOM SIDE OF THE PCB IS CONTINUOUS GROUND PLANE.



DENOTES COPPER LAND PATTERN FREE OF SOLDERMASK



Α	В		С	D	E	F	G	н	J	ĸ
-	-	Min	Max	-	-	-	-	-	-	-
.250	.250	.075	.100	.075	.125	.092	.201	.041	.050	.046
6.35	6.35	1.91	2.54	1.91	3.18	2.34	5.11	1.04	1.27	1.17
L	М		Ν	Р	Q					Wt.
-	-		-	-	-					VVI.
										grams
.168	.117		.042	.260	.234					•
4.27	2.97		1.07	6.60	5.94					0.25

A Performance and quality attributes and conditions not expressly stated in this specification document are intended to be excluded and do not form a part of this specification document. B. Electrical specifications and performance data contained in this specification document are based on Min-Circuit's applicable established test performance criteria and measurement instructions. G. The parts covered by this specification document are subject to Min-Circuits and ard limited warranty and terms and conditions (collectivity, "Standard Terms"); Purchasers of this part are entitled to the rights and benefits contained therein. For a full statement of the Standard Terms and the exclusive rights and remedies thereunder, please visit Mini-Circuits' website at www.minicircuits.com/MCLStore/terms.jsp

Mini-Circuits

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Mini-Circuits: