SIEMENS

Data sheet

6ES7144-6KD50-0AB0



SIMATIC DP, ET 200ECO PN, 8 AI RTD/TC; 8x M12, Degree of protection IP67

Fi	g	ur	e	si	m	il	ar

General information				
Vendor identification (VendorID)	002AH			
Device identifier (DeviceID)	0306H			
Supply voltage				
Rated value (DC)	24 V			
Reverse polarity protection	Yes; against destruction			
power supply according to NEC Class 2 required	Yes			
Input current				
Current consumption, typ.	110 mA			
Power loss				
Power loss, typ.	2.8 W			
Analog inputs				
Number of analog inputs	8			
• For resistance/resistance thermometer measurement	8			
 For thermocouple measurement 	8			
Input ranges (rated values), voltages				
• -80 mV to +80 mV	Yes			
Input ranges (rated values), thermocouples				
• Туре Е	Yes			
• Туре Ј	Yes			
• Туре К	Yes			
• Type N	Yes			
Input ranges (rated values), resistance thermometer				
• Ni 100	Yes			
• Ni 1000	Yes			
• Ni 120	Yes			
• Ni 200	Yes			
• Ni 500	Yes			
• Pt 100	Yes			
• Pt 1000	Yes			
• Pt 200	Yes			
• Pt 500	Yes			
Input ranges (rated values), resistors				
• 0 to 150 ohms	Yes			
• 0 to 300 ohms	Yes			
• 0 to 600 ohms	Yes			
• 0 to 3000 ohms	Yes			
Thermocouple (TC)				
Temperature compensation				

— parameterizable	Yes
— internal temperature compensation	Yes
 — external temperature compensation with Pt100 	Yes
 — external temperature compensation with compensations socket 	Yes
 — dynamic reference temperature value 	Yes
 for definable comparison point temperature 	Yes
Cable length	
• shielded, max.	30 m
Analog value generation for the inputs	
Analog value display	SIMATIC S7 format
Measurement principle	integrating
Integration and conversion time/resolution per channel	
 Resolution with overrange (bit including sign), max. 	16 bit
 Integration time, parameterizable 	Yes
 Integration time (ms) 	2/16.67/20/100 ms
 Interference voltage suppression for interference frequency f1 in Hz 	500 / 60 / 50 / 10 Hz
 Conversion time (per channel) 	4 / 19 / 22 / 102 ms
Smoothing of measured values	
parameterizable	Yes
Step: None	Yes; 1x cycle time
Step: low	Yes; 4x cycle time
Step: Medium	Yes; 16x cycle time
Step: High	Yes; 64x cycle time
Encoder	
Number of connectable encoders, max.	8
Connection of signal encoders	
 for resistance measurement with two-wire connection 	Yes
 for resistance measurement with three-wire connection 	Yes
 for resistance measurement with four-wire connection 	Yes
Errors/accuracies	
Errors/accuracies Linearity error (relative to input range), (+/-)	0.01 %
	0.01 % RTD: 0.0005%/°C; TC: 0.0035%/°C
Linearity error (relative to input range), (+/-)	
Linearity error (relative to input range), (+/-) Temperature error (relative to input range), (+/-)	RTD: 0.0005%/°C; TC: 0.0035%/°C
Linearity error (relative to input range), (+/-) Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input	RTD: 0.0005%/°C; TC: 0.0035%/°C -85 dB 0.008 %
Linearity error (relative to input range), (+/-) Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)	RTD: 0.0005%/°C; TC: 0.0035%/°C -85 dB 0.008 %
Linearity error (relative to input range), (+/-) Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference • Series mode interference (peak value of interference <	RTD: 0.0005%/°C; TC: 0.0035%/°C -85 dB 0.008 % erence frequency
Linearity error (relative to input range), (+/-) Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference • Series mode interference (peak value of interference < rated value of input range), min.	RTD: 0.0005%/°C; TC: 0.0035%/°C -85 dB 0.008 % erence frequency 46 dB
Linearity error (relative to input range), (+/-) Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference • Series mode interference (peak value of interference < rated value of input range), min. • Common mode interference, min.	RTD: 0.0005%/°C; TC: 0.0035%/°C -85 dB 0.008 % erence frequency 46 dB
Linearity error (relative to input range), (+/-) Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference • Series mode interference (peak value of interference < rated value of input range), min. • Common mode interference, min. Interfaces	RTD: 0.0005%/°C; TC: 0.0035%/°C -85 dB 0.008 % erence frequency 46 dB 70 dB
Linearity error (relative to input range), (+/-) Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference • Series mode interference (peak value of interference < rated value of input range), min. • Common mode interference, min. Interfaces Transmission procedure	RTD: 0.0005%/°C; TC: 0.0035%/°C -85 dB 0.008 % erence frequency 46 dB 70 dB 100BASE-TX
Linearity error (relative to input range), (+/-) Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference • Series mode interference (peak value of interference < rated value of input range), min. • Common mode interference, min. Interfaces Transmission procedure Number of PROFINET interfaces	RTD: 0.0005%/°C; TC: 0.0035%/°C -85 dB 0.008 % erence frequency 46 dB 70 dB 100BASE-TX
Linearity error (relative to input range), (+/-) Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interfer • Series mode interference (peak value of interference < rated value of input range), min. • Common mode interference, min. Interfaces Transmission procedure Number of PROFINET interfaces 1. Interface	RTD: 0.0005%/°C; TC: 0.0035%/°C -85 dB 0.008 % erence frequency 46 dB 70 dB 100BASE-TX
Linearity error (relative to input range), (+/-) Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference • Series mode interference (peak value of interference < rated value of input range), min. • Common mode interference, min. Interfaces Transmission procedure Number of PROFINET interfaces 1. Interface Interface types	RTD: 0.0005%/°C; TC: 0.0035%/°C -85 dB 0.008 % erence frequency 46 dB 70 dB 100BASE-TX 1
Linearity error (relative to input range), (+/-) Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference • Series mode interference (peak value of interference < rated value of input range), min. • Common mode interference, min. Interfaces Transmission procedure Number of PROFINET interfaces 1. Interface Interface types • integrated switch	RTD: 0.0005%/°C; TC: 0.0035%/°C -85 dB 0.008 % erence frequency 46 dB 70 dB 100BASE-TX 1
Linearity error (relative to input range), (+/-) Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interfer • Series mode interference (peak value of interference < rated value of input range), min. • Common mode interference, min. Interfaces Transmission procedure Number of PROFINET interfaces 1. Interface Interface types • integrated switch Interface types	RTD: 0.0005%/°C; TC: 0.0035%/°C -85 dB 0.008 % erence frequency 46 dB 70 dB 100BASE-TX 1
Linearity error (relative to input range), (+/-) Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interfer • Series mode interference (peak value of interference < rated value of input range), min. • Common mode interference, min. Interfaces Transmission procedure Number of PROFINET interfaces 1. Interface Interface types • integrated switch Interface types M12 port	RTD: 0.0005%/°C; TC: 0.0035%/°C -85 dB 0.008 % erence frequency 46 dB 70 dB 100BASE-TX 1
Linearity error (relative to input range), (+/-) Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interfer • Series mode interference (peak value of interference < rated value of input range), min. • Common mode interference, min. Interfaces Transmission procedure Number of PROFINET interfaces 1. Interface Interface types • integrated switch Interface types M12 port • Autonegotiation	RTD: 0.0005%/°C; TC: 0.0035%/°C -85 dB 0.008 % erence frequency 46 dB 70 dB 100BASE-TX 1 Yes Yes
Linearity error (relative to input range), (+/-) Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference • Series mode interference (peak value of interference < rated value of input range), min. • Common mode interference, min. Interfaces Transmission procedure Number of PROFINET interfaces 1. Interface Interface types • integrated switch Interface types M12 port • Autonegotiation • Autocrossing	RTD: 0.0005%/°C; TC: 0.0035%/°C -85 dB 0.008 % erence frequency 46 dB 70 dB 100BASE-TX 1 Yes Yes Yes Yes
Linearity error (relative to input range), (+/-) Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference • Series mode interference (peak value of interference < rated value of input range), min. • Common mode interference, min. Interfaces Transmission procedure Number of PROFINET interfaces 1. Interface Interface types • integrated switch Interface types M12 port • Autonegotiation • Autocrossing • Transmission rate, max.	RTD: 0.0005%/°C; TC: 0.0035%/°C -85 dB 0.008 % erence frequency 46 dB 70 dB 100BASE-TX 1 Yes Yes Yes Yes
Linearity error (relative to input range), (+/-) Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference • Series mode interference (peak value of interference < rated value of input range), min. • Common mode interference, min. Interfaces Transmission procedure Number of PROFINET interfaces 1. Interface Interface types • integrated switch Interface types M12 port • Autonegotiation • Autocrossing • Transmission rate, max. Protocols	RTD: 0.0005%/°C; TC: 0.0035%/°C -85 dB 0.008 % rence frequency 46 dB 70 dB 100BASE-TX 1 Yes Yes Yes 100 Mbit/s
Linearity error (relative to input range), (+/-) Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interfer • Series mode interference (peak value of interference < rated value of input range), min. • Common mode interference, min. Interfaces Transmission procedure Number of PROFINET interfaces 1. Interface Interface types • integrated switch Interface types M12 port • Autonegotiation • Autorossing • Transmission rate, max. Protocols Supports protocol for PROFINET IO	RTD: 0.0005%/°C; TC: 0.0035%/°C -85 dB 0.008 % rence frequency 46 dB 70 dB 100BASE-TX 1 Yes Yes
Linearity error (relative to input range), (+/-) Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference • Series mode interference (peak value of interference < rated value of input range), min. • Common mode interference, min. Interfaces Transmission procedure Number of PROFINET interfaces 1. Interface Interface types • integrated switch Interface types M12 port • Autonegotiation • Autocrossing • Transmission rate, max. Protocols Supports protocol for PROFINET IO PROFINET CBA	RTD: 0.0005%/°C; TC: 0.0035%/°C -85 dB 0.008 % rence frequency 46 dB 70 dB 100BASE-TX 1 Yes Yes Yes Yes Yes Yes Yes No
Linearity error (relative to input range), (+/-) Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference • Series mode interference (peak value of interference < rated value of input range), min. • Common mode interference, min. Interfaces Transmission procedure Number of PROFINET interfaces 1. Interface Interface types • integrated switch Interface types M12 port • Autonegotiation • Autocrossing • Transmission rate, max. Protocols Supports protocol for PROFINET IO PROFINET CBA PROFISafe	RTD: 0.0005%/°C; TC: 0.0035%/°C -85 dB 0.008 % rence frequency 46 dB 70 dB 100BASE-TX 1 Yes Yes Yes Yes Yes Yes Yes No
Linearity error (relative to input range), (+/-) Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference • Series mode interference (peak value of interference < rated value of input range), min. • Common mode interference, min. Interfaces Transmission procedure Number of PROFINET interfaces 1. Interface Interface types • integrated switch Interface types M12 port • Autonegotiation • Autocrossing • Transmission rate, max. Protocols Supports protocol for PROFINET IO PROFINET CBA PROFISafe PROFINET IO Device	RTD: 0.0005%/°C; TC: 0.0035%/°C -85 dB 0.008 % rence frequency 46 dB 70 dB 100BASE-TX 1 Yes Yes Yes Yes Yes Yes Yes No
Linearity error (relative to input range), (+/-) Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interfer • Series mode interference (peak value of interference < rated value of input range), min. • Common mode interference, min. Interfaces Transmission procedure Number of PROFINET interfaces 1. Interface Interface types • integrated switch Interface types M12 port • Autonegotiation • Autocrossing • Transmission rate, max. Protocols Supports protocol for PROFINET IO PROFINET CBA PROFINET IO Device Services	RTD: 0.0005%/°C; TC: 0.0035%/°C -85 dB 0.008 % prence frequency 46 dB 70 dB 100BASE-TX 1 Yes Yes Yes Yes Yes No No No No No No
Linearity error (relative to input range), (+/-) Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interfer • Series mode interference (peak value of interference < rated value of input range), min. • Common mode interference, min. Interfaces Transmission procedure Number of PROFINET interfaces 1. Interface Interface types • integrated switch Interface types M12 port • Autonegotiation • Autocrossing • Transmission rate, max. Protocols Supports protocol for PROFINET IO PROFINET CBA PROFINET IO Device Services — Prioritized startup	RTD: 0.0005%/°C; TC: 0.0035%/°C -85 dB 0.008 % prence frequency 46 dB 70 dB 100BASE-TX 1 Yes Yes Yes Yes Yes No No No No No No

— MRP	Yes			
Open IE communication	103			
• TCP/IP	No			
SNMP	Yes			
• SINN/P • DCP	Yes			
• LLDP	Yes			
	Yes			
 ping ARP 	Yes			
Interrupts/diagnostics/status information				
Diagnostics function	Yes			
Alarms	165			
Diagnostic alarm	Yes			
Diagnoses	103			
Diagnostic information readable	Yes			
Monitoring the supply voltage	Yes; green "ON" LED			
Group error				
Overflow/underflow	Yes; Red/yellow "SF/MT" LED Yes			
Potential separation	Tes			
	Vaa			
between the load voltages	Yes			
between load voltage and all other switching components between Ethernet and electronics	No Yes			
	165			
Potential separation channels • between the channels	Ne			
Permissible potential difference	No			
Between the inputs and MANA (UCM)	10 Vpp AC			
Isolation	10 үрр АС			
tested with	707 \/ DC (type teet)			
• 24 V DC circuits	707 V DC (type test)			
Test voltage for interface, rms value [Vrms]	1 500 V; According to IEEE 802.3			
Degree and class of protection	1005/07			
IP degree of protection	IP65/67			
Standards, approvals, certificates	Very Depleration of Confermity, and online support antry 400757000			
Suitable for applications according to AMS 2750	Yes; Declaration of Conformity, see online support entry 109757262			
Suitable for applications according to CQI-9	Yes; Based on AMS 2750 E			
connection method				
Design of electrical connection	4/5-pin M12 circular connectors			
Dimensions				
Width	60 mm			
Height	175 mm			
Depth	49 mm			
Weights				
Weight, approx.	930 g			
last modified.	0.22002			

last modified:

9/7/2023 🖸

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Siemens: 6ES71446KD500AB0