# **SIEMENS**

### **Data sheet**

## 3RA2125-1HA24-0BB4

	Fuseless motor starter Direct start 600VAC Size S0 5.5-8Amp 24V DC screw connection For screw mounting Or 35 mm rail-mounting Type of coordination 2 IQ = 150 KA Also full fills type Of coordination 1 1NO+1NC (MSP) 1NO+1NC (contactor)	
product brand name	SIRIUS	
product designation	non-fused motor starter 3RA2	
design of the product	direct starter	
manufacturer's article number		
of the supplied contactor	3RT2024-1BB40	
of the supplied circuit-breakers	3RV2011-1HA15	
of the supplied link module	3RA2921-1BA00	
General technical data		
size of the circuit-breaker	S00	
size of load feeder	S0	
product extension auxiliary switch	Yes	
insulation voltage with degree of pollution 3 at AC rated value	690 V	
degree of pollution	3	
surge voltage resistance rated value	6 kV	
shock resistance according to IEC 60068-2-27	6g / 11 ms	
mechanical service life (operating cycles) of contactor typical	10 000 000	
type of assignment	2	
Weight	0.95 kg	
Ambient conditions	0.00 ng	
ambient temperature		
during operation	-20 +60 °C	
during storage	-50 +80 °C	
during transport	-55 +80 °C	
<u> </u>	30 · · · · · · ·	
Main circuit		
Main circuit	3	
number of poles for main current circuit	3 electromechanical	
	3 electromechanical 5.5 8 A	
number of poles for main current circuit design of the switching contact adjustable current response value current of the current-	electromechanical	
number of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release	electromechanical	
number of poles for main current circuit  design of the switching contact  adjustable current response value current of the current- dependent overload release  operating voltage	electromechanical 5.5 8 A	
number of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage  • rated value • at AC-3 rated value maximum	electromechanical 5.5 8 A  690 V	
number of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value	electromechanical 5.5 8 A  690 V 690 V	
number of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage  • rated value • at AC-3 rated value maximum operating frequency rated value	electromechanical 5.5 8 A  690 V 690 V 50 60 Hz	
number of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value	electromechanical 5.5 8 A  690 V 690 V 50 60 Hz	
number of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3	electromechanical 5.5 8 A  690 V 690 V 50 60 Hz 6.5 A	
number of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage	electromechanical 5.5 8 A  690 V 690 V 50 60 Hz 6.5 A  3 000 W	
number of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage	electromechanical 5.5 8 A  690 V 690 V 50 60 Hz 6.5 A  3 000 W	
number of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage	electromechanical 5.5 8 A  690 V 690 V 50 60 Hz 6.5 A  3 000 W 4 000 W	
number of poles for main current circuit  design of the switching contact  adjustable current response value current of the current- dependent overload release  operating voltage  • rated value  • at AC-3 rated value maximum  operating frequency rated value  operational current at AC-3 at 400 V rated value  operating power at AC-3  • at 400 V rated value  • at 500 V rated value  Control circuit/ Control  control supply voltage at DC rated value	electromechanical 5.5 8 A  690 V 690 V 50 60 Hz 6.5 A  3 000 W 4 000 W	
number of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage	electromechanical 5.5 8 A  690 V 690 V 50 60 Hz 6.5 A  3 000 W 4 000 W	
number of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage	electromechanical 5.5 8 A  690 V 690 V 50 60 Hz 6.5 A  3 000 W 4 000 W	
number of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage	electromechanical 5.5 8 A  690 V 690 V 50 60 Hz 6.5 A  3 000 W 4 000 W  24 V 5.9 W	
number of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value • at 500 V rated value Control circuit/ Control control supply voltage at DC rated value holding power of magnet coil at DC Auxiliary circuit number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts Protective and monitoring functions	electromechanical 5.5 8 A  690 V 690 V 50 60 Hz 6.5 A  3 000 W 4 000 W  24 V 5.9 W	
number of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage	electromechanical 5.5 8 A  690 V 690 V 50 60 Hz 6.5 A  3 000 W 4 000 W  24 V 5.9 W	
number of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value • at 500 V rated value Control circuit/ Control control supply voltage at DC rated value holding power of magnet coil at DC Auxiliary circuit number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts Protective and monitoring functions	electromechanical 5.5 8 A  690 V 690 V 50 60 Hz 6.5 A  3 000 W 4 000 W  24 V 5.9 W	
number of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage	electromechanical 5.5 8 A  690 V 690 V 50 60 Hz 6.5 A  3 000 W 4 000 W  24 V 5.9 W  CLASS 10 thermal (bimetallic)	
number of poles for main current circuit  design of the switching contact  adjustable current response value current of the current- dependent overload release  operating voltage  • rated value  • at AC-3 rated value maximum  operating frequency rated value  operating power at AC-3 at 400 V rated value  operating power at AC-3  • at 400 V rated value  • at 500 V rated value  Control circuit/ Control  control supply voltage at DC rated value  holding power of magnet coil at DC  Auxiliary circuit  number of NC contacts for auxiliary contacts  number of NO contacts for auxiliary contacts  Protective and monitoring functions  trip class  design of the overload release  response value current of instantaneous short-circuit trip unit  UL/CSA ratings	electromechanical 5.5 8 A  690 V 690 V 50 60 Hz 6.5 A  3 000 W 4 000 W  24 V 5.9 W  CLASS 10 thermal (bimetallic)	
number of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage	electromechanical 5.5 8 A  690 V 690 V 50 60 Hz 6.5 A  3 000 W 4 000 W  24 V 5.9 W  CLASS 10 thermal (bimetallic)	

• at 600 V rated value	6.33 A	
yielded mechanical performance [hp]		
<ul> <li>for single-phase AC motor</li> </ul>		
— at 110/120 V rated value	0.33 hp	
— at 230 V rated value	1 hp	
• for 3-phase AC motor		
— at 200/208 V rated value	2 hp	
— at 220/230 V rated value	2 hp	
— at 460/480 V rated value	5 hp	
— at 575/600 V rated value	5 hp	
hort-circuit protection		
product function short circuit protection	Yes	
design of the short-circuit trip	magnetic	
conditional short-circuit current (Iq)		
• at 400 V according to IEC 60947-4-1 rated value	153 000 A	
nstallation/ mounting/ dimensions		
mounting position	vertical	
fastening method	Snap-mounted to DIN rail or screw-mounted with addition	nal push-in lug
height	193.1 mm	
width	45 mm	
depth	107 mm	
required spacing		
for grounded parts		
— forwards	10 mm	
— backwards	0 mm	
— upwards	30 mm	
— at the side	9 mm	
— downwards	10 mm	
for live parts		
— forwards	10 mm	
— backwards	0 mm	
— upwards	30 mm	
— downwards	10 mm	
— at the side	9 mm	
onnections/ Terminals		
type of electrical connection for main current circuit	screw-type terminals	
type of connectable conductor cross-sections for main contacts stranded	1 10 mm², 2x (2.5 6 mm²)	
connectable conductor cross-section for main contacts finely stranded with core end processing	1 6 mm²	
Safety related data		
proportion of dangerous failures with high demand rate according to SN 31920	73 %	
B10 value with high demand rate according to SN 31920	1 000 000	
Electrical Safety		
protection class IP on the front according to IEC 60529	IP20	
touch protection on the front according to IEC 60529	finger-safe, for vertical contact from the front	
Approvals Certificates		
General Product Approval		For use in hazard- ous locations





Confirmation







**Test Certificates** 

Marine / Shipping

Type Test Certificates/Test Report

Special Test Certificate









Marine / Shipping other Railway Dangerous goods







Confirmation

Special Test Certificate

**Transport Information** 

#### **Environment**

Environmental Confirmations

#### Further information

Information on the packaging

https://support.industry.siemens.com/cs/ww/en/view/109813875

Information- and Downloadcenter (Catalogs, Brochures,...)

https://www.siemens.com/ic10

Industry Mall (Online ordering system)

https://mall.industry.siemens.com/mall/en/en/Catalog/product?mlfb=3RA2125-1HA24-0BB4

Cax online generator

http://support.automation.siemens.com/WW/CAXorder/default.aspx?lang=en&mlfb=3RA2125-1HA24-0BB4

Service&Support (Manuals, Certificates, Characteristics, FAQs,...)

https://support.industry.siemens.com/cs/ww/en/ps/3RA2125-1HA24-0BB4

Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, EPLAN macros, ...)

 $\underline{\text{http://www.automation.siemens.com/bilddb/cax\_de.aspx?mlfb=3RA2125-1HA24-0BB4\&lang=en}}$ 

Characteristic: Tripping characteristics, I2t, Let-through current

https://support.industry.siemens.com/cs/ww/en/ps/3RA2125-1HA24-0BB4/char

Further characteristics (e.g. electrical endurance, switching frequency)

http://www.automation.siemens.com/bilddb/index.aspx?view=Search&mlfb=3RA2125-1HA24-0BB4&objecttype=14&gridview=view1

last modified: 12/15/2020 🖸

# **Mouser Electronics**

**Authorized Distributor** 

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

## Siemens:

3RA21251HA240BB4