3RA2125-4CA27-0AK6

## **Data sheet**



FUSELESS MOTOR STARTER DIRECT START 600V AC SZ S0 17-22A 110/120V AC 50/60HZ SCREW CONNECTION FOR SCREW MOUNTING OR 35 MM RAIL-MOUNTING TYPE OF COORDINATION 2 IQ = 50 KA ALSO FULFILLS TYPE OF COORDINATION 1 1NO+1NC (MSP) 1NO+1NC (CONTACTOR)

product brand name	SIRIUS
product designation	non-fused motor starter 3RA2
design of the product	direct starter
manufacturer's article number	
<ul> <li>of the supplied contactor</li> </ul>	3RT2027-1AK60
<ul> <li>of the supplied circuit-breakers</li> </ul>	3RV2021-4CA15
<ul> <li>of the supplied link module</li> </ul>	3RA2921-1AA00
General technical data	
size of the circuit-breaker	S0
size of load feeder	S0
product extension auxiliary switch	Yes
insulation voltage with degree of pollution 3 at AC rated value	690 V
degree of pollution	3
surge voltage resistance rated value	6 kV
shock resistance according to IEC 60068-2-27	6g / 11 ms
mechanical service life (operating cycles) of contactor typical	10 000 000
type of assignment	2
Weight	0.76 kg
Ambient conditions	
ambient temperature	
<ul> <li>during operation</li> </ul>	-20 +60 °C
during storage	-50 +80 °C
during transport	-55 +80 °C
Main circuit	
number of poles for main current circuit	3
design of the switching contact	electromechanical
adjustable current response value current of the current- dependent overload release	17 22 A
operating voltage	
rated value	690 V
at AC-3 rated value maximum	690 V
operating frequency rated value	50 60 Hz
operational current at AC-3 at 400 V rated value	22 A
operating power at AC-3	
• at 400 V rated value	11 000 W
at 500 V rated value	11 000 W
Control circuit/ Control	
control supply voltage at AC	
at 50 Hz rated value	110 V
at 50 Hz rated value	88 121 V

at 00 He astad or 1	4001/
• at 60 Hz rated value	120 V
• at 60 Hz rated value	96 132 V
apparent holding power of magnet coil at AC	9.4 VA
inductive power factor with the holding power of the coil  Auxiliary circuit	0.28
number of NC contacts for auxiliary contacts	2
number of NO contacts for auxiliary contacts	2
Protective and monitoring functions	2
trip class	CLASS 10
design of the overload release	thermal (bimetallic)
response value current of instantaneous short-circuit trip unit	286 A
UL/CSA ratings	
full-load current (FLA) for 3-phase AC motor	
at 480 V rated value	22 A
• at 600 V rated value	21.9 A
yielded mechanical performance [hp]	
<ul> <li>for single-phase AC motor</li> </ul>	
— at 110/120 V rated value	1.5 hp
— at 230 V rated value	3 hp
• for 3-phase AC motor	
— at 200/208 V rated value	5 hp
— at 220/230 V rated value	7.5 hp
— at 460/480 V rated value	15 hp
— at 575/600 V rated value	20 hp
Short-circuit protection	Von
product function short circuit protection	Yes
design of the short-circuit trip  conditional short-circuit current (Iq)	magnetic
at 400 V according to IEC 60947-4-1 rated value	153 000 A
• at 500 V according to IEC 60947-4-1 rated value	100 000 A
Installation/ mounting/ dimensions	
Installation/ mounting/ dimensions mounting position	vertical
	vertical Snap-mounted to DIN rail or screw-mounted with additional push-in lug
mounting position	
mounting position fastening method	Snap-mounted to DIN rail or screw-mounted with additional push-in lug
mounting position fastening method height width depth	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm
mounting position fastening method height width	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm
mounting position fastening method height width depth required spacing • for grounded parts	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm
mounting position fastening method height width depth required spacing • for grounded parts — forwards	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm
mounting position fastening method height width depth required spacing  • for grounded parts — forwards — backwards	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm 10 mm 0 mm
mounting position fastening method height width depth required spacing  • for grounded parts — forwards — backwards — upwards	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm  10 mm 0 mm 30 mm
mounting position fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm  10 mm 0 mm 30 mm 9 mm
mounting position fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm  10 mm 0 mm 30 mm
mounting position fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm  10 mm 0 mm 30 mm 9 mm 10 mm
mounting position fastening method height width depth required spacing  • for grounded parts — forwards — backwards — upwards — at the side — downwards  • for live parts — forwards	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm  10 mm 0 mm 30 mm 9 mm
mounting position fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — backwards • for lowerds — backwards — backwards	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm  10 mm 0 mm 30 mm 9 mm 10 mm
mounting position fastening method height width depth required spacing  • for grounded parts — forwards — backwards — upwards — at the side — downwards  • for live parts — forwards	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm  10 mm 0 mm 30 mm 9 mm 10 mm 10 mm
mounting position fastening method height width depth required spacing	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm  10 mm 0 mm 30 mm 10 mm 10 mm 10 mm
mounting position fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — backwards — upwards — downwards • for lowe parts — forwards — backwards — backwards — backwards — upwards — downwards	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm  10 mm 0 mm 30 mm 9 mm 10 mm 10 mm 0 mm 30 mm
mounting position fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — backwards — backwards — upwards — at the side — downwards — forwards — forwards — backwards — backwards — upwards — at the side	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm  10 mm 0 mm 30 mm 9 mm 10 mm 10 mm 0 mm 30 mm
mounting position fastening method height width depth required spacing  • for grounded parts — forwards — backwards — upwards — at the side — downwards  • for live parts — forwards — backwards — at the side — downwards — torwards — torwards — backwards — upwards — backwards — upwards — at the side Connections/ Terminals	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm  10 mm 0 mm 30 mm 9 mm 10 mm 10 mm 0 mm 9 mm 10 mm 9 mm 10 mm 9 mm 10 mm
mounting position  fastening method  height  width  depth  required spacing  • for grounded parts  — forwards  — backwards  — upwards  — at the side  — downwards  • for live parts  — forwards  — backwards  — at the side  — downwards  • for live parts  — forwards  — backwards  — backwards  — upwards  — at the side  Connections/ Terminals  type of electrical connection for main current circuit  type of connectable conductor cross-sections for main contacts	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm  10 mm 0 mm 30 mm 10 mm 10 mm 0 mm 30 mm 9 mm 10 mm 9 mm 10 mm 9 mm 10 mm 9 mm
mounting position fastening method height width depth required spacing  • for grounded parts — forwards — backwards — upwards — at the side — downwards  • for live parts — forwards — backwards — upwards — at the side — downwards — torwards — backwards — upwards — backwards — upwards — at the side  Connections/ Terminals  type of electrical connection for main current circuit type of connectable conductor cross-sections for main contacts stranded  connectable conductor cross-section for main contacts finely	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm  10 mm 0 mm 30 mm 9 mm 10 mm 0 mm 30 mm 9 mm 10 mm screw-type terminals 1 10 mm², 2x (2.5 6 mm²)
mounting position  fastening method  height  width  depth  required spacing  • for grounded parts  — forwards  — backwards  — upwards  — at the side  — downwards  • for live parts  — forwards  — backwards  — upwards  — a the side  — downwards  • for live parts  — forwards  — backwards  — upwards  — at the side  Connections/ Terminals  type of electrical connection for main current circuit  type of connectable conductor cross-sections for main contacts stranded  connectable conductor cross-section for main contacts finely stranded with core end processing	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm  10 mm 0 mm 30 mm 9 mm 10 mm 0 mm 30 mm 9 mm 10 mm screw-type terminals 1 10 mm², 2x (2.5 6 mm²)
mounting position fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — backwards — upwards — a the side — downwards — to backwards — upwards — backwards — upwards — at the side  Connections/ Terminals  type of electrical connection for main current circuit type of connectable conductor cross-sections for main contacts stranded connectable conductor cross-section for main contacts finely stranded with core end processing  Safety related data proportion of dangerous failures with high demand rate according to SN 31920  B10 value with high demand rate according to SN 31920	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm  10 mm 0 mm 30 mm 9 mm 10 mm 10 mm 0 mm 30 mm 10 mm 10 mm 10 mm 10 mm 10 mm 10 mm
mounting position fastening method height width depth required spacing • for grounded parts — forwards — backwards — upwards — at the side — downwards • for live parts — forwards — backwards — upwards — a the side — downwards — to backwards — backwards — upwards — at the side  Connections/ Terminals  type of electrical connection for main current circuit type of connectable conductor cross-sections for main contacts stranded connectable conductor cross-section for main contacts finely stranded with core end processing  Safety related data proportion of dangerous failures with high demand rate according to SN 31920	Snap-mounted to DIN rail or screw-mounted with additional push-in lug 193.1 mm 45 mm 97.1 mm  10 mm 0 mm 30 mm 9 mm 10 mm 10 mm 0 mm 30 mm 10 mm 10 mm 11 mm 11 mm 11 mm 12 mm 13 mm 14 mm 15 mm 16 mm 17 mm 18 mm 19 mm 19 mm 10 mm

## **Approvals Certificates**

## **General Product Approval**

For use in hazardous locations





Confirmation







**Test Certificates** 

Marine / Shipping

Type Test Certificates/Test Report

Special Test Certificate









Marine / Shipping





Confirmation

other

Special Test Certificate

Railway

Environmental Confirmations

**Environment** 

**Further information** 

Information on the packaging

https://support.industry.siemens.com/cs/ww/en/view/109813875

Information- and Downloadcenter (Catalogs, Brochures,...)

https://www.siemens.com/ic10

Industry Mall (Online ordering system)

Cax online generator

http://support.automation.siemens.com/WW/CAXorder/default.aspx?lang=en&mlfb=3RA2125-4CA27-0AK6

Service&Support (Manuals, Certificates, Characteristics, FAQs,...)

https://support.industry.siemens.com/cs/ww/en/ps/3RA2125-4CA27-0AK6

Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, EPLAN macros, ...)


 $\underline{\text{http://www.automation.siemens.com/bilddb/cax\_de.aspx?mlfb=3RA2125-4CA27-0AK6\&lang=en}$ 


Characteristic: Tripping characteristics,  $I^2t$ , Let-through current


https://support.industry.siemens.com/cs/ww/en/ps/3RA2125-4CA27-0AK6/char

Further characteristics (e.g. electrical endurance, switching frequency)

 $\underline{\text{http://www.automation.siemens.com/bilddb/index.aspx?view=Search\&mlfb=3RA2125-4CA27-0AK6\&objecttype=14\&gridview=view1}$ 







last modified: 12/15/2020 🖸



## **Mouser Electronics**

**Authorized Distributor** 

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Siemens:

3RA21254CA270AK6