# SIEMENS

Data sheet for SINAMICS G120X

### Article No. :

### 6SL3220-1YE28-0AF0



Figure similar

Client order no. :
Order no. :
Offer no. :
Remarks :

Rated data			
Input			
Number of phases	3 AC		
Line voltage	380 480 V +10 % -20 %		
Line frequency	47 63 Hz		
Rated voltage	400V IEC	480V NEC	
Rated current (LO)	29.50 A	26.00 A	
Rated current (HO)	24.50 A	21.30 A	
Output			
Number of phases	3 AC		
Rated voltage	400V IEC	480V NEC <sup>1)</sup>	
Rated power (LO)	15.00 kW	20.00 hp	
Rated power (HO)	11.00 kW	15.00 hp	
Rated current (LO)	32.00 A	27.00 A	
Rated current (HO)	26.00 A	21.00 A	
Rated current (IN)	33.00 A		
Max. output current	43.00 A		
Pulse frequency	4 kHz		
Output frequency for vector control	0 200 Hz		
Output frequency for V/f control	0 550 Hz		

### **Overload capability**

Low Overload (LO)

110% base load current IL for 60 s in a 300 s cycle time

High Overload (HO)

150% x base load current IH for 60 s within a 600 s cycle time

General tech. specifications			
Power factor $\lambda$	0.70 0.85		
Offset factor $\cos \phi$	0.96		
Efficiency η	0.98		
Sound pressure level (1m)	67 dB		
Power loss <sup>3)</sup>	0.438 kW		
Filter class (integrated)	RFI suppression filter for Category C2		
EMC category (with accessories)	Category C2		
Safety function "Safe Torque Off"	without SIRIUS device (e.g. via S7- 1500F)		
Communication			

Communication

PROFINET, EtherNet/IP

ltem no. : Consignment no. : Project :

Inputs / outputs			
Standard digital inputs			
Number	6		
Switching level: $0 \rightarrow 1$	11 V		
Switching level: $1 \rightarrow 0$	5 V		
Max. inrush current	15 mA		
Fail-safe digital inputs			
Number	1		
Digital outputs			
Number as relay changeover contact	2		
Output (resistive load)	DC 30 V, 5.0 A		
Number as transistor	0		
Analog / digital inputs			
Number	2 (Differential input)		
Resolution	10 bit		
Switching threshold as digital input			
0 → 1	4 V		
1 → 0	1.6 V		
Analog outputs			
Number	1 (Non-isolated output)		
PTC/ KTY interface			
1 motor temperature sensor input, ser Thermo-Click, accuracy $\pm$ 5 °C	nsors that can be connected PTC, KTY and		

Closed-loop control techniques		
V/f linear / square-law / parameterizable	Yes	
V/f with flux current control (FCC)	Yes	
V/f ECO linear / square-law	Yes	
Sensorless vector control	Yes	
Vector control, with sensor	No	
Encoderless torque control	No	
Torque control, with encoder	No	

## SIEMENS

### Data sheet for SINAMICS G120X

### Article No. :

### 6SL3220-1YE28-0AF0

Ambie	ent conditions	
Standard board coating type	Class 3C2, according to IEC 60721-3-3: 2002	
Cooling	Air cooling using an integrated fan	
Cooling air requirement	0.018 m³/s (0.653 ft³/s)	
Installation altitude	1,000 m (3,280.84 ft)	
Ambient temperature		
Operation	-20 45 °C (-4 113 °F)	
Transport	-40 70 °C (-40 158 °F)	
Storage	-25 55 °C (-13 131 °F)	
Relative humidity		
Max. operation	95 % At 40 °C (104 °F), condensation and icing not permissible	
Connections		
Signal cable		
Conductor cross-section	0.15 1.50 mm² (AWG 24 AWG 16)	
Line side		
Version	screw-type terminal	
Conductor cross-section	1.50 16.00 mm² (AWG 16 AWG 6)	
Motor end		
Version	Screw-type terminals	
Conductor cross-section	1.50 16.00 mm² (AWG 16 AWG 6)	
DC link (for braking resistor)		
PE connection	On housing with M4 screw	
Max. motor cable length		
Shielded	150 m (492.13 ft)	

Me	chanical data		
Degree of protection	IP20 / UL open type	IP20 / UL open type	
Frame size	FSC	FSC	
Net weight	7.66 kg (16.89 lb)		
Dimensions			
Width	140 mm (5.51 in)	140 mm (5.51 in)	
Height	295 mm (11.61 in)	)	
Depth	218 mm (8.58 in)		
	Standards		
Compliance with standards	UL, cUL, CE, C-Tick SEMI F47, REACH	UL, cUL, CE, C-Tick (RCM), EAC, KCC, SEMI F47, REACH	
CE marking		EMC Directive 2004/108/EC, Low- Voltage Directive 2006/95/EC	
Converter losses to IEC61800-9-2*			
Efficiency class	IE2		
Comparison with the reference converter (90% / 100%)	39.1 %		
I ▲ 279.0 W (1.3 %)	338.0 W (1.5 %)	438.0 W (2.0 %)	
100% •	•		
174.0 W (0.8 %)	195.0 W (0.9 %)	227.0 W (1.0 %)	
138.0 W (0.6 %)	147.0 W (0.7 %)		
25% •	•		

The percentage values show the losses in relation to the rated apparent power of the converter.

90% **f** 

50%

The diagram shows the losses for the points (as per standard IEC61800-9-2) of the relative torque generating current (I) over the relative motor stator frequency (f). The values are valid for the basic version of the converter without options/components.

\*converted values

<sup>1)</sup>The output current and HP ratings are valid for the voltage range 440V-480V

<sup>3)</sup>Typical value. More information can be found in the element group "Converter losses to IEC 61800-9-2" in this datasheet.

### **Mouser Electronics**

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Siemens: 6SL32201YE280AF0