










CODE NO.	CONTACT	K	L	M	N	P
CL0683-0142-1-57	20	24	-	11.5	10.3	25.5
CL0683-0143-4-57	30	24	-	11.5	12.8	25.5
CL0683-0144-7-57	40	24	-	11.5	15.3	25.5
CL0683-0145-0-57	50	32	28.4	14.2	17.8	33.5
CL0683-0146-2-57	60	32	28.4	14.2	20.3	33.5
CL0683-0147-5-57	70	44	40.4	20.2	22.8	45.5
CL0683-0148-8-57	80	44	40.4	20.2	25.3	45.5



STYLE AND DIMENSION OF REEL (FREE)




DETAIL OF PART NO. LABEL

— SUPPLIER
— QUANTITY
— PART NO.
— CODE NO.
— DATE OF MANUFACTURED

生産月日	年 月 日
図 番	CL683-****-*57
品 名	DF17B(4.0)*DP-0.5V(57)
納入数量	1000 K0
納入者	ヒロセ電機(株)

S-S (FREE)



8 REINFORCEMENT COLLAR / TAPE AND REEL POCKET

NOTES 3 : 1 REEL : 1000 CONNECTORS.

4 : AT THE BEGINNING OF THE REEL , 30 COMPONENTS SHALL BE EMPTY.
AT THE END OF THE REEL, 20 COMPONENTS SHALL BE EMPTY.

5 WHEN THE TAPE WIDTH IS 32mm or 44mm, SPROCKET HOLES SHALL BE SET ON BOTH SIDES OF REEL AS SHOWN ON THIS DRAWING.

6 : PEEL FORCE REFERS TO JIS C 0806.

7 ➤ A POCKET SHAPE IS DIFFERENT AT INTERVALS OF EACH CAVITY NUMBER TO AVOID OVERLAP.

8 AFTER PACKAGING, ROLL 2 METERS OF THE REINFORCEMENT COLLAR TO OUTER CIRCUMFERENCE OF TAPE AND REEL POCKET, AND TAPE DOWN AT THE END THE COLLAR.



DRAWING NO.	EDC3-162141-77	
PART NO.	DF17B(4.0)-*DP-0.5V(57)	
CODE NO.	CL683-	 2

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

[Hirose Electric:](#)

[DF17B\(4.0\)-30DP-0.5V\(57\)](#)