
SMD ONE PORT 315.0 MHz SAW RESONATOR

ASR315S2





> STANDARD SPECIFICATIONS:

CHARACTERISTICS		UNIT	MIN.	TYP.	MAX.	
Center Frequency Fo			MHz	314.925	315.000	315.075
Tolerance from Fo			KHz		±75	
Insertion Loss			dB	-	1.7	2.4
Quality Factor	Unloaded		-		12,200	
	50Ω loaded				1,500	
Temperature Stability	Turnover Tem	perature	°C	20	35	50
	Turnover Frequency		KHz		Fc	
	Freq. Temp. Coefficient		ppm/°C ²		0.032	
Frequency Aging		ppm/year		±10		
DC Insulation Resistance			MΩ	1.0		
RF Equivalent RLC Model	Motional Resistance R ₁		Ω		14	25
	Motional Inductance L ₁		μΗ		86	
	Motional Capacitance C ₁		fF		2.95	
	Shunt Capacitance C ₀		pF		2.4	
Operating temp.		°C	-45°C to +85°C			
Storage temp.		°C	-45°C to +85°C			
Max. Rating	DC voltage V		±10V			
RF Power Dissipation		dBm	0			

^(*) Option 75 for ± 0.075MHz

Data measured with: Source Impedance: Zs= 50Ω , Load Impedance: ZL= 50Ω , TA= 25° C Electrostatic Sensitive Device. Handle with precaution.


> MARKING:

- 315R - A ZYX (315.0 Frequency in MHz) (ZY: Date code Z for month from A to L; Y for year,


I.e. 4 for 2004 X: Traceability code)

PIN NO.	CONNECTIONS	
1	Input/Output	
2	GND	
3	Output/Input	
4	GND	

> TEST CIRCUIT:



> FREQUENCY RESPONSE:



ATTENTION: Abracon Corporation's products are COTS – Commercial-Off-The-Shelf products; suitable for Commercial, Industrial and, where designated, Automotive Applications. Abracon's products are not specifically designed for Military, Aviation, Aerospace, Life-dependant Medical applications or any application requiring high reliability where component failure could result in loss of life and/or property. For applications requiring high reliability and/or presenting an extreme operating environment, written consent and authorization from Abracon Corporation is required. Please contact Abracon Corporation for more information.





Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

ABRACON:

<u>ASR315.00N01-SD11</u> <u>ASR315.00N01-SD12</u> <u>ASR315.00N01-SE</u> <u>ASR315.20N01-SD02</u> <u>ASR315.50N01-SE</u> ASR315.00N01-SS2 ASR315.00N01-SD02 ASR315.00N01-SD01 ASR315.50N01-SD02 ASR315.50N01-SS2