



Si4010/Si4355 EZRADIO[®] REMOTE CONTROL DEMO KIT USER'S GUIDE

1. Purpose

Thank you for your interest in Silicon Laboratories' EZRadio Remote Control Demo Kit. The Silicon Laboratories EZRadio Remote Control Demo Kit (P/N EZR-LEDK1W-XXX) contains everything you need to familiarize yourself with and evaluate the Si4010 RF SoC transmitter and the Si4355 receiver. The kit has three versions: one for the 434 MHz band, one for the 868 MHz band, and one for the 915 MHz band. The key features of the demo kit are as follows:

- The key fob demo board has five push buttons and one LED output.
- The receiver demo board has four LEDs to display received key fob commands.
- The provided software pack contains all the documentation and files needed to develop a user application.
- The kit supports the use of the Silicon Laboratories Integrated Development Environment (IDE) for software debugging and the use of the Keil C compiler, assembler, and linker toolchain.
- Contains demo applications using API functions and the key fob demo application.

1.1. Kit Content

Qty	Part Number	Description	
	EZR-LEDK1W-434	EZRadio Remote Control Demo Kit 434 MHz	
1	4010-KFOB-434	Si4010 Universal Key Fob 434 MHz	
1	4355-LED-434-SRX	Si4355 RFStick 434 MHz EZRadio receiver board	
1	MSC-PLPB_1	Key Fob Plastic Case (translucent gray)	
2	AAA	AAA alkaline battery	
1	CRD2032	CR2032 3 V coin battery	
	EZR-LEDK1W-868	EZRadio Remote Control Demo Kit 868 MHz	
1	4010-KFOB-868	Si4010 Universal Key Fob 868 MHz	
1	4355-LED-868-SRX	Si435 RFStick 868 MHz EZRadio receiver board	
1	MSC-PLPB_2	Key Fob Plastic Case (translucent red)	
2	AAA	AAA alkaline battery	
1	CRD2032	CR2032 3 V coin battery	
	EZR-LEDK1W-915	EZRadio Remote Control Demo Kit 915 MHz	
1	4010-KFOB-915	Si4010 Universal Key Fob 915 MHz	
1	4355-LED-915-SRX	Si4355 RFStick 915 MHz EZRadio receiver board	
1	MSC-PLPB_2	Key Fob Plastic Case (translucent red)	
2	AAA	AAA alkaline battery	
1	CRD2032	CR2032 3 V coin battery	

Table 1. Kit Content



Figure 1. Si4010 Universal Key Fob Board and Plastic Case (P/N 4010-KFOB-434 and MSC-PLPB_1)



Figure 2. Si4355 RFStick 434 MHz Receiver Board (P/N 4355-LED-434-SRX)

2. Operating the Demo

The Si4010 key fob transmitter and the Si4355 RFStick receiver are the transmitter and receiver devices used in the one way link demo. This transmitter/receiver pair can be used to evaluate the capabilities of the Si4010 transmitter and the Si4355 receiver.

The first step is to insert the CR2032 battery in the battery holder on the 4010-KFOB-XXX demo board and then place the board into the plastic key fob case. Next, insert the two AAA batteries in the battery holder on the 4355-LED-XXX receiver board and turn it on by setting the S6 switch to the "Battery" position. LED4 will light continuously indicating that power is on and the SRX firmware is running.

When a button is pressed on the key fob, LEDs flash on the receiver board according to which button was pressed. In the next table, buttons are named according to their position when the key fob is held with its LED facing forward.

Key Fob Button Pressed	RF Stick LED Flashed	
Left Button	LED1	
Middle Button	LED2	
Right Button	LED3	
Rear Button	LED1 + LED3	
Front Button	LED1 + LED2 + LED3	

Table 2. Key Fob Buttons and Resulting LEDs



3. RF Parameters

Kit Part Number	Center Frequency	Deviation
EZR-LEDK1W-434	433.92 MHz	\pm 59 kHz
EZR-LEDK1W-868	868.30 MHz	\pm 119 kHz
EZR-LEDK1W-917	917.00 MHz	± 120 kHz

The demo kit uses the following RF parameters according to the kit's frequency band.

The modulation is FSK.

4. Transmitter Side Program

The Si4010 in the key fob is factory programmed with the rke_demo_2 program. Since the program is burned in the NVM (OTP) memory of the Si4010, it cannot be changed. The whole rke_demo_2 software project can be found in the example programs package of the Si4010. It is available at the web page

http://www.silabs.com/products/wireless/EZRadio/Pages/Si4010.aspx on the Tools tab.

The key fob transmits an RF packet three times each time a button is pressed, and it also blinks the LED on the key fob. The packet structure is as follows:

Number of Bytes	Field Name	Description	
13 Preamble		Охаа	
2	Sync	0x2d, 0xd4	
4	Chip ID	Unique, factory-burned chip ID	
1 Status		Lower 5 bits are the button information	
2 Packet count		Rolling counter for PER measurement	
2 CRC-16		Generator X16+X15+X2+1, start value 0xFFFF	

Symbol rate is 9.6 kBd.

Each packet contains 18 additional bytes that are not received by the receiver of this demo. These additional bytes are AES-encrypted and are used by the AES demo kit. See details in the user's guide of the AES demo kit (P/N 4010-AESK1W-434).

In the key fob program the frequency and deviation is pin-selected by the PCB layout. This operating frequency is indicated on a label on the back of the key fob PCB.

GPIO8	GPIO9	Center Frequency	Deviation
High	Low	316.66 MHz	\pm 43 kHz
High	High	433.92 MHz	\pm 59 kHz
Low	High	868.30 MHz	± 119 kHz
Low	Low	917.00 MHz	± 120 kHz

The 316.667 MHz key fob is available in the 4010-AESK1W-315 demo kit or separately from Silicon Labs.

The key fob's default modulation is FSK but if the middle button is pressed and held during battery insertion, the modulation will be OOK until the next powerdown (battery removal).



5. Receiver Side Program

The 8051F930 MCU on the RFStick receiver board is factory-programmed with the Si4355 Remote Control Demo Receiver program. Since the program is programmed in flash memory, it can be overwritten using a Silicon Labs Toolstick Base Adapter that is part of the Si4010 development kit or can be ordered separately as well (P/N Toolstick_BA). The complete demo software project can be found on the Tools tab of the following web page: http://www.silabs.com/products/wireless/EZRadio/Pages/Si4355.aspx. The file name is Si4355 RCdemo SW.zip.

The receiver program configures and controls the Si4355 receiver chip via the SPI bus. The Si4355 receives the packets transmitted by the keyfob, checks the preamble, the syn bytes and the CRC. If the packet is OK, the program flashes the LEDs according to the button information in the status byte of the received packet.

6. Schematics

Schematics of the transmitter and receiver boards of the kit can be seen on the following pages. Complete manufacturing file pack with CAD/CAM files and BOMs can be found at http://www.silabs.com.









Si4010-RC-DEMO











DOCUMENT CHANGE LIST

Revision 0.1 to Revision 0.2

- Updated "2. Operating the Demo" on page 2.
- Updated Table 2 on page 2.

Revision 0.2 to Revision 0.3

- Updated Table 1, "Kit Content," on page 1.
- Updated name and filename of receiver-side program.



NOTES:





Disclaimer

Silicon Laboratories intends to provide customers with the latest, accurate, and in-depth documentation of all peripherals and modules available for system and software implementers using or intending to use the Silicon Laboratories products. Characterization data, available modules and peripherals, memory sizes and memory addresses refer to each specific device, and "Typical" parameters provided can and do vary in different applications. Application examples described herein are for illustrative purposes only. Silicon Laboratories reserves the right to make changes without further notice and limitation to product information, specifications, and descriptions herein, and does not give warranties as to the accuracy or completeness of the included information. Silicon Laboratories shall have no liability for the consequences of use of the information supplied herein. This document does not imply or express copyright licenses granted hereunder to design or fabricate any integrated circuits. The products must not be used within any Life Support System without the specific to result in significant personal injury or death. Silicon Laboratories products are generally not intended to support or sustain life and/or health, which, if it fails, can be reasonably expected to result in significant personal injury or death. Silicon Laboratories products are generally not intended for military applications. Silicon Laboratories used in weapons of mass destruction including (but not limited to) nuclear, biological or chemical weapons, or missiles capable of delivering such weapons.

Trademark Information

Silicon Laboratories Inc., Silicon Laboratories, Silicon Labs, SiLabs and the Silicon Labs logo, CMEMS®, EFM, EFM32, EFR, Energy Micro, Energy Micro logo and combinations thereof, "the world's most energy friendly microcontrollers", Ember®, EZLink®, EZMac®, EZRadio®, EZRadioPRO®, DSPLL®, ISOmodem ®, Precision32®, ProSLIC®, SiPHY®, USBXpress® and others are trademarks or registered trademarks of Silicon Laboratories Inc. ARM, CORTEX, Cortex-M3 and THUMB are trademarks or registered trademarks of ARM Holdings. Keil is a registered trademark of ARM Limited. All other products or brand names mentioned herein are trademarks of their respective holders.



Silicon Laboratories Inc. 400 West Cesar Chavez Austin, TX 78701 USA

http://www.silabs.com

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Silicon Laboratories: EZR-LEDK1W-434 EZR-LEDK1W-868 EZR-LEDK1W-915