


SPECIFICATIONS									
WIRING	INPUT		VOLTS	OUTPUT				TERMINAL CONNECTIONS AS VIEWED FROM BASE END	
	VOLTS	HERTZ		CONSTANT CURRENT LOAD		CONSTANT IMPEDANCE LOAD			
				MAX. AMPS	MAX. KVA	MAX. AMPS	MAX. KVA	INPUT	OUTPUT
SINGLE PHASE	120	50/60	0-120	5.0	0.60	7.0	0.84	1-4	4-3
			0-140	5.0	0.70	-	-	4-2	4-3
UNLESS OTHERWISE SPECIFIED, TOLERANCE IS ±			SPEC. CONTROL DRAWING VARIABLE TRANSFORMER MODEL: 511						
DECIMALS .XX .0000 .06 .0002 .01 1° 1-1/2°									
MATERIAL:									
ALL DIMENSIONS APPLY AFTER PLATING									
TITLE:			SPEC. CONTROL DRAWING VARIABLE TRANSFORMER MODEL: 511						
DRAWN BY S.A. SMITH			DATE 2/6/96	FIRST USED ON		DO NOT SCALE DWG.		CUSTOMER APPROVAL	
CHECKER			DATE	WEIGHT APPROX. 4.25 LBS		CODE IDENT. NO. 83008		DWG. SIZE D	DWG. NO. 031-0825
ENGINEER			DATE	SCALE 1=1		SHEET 1 OF 1			

The information and design disclosed herein was originated by and is the property of STACO ENERGY PRODUCTS CO., which reserves all patent, proprietary, design, manufacturing, reproduction, use and sale rights thereto, and to any article disclosed therein except to the extent rights are expressly granted to others. The foregoing does not apply to vendor proprietary parts.



STACO
ENERGY PRODUCTS CO.
A COMPONENTS CORPORATION OF AMERICA COMPANY
DAYTON, OHIO U.S.A.

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Staco:

511