


NOTE:
UNIT IS SUPPLIED WITH OPTIONAL
PUSH-ON #6-32 SCREW TERMINALS
FOR TRANSFORMER CONNECTIONS.

+ MOTOR DRIVEN UNITS USE TERMINAL CONNECTIONS FOR CCW
INCREASING VOLTAGE, AS VIEWED FROM BASE END.

SPEED (SECONDS)	MODEL NUMBER	DIM "A"
5	5M501C	9.34 [237.2]
15	15M501C	9.34 [237.2]
30	30M501C	9.73 [247.1]
60	60M501C	9.73 [247.1]

SPECIFICATIONS																							
WIRING	INPUT		OUTPUT				SHAFT ROTATION TO INCREASE VOLTAGE	TERMINAL CONNECTIONS															
	VOLTS	HERTZ	VOLTS	CONSTANT CURRENT LOAD		CONSTANT IMPEDANCE LOAD		FOR INCREASING VOLTAGE AS VIEWED FROM BASE END +															
				MAX. AMPS	MAX. KVA	MAX. AMPS		MAX. KVA	INPUT	JUMPER	OUTPUT												
SINGLE PHASE	120	50/60	0-120	5.0	0.60	7.0	0.84	CW	1-4	——	4-3												
									CCW	1-4	——	1-3											
									CW	4-5	——	4-3											
			0-140	5.0	0.70	——	——	CCW	1-2	——	1-3												
UNLESS OTHERWISE SPECIFIED, TOLERANCE IS ±			TITLE: SPEC. CONTROL DRAWING VARIABLE TRANSFORMER MODEL: M501C																				
DECIMALS .XX .0005												Holes .06			ANGLES 1°			DRAFT 1-1/2°			UNITS IN [mm]		
MATERIAL			ALL DIMENSIONS APPLY AFTER PLATING			 A COMPANY OF AMERICA COMPANY DAYTON, OHIO U.S.A.																	
The information and design disclosed herein was originated by and is the property of STACO ENERGY PRODUCTS CO., which reserves all patent, proprietary, design, manufacturing, reproduction, use and sale rights thereto, and to any article disclosed therein except to the extent rights are expressly granted to others. The foregoing does not apply to vendor proprietary parts.																							
												DRAWN BY TIM RAU		DATE 3/16/99		FIRST USED ON		DO NOT SCALE DWG.		CUSTOMER APPROVAL		DATE	
												CHECKER		DATE		WEIGHT APPROX. 11.5 LBS		CODE IDENT. NO. 83008		DWG. NO. 031-0564		D	
ENGINEER		DATE		SCALE 1 = 1		SHEET 1 OF 1																	

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

[Staco:](#)

[M501C](#)