

Tripp Lite
1111 W. 35th Street
Chicago, IL 60609 USA
Telephone: 773.869.1234
www.tripplite.com

AVR Series 120V 700VA 350W Ultra-Compact Line-Interactive UPS with USB port and Muted Alarm

MODEL NUMBER: AVR700UXRM









Description

Tripp Lite's AVR700UXRM Ultra-Compact Line Interactive UPS offers complete power protection for desktop PCs, network workstations and a wide variety of professional and consumer electronic devices. Uninterruptible Power Supply / UPS circuits switch to battery backup mode within milliseconds to keep connected equipment running without interruption or data loss during power failures. Automatic Voltage Regulation / AVR power conditioning maintains smooth, continuous operation of connected equipment during brownouts and overvoltages. Surge-only outlets offer convenient protection for printers and other desktop accessories not requiring battery support. AC and dataline surge suppression prevents connected equipment damage. USB communications port supports built-in power management and auto-shutdown features of Windows and Mac OS X or full featured monitoring and data-saving auto-shutdown options using Tripp Lite's free PowerAlert monitoring software.

Features

- AVR700UXRM ultra-compact 120V line interactive UPS offers complete AC power protection from blackouts, brownouts and transient surges
- 700VA / 350 watt UPS output capacity
- Audible alarm is completely muted from the factory; Alarm operation can be restored using PowerAlert UPS management software
- Uninterruptible Power Supply / UPS operation maintains battery-derived AC output during blackouts to prevent data loss and system downtime for connected equipment
- Built-in USB port enables data-saving unattended shutdown when used with Tripp Lite's PowerAlert software, available via FREE download from www.tripplite.com/poweralert
- HID-compliant USB port also enables integration with built-in power management and auto shutdown features of Windows and Mac OS X

Highlights

- 700VA ultra-compact 120V line interactive UPS
- Audible alarm is muted for fulltime silent operation
- Corrects brownouts and overvoltages from 83V to 147V
- 4 UPS battery supported outlets,
 4 surge-only outlets
- USB port, TEL/DSL protection,
 Wall mountable, 98% efficient
- 50% longer runtime than Tripp Lite AVR700U
- NEMA 5-15P input plug and 8
 NEMA 5-15R outlets

Package Includes

- AVR700UXRM UPS System
- USB cable
- Instruction manual



- Automatic Voltage Regulation / AVR corrects extended brownouts and overvoltages from 83 to 147V,
 without using battery power
- Large internal battery offers 50% longer runtime than Tripp Lite AVR700U
- 11.8 minutes runtime at 50% load (175 watts)
- Up to 42 minutes runtime for a single desktop computer system consuming 60 watts continuous
- 8 built-in NEMA 5-15R outlets, two with extra wide spacing to accommodate transformer plugs
- 4 UPS battery backup outlets, plus 4 additional surge-only outlets
- Right angle NEMA 5-15P input connection with 6ft / 1.8m line cord
- Network grade AC surge protection is available from all outlets
- Built-in data line surge suppression protects a single dialup or DSL line
- Supports Tripp Lite's Watchdog system service to restore operation to locked equipment through soft reboot of application/OS or hard power off/on reboot of connected equipment, ideal for unattended kiosk applications
- 98% line mode efficiency rating uses less energy and BTU emissions
- Built-in grounding lug
- Hot swappable user battery replacement
- Optional PDUB15 bypass PDU enable hot-swappable UPS replacement with no disruption to connected
- Space saving, ultra-compact housing with support for wall-mount, desktop or floor placement

Specifications

OVERVIEW		
UPC Code	037332183682	
UPS Type	Line-Interactive	
INPUT		
Rated input current (Maximum Load)	12A	
Nominal Input Voltage(s) Supported	120V AC	
UPS Input Connection Type	5-15P; Right-Angled	
UPS Input Cord Length (ft.)	6	
UPS Input Cord Length (m)	1.8	
Recommended Electrical Service	15A 120V	
Input Phase	Single-Phase	
ОИТРИТ		
Output Volt Amp Capacity (VA)	700	



Output Voltage Details 115v nominal output in battery mode 115v nominal output voltage Regulation (Battery Mode) 115v Note Note Regulation (Battery Mode) 115v Note Note PDU Options 115v Note Note Note Note Note Note Note Note			
Frequency Compatibility Output Voltage Regulation (Line 48%, -21% Output Voltage Regulation (Battery 46%, -21% Mode) 1/25 Cutput Receptocles (Surge Suppression Only) 4 UPS outlets, 4 surge-only outlets Hot-Swap PDU options PDUB15 (2U / 8 5-15R outlets) Output AC Waveform (AC Mode) Sine wave Output AC Waveform (Battery PWM sine wave Mode) 110V: 115V: 120V Output Receptacles (8) 5-15R Individually Controllable Load Banks No BATTERY Battery Type Valve Regulated Lead Acid (VRLA) Half Load Runtime (min.) 11.8 min. (175w) Expandable Runtime No Co System Voltage (Runc) 15.8 hours (10% to 90%) Battery Recharge Rate (Included Batteries) Battery Replacement Battery Battery Replacement Battery Battery Replacement Description Hot-swappable, user replaceable batteries VOLTAGE REGULATION Voltage Regulation Section 1.0 mput voltage regulation (AVR) maintains line power operation with an input voltage range of 83 to 147 Overvoltage Correction Input voltages between 83 and 147 are reduced by 12% User Interescent Combination switch controls on/oil power status and self-test operation James is factory mudel for silent operations, wutlet leading power failure and overload conditions using Power/let UPS management software Voltage Runtimes Audible Alarm	Output Watt Capacity (Watts)	350	
Output Voltage Regulation (Line Mode) 48%, -21% UPS Output Receptacles (Surge Suppression Child Supp	Nominal Voltage Details	115v nominal output in battery mode	
Mode) Output Voltage Regulation (Battery Mode) UPS Output Receptacles (Surge Suppression Only) 4 UPS outlets, 4 surge-only outlets UPS Output Receptacles (Surge Suppression Only) Hot-Swap PDU options PDUB15 (ZU / 8 5-15R outlets) Output AC Waveform (AC Mode) Output AC Waveform (Battery Mode) PWM sine wave Output AC Waveform (Battery PWM sine wave Nominal Output Voltage(s) Supported 110V: 115V: 120V Output Receptacles (8) 5-15R Individually Controllable Load Banks No BATTERY Sattery Type Valve Regulated Lead Acid (VRLA) Half Load Runtime (min.) 11.8 min. (175w) Expandable Runtime No DC System Voltage (VDC) 12 Battery Recharge Rate (Included Battery Sattery Satt	Frequency Compatibility	60 Hz	
UPS Output Receptacles (Surge Suppression Only) 4 UPS outlets, 4 surge-only outlets 4 UPS Output Receptacles (Surge Suppression Only) 4 UPS outlets, 4 surge-only outlets Output AC Waveform (AC Mode) Output AC Waveform (Battery Mode) PWM sine wave Output AC Waveform (Battery Mode) Nominal Output Voltage(s) Supported 110V; 115V; 120V Output Receptacles (8) 5-15R Individually Controllable Load Banks No BATTERY Battery Type Valve Regulated Lead Acid (VRLA) Half Load Runtime (min.) 11.8 min. (175w) Expandable Runtime No DC System Voltage (VDC) Battery Recharge Rate (Included Batteries) Battery Access Battery access door Internal UPS Replacement Battery Battery Replacement Description Hot-swappable, user replaceable batteries VOLTAGE REGULATION VOLTAGE REGULATION Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 83 to 147 Overvoltage Correction Input voltages between 128 and 147 are reduced by 12% Undervoltage Correction Linear Script must for silent operation, and be restored to indicate power failure and overload conditions using Power/Alert UPS management software Addible Alarm Alarm is factory mused for silent operation, Audible alarm can be restored to indicate power failure and overload conditions using Power/Alert UPS management software		+8%, -21%	
Hot-Swap PDU options PDUB15 (2U / 8 5-15R outliets) Output AC Waveform (AC Mode) Sine wave Output AC Waveform (Battery PWM sine wave Nominal Output Voltage(s) 110V; 115V; 120V Output Receptacles (8) 5-15R Individually Controllable Load Banks No BATTERY Battery Type Valve Regulated Lead Acid (VRLA) Half Load Runtime (min.) 11.8 min. (175w) Expandable Runtime No DC System Voltage (VDC) 12 Battery Racharge Rate (Included Battery access door Battery Access Battery access door Internal UPS Replacement Battery Battery access door Internal UPS Replacement Battery Battery Access door Internal UPS Replacement Description Hot-swappable, user replaceable batteries Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 83 to 147 Overvoltage Correction Input voltages between 128 and 147 are reduced by 12% Undervoltage Correction Input voltages between 83 and 104 are boosted by 14% USER INTERFACE, ALERTS & CONTROLS Sine wave Sine wave PWM sine wave PWM sine wave PWM sine wave PWM sine wave (8) 5-15R Output (9) 110V; 115V; 120V Output Receptacles No Valve Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 83 to 147 Overvoltage Correction Input voltages between 83 and 104 are boosted by 14% USER INTERFACE, ALERTS & CONTROLS Switches Combination switch controls on/off power status and self-test operation Audible Alarm Sactory muted for silent operation. Audible alarm can be restored to indicate power failure and overload conditions using PowerAlert UPS management software		+/- 5%	
Output AC Waveform (AC Mode) Sine wave Output AC Waveform (Battery Mode) PWM sine wave 110V: 115V; 120V Output Receptacles (8) 5-15R Individually Controllable Load Banks No BATTERY Battery Type Valve Regulated Lead Acid (VRLA) Half Load Runtime (min.) 11.8 min. (175w) Expandable Runtime No DC System Voltage (VDC) 12 Battery Recharge Rate (Included Batteries) Battery Access Battery Replacement Battery Shops, ac class="productLink" href="//www.tripplite.com/UPS-Replacement-Battery-Cartridge-Tripp-Lite-APC-Belkin-Best-Powerware-Liebert-other-UPS-RBC51">RB	UPS Output Receptacles (Surge Suppression Only)	4 UPS outlets, 4 surge-only outlets	
Output AC Waveform (Battery Mode) Nominal Output Voltage(s) Supported 110V; 115V; 120V Output Receptacles (8) 5-15R Individually Controllable Load Banks No BATTERY Battery Type Valve Regulated Lead Acid (VRLA) Half Load Runtime (min.) 11.8 min. (175w) Expandable Runtime No DC System Voltage (VDC) 12 Battery Recharge Rate (included Batteries) Battery Access Internal UPS Replacement Battery Cartridge Battery Access Internal UPS Replacement Description Hot-swappable, user replaceable batteries VOLTAGE REGULATION Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 83 to 147 Overvoltage Correction Input voltages between 83 and 104 are boosted by 14% USER INTERFACE, ALERTS & CONTROLS Switches Combination switch controls on/off power status and self-test operation Audible Alarm Alarm is factory muted for silent operation: Audible alarm can be restored to indicate power failure and overload conditions using PowerAlert UPS management software	Hot-Swap PDU options	PDUB15 (2U / 8 5-15R outlets)	
Nominal Output Voltage(s) Nominal Output Voltage(s) Supported 110V; 115V; 120V Output Receptacles (8) 5-15R Individually Controllable Load Banks No BATTERY Battery Type Valve Regulated Lead Acid (VRLA) Half Load Runtime (min.) 11.8 min. (175w) Expandable Runtime No DC System Voltage (VDC) 12 Battery Recharge Rate (included Battery access door Internal UPS Replacement Battery Cartridge Battery Access Hattery Replacement Description Hot-swappable, user replaceable batteries VOLTAGE REGULATION Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 83 to 147 Overvoltage Correction Input voltages between 83 and 104 are boosted by 14% USER INTERFACE, ALERTS & CONTROLS Switches Combination switch controls on/off power status and self-test operation Audible Alarm Alarm is factory muted for silent operation, Audible alarm can be restored to indicate power failure and overfoad conditions using PowerAlert UPS management software	Output AC Waveform (AC Mode)	Sine wave	
Output Receptacles (8) 5-15R Individually Controllable Load Banks No BATTERY Battery Type Valve Regulated Lead Acid (VRLA) Half Load Runtime (min.) 11.8 min. (175w) Expandable Runtime No DC System Voltage (VDC) 12 Battery Recharge Rate (Included Batteries) 15.8 hours (10% to 90%) Battery Access Battery access door Internal UPS Replacement Battery Battery Access door Internal UPS Replacement Battery Battery Access Battery Recharge Replacement Battery Battery Access Battery Access Battery Replacement Battery Battery Access Battery Replacement Description Battery Battery Replacement Description Battery Replacement Description Hot-swappable, user replaceable batteries VOLTAGE REGULATION Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 83 to 147 Overvoltage Correction Input voltages between 128 and 147 are reduced by 12% Undervoltage Correction Input voltages between 83 and 104 are boosted by 14% USER INTERFACE, ALERTS & CONTROLS Switches Combination switch controls on/off power status and self-test operation Audible Alarm Alarm is factory muted for silent operation; Audible alarm can be restored to indicate power failure and overload conditions using PowerAlert UPS management software	Output AC Waveform (Battery Mode)	PWM sine wave	
Individually Controllable Load Banks BATTERY Battery Type	Nominal Output Voltage(s) Supported	110V; 115V; 120V	
BATTERY Battery Type Valve Regulated Lead Acid (VRLA) Half Load Runtime (min.) 11.8 min. (175w) Expandable Runtime No DC System Voltage (VDC) 12 Battery Recharge Rate (Included Batteries) 15.8 hours (10% to 90%) Battery Access Battery access door Internal UPS Replacement Battery Best-Powerware-Liebert-other-UPS-RBC51*>RBC51**>RBC51**>RBC51**>RBC51**>RBC51**>RBC51*	Output Receptacles	(8) 5-15R	
Battery Type Valve Regulated Lead Acid (VRLA) Half Load Runtime (min.) 11.8 min. (175w) Expandable Runtime No DC System Voltage (VDC) 12 Battery Recharge Rate (Included Batteries) 15.8 hours (10% to 90%) Battery Access Battery access door Internal UPS Replacement Battery 8. hbsp; RBC51*/RBC51*/as- Battery Replacement Description Hot-swappable, user replaceable batteries VOLTAGE REGULATION Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 83 to 147 Overvoltage Correction Input voltages between 128 and 147 are reduced by 12% Undervoltage Correction Input voltages between 83 and 104 are boosted by 14% USER INTERFACE, ALERTS & CONTROLS Switches Combination switch controls on/off power status and self-test operation Aldible Alarm Alarm is factory muted for silent operation; Audible alarm can be restored to indicate power failure and overload conditions using PowerAlert UPS management software	BATTERY		
Expandable Runtime No DC System Voltage (VDC) 12 Battery Recharge Rate (Included Batteries) 15.8 hours (10% to 90%) Battery Recharge Rate (Included Batteries) 25.8 hours (10% to 90%) Battery Access Battery access door Internal UPS Replacement Battery 25.4 class="productLink" href="//www.tripplite.com/UPS-Replacement-Battery-Cartridge-Tripp-Lite-APC-Belkin-Best-Powerware-Liebert-other-UPS-RBC51">RBC51 **Alexage Correction Battery Cartridge-Tripp-Lite-APC-Belkin-Best-Powerware-Liebert-other-UPS-RBC51">RBC51">RBC51 **Alexage Correction Battery Cartridge-Tripp-Lite-APC-Belkin-Best-Powerware-Liebert-other-UPS-RBC51">RBC51 **ABC51	Battery Type	Valve Regulated Lead Acid (VRLA)	
Battery Recharge Rate (Included Battery Recharge Rate (Included Batteries) Battery Access Battery access door Internal UPS Replacement Battery Anbsp; RBC51 RBC51 RBC51 RBC51 RBC51 RBC51 <a< td=""></a<>			
Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 83 to 147 Overvoltage Correction Input voltages between 128 and 147 are reduced by 12% Undervoltage Correction Input voltages between 83 and 104 are boosted by 14% USER INTERFACE, ALERTS & CONTROLS Switches Combination switch controls on/off power status and self-test operation Alarm is factory muted for silent operation; Audible alarm can be restored to indicate power failure and overload conditions using PowerAlert UPS management software	Battery Replacement Description	Hot-swappable, user replaceable batteries	
Overvoltage Correction Input voltages between 128 and 147 are reduced by 12% Undervoltage Correction Input voltages between 83 and 104 are boosted by 14% USER INTERFACE, ALERTS & CONTROLS Switches Combination switch controls on/off power status and self-test operation Audible Alarm Alarm is factory muted for silent operation; Audible alarm can be restored to indicate power failure and overload conditions using PowerAlert UPS management software	VOLTAGE REGULATION		
Undervoltage Correction Input voltages between 83 and 104 are boosted by 14% USER INTERFACE, ALERTS & CONTROLS Switches Combination switch controls on/off power status and self-test operation Audible Alarm Alarm is factory muted for silent operation; Audible alarm can be restored to indicate power failure and overload conditions using PowerAlert UPS management software	Voltage Regulation Description	Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 83 to 147	
USER INTERFACE, ALERTS & CONTROLS Switches Combination switch controls on/off power status and self-test operation Alarm is factory muted for silent operation; Audible alarm can be restored to indicate power failure and overload conditions using PowerAlert UPS management software	Overvoltage Correction	Input voltages between 128 and 147 are reduced by 12%	
Switches Combination switch controls on/off power status and self-test operation Audible Alarm Alarm is factory muted for silent operation; Audible alarm can be restored to indicate power failure and overload conditions using PowerAlert UPS management software	Undervoltage Correction	Input voltages between 83 and 104 are boosted by 14%	
Audible Alarm Alarm is factory muted for silent operation; Audible alarm can be restored to indicate power failure and overload conditions using PowerAlert UPS management software	USER INTERFACE, ALERTS & CONTROLS		
conditions using PowerAlert UPS management software	Switches	Combination switch controls on/off power status and self-test operation	
LED Indicators 2 LEDs indicate power status and overload/check battery status	Audible Alarm	Alarm is factory muted for silent operation; Audible alarm can be restored to indicate power failure and overload conditions using PowerAlert UPS management software	
	LED Indicators	2 LEDs indicate power status and overload/check battery status	





SURGE / NOISE SUPPRESSION		
UPS AC Suppression Joule Rating	420	
UPS AC Suppression Response Time	Instantaneous	
UPS Dataline Suppression	1 line TEL/DSL (1 in / 1 out)	
EMI / RFI AC Noise Suppression	Yes	
PHYSICAL		
Installation Form Factors Supported with Included Accessories	Tower; Ultra-compact desktop; Wallmount	
Primary Form Factor	Desktop	
Primary UPS Depth (mm)	152	
Primary UPS Height (mm)	89	
Primary UPS Width (mm)	287	
Shipping Dimensions (hwd / cm)	11.68 x 34.04 x 21.84	
Shipping Dimensions (hwd / in.)	4.60 x 13.40 x 8.60	
Shipping Weight (kg)	5.35	
Shipping Weight (lbs.)	11.80	
UPS Housing Material	ABS	
UPS Power Module Dimensions (hwd, cm)	8.89 x 28.70 x 15.24	
UPS Power Module Dimensions (hwd, in.)	3.5 x 11.3 x 6	
UPS Power Module Weight (kg)	4.99	
UPS Power Module Weight (lbs.)	11	
ENVIRONMENTAL		
Operating Temperature Range	+32 to +104 degrees Fahrenheit / 0 to +40 degrees Celsius	
Storage Temperature Range	+5 to +122 degrees Fahrenheit / -15 to +50 degrees Celsius	
Relative Humidity	0 to 95%, non-condensing	
AC Mode BTU / Hr. (Full Load)	30	
AC Mode Efficiency Rating (100% Load)	98%	
COMMUNICATIONS		
PowerAlert Software	For local monitoring via the UPS's built-in communication ports, download PowerAlert Local software at http://www.tripplite.com/poweralert	
Communications Cable	USB interface cable included	
WatchDog Compatibility	Supports Watchdog application, OS and hard-reboot restart options for remote applications	





NUT compatible. See the full list of Tripp Lite NUT compatible UPS systems at http://www.networkupstools.org/stable-hcl.html?manufacturer=Tripp Lite		
USB (HID enabled)		
1-4 milliseconds		
83		
147		
Included		
Cold-start operation supported		
Hot swappable batteries		
Greater than 95% efficiency - GREEN UPS		
STANDARDS & COMPLIANCE		
Tested to UL1778 (USA); Tested to CSA (Canada); Tested to NOM (Mexico); Meets FCC Part 15 Category B (EMI)		
3-year limited warranty		
3-year limited warranty		
2-year limited warranty		
3-year limited warranty		
\$100,000 Ultimate Lifetime Insurance		

© 2021 Tripp Lite. All rights reserved. All product and company names are trademarks or registered trademarks of their respective holders. Use of them does not imply any affiliation with or endorsement by them. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Tripp Lite uses primary and third-party agencies to test its products for compliance with standards. See a list of Tripp Lite's testing agencies: https://www.tripplite.com/products/product-certification-agencies

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Tripp Lite:

AVR700UXRM