



### TAA SmartPro 120V 3kVA 2.25kW Line-Interactive Sine Wave UPS, 2U, Extended Run, Network Card Options, LCD, USB, DB9

MODEL NUMBER: SM3000RM2UTAA











#### Description

Tripp Lite SmartPro Line Interactive UPS with enhanced LCD interface offers network-grade power protection for critical server, network and telecommunications equipment. Line Interactive Uninterruptible Power Supply (UPS) with built-in Auto-Voltage Regulation (AVR) actively corrects brownouts and overvoltages back to usable levels while maintaining a full battery charge in case of power failure. Tripp Lite's unique configuration excels in exceptionally poor-power environments with two separate levels of voltage boost to correct both slight undervoltages and severe brownout conditions. Interactive LCD interface reports UPS operating mode, detailed UPS and site-power data, plus enables a variety of UPS setup and configuration options. Super-fast switchover from line to battery power occurs within milliseconds to maintain operation of connected equipment without interruption or reboot. 98% line-mode efficiency offers reduced heat emissions and operating costs. Network management interfaces support communications via USB, RS-232 and slot for network management card options. HID-compliant USB port enables integration with built-in power management and auto shutdown features of Windows and Mac OS X. Network communications ports enable detailed monitoring of equipment load levels, self-test data and utility power conditions. PowerAlert UPS monitoring and auto shutdown software is available via free download. Switched output load banks enable scheduled and real-time remote reboot and load shedding of select outlets. Emergency Power Off (EPO) interface. LCD display panel easily rotates for viewing in rackmount or tower configurations. Audible alarm with push-button momentary alarm-cancel and silent-mode configuration options. Programmable self-test. Field-replaceable, hot-swappable battery modules.

#### **Features**

- Federal Trade Agreements Act / TAA compliant for GSA schedule purchases
- Tripp Lite SM3000RM2UTAA line interactive 2U rack/tower UPS with 3000VA / 3kVA capacity (1600W maximum load with external battery packs)

#### **Highlights**

- 3kVA / 3000VA / 2250W line interactive 2U rack/tower UPS,
   Sine Wave
- Extended runtime options up to 1600W, Interactive LCD interface
- USB, RS232, EPO and slot for network management card options
- 120V NEMA L5-30P input, 8
   NEMA 5-15/20R & 1 L5-30R
   outlets
- TAA Compliant for GSA
   Schedule purchases
- To use the Auto Probe feature, this product requires a WEBCARDLX network interface (sold separately) running LX firmware update 15.5.2 or later

#### Package Includes

- SM3000RM2UTAA UPS System
- USB, Serial & EPO cabling
- · 4-post rackmount installation kit
- Owner's manual

# Tripp Lite 1111 W. 35th Street Chicago, IL 60609 USA Telephone: 773.869.1234



- Line interactive UPS with Automatic Voltage Regulation (AVR) corrects brownouts and overvoltages from 83 to 145V
- NEMA L5-30P input plug; 8 NEMA 5-15/20R and 1 L5-30R output receptacles, Two independently switchable output load banks
- Maintains uninterrupted operation of connected networking equipment during blackouts, surges, brownouts and overvoltages
- High 98% efficiency rating in line-power mode offers reduced power consumption and BTU emissions
- Internal batteries offer 10 minutes at 50% load (1125W) and 3.5 minutes at 100% load (2250W)
- Extended runtime is available with optional BP48V242UTAA (limit 1), BP48V24-2U (limit 1),
   BP48V60RT-3U (multi-pack compatible), BP48V60RT3UTAA (multi-pack compatible), and BP48V27-2US (multi-pack compatible) external battery packs (max output de-rates to 1600 watts with external batteries)
- External battery configurations require the use of Tripp Lite's External Battery Configuration Software (see manual)
- Hot-swappable, user-replaceable internal batteries and external battery packs can be replaced with no disruption to connected equipment
- Front panel LCD monitoring screen with MODE and ENTER buttons reports operating mode with 5-bar battery charge graphic, plus 7 selectable screens of detailed UPS and site power information
- LCD interface also supports a number of advanced user setup and operating preferences
- Ships with 4 post rackmount installation hardware; Optional 2POSTRMKITWM enables 2 post rackmount/wallmount installation; Optional 2-9USTAND enables tower placement
- Built-in USB, RS-232 and slot for network management card options; Compatible with Tripp Lite UPS management card options TLNETCARD, WEBCARDLX and SNMPWEBCARD
- HID-compliant USB port enables integration with built-in power management and auto shutdown features of Windows and Mac OS X
- USB & Serial ports enable data-saving unattended shutdown when used with Tripp Lite's PowerAlert software, available via FREE download from <a href="https://www.tripplite.com/poweralert">www.tripplite.com/poweralert</a>
- Built-in Emergency Power Off (EPO) interface with cable

## **Specifications**

OVERVIEW		
UPC Code	037332184207	
UPS Type	Line-Interactive	
INPUT		
Rated input current (Maximum Load)	24A	
Nominal Input Voltage(s) Supported	120V AC	





UPS Input Connection Type	L5-30P
UPS Input Cord Length (ft.)	10
UPS Input Cord Length (m)	3.1
Recommended Electrical Service	30A 120V
Input Phase	Single-Phase
ОИТРИТ	
Output Volt Amp Capacity (VA)	3000
Output kVA Capacity (kVA)	3.00
Output Watt Capacity (Watts)	2250
Output kW Capacity (kW)	2.25
Output Capacity Details	Output is reduced to 1600 watts maximum when used with external battery packs
Power Factor	0.75
Nominal Voltage Details	120v nominal output in battery mode
Frequency Compatibility	60 Hz
Output Voltage Regulation (Line Mode)	-14%, +6%
Output Voltage Regulation (Battery Mode)	+/- 5%
Load Management Receptacles	Two switchable single-outlet load banks
Output Circuit Breakers	Two 20A output breakers protect 4 5-15/20R outlets each
Output AC Waveform (AC Mode)	Pure Sine wave
Output AC Waveform (Battery Mode)	Pure Sine wave
Nominal Output Voltage(s) Supported	110V; 115V; 120V
Output Receptacles	(8) 5-15/20R; (1) L5-30R
Individually Controllable Load Banks	Yes
BATTERY	
Battery Type	Valve Regulated Lead Acid (VRLA)
Full Load Runtime (min.)	3.5 min. (2250w)
Half Load Runtime (min.)	10 min. (1125w)
Expandable Battery Runtime	Extended runtime supported via optional external battery packs
Expandable Runtime	Yes





External Battery Pack Compatibility	
	<a class="productLink" href="//www.tripplite.com/External-48V-2U-Rack-Tower-Battery-Pack-Enclosure-DC-Cabling-select-UPS-Systems~BP48V24-2U">BP48V24-2U</a> (limit 1); <a class="productLink" href="//www.tripplite.com/TAA-Compliant-External-48V-2U-Rack-Tower-Battery-Pack-Enclosure-for-select-UPS-Systems~BP48V242UTAA">BP48V242UTAA</a> (limit 1); <a class="productLink" href="//www.tripplite.com/External-48V-2U-Rack-Tower-Battery-Pack-for-UPS-Systems~BP48V27-2US">BP48V27-2US</a> &a hbsp; (multi-pack compatible); <a class="productLink" href="//www.tripplite.com/External-48V-3U-Rack-Tower-Battery-Pack-Enclosure-DC-Cabling-select-UPS-Systems~BP48V60RT-3U">BP48V27-2US</a> &a hbsp; (multi-pack compatible); <a class="productLink" href="//www.tripplite.com/External-48V-3U-Rack-Tower-Battery-Pack-Enclosure-DC-Cabling-select-UPS-Systems~BP48V60RT-3U">BP48V60RT-3U"&gt;BP48V60RT-3U"&gt;BP48V60RT-3U"&gt;BP48V60RT-3U"&gt;BP48V60RT-3U"&gt;BP48V60RT-3U"&gt;BP48V60RT-3U"&gt;BP48V60RT-3U"&gt;BP48V60RT-3U"&gt;BP48V60RT-3U"<brown-tripplite.com taa-compliant-external-48v-3u-battery-pack-for-select-tripp-lite-ups-systems~bp48v60rt3utaa"="">BP48V60RT3UTAA</brown-tripplite.com></a> (multi-pack compatible)
DC System Voltage (VDC)	48
Battery Recharge Rate (Included Batteries)	Less than 4.5 hours from 10% to 90%
Battery Access	Front panel battery access door
Internal UPS Replacement Battery Cartridge	<a class="productLink" href="//www.tripplite.com/2U-UPS-Replacement-48VDC-Battery-Cartridge-1-set-4-select-Tripp-Lite-SmartPro-UPS~RBC94-2U">RBC94-2U</a>
Battery Replacement Description	Hot-swappable, user replaceable batteries
VOLTAGE REGULATION	
Voltage Regulation Description	Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 83 to 145
Overvoltage Correction	Input voltages between 127 and 145 are reduced by 12%
Undervoltage Correction	Input voltages between 108 and 96 are boosted by 12%
Severe Undervoltage Correction	Input voltages between 83 and 95 are boosted by 24%
USER INTERFACE, ALERTS & CON	TROLS
USER INTERFACE, ALERTS & CON Front Panel LCD Display	TROLS  Front panel LCD information and configuration screen offers detailed UPS and site power status and operating data, plus configuration of voltage, operating mode, alarm function and a variety of additional options (see manual for detailed LCD configuration and monitoring options)
· · · · · · · · · · · · · · · · · · ·	Front panel LCD information and configuration screen offers detailed UPS and site power status and operating data, plus configuration of voltage, operating mode, alarm function and a variety of additional options (see manual for
Front Panel LCD Display	Front panel LCD information and configuration screen offers detailed UPS and site power status and operating data, plus configuration of voltage, operating mode, alarm function and a variety of additional options (see manual for detailed LCD configuration and monitoring options)
Front Panel LCD Display Switches	Front panel LCD information and configuration screen offers detailed UPS and site power status and operating data, plus configuration of voltage, operating mode, alarm function and a variety of additional options (see manual for detailed LCD configuration and monitoring options)  3 pushbutton switches control OFF / ON power status, MODE selection and MUTE / ENTER control functions  Power-fail alarm can be temporarily silenced using alarm-cancel switch; silent mode alarm configuration option
Front Panel LCD Display  Switches  Alarm Cancel Operation	Front panel LCD information and configuration screen offers detailed UPS and site power status and operating data, plus configuration of voltage, operating mode, alarm function and a variety of additional options (see manual for detailed LCD configuration and monitoring options)  3 pushbutton switches control OFF / ON power status, MODE selection and MUTE / ENTER control functions  Power-fail alarm can be temporarily silenced using alarm-cancel switch; silent mode alarm configuration option available  Audible alarm indicates UPS startup, power-failure, low-battery, overload, UPS fault and remote shutdown
Front Panel LCD Display  Switches  Alarm Cancel Operation  Audible Alarm	Front panel LCD information and configuration screen offers detailed UPS and site power status and operating data, plus configuration of voltage, operating mode, alarm function and a variety of additional options (see manual for detailed LCD configuration and monitoring options)  3 pushbutton switches control OFF / ON power status, MODE selection and MUTE / ENTER control functions  Power-fail alarm can be temporarily silenced using alarm-cancel switch; silent mode alarm configuration option available  Audible alarm indicates UPS startup, power-failure, low-battery, overload, UPS fault and remote shutdown
Front Panel LCD Display  Switches  Alarm Cancel Operation  Audible Alarm  SURGE / NOISE SUPPRESSION	Front panel LCD information and configuration screen offers detailed UPS and site power status and operating data, plus configuration of voltage, operating mode, alarm function and a variety of additional options (see manual for detailed LCD configuration and monitoring options)  3 pushbutton switches control OFF / ON power status, MODE selection and MUTE / ENTER control functions  Power-fail alarm can be temporarily silenced using alarm-cancel switch; silent mode alarm configuration option available  Audible alarm indicates UPS startup, power-failure, low-battery, overload, UPS fault and remote shutdown conditions
Front Panel LCD Display  Switches  Alarm Cancel Operation  Audible Alarm  SURGE / NOISE SUPPRESSION  UPS AC Suppression Joule Rating  UPS AC Suppression Response	Front panel LCD information and configuration screen offers detailed UPS and site power status and operating data, plus configuration of voltage, operating mode, alarm function and a variety of additional options (see manual for detailed LCD configuration and monitoring options)  3 pushbutton switches control OFF / ON power status, MODE selection and MUTE / ENTER control functions  Power-fail alarm can be temporarily silenced using alarm-cancel switch; silent mode alarm configuration option available  Audible alarm indicates UPS startup, power-failure, low-battery, overload, UPS fault and remote shutdown conditions
Front Panel LCD Display  Switches  Alarm Cancel Operation  Audible Alarm  SURGE / NOISE SUPPRESSION  UPS AC Suppression Joule Rating  UPS AC Suppression Response Time	Front panel LCD information and configuration screen offers detailed UPS and site power status and operating data, plus configuration of voltage, operating mode, alarm function and a variety of additional options (see manual for detailed LCD configuration and monitoring options)  3 pushbutton switches control OFF / ON power status, MODE selection and MUTE / ENTER control functions  Power-fail alarm can be temporarily silenced using alarm-cancel switch; silent mode alarm configuration option available  Audible alarm indicates UPS startup, power-failure, low-battery, overload, UPS fault and remote shutdown conditions  570  Instantaneous
Front Panel LCD Display  Switches  Alarm Cancel Operation  Audible Alarm  SURGE / NOISE SUPPRESSION  UPS AC Suppression Joule Rating  UPS AC Suppression Response Time  UPS Dataline Suppression	Front panel LCD information and configuration screen offers detailed UPS and site power status and operating data, plus configuration of voltage, operating mode, alarm function and a variety of additional options (see manual for detailed LCD configuration and monitoring options)  3 pushbutton switches control OFF / ON power status, MODE selection and MUTE / ENTER control functions  Power-fail alarm can be temporarily silenced using alarm-cancel switch; silent mode alarm configuration option available  Audible alarm indicates UPS startup, power-failure, low-battery, overload, UPS fault and remote shutdown conditions  570  Instantaneous  1 line TEL/DSL or Ethernet
Front Panel LCD Display  Switches  Alarm Cancel Operation  Audible Alarm  SURGE / NOISE SUPPRESSION  UPS AC Suppression Joule Rating  UPS AC Suppression Response Time  UPS Dataline Suppression  EMI / RFI AC Noise Suppression	Front panel LCD information and configuration screen offers detailed UPS and site power status and operating data, plus configuration of voltage, operating mode, alarm function and a variety of additional options (see manual for detailed LCD configuration and monitoring options)  3 pushbutton switches control OFF / ON power status, MODE selection and MUTE / ENTER control functions  Power-fail alarm can be temporarily silenced using alarm-cancel switch; silent mode alarm configuration option available  Audible alarm indicates UPS startup, power-failure, low-battery, overload, UPS fault and remote shutdown conditions  570  Instantaneous  1 line TEL/DSL or Ethernet
Front Panel LCD Display  Switches  Alarm Cancel Operation  Audible Alarm  SURGE / NOISE SUPPRESSION  UPS AC Suppression Joule Rating  UPS AC Suppression Response Time  UPS Dataline Suppression  EMI / RFI AC Noise Suppression	Front panel LCD information and configuration screen offers detailed UPS and site power status and operating data, plus configuration of voltage, operating mode, alarm function and a variety of additional options (see manual for detailed LCD configuration and monitoring options)  3 pushbutton switches control OFF / ON power status, MODE selection and MUTE / ENTER control functions  Power-fail alarm can be temporarily silenced using alarm-cancel switch; silent mode alarm configuration option available  Audible alarm indicates UPS startup, power-failure, low-battery, overload, UPS fault and remote shutdown conditions  570  Instantaneous  1 line TEL/DSL or Ethernet  Yes





Installation Form Factors Supported with Optional Accessories	2 post rackmount ( <a class="productLink" href="//www.tripplite.com/2-Post-Rack-Mount-Wall-Mount-Adapter-Kit-select-Rack-Mount-UPS-Systems-2POSTRMKITWM">2POSTRMKITWM</a> ); 2-4 post front rail rackmount ( <a class="productLink" href="//www.tripplite.com/Heavy-Duty-2-post-Front-Mounting-Ear-Kit~UPSHDEARKIT">UPSHDEARKIT</a> ); 4 post rackmount short-depth ( <a class="productLink" href="//www.tripplite.com/2U-9U-Tower-Stand-Kit-select-Rack-Mount-UPS-Systems-2-9USTAND" productlink"="">2-9USTAND"&gt;2-9USTAND</a> ); Wallmount ( <a class="productLink" href="//www.tripplite.com/2U-9U-Tower-Stand-Kit-select-Rack-Mount-UPS-Systems~2-9USTAND" productlink"="">2-9USTAND</a> enables upright tower UPS placement; <a class="productLink" href="//www.tripplite.com/2-Post-Rack-Mount-Wall-Mount-Adapter-Kit-select-Rack-Mount-UPS-Systems~2POSTRMKITWM">2POSTRMKITWM</a> enables wall-mount and 2-post rackmount installation; <a class="productLink" href="//www.tripplite.com/4-Post-1U-Universal-Adjustable-Rack-Mount-Shelf-Kit-for-Wall-Mount-Racks~4POSTRAILKITWM">4POSTRAILKITWM</a> enables installation in 4-post short-depth racks from 14.5 to 23.5 inches (368 to 597mm); <a class="productLink" href="//www.tripplite.com/Heavy-Duty-2-post-Front-Mounting-Ear-Kit~UPSHDEARKIT">UPSHDEARKIT</a> enables installation in 2 or 4-post racks using front vertical rails only, without rear support
Primary Form Factor	Rackmount
Primary UPS Depth (mm)	494
Primary UPS Height (mm)	88
Primary UPS Width (mm)	440
Rack Height	2U
Shipping Dimensions (hwd / cm)	21.59 x 62.23 x 55.37
Shipping Dimensions (hwd / in.)	8.50 x 24.50 x 21.80
Shipping Weight (kg)	36.74
Shipping Weight (lbs.)	81.00
UPS Housing Material	Steel
UPS Power Module Dimensions (hwd, cm)	8.79 x 43.99 x 49.43
UPS Power Module Dimensions (hwd, in.)	3.46 x 17.32 x 19.46
UPS Power Module Weight (kg)	28.49
UPS Power Module Weight (lbs.)	62.8
ENVIRONMENTAL	
Operating Temperature Range	+32 to +104 degrees Fahrenheit / 0 to +40 degrees Celsius
Storage Temperature Range	+5 to +122 degrees Fahrenheit / -15 to +50 degrees Celsius
Relative Humidity	0 to 95%, non-condensing





AC Mode BTU / Hr. (Full Load)	189
Battery Mode BTU / Hr. (Full Load)	1356
AC Mode Efficiency Rating (100% Load)	98%
Operating Elevation (ft.)	0-3000m / 0-10,000 ft.
Audible Noise	45 dBA maximum, front side 1m
Operating Elevation (m)	0 - 3000 m
COMMUNICATIONS	
Network Management Cards	<a class="productLink" href="//www.tripplite.com/SNMP-Web-Management-Accessory-Card-SmartPro-SmartOnline-UPS-Systems~SNMPWEBCARD">SNMPWEBCARD</a> ; <a class="productLink" href="//www.tripplite.com/Web-Management-Accessory-Card-SmartPro-SmartOnline-UPS-Systems~TLNETCARD">TLNETCARD</a> ; <a class="productLink" href="//www.tripplite.com/Web-Management-Accessory-Card~WEBCARDLX">WEBCARDLX</a>
Network Monitoring Port Description	Supports detailed monitoring of UPS and site power conditions
PowerAlert Software	For local monitoring via the UPS's built-in communication ports, download PowerAlert Local software at https://www.tripplite.com/poweralert
Communications Cable	USB and DB9 cabling included
WatchDog Compatibility	Supports Watchdog application, OS and hard-reboot restart options for remote applications
Network UPS Tools Compatibility	NUT compatible. See the full list of Tripp Lite NUT compatible UPS systems at http://www.networkupstools.org/stable-hcl.html?manufacturer=Tripp Lite
Communications Interface	DB9 Serial; EPO (emergency power off); Slot for SNMP/Web interface; USB (HID enabled)
LINE / BATTERY TRANSFER	
Transfer Time	5 milliseconds (AC to battery); 1 millisecond (battery to AC)
Low Voltage Transfer to Battery Power (Setpoint)	83
High Voltage Transfer to Battery Power (Setpoint)	145
SPECIAL FEATURES	
Grounding Lug	Includes back panel grounding lug
Cold Start (Startup in Battery Mode During a Power Failure)	Cold-start operation supported
High Availability UPS Features	Auto Probe Monitoring and Reboot (requires WEBCARDLX); Automatic Voltage Regulation (AVR); Hot swappable batteries; Remote management; Sine wave output; Surge/noise protection
Green Energy-Saving Features	Greater than 95% efficiency - GREEN UPS; Individually controllable load banks
STANDARDS & COMPLIANCE	
UPS Certifications	Meets FCC Part 15 Category A (EMI); ROHS (Restriction of Hazardous Substances); TAA Compliant; Tested to CSA (Canada); Tested to NOM (Mexico); Tested to UL1778 (USA)
Certification Details	SAFETY STANDARD (U.S.) - UL1778:2014 (5th Ed) R10.17; SAFETY STANDARD (CANADA) - CAN/CSA-C22.2 No. 107.3-14 (3rd Ed) + GI1 / FCC/ICES COMPLIANT - CLASS A



**Tripp Lite**1111 W. 35th Street
Chicago, IL 60609 USA
Telephone: 773.869.1234

WARRANTY	
Product Warranty Period (Worldwide)	2-year limited warranty
Connected Equipment Insurance (U.S., Canada & Puerto Rico)	\$250,000 <a class="insuranceLink" href="//www.tripplite.com/support/insurance-policy">Ultimate Lifetime Insurance</a>

© 2021 Tripp Lite. All rights reserved. All product and company names are trademarks or registered trademarks of their respective holders. Use of them does not imply any affiliation with or endorsement by them. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Tripp Lite uses primary and third-party agencies to test its products for compliance with standards. See a list of Tripp Lite's testing agencies: <a href="https://www.tripplite.com/products/product-certification-agencies">https://www.tripplite.com/products/product-certification-agencies</a>

## **Mouser Electronics**

**Authorized Distributor** 

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Tripp Lite:
SM3000RM2UTAA