SPECIFICATIONS 1503

DESCRIPTION: 0-12VDC 5A, 12VAC 5A **Power Supply**

INPUT VOLTAGE: 115, 60Hz

ENVIRONMENTAL TEMPERATURE: 25°C

UT VOLTAGE: Min. Max.
JT VOLTAGE: Min.

0-12VDC:

Output Voltage Range 0.1V 12V Minimum Output Voltage 0.8V,typ. 1V

Output Current 5A, typ.

VOLTAGE REGULATION:

 Load (0-100% load)
 800mV

 Line (100-120VAC Variation)
 100mV

 Ripple & Noise
 500mVp-p

12VAC:

Output Voltage No Load 12.5V 13.5V

Output Voltage Full Load 11.5V Output Current 5A, typ.

No Load Input Current 80mA Full Load Input Current (All rated Load) 1.5A

POWER CONSUMPTION:

Meter Accuracy +- 2.5%FS Ammeter +- 2.5%FS

Fuse 3Amps

Dimensions (W X D X H): 184 mm x 178 mm x 110 mm

Weight: 3.10 kgs

Description:

This power supply fits for any low voltage application you may have. The 1503 has a double output 12VAC/VDC along with 5Amps at both outputs, with a Voltmeter and an Ammeter.

Operation:

Plug model 1504 into an AC outlet. Turn power switch on. Adjust voltage with control knob. Connect to either 12VAC (constant) or 12VDC (variable).

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

B&K Precision:

1503