STRAIGHT SQUARE FLANGE JACK FULL CRIMP-TYPE - CABLE 5/50 S

R161.282.000

4holes DIA 0.13 (\$\phi 3.3) / 1.547 (39.3)DIA 0.62 (ø15.75) DIA 0.213 (ø5.41) DIA 0.041-(Ø1.05) (PERCAGE PANNEAU) (MOUNTING HOLE) Π C A DIA B DIA 4 holes square 0.719 0.657 (18.25) maxi | mini | maxi | mini (2)(16.7)A 16.3 16.1 0.642 0.63 B 3.3 3.2 0.13 0.126 square 1 $(\Box 25.4)$

NOMINAL IMPEDANCE 50 CABLES : BSSM 742 KX 15 FREQUENCY RANGE **0-11** GHz RG 141 **-55/+155** °C RG 58 TEMPERATURE RATING V.S.W.R 1.30 +x F(GHz)Maxi 0.048 √F(GHz) dB Maxi RF INSERTION LOSS 850 Veff Maxi **VOLTAGE RATING** DIELECTRIC WITHSTANDING VOLTAGE 1500 Veff Mini OTHERS CHARACTERISTICS 5000 INSULATION RESISTANCE MΩMini Atm.cm³/s HERMETIC SEAL NA CABLE RETENTION **150** N Mini LEAKAGE (pressurized only) NA CENTER CONTACT RETENTION 27 N Mini Axial force - mating end 500 MECHANICAL DURABILITY Cycles 27 N Mini Axial force - opposite end WEIGHT 33 cm.N Mini Torque SPECIFICATION RECOMMENDED TORQUES NA Mating cm.N Panel nut NA cm.N cm.N Clamp nut

(all values are given) in micrometers CONNECTOR PARTS: MATERIALS FINISH BODY BRASS BBR 2 BBR 2 **OUTER CONTACT BRASS** CENTER CONTACT BERYLLIUM COPPER GOLD 0.5 OVER NICKEL 2 **INSULATOR** PTFE **GASKET** OTHERS PIECES BRASS :BBR 2

188UE **9739C01** 21/07/1993


FILE PART-NUMBER


EPC 96-07





9739C01 SERIES





1

Slide onto the cable the ferrule Strip the cable .

|--|

5	Stripping	а	b	С	d	е
Г	inch	0.177	0.315	0.551	0	0.374
	mm	4.5	8	14		9.5


2

Slide on centre contact until it bottoms against cable dielectrique .

Solder or crimp centre contact .

Crimping tool : R282 223 000 (Hex. :.068) or R282 293 000 (M22520/5-01)

+ dies R282 235 011 (M22520/5-11) .




3

Fan the braid .

Slide cable into the body until bottoms against insulator .

Slide ferrule over the braid .


(In direction F)



(4)

Crimp the ferrule with crimping tool R 282 223 000 (Hex. : .213) or crimping tool R282 293 000 (M22520/5-01) + dies R282 235 011 (M22520/5-11)

Cut the excess of braid .



Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Radiall:

R161282000