Industrial Routers LAN ROUTER

XR5i v2F Series

B+B SMARTWORX

Powered by

AD\ANTECH



The XR5i v2F industrial router secures connections between two local networks (LAN) via two Ethernet interfaces 10/100. The XR5i v2F can also convert serial RS232, RS485, M-BUS, I/O to IP local area network (LAN Ethernet 10/100). WiFi models are available.

The XR5i v2F Industrial router will also connect two devices with different serial interfaces (RS232, RS485, M-Bus, I/O, etc.) to the local network. In this configuration, the communication device has an Ethernet 10/100 port and two serial interfaces which user definable. A third option uses combination of two previous versions, when the industrial XR5i v2F router equipped with two Ethernet interfaces 10/100 and one optional serial interface. Standard on the XR5i v2F Industrial Router is one Ethernet 10/100 port, one USB A (host) port, I/O port and two optional interfaces. Users can select a second Ethernet port, 10/100, serial interface RS232/RS485/RS422/MBUS or other Inputs/Outputs (I/O). Industrial XR5i v2F router can be ordered with either a plastic or metal housing.

Configuration is password protected, via web interface. The router supports creation of VPN tunnels using IPsec, OpenVPN and L2TP to ensure safe communication. Web interface provides detail statistics about router activities.

SELECTED APPLICATIONS

Transportation and security IT and communication Self-service terminals Energy and power industry Metrology, alarm and warning systems

PRODUCT FEATURES

- Modular design to fit application requirements
- Provided secure connection between two networks
- Provides USB, Serial and I/O connectivity
- SNMP protocol for remote management
- VPN support

ORDERING INFORMATION

Note: Check with your local distributor for availability and options. Contact Advantech B+B SmartWorx distributors.

Europe, Middle East, Africa, Asia, South America, Latin America.

BB-XR2F00XXXX

| 1 00 7 7 7 | ~ | |
|------------|---------------------------------------------------------------------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| | Accessories 0 1 2 3 4 | No Accessories Accessories with EU power supply Accessories with UK power supply Accessories with Australia power supply Accessories with US power supply |
| | Enclosure 1 2 | Plastic enclosure Metal enclosure |
| | PORT2 (Full version only) 0 1 2 3 4 5 6 7 8 | No expansion port ETH RS232 RS485 RS422 MBUS CNT (4× Bl, 2×, 1×B0) - I/O port WiFi WMBUS (Wireless M-BUS) |
| | PORT1 0 1 2 3 4 5 6 9 | No expansion port ETH RS232 RS485 RS422 MBUS CNT (4× Bl, 2×, 1×B0) - I/O port Switch |

R-SEENET™

Router Management Software consisting of two parts:

- **R-SeeNet Server** application can be programmed to automatically send SNMP queries (Simple Network Management Protocol) to each router defined in the network. The application retrieves status information from the routers and records it in the SQL database.
- **R-SeeNet PHP** is a web-based application that accesses the SQL database and provides the network administrator detailed information on individual routers and network health.

SMARTWORX HUB[™]

- **SmartWorx HUB** takes management of your devices to new levels of flexibility and efficiency. Giving you a complete view of your installed device population, SmartWorx Hub delivers invaluable configuration, diagnostic and management facilities directly to your desktop, wherever you are.
- Manage a single device or your entire device population at the same time. Whether you need to modify configuration parameters, download or upgrade installed firmware and applications or view detailed information regarding network statistics, you can do it all from any location.

Industrial Routers LAN ROUTER

XR5i v2F Series

SPECIFICATIONS

| 0. 20. 10. 11 | | | | | |
|-------------------------------|--------------------------------------------------------------------------------------------------------------|--|--|--|--|
| FIXED INTERFACES | | | | | |
| 1× Ethernet | 10/100 Mbits, independent or bridged | | | | |
| 1× I/0 | Binary input/output | | | | |
| 1× USB | USB 2.0 Host, Type A | | | | |
| OPTIONAL INTERFACES | | | | | |
| 1× PORT 1 | Ethernet (10/100Mbps), RS232, RS422/485, M-Bus I/O Input/Output, Ethernet Switch (with PORT 2) | | | | |
| 1× PORT 2 | RS232, RS422/485, M-Bus, WM-Bus, SDH, WiFi Ethernet Switch (with PORT 1) | | | | |
| POWER | | | | | |
| Source | 9 - 36 VDC | | | | |
| Consumption | ldle - 1.6 W WiFi Com. to 1.9 W Full Com. to 2.5 W | | | | |
| MECHANICAL | | | | | |
| Dimension Plastic version | 51 x 87 x 116mm | | | | |
| Dimension Metallic version | 42 x 87 x 113mm | | | | |
| Protection | IP30 | | | | |
| Weight Plastic version | 150 g | | | | |
| Weight Metallic version | 280 g | | | | |
| ENVIRONMENTAL | | | | | |
| Operating Temperature | -40 to +75°C | | | | |
| Storage Temperature | -40° to +85°C | | | | |
| Humidity | Operating - 0 to 95% relative humidity non condensing Storage - 0 to 95% relative humidity non condensing | | | | |
| I/O PORT | | | | | |
| Binary input Binary output | Reed contact with trigger level 1.3 up to 1.4 V 100 mA/ max. 30 V | | | | |

| CPU & MEMORY | | | | |
|--------------|--------------------------------------------|--|--|--|
| CPU | 32b ARM microprocessor, 0.25 DMIPS per MHz | | | |
| Flash memory | 16 MB DDR SDRAM | | | |
| RAM | 64 MB | | | |
| M-RAM | 128 kB | | | |

NETWORKING DHCP – automatic IP addressing in LAN network NAT/PAT - IP address and ports translation between inside/outside network VRRP - virtual backup router function DynDNS client - access to the router with a dynamic IP address Dial-in - the ability to communicate over dial CSD call PPPoE Bridge - PPP frames encapsulation inside ETH frames VPN TUNNELING IPsec, OpenVPN, L2TP - secure encrypted tunnels CONFIGURATION AND DIAGNOSTIC HTTP server - configuration via web server Telnet - configuration and access to the file system SNMP - router diagnostics, communication with I/O and M-Bus Remote router group configuration change, switching among configuration profiles SSH - encrypted configuration and access to the file system STANDARDS/REGULATION ETSI EN 301 489-1 V2.1.1, ETSI EN 301 489-17 V3.1.1, ETSI EMC EN 301 489-3 V2.1.1 EN 60950-1:2006 + A11:2009 + A1:2010 + A12:2011 + A2:2013 Safety + AC:2011 WIFI *

SOFTWARE FEATURES

Linux based, possibility to program your own application NTP client, NTP Server – time synchronization

M-RAM memory inside - router statistic's saving into memory

| Antenna connector | R-SMA – 50 Ohms | | |
|----------------------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|--|--|
| Supported WiFi band | 2.4 GHz | | |
| Standards | 802.11b, 802.11g, 802.11n | | |
| 2.4 GHz supported channels | 1, 2, 3, 4, 5, 6, 7, 8, 9, 10, 11, 12, 13 | | |
| RX Sensitivity | 11b, 11 Mbps: typ85 dBm 11g, 54 Mbps: typ70 dBm (HT20) 11n, MSC7: typ66 dBm (HT40) 11n, MSC7: typ62 dBm | | |
| TX Output Power | 11b, 11 Mbps: min. 18, typ. 19, max. 20 dBm 11g, 54 Mbps: min. 14.5, typ. 16, max. 17.5 dBm 802.11n (HT20): min. 13.5, typ. 15, max. 16.5 dBm 802.11n (HT40): min. 13.5, typ. 15, max. 16.5 dBm | | |
| Type of device | Access point, station | | |

| ACCESSORIES | | Included in Package | INCLUDED IN Set Package | SOLD SEPARATELY |
|-------------------|-------------------------------------------------------------|------------------------|----------------------------|--------------------|
| ORDER CODE | DESCRIPTION | | | |
| BB-SBD40 | Metal DIN holder for Metal versions of routers v2 | ~ | ~ | ~ |
| BB-CPD2-G | Plastic DIN holder for Plastic versions of routers v2 | ~ | ~ | ~ |
| BB-AW-A24G-M5SRP | Antenna WiFi stick 5dB, SMA-RP connector | | ~ | ~ |
| BB-KD-ETH | Ethernet cross cable 1.5m | | 2× | ~ |
| BB-CON-WR2 | 2-pin Terminal block for Power Supply | ~ | | ~ |
| BB-CON-WR3 | 3-pin terminal block for I/O | ~ | ~ | ~ |
| BB-RPS-v2-WR2-EU | Power supply with WR connector (2 pins) - 12V/1A - EU plug | | ~ | ~ |
| BB-RPS-v2-WR2-US | Power supply with WR connector (2 pins) - 12V/1A - US plug | | ~ | ~ |
| BB-RPS-v2-WR2-UK | Power supply with WR connector (2 pins) - 12V/1A - UK plug | | ~ | ~ |
| BB-RPS-v2-WR2-AUS | Power supply with WR connector (2 pins) - 12V/1A - AUS plug | | ~ | ~ |
| BB-KN-WR2-3 | Power supply cable 2-wire, 3m | | v | ~ |
| Quick Start Guide | | ~ | ~ | |



B+B SMARTWORX orders@advantech-bb.com

orders@advantech-bb.com / Corporate Headquarters: 707 Dayton Road, PO Box 1040 Ottawa, IL 61350 USA 815-433-5100 Fax 433-5104 support@advantech-bb.com / European Office: Westlink Commercial Park, Oranmore Co. Galway Ireland +353 91 792444 Fax +353 91 792444

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Advantech: BB-XR2F001011