# **In-Series Adapters**

# **TNC Types**

### TNC Male Plug to TNC Female Jack

### **Model Number**


### **ADT-2596-MF-TNC-02**

### **SPECIFICATIONS**

Frequency: DC - 18.0 GHz VSWR: 1.05 @ DC - 4.0 GHz 1.10 @ 4.0 - 8.0 GHz 1.15 @ 8.0 - 18.0 GHz

Impedance: 50 Ohms

Finish: Passivated Stainless Steel





### TNC Female Jack to TNC Female Jack

### **Model Number**


### **ADT-2598-FF-TNC-02**

### **SPECIFICATIONS**

Frequency: DC - 18.0 GHz VSWR: 1.05 @ DC - 4.0 GHz 1.10 @ 4.0 - 8.0 GHz 1.15 @ 8.0 - 18.0 GHz

Impedance: 50 Ohms

Finish: Passivated Stainless Steel





### TNC Male Plug to TNC Male Plug

### **Model Number**


### **ADT-2597-MM-TNC-02**

### **SPECIFICATIONS**

Frequency: DC - 18.0 GHz VSWR: 1.05 @ DC - 4.0 GHz 1.10 @ 4.0 - 8.0 GHz 1.15 @ 8.0 - 18.0 GHz

**Impedance:** 50 Ohms

Finish: Passivated Stainless Steel





### TNC Female Jack to TNC Female Jack - Flange Mount

### **Model Number**


### **ADT-2826-FF-TNC-02**


### **SPECIFICATIONS**

Frequency: DC - 18.0 GHz VSWR: 1.05 @ DC - 4.0 GHz 1.10 @ 4.0 - 8.0 GHz

1.15 @ 8.0 - 18.0 GHz Impedance: 50 Ohms

Finish: Passivated Stainless Steel









## **Mouser Electronics**

**Authorized Distributor** 

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Cinch Connectivity Solutions:

ADT-2597-MM-TNC-02