



SmartOnline 3000VA 2700W 120V Double-Conversion Sine Wave UPS - 7 Outlets, Extended Run, Network Card Option, LCD, USB, DB9, 2U Rack/Tower, TAA

MODEL NUMBER: SU3000RTXLCD2UTAA











Provides battery backup, power protection and sine wave output for mission-critical IT installations and other network applications requiring TAA compliance.

Features

3kVA 2.7kW 120V Battery Backup Protects Equipment Against Damage, Downtime and Data Loss This on-line double-conversion UPS system maintains perfect output by converting AC input to DC, then reconverting UPS output to fully regulated sine wave AC. Constant on-line operation completely isolates sensitive equipment from every power problem on the AC line. The SmartOnline® SU3000RTXLCD2UTAA provides the highest level of power protection and battery backup for education, healthcare, military, government and other mission-critical IT applications where space is limited, but premium power reliability is essential.

Reliable, Expandable Battery Backup Keeps You Operational Through Power Outages

The field-replaceable, hot-swappable VRLA battery modules allow you to work through short power failures and give you enough time to safely save files and shut down your system in the case of a prolonged blackout. Zero transfer time between on-line and battery modes maintains continuous operation of connected equipment without interruption or rebooting. Extra runtime is available by connecting up to four optional extended battery modules (BP72RT2UTAA, sold separately).

Optional Network Management Card Allows 24/7 Remote Access

The WEBCARDLXE network interface (sold separately) enables full remote configuration and management, including load shedding, reboots of connected equipment and safe shutdowns. The IP-based Auto Probe feature ensures continuous network uptime by communicating with other network devices, detecting lost connectivity and automatically rebooting IT equipment. Optional EnviroSense2 modules (E2MT, E2MTDO and E2MTHDI, all sold separately) provide a variety of environmental monitoring and control options. *Note: The SU3000RTXLCD2UTAA is not compatible with WEBCARDLX*.

NEMA Outlets Protect Your Connected Components

One L5-30R and six 5-20R managed outlets provide connected equipment with pure sine wave AC output and allow you to manage power consumption down to the outlet group level. Power provided by these outlets is filtered to protect connected equipment against damaging surges and line noise. Four 5-20R outlets are split evenly into two switchable load banks that let you reboot select components or shed non-critical loads in order to extend runtime for critical loads during an outage.

Premium Protection from EMI/RFI Line Noise Helps Your Equipment Perform Better

Highlights

- Offers network-grade protection against power failures and voltage fluctuations
- Zero transfer time between online and battery modes for uninterrupted operation
- Keeps equipment running during outages to allow time for file saves and safe shutdown
- Optional WEBCARDLXE network interface enables 24/7 complete and remote control
- Compliant with the Federal Trade Agreements Act (TAA) for GSA Schedule purchases

Package Includes

- 3000VA 2700W 120V Double-Conversion UPS
- USB cable
- DB9 cable
- Rack-mounting hardware
- Tower support stands
- Safety instructions
- Quick Start Guide





This UPS system filters out disruptive electromagnetic and radio frequency interference that can inflict hardware damage or data loss. This EMI/RFI filtering also helps your connected components perform better and last longer.

Intuitive Front-Panel Interface for Convenient UPS Operation and Monitoring

The two-line front-panel LCD features 10 selectable screens that allow quick access to a wide range of detailed UPS and site power information. LEDs show UPS status: a green light means utility power is on, an orange light means the UPS is in battery or bypass mode and a red light indicates an active alarm or fault. The control panel rotates to accommodate both rack-mount and tower configurations.

Advanced Communications Ports Allow for Automatic Saves and Shutdowns

RS-232 and USB ports connect to a device for a variety of communication options (cables are included). A dry-contact relay port can be programmed through the LCD to provide reliable communications to automation and industrial components. The RPO/ROO port permits emergency shutdown or remote restart of all connected equipment.

Automatically Turns Back On After Power Is Restored

Battery-independent restart ensures automatic UPS power-up without user interaction after lengthy power outages, even after a complete battery discharge. This can save you a costly site visit.

Versatile Installation Options

Hardware is included for mounting the UPS system in 2U of space in an EIA-standard 19-inch 4-post rack. You can also adapt it for 2-post rack mounting with the optional RK2PC (sold separately) or tower installation using the included support stands. The eight-foot power cord with NEMA 5-30P plug connects to any compatible AC outlet.

TAA-Compliant for GSA Schedule Purchases

The SU3000RTXLCD2UTAA is compliant with the Federal Trade Agreements Act (TAA), which makes it eligible for GSA (General Services Administration) Schedule and other federal procurement contracts.

Specifications

•		
OVERVIEW		
UPC Code	786689875787	
UPS Type	On-Line	
INPUT		
Input Phase	Single-Phase	
Rated input current (Maximum Load)	24A	
Nominal Input Voltage(s) Supported	100V AC; 110V AC; 120V AC	
Nominal Input Voltage Description	120V factory default	
UPS Input Connection Type	L5-30P	
UPS Input Cord Length (ft.)	8	
UPS Input Cord Length (m)	2.4	
Recommended Electrical Service	120V 30A	
Maximum Input Amps	24	
Input Plug Type	NEMA L5-30P	
Input Cord Length (ft.)	8	





Input Current 24A Power Factor (Input) 0.99 OUTPUT Output Capacity (VA) 3000 Output Capacity (VA) 3 Output Capacity (VA) 2.7 Output Capacity (VAY) 2.7 Power Factor 0.9 Crest Factor 3:1 1.20 / factory-default nominal voltage Crest Factor 3:1 1.20 / factory-default nominal voltage Frequency Compatibility 0.9 / 50 / 50 / 12 Frequency Compatibility 0.9 / 10 / 10 / 10 / 10 / 10 / 10 / 10 / 1	Input Cord Length (m)	2.44
Output Capacity (VA) 3000 Output Capacity (Watts) 2700 Output Capacity (Watts) 2700 Output Capacity (Watts) 2700 Output Capacity (Watts) 2.7 Power Factor 0.9 Crest Factor 3.1 Nominal Voltage Details 120V factory-default nominal voltage Frequency Compatibility 50 / 60 Hz Frequency Compatibility 50 / 60 Hz Frequency Compatibility Details Online Mode: Sync with line ±5% of nominal line frequency (outside this range: ±0.5% of auto-selected nominal frequency): Ballery Mode: ±0.5% of auto-selected nominal frequency (outside this range: ±0.5% of auto-selected nominal frequency): He Mode: 4 / 1% Output Voltage Regulation (Line Mode: Sync with line ±5% of nominal line frequency (outside this range: ±0.5% of auto-selected nominal frequency): He Mode: 4 / 1% Output Voltage Regulation (Line Mode: Sync with line ±5% of auto-selected nominal frequency (outside this range: ±0.5% of auto-selected nominal frequency): He Mode: 4 / 1% Output Voltage Regulation (Line Mode: 4 / 1% Output Voltage Regulation (Baltery Mode: 4 / 2% Output Voltage Regulation (Baltery Mode: 4 / 2% Output Active Mode: 4 / 2% Output Active Mode: 4 / 2% Output Active Mode: 4 / 2 / 2 / 2 / 2 / 2 / 2 / 2 / 2 / 2 /	Input Current	24A
Output Capacity (VA) 30000 Output Capacity (WA) 3 Output Capacity (WA) 27 Output Capacity (WA) 2.7 Output Capacity (WA) 2.7 Power Factor 0.9 Output Capacity (WW) 2.7 Power Factor 3.1 Nominal Voltage Details 120V factory-default nominal voltage Frequency Compatibility 50 / 60 Hz Frequency Compatibility Details Office Mode: Sync with line 5% of nominal line frequency (outside this range: 20.5% of auto-selected nominal frequency Compatibility Details Office Mode: Sync with line 5% of nominal line frequency (outside this range: 20.5% of auto-selected nominal frequency Compatibility Details Office Mode: Sync with line 5% of nominal line frequency (outside this range: 20.5% of auto-selected nominal frequency Compatibility Details Office Mode: Sync with line 5% of nominal line frequency (outside this range: 20.5% of auto-selected nominal frequency Compatibility Details Office Mode: 20.5% of auto-selected nominal frequency (outside this range: 20.5% of auto-selected nominal frequency Compatibility Office Mode: 20.5% of auto-selected nominal frequency Output Voltage Regulation (Line Mode) 4/- 1% Output Voltage Regulation (Line Mode) 4/- 1% Output AC Waveform (AC Mode) Pura Sine wave Output AC Waveform (AC Mode) Pura Sine wave Output AC Waveform (AC Mode) Pura Sine wave Output AC Waveform (Battery Mode: 2700 Output Voltage(s) 100V; 110V; 115V; 120V; 127V Output Receptacles (6) 5-20R: (1) L5-30R Individually Controllable Load Banks Ves BATTERY BATTERY BATTERY BATTERY Valve Regulated Lead Acid (VRLA) Runtime Half Load (min.) 1.3.9 min. (1350W) Expandable Runtime Description Acid Mode: 60-select-Tirpp-Lite-series-UPS-2U-TAA-8P72RTZUTAA-Sa-P52PZTZUTAA-	Power Factor (Input)	0.99
Output Capacity (WAts) 3 Output Capacity (Watts) 2700 Output Capacity (WW) 2.7 Power Factor 0.9 Crest Factor 3.1 Nominal Voltage Details 120V factory-default nominal voltage Frequency Compatibility 50 / 60 Hz Frequency Compatibility 50 / 60 Hz Frequency Compatibility Details Online Mode: Sync with line a 5% of nominal line frequency (outside this range: x0.5% of auto-selected nominal frequency). Battery Mode: x0.5% of auto-selected nominal frequency Output Voltage Regulation (Line Mode) x/- 1% Output Voltage Regulation (Battery Mode: x0.5% of auto-selected nominal frequency) x/- 1% Output Voltage Regulation (Battery Mode) x/- 2% Output Voltage Regulation (Battery Mode) x/- 2% Output (Watts) 2700 Output (Watts) 2700 Output (Watts) 100V: 110V: 115V: 120V: 127V Supported (6) 5-20R: (1) L5-30R Individually Controllable Load Banks Yes Battery Type Valve Regulated Lead Acid (VRLA) Runtime Full Load (min.) 4.8 min. (2700W) Runtime Full Load (m	ОИТРИТ	
Output Capacity (Watts) 2700 Output Capacity (kW) 2.7 Power Factor 0.8 Crest Factor 3:1 Nominal Voltage Details 1207 factory-default nominal voltage Frequency Compatibility 50 / 60 Hz. Frequency Compatibility Details Online Mode: Sync with line ±5% of nominal line frequency (outside this range: ±0.5% of auto-selected nominal frequency.) Output Voltage Regulation (Line Mode: ±0.5% of auto-selected nominal frequency.) 4-1% Output Voltage Regulation (Battery Mode: ±0.5% of auto-selected nominal frequency.) 4-1% Output Voltage Regulation (Battery Mode: ±0.5% of auto-selected nominal frequency.) 4-1% Output Voltage Regulation (Battery Mode: ±0.5% of auto-selected nominal frequency.) 4-1% Output Voltage Regulation (Battery Mode: ±0.5% of auto-selected nominal frequency.) 4-1% Output AC Waveform (Battery Mode: ±0.5% of auto-selected nominal frequency.) 4-2% Output (Watts) 2700 Output (Watts) 2700 Output AC Waveform (Battery Mode) 100V: 110V: 115V: 120V: 127V Output AC Waveform (Battery Mode) (6) 5-20R: (1) L5-30R Individually Controllable Load Banks 7ex Patter	Output Capacity (VA)	3000
Output Capacity (kW) 2.7 Power Factor 0.9 Crest Factor 3:1 Nominal Voltage Details 120V factory-default nominal voltage Frequency Compatibility 5 of 56 Hz Frequency Compatibility Details Online Mode: Sync with line ±5% of nominal line frequency (outside this range: ±0.5% of auto-selected nominal frequency). Battery Mode: ±0.5% of auto-selected nominal frequency (outside this range: ±0.5% of auto-selected nominal frequency). Battery Mode: ±0.5% of auto-selected nominal frequency (outside this range: ±0.5% of auto-selected nominal frequency). Battery Mode: ±0.5% of auto-selected nominal frequency (outside this range: ±0.5% of auto-selected nominal frequency). Battery Mode: ±0.5% of auto-selected nominal frequency (outside this range: ±0.5% of auto-selected nominal frequency). Battery Mode: ±0.5% of auto-selected nominal frequency (outside this range: ±0.	Output Capacity (kVA)	3
Power Factor 0.9 Crest Factor 3:1 Nominal Voltage Details 120V factory-default nominal voltage Frequency Compatibility 50 / 60 Hz Frequency Compatibility 50 / 60 Hz Frequency Compatibility Details 70 / 60 Hz Frequency Compatibility Patients 70 / 60 Hz Frequency Compatibility 70 / 70 Hz Fre	Output Capacity (Watts)	2700
Crest Factor 3:1 Nominal Voltage Details 120V factory-default nominal voltage Frequency Compatibility 50 / 60 Hz Frequency Compatibility Details Cnline Mode: Sync with line ±5% of nominal line frequency (outside this range: ±0.5% of auto-selected nominal frequency). Battery Mode: ±0.5% of auto-selected nominal frequency Output Voltage Regulation (Line Mode) √-1% Output Voltage Regulation (Battery Mode) √-2% Load Management Receptacles Two switchable two-outlet load banks Output Voltage Regulation (Battery Mode) Pure Sine wave Output (Watts) 2700 Output (Watts) 2700 Output AC Waveform (Battery Mode) Pure Sine wave Nominal Output Voltage(s) 100V; 110V; 115V; 120V; 127V Output Receptacles (6) 5-20R; (1) L5-30R Individually Controllable Load Banks Yes BATTERY Valve Regulated Lead Acid (VRLA) Runtime Full Load (min.) 4.8 min. (2700W) Runtime Full Load (min.) 13.9 min. (1350W) Expandable Runtime Yes Expandable Runtime Yes Expandable Runtime Ae sextended battery modules (EBM). Part number A	Output Capacity (kW)	2.7
Nominal Voltage Details 120V factory-default nominal voltage Frequency Compatibility 50 / 60 Hz Frequency Compatibility Details Online Mode: Sync with line ±5% of nominal line frequency (outside this range: ±0.5% of auto-selected nominal frequency). Battery Mode: ±0.5% of auto-selected nominal frequency Output Voltage Regulation (Line Mode)	Power Factor	0.9
Frequency Compatibility 50 / 60 Hz Frequency Compatibility Details Online Mode: Sync with line ±5% of nominal line frequency (outside this range: ±0.5% of auto-selected nominal frequency). Battery Mode: ±0.5% of auto-selected nominal frequency Output Voltage Regulation (Line Mode: ±0.5% of auto-selected nominal frequency #/- 1% Output Voltage Regulation (Battery Mode)	Crest Factor	3:1
Frequency Compatibility Details Online Mode: Sync with line ±5% of nominal line frequency (outside this range: ±0.5% of auto-selected nominal frequency) Output Voltage Regulation (Line Mode) 4/- 1% Output Voltage Regulation (Battery Mode: ±0.5% of auto-selected nominal frequency) Output Voltage Regulation (Battery Mode) 4/- 1% Output Voltage Regulation (Battery Mode) V/- 2% Load Management Receptacles Two switchable two-outlet load banks Output AC Waveform (AC Mode) Pure Sine wave Output (Watts) 2700 Output AC Waveform (Battery Mode) Pure Sine wave Nominal Output Voltage(s) Supported 100V; 110V; 115V; 120V; 127V Output Receptacles (6) 5-20R; (1) L5-30R Individually Controllable Load Banks Pes BATTERY Battery Type Valve Regulated Lead Acid (VRLA) Runtime Full Load (min.) 4.8 min. (2700W) Runtime Half Load (min.) 13.9 min. (1350W) Expandable Runtime Expandable Runtime Description Add up to 4 extended battery modules (EBM). Part number & nbsp; a class="productLink" here!-//iripplite.eaton.com/External-72V-Battery-Module-for-select-Tripp-Lite-series-UPS-2U-TAA-ABP72RT2UTAA-/aBP72RT2UTAA-/aB- External Battery Pack Compatibility Anbsp;-a class="productLink" here!-//iripplite.eaton.com/External-72V-Battery-Module-for-select-Tripp-Lite-series-UPS-2U-TAA-BP72RT2UTAA-/aB-	Nominal Voltage Details	120V factory-default nominal voltage
Output Voltage Regulation (Line Mode) +/- 1% Output Voltage Regulation (Battery Mode) +/- 1% Output Voltage Regulation (Battery Mode) +/- 2% Load Management Receptacles Two switchable two-outlet load banks Output AC Waveform (AC Mode) Pure Sine wave Output (Watts) 2700 Output AC Waveform (Battery Mode) Pure Sine wave Nominal Output Voltage(s) 100V; 110V; 115V; 120V; 127V Output Receptacles (6) 5-20R; (1) L5-30R Individually Controllable Load Banks Yes BATTERY Battery Type Valve Regulated Lead Acid (VRLA) Runtime Full Load (min.) 4.8 min. (2700W) Runtime Full Load (min.) 13.9 min. (1350W) Expandable Runtime Description Add up to 4 extended battery modules (EBM). Part number . <a <a="" ap- ="" ap- <="" battery="" class="productLink" compatibility="" external="" href="//tripplite.eaton.com/External-72V-Battery-Module-for-select-Tripp-Lite-series-UPS-2U-TAA-BP72RT2UTAA" pack="" productlink"="" td=""><td>Output (Watts)</td><td>2700</td>	Output (Watts)	2700
Output Receptacles (6) 5-20R; (1) L5-30R Individually Controllable Load Banks Yes BATTERY Battery Type Valve Regulated Lead Acid (VRLA) Runtime Full Load (min.) 4.8 min. (2700W) Runtime Half Load (min.) 13.9 min. (1350W) Expandable Runtime Yes Expandable Runtime Description Add up to 4 extended battery modules (EBM). Part number BP72RT2UTAA-BP72RT2UTAA-BP72RT2UTAA BP72RT2UTAA BP72RT2UTAA External Battery Pack Compatibility BP72RT2UTAA	Output Receptacles	(6) 5-20R; (1) L5-30R
Battery Type Valve Regulated Lead Acid (VRLA) Runtime Full Load (min.) 4.8 min. (2700W) Runtime Half Load (min.) 13.9 min. (1350W) Expandable Runtime Yes Expandable Runtime Description Add up to 4 extended battery modules (EBM). Part number BP72RT2UTAA External Battery Pack Compatibility BP72RT2UTAA	Individually Controllable Load Banks	Yes
Runtime Full Load (min.) Runtime Half Load (min.) 13.9 min. (1350W) Expandable Runtime Yes Expandable Runtime Description Add up to 4 extended battery modules (EBM). Part number BP72RT2UTAA > BP72RT2UTAA . External Battery Pack Compatibility BP72RT2UTAA	Battery Type	Valve Regulated Lead Acid (VRLA)
Expandable Runtime Pescription Add up to 4 extended battery modules (EBM). Part number BP72RT2UTAA > External Battery Pack Compatibility BP72RT2UTAA	Runtime Full Load (min.)	4.8 min. (2700W)
Expandable Runtime Description Add up to 4 extended battery modules (EBM). Part number BP72RT2UTAA External Battery Pack Compatibility BP72RT2UTAA	Runtime Half Load (min.)	13.9 min. (1350W)
TAA~BP72RT2UTAA">BP72RT2UTAA . External Battery Pack Compatibility BP72RT2UTAA	Expandable Runtime	Yes
UPS-2U-TAA~BP72RT2UTAA">BP72RT2UTAA	Expandable Runtime Description	Add up to 4 extended battery modules (EBM). Part number BP72RT2UTAA .
DC System Voltage (VDC) 72	External Battery Pack Compatibility	BP72RT2UTAA
	DC System Voltage (VDC)	72





Battery Recharge Rate (Included Batteries)	3 hours recharge to 90%		
Battery Access	Battery access door		
Internal UPS Replacement Battery Cartridge	744-A3122		
Battery Replacement Description	Hot-swappable, user replaceable batteries		
Capacity (Ah)	9		
VOLTAGE REGULATION			
Voltage Regulation Description	Online, double-conversion power conditioning		
USER INTERFACE, ALERTS & CON	USER INTERFACE, ALERTS & CONTROLS		
Front Panel LCD Display	Front panel LCD information and configuration screen offers detailed UPS and site power status and operating data, plus configuration of voltage, frequency, operating mode, alarm function and a variety of additional options		
Switches	RPO / ROO		
Alarm Cancel Operation	Power-fail alarm can be temporarily silenced using alarm-cancel switch; silent mode alarm configuration option available		
Audible Alarm	Audible alarm indicates UPS startup, power-failure, low-battery, overload, UPS fault and remote shutdown conditions		
LED Indicators	4 status-indicating LEDs		
SURGE / NOISE SUPPRESSION			
EMI / RFI AC Noise Suppression	Yes		
AC Suppression Joule Rating	190		
AC Suppression Response Time	Instantaneous		
PHYSICAL			
Primary Form Factor	Rackmount		
Rack Height	2U		
Cooling Method	Fan		
Installation Form Factors Supported with Included Accessories	4 post 19 inch rackmount		
Installation Form Factors Supported with Optional Accessories	2 post rackmount (RK2PC)		
Minimum Required Rack Depth (cm)	68.07		
Minimum Required Rack Depth (inches)	26.8		
Optional Mounting Accessory Notes	2 post rail kit available, part # RK2PC		
Shipping Dimensions (hwd / in.)	9.45 x 22.84 x 30.71		
Shipping Weight (lbs.)	77.83		
Shipping Weight (kg)	35.30		





The state of the s	Metal
Unit Dimensions (hwd / in)	
Cint Billionic (ilwa / ilii)	3.410 x 17.330 x 23.820
Unit Weight (lbs.) 6	63.06
Unit Weight (kg) 2	28.60
Mounting Details	Includes 4 post rackmount installation accessories
ENVIRONMENTAL	
Operating Temperature Range 3	32° to 104°F (0° to 40°C)
Storage Temperature Range V	With battery: 32° to 104°F (0° to 40°C); without battery: -13° to 131°F (-25° to 55°C)
Relative Humidity 0	0-96% non-condensing
AC Mode Efficiency Rating (100% Load)	91.6
AC Economy Mode Efficiency Rating (100% Load)	97.2
Online Mode Heat Dissipation (BTU/Hr) @ Full Load	844
Battery Mode Heat Dissipation (BTU/Hr) @ Full Load	1462
Operating Elevation 0	0-10000 ft. (0-3000 m)
Audible Noise 4	47 dB at 1m
COMMUNICATIONS	
Network Management Cards 8	<a class="productLink" href="//tripplite.eaton.com/Network-Card-Eaton-Tripp-Lite-Series-UPS-
Systems~WEBCARDLXE">WEBCARDLXE
Network Monitoring Port Description V	WEBCARDLXE Supports detailed monitoring of UPS and site power conditions; DB9 port supports RS232 and contact closure communications; not compatible with WEBCARDLX
PowerAlert Software F	For local monitoring via the UPS's built-in communication ports, download PowerAlert software at https://tripplite.eaton.com/products/power-alert
Communications Cable	USB and RS232 cable included
WatchDog Compatibility S	Supports Watchdog application, OS and hard-reboot restart options for remote applications
Network Management Card Description	Network management card optional
Communications Interface (**	(1) Contact closure; (1) RS-232; (1) Slot for SNMP/Web interface; (1) USB
Emergency Power Off (EPO)/Remote On-Off (ROO)	Yes
LINE / BATTERY TRANSFER	
Transfer Time 0	0ms
FEATURES & SPECIFICATIONS	
Cold Start (Startup in Battery Mode During a Power Failure)	Cold-start operation supported
High Availability UPS Features E	Expandable battery backup; Hot swappable batteries; On-Line/Double-Conversion; Remote management; Sine wave output; Surge/noise protection; Zero transfer time





Green Energy-Saving Features	High efficiency economy mode operation; Individually controllable load banks
APPLICATIONS	
UPS Applications	Mission Critical Applications
STANDARDS & COMPLIANCE	
Product Certifications	UL 1778; cTUVus
Product Compliance	CE (Europe); FCC (USA); REACH; RoHS; Trade Agreements Act (TAA)
WARRANTY & SUPPORT	
Product Warranty Period (Worldwide)	2-year limited warranty
Connected Equipment Insurance (U.S., Canada & Puerto Rico)	\$250,000 Ultimate Lifetime Insurance
Extended Service Plans	ADVANCED DEPOT EXCHANGEService Part Number: TL9SW5Y-3000UCParts, electronics and UPS batteries coverageNext business day shippingTechnical support5-year onsite plan: TLWFLN75XX-6009UCOnsite parts and labor coverage for 5 yearsParts, electronics and UPS batteries coverage24x7 onsite labor coverage, next-day responseNext-day shippingTechnical support

1000 Eaton Boulevard Cleveland, OH 44122 United States https://tripplite.eaton.com © 2025 Eaton. All Rights Reserved.

Eaton is a registered trademark. All other trademarks are the property of their respective owners.