## **SIEMENS**

## **Data sheet**

## 3RA2125-4BA26-0BB4

	FUSELESS MOTOR STARTER DIRECT START 600V AC SZ S0 14-20A 24V DC SCREW CONNECTION FOR SCREW MOUNTING OR 35 MM RAIL-MOUNTING TYPE OF COORDINATION 2 IQ = 50 KA ALSO FULFILLS TYPE OF COORDINATION 1 1NO+1NC (MSP) 1NO+1NC (CONTACTOR)
product brand name	SIRIUS
product designation	non-fused motor starter 3RA2
design of the product	direct starter
manufacturer's article number	
of the supplied contactor	3RT2026-1BB40
of the supplied circuit-breakers	3RV2021-4BA15
of the supplied link module	3RA2921-1BA00
General technical data	
size of the circuit-breaker	S0
size of load feeder	S0
product extension auxiliary switch	Yes
insulation voltage with degree of pollution 3 at AC rated value	690 V
degree of pollution	3
surge voltage resistance rated value	6 kV
shock resistance according to IEC 60068-2-27	6g / 11 ms
mechanical service life (operating cycles) of contactor typical	10 000 000
type of coordination	2
Weight	0.95 kg
Ambient conditions	0.00 Ng
ambient temperature	
during operation	-20 +60 °C
during operation     during storage	-50 +80 °C
during storage     during transport	-55 +80 °C
	-55 100 O
Main circuit	3
number of poles for main current circuit	3 electromechanical
	3 electromechanical 14 20 A
number of poles for main current circuit design of the switching contact adjustable current response value current of the current-	electromechanical
number of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release	electromechanical
number of poles for main current circuit  design of the switching contact  adjustable current response value current of the current- dependent overload release  operating voltage	electromechanical 14 20 A
number of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value	electromechanical 14 20 A 690 V
number of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum	electromechanical 14 20 A 690 V 690 V
number of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value	electromechanical 14 20 A 690 V 690 V 50 60 Hz
number of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value	electromechanical 14 20 A 690 V 690 V 50 60 Hz
number of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3	electromechanical 14 20 A 690 V 690 V 50 60 Hz 15.5 A
number of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value	electromechanical 14 20 A  690 V 690 V 50 60 Hz 15.5 A  7 500 W
number of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage	electromechanical 14 20 A  690 V 690 V 50 60 Hz 15.5 A  7 500 W
number of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage	electromechanical 14 20 A  690 V 690 V 50 60 Hz 15.5 A  7 500 W 11 000 W
number of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage	electromechanical 14 20 A  690 V 690 V 50 60 Hz 15.5 A  7 500 W 11 000 W
number of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage	electromechanical 14 20 A  690 V 690 V 50 60 Hz 15.5 A  7 500 W 11 000 W
number of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage	electromechanical 14 20 A  690 V 690 V 50 60 Hz 15.5 A  7 500 W 11 000 W
number of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage	electromechanical 14 20 A  690 V 690 V 50 60 Hz 15.5 A  7 500 W 11 000 W
number of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3 • at 400 V rated value • at 500 V rated value Control circuit/ Control control supply voltage at DC rated value holding power of magnet coil at DC Auxiliary circuit number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts	electromechanical 14 20 A  690 V 690 V 50 60 Hz 15.5 A  7 500 W 11 000 W  24 V 5.9 W
number of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage	electromechanical 14 20 A  690 V 690 V 50 60 Hz 15.5 A  7 500 W 11 000 W  24 V 5.9 W
number of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage	electromechanical 14 20 A  690 V 690 V 50 60 Hz 15.5 A  7 500 W 11 000 W  24 V 5.9 W  CLASS 10 thermal (bimetallic)
number of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage	electromechanical 14 20 A  690 V 690 V 50 60 Hz 15.5 A  7 500 W 11 000 W  24 V 5.9 W
number of poles for main current circuit  design of the switching contact  adjustable current response value current of the current- dependent overload release  operating voltage  • rated value  • at AC-3 rated value maximum  operating frequency rated value  operating power at AC-3 at 400 V rated value  operating power at AC-3  • at 400 V rated value  • at 500 V rated value  Control circuit/ Control  control supply voltage at DC rated value  holding power of magnet coil at DC  Auxiliary circuit  number of NC contacts for auxiliary contacts  number of NO contacts for auxiliary contacts  Protective and monitoring functions  trip class  design of the overload release  response value current of instantaneous short-circuit trip unit  UL/CSA ratings	electromechanical 14 20 A  690 V 690 V 50 60 Hz 15.5 A  7 500 W 11 000 W  24 V 5.9 W  CLASS 10 thermal (bimetallic)
number of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage	electromechanical 14 20 A  690 V 690 V 50 60 Hz 15.5 A  7 500 W 11 000 W  24 V 5.9 W  CLASS 10 thermal (bimetallic)

• at 600 V rated value	17.8 A			
yielded mechanical performance [hp]				
<ul> <li>for single-phase AC motor</li> </ul>				
<ul> <li>— at 110/120 V rated value</li> </ul>	1.5 hp			
— at 230 V rated value	3 hp			
• for 3-phase AC motor				
— at 200/208 V rated value	5 hp			
— at 220/230 V rated value	5 hp			
— at 460/480 V rated value	10 hp			
— at 575/600 V rated value	15 hp			
Short-circuit protection				
product function short circuit protection	Yes			
design of the short-circuit trip	magnetic			
conditional short-circuit current (Iq)				
<ul> <li>at 400 V according to IEC 60947-4-1 rated value</li> </ul>	153 000 A			
Installation/ mounting/ dimensions				
mounting position	vertical			
fastening method	Snap-mounted to DIN rail or so	crew-mounted with additio	nal push-in lug	
height	193.1 mm			
width	45 mm			
depth	107 mm			
required spacing				
for grounded parts				
— forwards	10 mm			
— backwards	0 mm			
— upwards	30 mm			
— at the side	9 mm			
— downwards	10 mm			
• for live parts				
— forwards	10 mm			
— backwards	0 mm			
— upwards	30 mm			
— downwards	10 mm			
— at the side	9 mm			
Connections/ Terminals				
type of electrical connection for main current circuit	screw-type terminals			
type of connectable conductor cross-sections for main contacts stranded	1 10 mm², 2x (2.5 6 mm²)			
connectable conductor cross-section for main contacts finely stranded with core end processing	1 6 mm²			
Safety related data				
proportion of dangerous failures with high demand rate according to SN 31920	73 %			
B10 value with high demand rate according to SN 31920	1 000 000	1 000 000		
Electrical Safety				
protection class IP on the front according to IEC 60529	IP20			
touch protection on the front according to IEC 60529	finger-safe, for vertical contact	from the front		
Approvals Certificates				
General Product Approval		For use in hazard- ous locations	Test Certificates	











Special Test Certificate

**Test Certificates** 

Maritime application

Type Test Certificates/Test Report











Maritime application

other

Railway

Dangerous goods







Confirmation

Special Test Certificate

**Transport Information** 

**Environment** 

Environmental Confirmations

## Further information

Information on the packaging

https://support.industry.siemens.com/cs/ww/en/view/109813875

Information for data generation and storage

https://support.industry.siemens.com/cs/ww/en/view/109995012

Information- and Downloadcenter (Catalogs, Brochures,...)

https://www.siemens.com/ic10

Industry Mall (Online ordering system)

https://mall.industry.siemens.com/mall/en/en/Catalog/product?mlfb=3RA2125-4BA26-0BB4

Cax online generator

 $\underline{\text{http://support.automation.siemens.com/WW/CAXorder/default.aspx?lang=en\&mlfb=3RA2125-4BA26-0BB4}$ 

Service&Support (Manuals, Certificates, Characteristics, FAQs,...)

https://support.industry.siemens.com/cs/ww/en/ps/3RA2125-4BA26-0BB4

Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, EPLAN macros, ...)

 $\underline{\text{http://www.automation.siemens.com/bilddb/cax\_de.aspx?mlfb=3RA2125-4BA26-0BB4\&lang=ender.pdf}}$ 

Characteristic: Tripping characteristics,  $I^2t$ , Let-through current

https://support.industry.siemens.com/cs/ww/en/ps/3RA2125-4BA26-0BB4/char

Further characteristics (e.g. electrical endurance, switching frequency)

http://www.automation.siemens.com/bilddb/index.aspx?view=Search&mlfb=3RA2125-4BA26-0BB4&objecttype=14&gridview=view1

last modified:	12/15/2020
last illoanica.	12/13/2020