

# FMC00159-200CM DATA SHEET

# RA N Male to BNC Male Cable RG-58 Coax with Heat Shrink in 200 CM length

The RA type N male to BNC male 200 cm cable using RG-58 coax, part number FMC00159-200CM, from Fairview Microwave is in-stock and ships same day. This Fairview type N to BNC cable assembly has a male to male gender configuration with 50 ohm flexible RG58C/U coax. Fairview Microwave's flexible RF cable assemblies are ideal for applications where tight bends and continual flexure are required. The FMC00159-200CM type N male to BNC male cable assembly operates to 1 GHz. The right angle type N interface on the RG58C/U cable allows for easier connections in tight spaces.

Custom versions of most RF cable assemblies can be built and shipped same day. Custom cable assembly lengths can be obtained by specifying the desired length on the web site at time of order or by contacting a sales representative. Other RF cable assembly value added services including connector orientation or clocking, heat shrink booting and labeling are also available. RF testing can also be performed to document the electrical performance of your cable assembly.

# **Electrical Specifications**

Description	Min	Т	ур	Max	ι	Inits
Frequency Range	DC		-	1,000		MHz
VSWR				1.4:1		
Velocity of Propagation		(	66			%
Capacitance		30.8 [101.05]		pF/ft [pF/m]		
Operating Voltage (AC)				500	١	/rms

### **Performance by Frequency**

Description	F1	F2	F3	F4	F5	Units
Frequency	50	100	250	500	1,000	MHz
Insertion Loss (Typ.)	0.24	0.39	0.59	0.91	1.52	dB

#### Electrical Specification Notes:

The Insertion Loss data above is based on the performance specifications of the coax and connectors used in this assembly. The Insertion Loss includes an estimated insertion loss of 0.1\*SQRT(FGHz) dB per connector.

# **Mechanical Specifications**

### **Cable Assembly**

Length\* 78.74 in [200 cm]
Weight 0.182 lbs [82.55 g]

### Cable

Cable Type
Impedance
Inner Conductor Type
Inner Conductor Material and Plating
Dielectric Type
Number of Shields
Shield Layer 1
Jacket Material

RG58C/U 50 Ohms Stranded Copper, Tin PE

PVC, Black

Tinned Copper Braid

# 0

# **Configuration:**

- N Male Right Angle
- BNC Male
- RG58C/U

### **Features:**

- Max Frequency 1 GHz
- 66% Phase Velocity
- PVC Jacket

# **Applications:**

- General Purpose
- Laboratory Use

Fairview Microwave 301 Leora Ln., Suite 100 Lewisville, TX 75056 Tel: 1-800-715-4396 / (972) 649-6678 Fax: (972) 649-6689 www.fairviewmicrowave.com sales@fairviewmicrowave.com





Jacket Diameter

0.195 in [4.95 mm]

### **Connectors**

Description	Connector 1	Connector 2		
Туре	N Male	BNC Male		
Specification	MIL-STD-348A	MIL-STD-348A		
Impedance	50 Ohms	50 Ohms		
Contact Material & Plating	Brass, Gold	Brass, Gold		
Contact Plating Spec.		30 µin minimum		
Dielectric Type	Teflon	PTFE		
Body Material & Plating	Brass, Nickel	Brass, Nickel		
Body Plating Spec.		100 µin minimum		
Coupling Nut Material & Pla	iting Brass, Nickel	Brass, Nickel		
Coupling Nut Plating Spec.		100 µin minimum		

## **Environmental Specifications**

Temperature

Operating Range

-40 to +80 deg C

**Compliance Certifications** (see product page for current document)

**Plotted and Other Data** 

Notes:

### **How to Order**

Part Number Configuration:

FMC00159 - xx uu

cm = Centimeters
<br/>
<br/>
<br/>
clank> = Inches

Length

Example: FMC00159-12 = 12 inches long cable
FMC00159-100cm = 100 cm long cable

301 Leora Ln., Suite 100, Lewisville, TX 75056 | Tel: 1-800-715-4396 / (972) 649-6678 / Fax: (972) 649-6689





RA N Male to BNC Male Cable RG-58 Coax with Heat Shrink in 200 CM length from Fairview Microwave has same day shipment for domestic and International orders. Our RF, microwave and millimeter wave products maintain a 99% availability and are part of the broadest selection in the industry.

Click the following link to obtain additional part information: RA N Male to BNC Male Cable RG-58 Coax with Heat Shrink in 200 CM length FMC00159-200CM

URL: https://www.fairviewmicrowave.com/ra-n-male-to-bnc-male-cable-rg-58-coax-in-200-cm-fmc00159-200cm-p.aspx







