

HMC-C004

v04.1007






Typical Applications

The HMC-C004 Wideband Driver is ideal for:

- OC192 LN/MZ Modulator Driver
- Telecom Infrastructure
- Microwave Radio & VSAT
- Military & Space
- Test Instrumentation

Functional Diagram



WIDEBAND DRIVER AMPLIFIER MODULE, 10 MHz - 20 GHz

Features

Gain: 15 dB Saturated Output Power: +24 dBm 50 Ohm Matched Input/Output Regulated Supply and Bias Sequencing Hermetically Sealed Module Field Replaceable SMA connectors -55 to +85°C Operating Temperature

General Description

The HMC-C004 is a GaAs MMIC PHEMT Distributed Driver Amplifier in a miniature, hermetic module with replaceable SMA connectors which operates between 10 MHz and 20 GHz. The self-biased amplifier provides 15 dB of gain, 3 to 4 dB noise figure and +24 dBm of saturated output power while requiring a single +12V supply. Gain flatness is excellent at ± 0.5 dB as well as ± 2 deg deviation from linear phase from 0.01 to 10 GHz making the HMC-C004 ideal for OC192 fiber optic LN/MZ modulator driver applications. The wideband amplifier I/Os are internally matched to 50 Ohms and are internally DC blocked.

Electrical Specifications, $T_A = +25^{\circ}$ C, Vs= +11.6V to +12.4V

Parameter	Min.	Тур.	Max.	Min.	Тур.	Max.	Min.	Тур.	Max.	Units
Frequency Range		0.010 - 6.0		6.0 - 12.0			12.0 - 20.0			GHz
Gain	14	16		13	15		10	13		dB
Gain Flatness		±0.5			±0.5			±1.0		dB
Gain Variation Over Temperature		0.012	0.02		0.012	0.02		0.012	0.02	dB/ °C
Noise Figure		3			3			4		dB
Input Return Loss		19			17			10		dB
Output Return Loss		14			14			10		dB
Output Power for 1 dB Compression (P1dB)	20	23		19	22		17	20		dBm
Saturated Output Power (Psat)		25			24			22		dBm
Output Third Order Intercept (IP3)		33			30			26		dBm
Saturated Output Voltage		10			10			8		Vpk-pk
Group Delay		±3			±3			±3		ps
Spurious Response		-50			-60			-60		dBc
Supply Current		195			195			195		mA

Information furnished by Analog Devices is believed to be accurate and reliable. However, no responsibility is assumed by Analog Devices for its use, nor for any infringements of patents or other rights of third parties that may result from its use. Specifications subject to change without notice. No license is granted by implication or otherwise under any patent or patent rights of Analog Devices. Trademarks and registered trademarks are the property of their respective owners.




HMC-C004




v04.1007


Gain & Return Loss



Input Return Loss vs. Temperature




Reverse Isolation vs. Temperature




MODULE, 10 MHz - 20 GHz

WIDEBAND DRIVER AMPLIFIER


Gain vs. Temperature



Output Return Loss vs. Temperature



Noise Figure vs. Temperature



9


Information furnished by Analog Devices is believed to be accurate and reliable. However, no responsibility is assumed by Analog Devices for its use, nor for any infringements of patents or other rights of third parties that may result from its use. Specifications subject to change without notice. No license is granted by implication or otherwise under any patent or patent rights of Analog Devices. Trademarks and registered trademarks are the property of their respective owners.






v04.1007


P1dB vs. Temperature




Output IP3 vs. Temperature




Deviation from Linear Phase




WIDEBAND DRIVER AMPLIFIER MODULE, 10 MHz - 20 GHz





Low Frequency Gain and Return Loss



Information furnished by Analog Devices is believed to be accurate and reliable. However, no responsibility is assumed by Analog Devices for its use, nor for any infringements of patents or other rights of third parties that may result from its use. Specifications subject to change without notice. No license is granted by implication or otherwise under any patent or patent rights of Analog Devices. Trademarks and registered trademarks are the property of their respective owners.




HMC-C004



v04.1007

Input OC-192 Eye Diagram ^{[1][2]}



[1] Test Conditions:

Pattern generated with an Agilent N4901B Serial BERT Eye diagram data presented on an infiniium DCA 86100A. Rate = 10.709 GB/s Pseudo Random Code = 2²³-1


[2] Vertical Scale = 200 mV/Div.

[3] Vertical Scale = 1 V/Div.

Output OC-192 Eye Diagram [1][3]

WIDEBAND DRIVER AMPLIFIER

MODULE, 10 MHz - 20 GHz



Absolute Maximum Ratings

Bias Supply Voltage (Vs)	+11 Vdc to +13 Vdc		
RF Input Power (RFIN)	+23 dBm		
Storage Temperature	-65 to +150 °C		
Operating Temperature	-55 to +85 °C		



Pin Descriptions

Pin Number	Function	Description	Interface Schematic		
1	RFIN & RF Ground	RF input connector, SMA female, field replaceable. This pin is AC coupled and matched to 50 Ohms.			
2	Vs	Power supply voltage for the amplifier.			
3	RFOUT & RF Ground	RF output connector, SMA female. This pin is AC coupled and matched to 50 Ohms.			
4	GND	Power supply ground.			

Information furnished by Analog Devices is believed to be accurate and reliable. However, no responsibility is assumed by Analog Devices for its use, nor for any infringements of patents or other rights of third parties that may result from its use. Specifications subject to change without notice. No license is granted by implication or otherwise under any patent or patent rights of Analog Devices. Trademarks and registered trademarks are the property of their respective owners.

For price, delivery, and to place orders: Analog Devices, Inc., One Technology Way, P.O. Box 9106, Norwood, MA 02062-9106 Phone: 781-329-4700 • Order online at www.analog.com Application Support: Phone: 1-800-ANALOG-D 9



v04.1007



WIDEBAND DRIVER AMPLIFIER MODULE, 10 MHz - 20 GHz


Package Type

Spacer Weight

Package Weight^[1]

[2] ±1 gms Tolerance

[1] Includes the connectors



2. SPACER MATERIAL: ALUMINUM

- 3. PLATING: ELECTROLYTIC GOLD 50 MICROINCHES MIN., OVER ELECTROLYTIC NICKEL 75 MICROINCHES MIN.
- 4. ALL DIMENSIONS ARE IN INCHES [MILLIMETERS].
- 5. TOLERANCES ±.005 [0.13] UNLESS OTHERWISE SPECIFIED.
- 6. FIELD REPLACEABLE SMA CONNECTORS. TENSOLITE 5602 - 5CCSF OR EQUIVALENT.
- ▲ TO MOUNT MODULE TO SYSTEM PLATFORM REPLACE 0 -80 HARDWARE WITH DESIRED MOUNTING SCREWS.

Information furnished by Analog Devices is believed to be accurate and reliable. However, no responsibility is assumed by Analog Devices for its use, nor for any infringements of patents or other rights of third parties that may result from its use. Specifications subject to change without notice. No license is granted by implication or otherwise under any patent or patent rights of Analog Devices. Trademarks and registered trademarks are the property of their respective owners.

C-3

N/A

12 gms [2]



v04.1007

HMC-C004

WIDEBAND DRIVER AMPLIFIER MODULE, 10 MHz - 20 GHz



Notes:

Information furnished by Analog Devices is believed to be accurate and reliable. However, no responsibility is assumed by Analog Devices for its use, nor for any infringements of patents or other rights of third parties that may result from its use. Specifications subject to change without notice. No license is granted by implication or otherwise under any patent or patent rights of Analog Devices. Trademarks and registered trademarks are the property of their respective owners.

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Analog Devices Inc.:

HMC-C004