

Sticklers™ 1.25 mm CleanClicker™ 400

Fiber Optic Cleaner



Product Features:

- 104mm (4") compact size for cleaning in confined spaces
- Click-to-clean dust, particulate and oil contamination
- 400+ cleaning capacity


Cleaning Capabilities:

MU in adapter and cable assembly
ARINC 801 pin and socket termini
MIL PRF 29504/18 and /20 termini
Radiall LuxCis® termini
Huber+Suhner ODC® -2 and -4 connectors
LC/UPC and LC/APC in adapter and cable assembly
Rosenberger RDC connectors for pin & socket
Neutrik opticalCON DUO jack and plug ferrul
CS in adapter & cable assembly QSFP-DD connectors
Amphenol AARC connectors for pin & socket

Typical Cleaning Applications:

Fiber To The Antenna (FTTA) Networks
Remote Radio Heads (RRH) Networks
Enterprise Networks
Military & COTS Optical Networks
Commercial Aviation
Field Installation Kits

Packaging:

Part Number	MCC-CCM125
Case Quantity	10 Clickers Per Case
GHS/HCS Pictogram	Not Applicable
Recycle Symbol	

When you need perfectly clean splices & connectors™

MicroCare Corporation

595 John Downey Drive
New Britain, CT 06051 USA
CAGE: OATV9
Tel: +1 860 827 0626
Toll Free: 1 800 638 0125
Email: TechSupport@MicroCare.com

MicroCare Europe BVBA

Vekestraat 29 B11
Industriezone 't Sas
1910 Kampenhout, Belgium
Tel: +32 2 251 95 05
Email: EuroSales@MicroCare.com

MicroCare U.K. Ltd

Seven Hills Business Park,
Morley,
Leeds, West Yorkshire, UK
LS27 8AT
Tel: +44 (0) 113 3501008
Email: mceurope@microcare.com

MicroCare Asia Pte Ltd

102E Pasir Panjang Road
#03-01 Citilink Warehouse Complex
Singapore 118529
Tel: +65 6271 0182
Email: TechSupport@MicroCare.sg

www.SticklersCleaners.com

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

[MicroCare:](#)

[MCC-CCM125](#)