SIEMENS

Data sheet

3LD3130-1TK13



Load disconnector 3LD3, lu 25 A Main switch 3-pole Rated operating capacity at AC-23 A at 400V 9.0kW Installation in distribution boards, Basic switch with selector knob red / yellow with auxiliary switch 10E + 1S

Model	
product brand name	SENTRON
product designation	Switch disconnector
design of the product	EMERGENCY-STOP switch
display version for switch position indicator manual operation	1 ON - 0 OFF
type of switch	DIN-rail mounting
design of the actuating element	selector switch
color of the actuating element	red
design of handle	knob-operated mechanism, red/yellow
type of the driving mechanism motor drive	No
General technical data	
number of poles	3
number of poles note	3
mechanical service life (operating cycles) typical	100 000
electrical endurance (operating cycles)	
• at AC-23 A at 690 V	6 000
operating frequency maximum	50 1/h
degree of pollution	3
Voltage	
insulation voltage rated value	690 V
surge voltage resistance rated value	6 kV
operating voltage	
at AC rated value	690 V
operating frequency rated value	
• minimum	50 Hz
• maximum	60 Hz
Protection class	
protection class IP	IP40
protection class IP on the front	IP40
Dissipation	
power loss [W] for rated value of the current at AC in hot operating state per pole	1.1 W
Main circuit	
operational current	
• at AC-21 at 690 V rated value	25 A
• at AC-21 A at 240 V rated value	25 A
• at AC-21 A at 400 V rated value	25 A
• at AC-21 A at 440 V rated value	25 A
 at AC-23 A at 400 V rated value 	20 A
operating power	

at AC-23 A at 240 V rated value	4 kW
 at AC-23 A at 400 V rated value 	10 kW
 at AC-23 A at 440 V rated value 	9 kW
 at AC-23 A at 690 V rated value 	9 kW
 at AC-3 at 240 V rated value 	4 kW
 at AC-3 at 400 V rated value 	8 kW
 at AC-3 at 690 V rated value 	7.5 kW
Auxiliary circuit	
number of CO contacts for auxiliary contacts	0
number of NC contacts for auxiliary contacts	1
number of NO contacts for auxiliary contacts	1
operating voltage of auxiliary contacts at AC maximum	500 V
continuous current of the auxiliary contact rated value	10 A
insulation voltage of the auxiliary switch rated value	500 V
Suitability	
suitability for use	
main switch	Yes
switch disconnector	Yes
EMERGENCY OFF switch	Yes
safety switch	Yes
maintenance/repair switch	Yes
maintenance/repair switch Product details	
	Can be leaked in zero position
special product feature	Can be locked in zero position
product feature can be locked into OFF position	Yes
accessories	
product extension optional	
motor drive	No
voltage trigger	No
number of connectable NC contacts for auxiliary contacts attachable maximum	2
number of connectable NO contacts for auxiliary contacts attachable maximum	4
number of connectable CO contacts for auxiliary contacts attachable maximum	0
number of bracket locks maximum	2
hasp thickness of the bracket locks	4 6 mm
Short circuit	
conditional short circuit current with line side fues protection	
conditional short-circuit current with line-side fuse protection	
at 440 V by gG fuse rated value	10 kA
-	10 kA 6 kA
• at 440 V by gG fuse rated value	
 at 440 V by gG fuse rated value at 690 V by gG fuse rated value 	
at 440 V by gG fuse rated value at 690 V by gG fuse rated value let-through current with closed switch	6 kA
 at 440 V by gG fuse rated value at 690 V by gG fuse rated value let-through current with closed switch at 240 V for combination switch + gG fuse maximum 	6 kA 3.5 kA
 at 440 V by gG fuse rated value at 690 V by gG fuse rated value let-through current with closed switch at 240 V for combination switch + gG fuse maximum at 440 V for combination switch + gG fuse maximum 	6 kA 3.5 kA 3.5 kA
 at 440 V by gG fuse rated value at 690 V by gG fuse rated value let-through current with closed switch at 240 V for combination switch + gG fuse maximum at 440 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum 	6 kA 3.5 kA 3.5 kA
 at 440 V by gG fuse rated value at 690 V by gG fuse rated value let-through current with closed switch at 240 V for combination switch + gG fuse maximum at 440 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum 	6 kA 3.5 kA 3.5 kA
 at 440 V by gG fuse rated value at 690 V by gG fuse rated value let-through current with closed switch at 240 V for combination switch + gG fuse maximum at 440 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum permissible l2t value with closed switch 	6 kA 3.5 kA 3.5 kA 4 kA
 at 440 V by gG fuse rated value at 690 V by gG fuse rated value let-through current with closed switch at 240 V for combination switch + gG fuse maximum at 440 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum permissible l2t value with closed switch at 240 V for combination switch + gG fuse maximum 	6 kA 3.5 kA 3.5 kA 4 kA 4 kA
 at 440 V by gG fuse rated value at 690 V by gG fuse rated value let-through current with closed switch at 240 V for combination switch + gG fuse maximum at 440 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum let value with closed switch at 240 V for combination switch + gG fuse maximum at 440 V for combination switch + gG fuse maximum 	6 kA 3.5 kA 3.5 kA 4 kA 4 kA 2.s
 at 440 V by gG fuse rated value at 690 V by gG fuse rated value let-through current with closed switch at 240 V for combination switch + gG fuse maximum at 440 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum l2t value with closed switch at 240 V for combination switch + gG fuse maximum at 440 V for combination switch + gG fuse maximum at 440 V for combination switch + gG fuse maximum at 440 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum 	6 kA 3.5 kA 3.5 kA 4 kA 4 kA 2.s
 at 440 V by gG fuse rated value at 690 V by gG fuse rated value let-through current with closed switch at 240 V for combination switch + gG fuse maximum at 440 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum permissible l2t value with closed switch at 240 V for combination switch + gG fuse maximum at 240 V for combination switch + gG fuse maximum at 240 V for combination switch + gG fuse maximum at 240 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum 	6 kA 3.5 kA 3.5 kA 4 kA 4 kA 2.s 4 kA2.s 4 kA2.s
 at 440 V by gG fuse rated value at 690 V by gG fuse rated value let-through current with closed switch at 240 V for combination switch + gG fuse maximum at 440 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum permissible l2t value with closed switch at 240 V for combination switch + gG fuse maximum at 440 V for combination switch + gG fuse maximum at 440 V for combination switch + gG fuse maximum at 440 V for combination switch + gG fuse maximum at 460 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum 	6 kA 3.5 kA 3.5 kA 4 kA 4 kA 4 kA 2.s 4 kA2.s 4 kA2.s 4 kA2.s 5 kA 4 kA2.s
 at 440 V by gG fuse rated value at 690 V by gG fuse rated value let-through current with closed switch at 240 V for combination switch + gG fuse maximum at 440 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum at 240 V for combination switch + gG fuse maximum at 240 V for combination switch + gG fuse maximum at 240 V for combination switch + gG fuse maximum at 440 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum 	6 kA 3.5 kA 3.5 kA 4 kA 4 kA 4 kA 5 kA 4 kA 5 kA 4 kA 5 kA 4 kA 5
 at 440 V by gG fuse rated value at 690 V by gG fuse rated value let-through current with closed switch at 240 V for combination switch + gG fuse maximum at 440 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum at 240 V for combination switch + gG fuse maximum at 240 V for combination switch + gG fuse maximum at 240 V for combination switch + gG fuse maximum at 240 V for combination switch + gG fuse maximum at 440 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum design of the fuse link for short-circuit protection of the main circuit required for short-circuit protection of the auxiliary switch required operational current of upstream fuse rated value 	6 kA 3.5 kA 3.5 kA 4 kA 4 kA 4 kA 5 kA 4 kA 5 kA 4 kA 5 kA 4 kA 5
 at 440 V by gG fuse rated value at 690 V by gG fuse rated value let-through current with closed switch at 240 V for combination switch + gG fuse maximum at 440 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum at 240 V for combination switch + gG fuse maximum at 240 V for combination switch + gG fuse maximum at 240 V for combination switch + gG fuse maximum at 240 V for combination switch + gG fuse maximum at 440 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum design of the fuse link for short-circuit protection of the main circuit required for short-circuit protection of the auxiliary switch required operational current at AC according to UL 508/UL 60947-4-1 rated value operating voltage at AC at 50/60 Hz according to UL 508/UL 	6 kA 3.5 kA 3.5 kA 4 kA 4 kA 4 kA 5 kA 4 kA 5 kA 4 kA 5 kA 4 kA 5 kA 4 kA 5 kA 5 kA 6 kA 6 kA 7
 at 440 V by gG fuse rated value at 690 V by gG fuse rated value let-through current with closed switch at 240 V for combination switch + gG fuse maximum at 440 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum permissible l2t value with closed switch at 240 V for combination switch + gG fuse maximum at 440 V for combination switch + gG fuse maximum at 240 V for combination switch + gG fuse maximum at 240 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum design of the fuse link for short-circuit protection of the main circuit required for short-circuit protection of the auxiliary switch required operational current of upstream fuse rated value according UL operating voltage at AC at 50/60 Hz according to UL 508/UL 60947-4-1 rated value active power [hp] at AC at 480 V according to UL 508/UL 60947- 	6 kA 3.5 kA 3.5 kA 4 kA 4 kA 4 kA 5 kA 4 kA 2.5 4 kA 2.5 4 2.5 4 2.5 4 2.5 4 2.5 4 2.5 4 2.5 4 2.5 4 2.5 4 2.5 4 2.5 4 2.5 4 2.5 4 2.5 4 2.5 4 2.5 4 2.5 4 2.5 4 2.5 4 2.5 2.5 2.5 2.5 2.5 2.5 2.5 2.5
 at 440 V by gG fuse rated value at 690 V by gG fuse rated value let-through current with closed switch at 240 V for combination switch + gG fuse maximum at 440 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum at 240 V for combination switch + gG fuse maximum at 240 V for combination switch + gG fuse maximum at 240 V for combination switch + gG fuse maximum at 440 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum design of the fuse link for short-circuit protection of the main circuit required for short-circuit protection of the auxiliary switch required operational current of upstream fuse rated value according UL operating voltage at AC at 50/60 Hz according to UL 508/UL 60947-4-1 rated value active power [hp] at AC at 480 V according to UL 508/UL 60947-4-1 rated value active power [hp] at AC at 600 V according to UL 508/UL 60947- 	6 kA 3.5 kA 3.5 kA 4 kA 4 kA 4 kA 2 s 4 kA2.s 4 kA2.s 4 kA2.s 5 s 6 use gL/gG: 25 A fuse gL/gG: 10 A 25 A 600 V
 at 440 V by gG fuse rated value at 690 V by gG fuse rated value let-through current with closed switch at 240 V for combination switch + gG fuse maximum at 440 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum permissible l2t value with closed switch at 240 V for combination switch + gG fuse maximum at 240 V for combination switch + gG fuse maximum at 440 V for combination switch + gG fuse maximum at 440 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum design of the fuse link for short-circuit protection of the main circuit required for short-circuit protection of the auxiliary switch required operational current of upstream fuse rated value according UL operating voltage at AC at 50/60 Hz according to UL 508/UL 60947-4-1 rated value active power [hp] at AC at 480 V according to UL 508/UL 60947-4-1 	6 kA 3.5 kA 3.5 kA 4 kA 4 kA 4 kA 4 kA2.s 4 kA2.s 4 kA2.s fuse gL/gG: 25 A fuse gL/gG: 10 A 25 A 600 V 10

508/UL 60947-4-1	
continuous current of upstream fuse according to UL rated value	50 A
type of fuse according to UL	RK5
Connections	
AWG number as coded connectable conductor cross section solid	
• maximum	6
• minimum	14
type of connectable conductor cross-sections for copper conductor	
• solid	1x (2.5 to 16 mm²)
 finely stranded with core end processing 	1x (2.516 mm²)
• stranded	1x (2.5 to 16 mm²)
type of connectable conductor cross-sections for auxiliary contacts	
• solid	2x (0.75 2.5 mm²), 1x 4 mm²
 finely stranded with core end processing 	2x (0.75 1.5 mm²), 1x 2.5 mm²
• stranded	2x (0.75 2.5 mm²), 1x 4 mm²
type of electrical connection	
for main current circuit	box terminal
for auxiliary contacts	Box terminals
Mechanical Design	
height	60 mm
width	47 mm
depth	77 mm
type of device	fixed mounting
fastening method	Built-in unit fixed-mounted version
fastening method	
4-hole front mounting	No
front mounting with central attachment	No
	Yes
rail mounting net weight	200 g
-	200 g
Environmental conditions	
ambient temperature during operation	05.00
• minimum	-25 °C
• maximum	55 °C
ambient temperature during storage	
• minimum	-25 °C
• maximum	55 °C
General Product Approval	Declaration of Conformity
Confirmation	
other Environment	
Miscellaneous Confirmation Environmental firmations	
Further information	

Siemens has decided to exit the Russian market (see here).

https://press.siemens.com/global/en/pressrelease/siemens-wind-down-russian-business

Siemens is working on the renewal of the current EAC certificates.

Please contact your local Siemens office on the status of validity of the EAC certification if you intend to import or offer to supply these products to an EAC relevant market (other than the sanctioned EAEU member states Russia or Belarus).

Information on the packaging

https://support.industry.siemens.com/cs/ww/en/view/109813875

Information- and Downloadcenter (Catalogs, Brochures,...)


http://www.siemens.com/lowvoltage/catalogs


Industry Mall (Online ordering system)


https://mall.industry.siemens.com/mall/en/en/Catalog/product?mlfb=3LD3130-1TK13 Service&Support (Manuals, Certificates, Characteristics, FAQs,...) https://support.industry.siemens.com/cs/ww/en/ps/3LD3130-1TK13 Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, ...) http://www.automation.siemens.com/bilddb/cax_en.aspx?mlfb=3LD3130-1TK13 CAx-Online-Generator


http://www.siemens.com/cax Tender specifications

http://www.siemens.com/specifications









last modified:

6/20/2023 🖸

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Siemens: 3LD31301TK13