SIEMENS

Data sheet 3LD3210-0TK05



Load disconnector 3LD3, lu 32 A Main switch 3-pole Rated operating capacity for AC-23 A at 400V 11.5kW Installation in distribution boards, Basic switch without Knob-operated mechanism

Model	
product brand name	SENTRON
product designation	Switch disconnector
design of the product	Switch
display version for switch position indicator manual operation	1 ON - 0 OFF
type of switch	DIN-rail mounting
design of the actuating element	Without handle
design of handle	without
type of the driving mechanism motor drive	No
General technical data	
number of poles	3
number of poles note	3
mechanical service life (operating cycles) typical	100 000
electrical endurance (operating cycles)	
• at AC-23 A at 690 V	6 000
operating frequency maximum	50 1/h
degree of pollution	3
Voltage	
insulation voltage rated value	690 V
surge voltage resistance rated value	6 kV
operating voltage	
at AC rated value	690 V
operating frequency rated value	
• minimum	50 Hz
• maximum	60 Hz
Protection class	
protection class IP	IP20
protection class IP on the front	IP20
Dissipation	
power loss [W] for rated value of the current at AC in hot operating state per pole	1.8 W
Main circuit	
operational current	
• at AC-21 at 690 V rated value	32 A
• at AC-21 A at 240 V rated value	32 A
• at AC-21 A at 400 V rated value	32 A
• at AC-21 A at 440 V rated value	32 A
at AC-23 A at 400 V rated value	22 A
operating power	
• at AC-23 A at 240 V rated value	6 kW

 at AC-23 A at 400 V rated value 	12 kW
 at AC-23 A at 440 V rated value 	11.5 kW
 at AC-23 A at 690 V rated value 	12 kW
 at AC-3 at 240 V rated value 	5.5 kW
 at AC-3 at 400 V rated value 	10 kW
at AC-3 at 690 V rated value	9.5 kW
Auxiliary circuit	
number of CO contacts for auxiliary contacts	0
number of NC contacts for auxiliary contacts	0
number of NO contacts for auxiliary contacts	0
operating voltage of auxiliary contacts at AC maximum	500 V
continuous current of the auxiliary contact rated value	10 A
insulation voltage of the auxiliary switch rated value	500 V
Suitability	
suitability for use	V
• main switch	Yes
switch disconnector FMEDCENCY OFF switch	Yes
EMERGENCY OFF switch Acceptable switch	Yes
• safety switch	Yes
maintenance/repair switch	Yes
Product details	
special product feature	Basic Switch
product feature can be locked into OFF position	No
accessories	
product extension optional	No
motor drive voltage trigger	
voltage trigger Purpler of connectable NC contacts for quviliery contacts	No 2
number of connectable NC contacts for auxiliary contacts attachable maximum	
number of connectable NO contacts for auxiliary contacts attachable maximum	4
number of connectable CO contacts for auxiliary contacts attachable maximum	0
Short circuit	
conditional short-circuit current with line-side fuse protection	
- at 110 \/ by a C five - instantive	10 kA
 at 440 V by gG fuse rated value 	
at 690 V by gG fuse rated value	6 kA
at 690 V by gG fuse rated value let-through current with closed switch	6 kA
at 690 V by gG fuse rated value let-through current with closed switch at 240 V for combination switch + gG fuse maximum	6 kA 4.5 kA
at 690 V by gG fuse rated value let-through current with closed switch at 240 V for combination switch + gG fuse maximum at 440 V for combination switch + gG fuse maximum	6 kA 4.5 kA 4.5 kA
at 690 V by gG fuse rated value let-through current with closed switch at 240 V for combination switch + gG fuse maximum	6 kA 4.5 kA
 at 690 V by gG fuse rated value let-through current with closed switch at 240 V for combination switch + gG fuse maximum at 440 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum 	6 kA 4.5 kA 4.5 kA
at 690 V by gG fuse rated value let-through current with closed switch at 240 V for combination switch + gG fuse maximum at 440 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum permissible	6 kA 4.5 kA 4.5 kA
at 690 V by gG fuse rated value let-through current with closed switch at 240 V for combination switch + gG fuse maximum at 440 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum permissible l2t value with closed switch at 240 V for combination switch + gG fuse maximum	6 kA 4.5 kA 4.5 kA
at 690 V by gG fuse rated value let-through current with closed switch at 240 V for combination switch + gG fuse maximum at 440 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum permissible l2t value with closed switch	6 kA 4.5 kA 4.5 kA 5 kA
at 690 V by gG fuse rated value let-through current with closed switch at 240 V for combination switch + gG fuse maximum at 440 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum permissible l2t value with closed switch at 240 V for combination switch + gG fuse maximum at 440 V for combination switch + gG fuse maximum	6 kA 4.5 kA 4.5 kA 5 kA 9 kA2.s
 at 690 V by gG fuse rated value let-through current with closed switch at 240 V for combination switch + gG fuse maximum at 440 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum permissible l2t value with closed switch at 240 V for combination switch + gG fuse maximum at 440 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum 	6 kA 4.5 kA 4.5 kA 5 kA 9 kA2.s
at 690 V by gG fuse rated value let-through current with closed switch at 240 V for combination switch + gG fuse maximum at 440 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum permissible l2t value with closed switch at 240 V for combination switch + gG fuse maximum at 440 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum	6 kA 4.5 kA 4.5 kA 5 kA 9 kA2.s 9 kA2.s
at 690 V by gG fuse rated value let-through current with closed switch at 240 V for combination switch + gG fuse maximum at 440 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum permissible l2t value with closed switch at 240 V for combination switch + gG fuse maximum at 440 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum design of the fuse link for short-circuit protection of the main circuit required	6 kA 4.5 kA 4.5 kA 5 kA 9 kA2.s 9 kA2.s 9 kA2.s
at 690 V by gG fuse rated value let-through current with closed switch at 240 V for combination switch + gG fuse maximum at 440 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum permissible l2t value with closed switch at 240 V for combination switch + gG fuse maximum at 440 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum design of the fuse link for short-circuit protection of the main circuit required for short-circuit protection of the auxiliary switch required	6 kA 4.5 kA 4.5 kA 5 kA 9 kA2.s 9 kA2.s 9 kA2.s fuse gL/gG: 25 A fuse gL/gG: 10 A
at 690 V by gG fuse rated value let-through current with closed switch at 240 V for combination switch + gG fuse maximum at 440 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum permissible l2t value with closed switch at 240 V for combination switch + gG fuse maximum at 440 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum be at 690 V for combination switch + gG fuse maximum design of the fuse link for short-circuit protection of the main circuit required for short-circuit protection of the auxiliary switch required operational current of upstream fuse rated value	6 kA 4.5 kA 4.5 kA 5 kA 9 kA2.s 9 kA2.s 9 kA2.s fuse gL/gG: 25 A fuse gL/gG: 10 A
at 690 V by gG fuse rated value let-through current with closed switch at 240 V for combination switch + gG fuse maximum at 440 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum permissible l2t value with closed switch at 240 V for combination switch + gG fuse maximum at 440 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum be at 690 V for combination switch + gG fuse maximum design of the fuse link for short-circuit protection of the main circuit required for short-circuit protection of the auxiliary switch required operational current of upstream fuse rated value according UL operational current at AC according to UL 508/UL 60947-4-1	6 kA 4.5 kA 4.5 kA 5 kA 9 kA2.s 9 kA2.s 9 kA2.s fuse gL/gG: 25 A fuse gL/gG: 10 A 32 A
at 690 V by gG fuse rated value let-through current with closed switch at 240 V for combination switch + gG fuse maximum at 440 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum permissible l2t value with closed switch at 240 V for combination switch + gG fuse maximum at 440 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum be at 690 V for combination switch + gG fuse maximum design of the fuse link for short-circuit protection of the main circuit required for short-circuit protection of the auxiliary switch required operational current of upstream fuse rated value according UL operational current at AC according to UL 508/UL 60947-4-1 rated value operating voltage at AC at 50/60 Hz according to UL 508/UL	6 kA 4.5 kA 4.5 kA 5 kA 9 kA2.s 9 kA2.s 9 kA2.s fuse gL/gG: 25 A fuse gL/gG: 10 A 32 A
 at 690 V by gG fuse rated value let-through current with closed switch at 240 V for combination switch + gG fuse maximum at 440 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum permissible l2t value with closed switch at 240 V for combination switch + gG fuse maximum at 440 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum for short-circuit protection of the main circuit required for short-circuit protection of the auxiliary switch required perational current of upstream fuse rated value according UL operational current at AC according to UL 508/UL 60947-4-1 rated value active power [hp] at AC at 480 V according to UL 508/UL 60947-4-1 rated value active power [hp] at AC at 600 V according to UL 508/UL 60947-4-1 rated value 	6 kA 4.5 kA 4.5 kA 5 kA 9 kA2.s 9 kA2.s 9 kA2.s fuse gL/gG: 25 A fuse gL/gG: 10 A 32 A 32 A
at 690 V by gG fuse rated value let-through current with closed switch at 240 V for combination switch + gG fuse maximum at 440 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum permissible l2t value with closed switch at 240 V for combination switch + gG fuse maximum at 440 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum for short-circuit protection of the main circuit required for short-circuit protection of the auxiliary switch required operational current of upstream fuse rated value according UL operational current at AC according to UL 508/UL 60947-4-1 rated value operating voltage at AC at 50/60 Hz according to UL 508/UL 60947-4-1 rated value active power [hp] at AC at 480 V according to UL 508/UL 60947-4-1 rated value	6 kA 4.5 kA 4.5 kA 5 kA 9 kA2.s 9 kA2.s 9 kA2.s fuse gL/gG: 25 A fuse gL/gG: 10 A 32 A 600 V
 at 690 V by gG fuse rated value let-through current with closed switch at 240 V for combination switch + gG fuse maximum at 440 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum permissible l2t value with closed switch at 240 V for combination switch + gG fuse maximum at 440 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum for short-circuit protection of the main circuit required for short-circuit protection of the auxiliary switch required for short-circuit protection of the auxiliary switch required operational current of upstream fuse rated value according UL operational current at AC according to UL 508/UL 60947-4-1 rated value active power [hp] at AC at 480 V according to UL 508/UL 60947-4-1 rated value active power [hp] at AC at 600 V according to UL 508/UL 60947-4-1 rated value short-time withstand current (SCCR) at 600 V according to UL 	6 kA 4.5 kA 4.5 kA 5 kA 9 kA2.s 9 kA2.s 9 kA2.s fuse gL/gG: 25 A fuse gL/gG: 10 A 32 A 32 A 600 V 20
 at 690 V by gG fuse rated value let-through current with closed switch at 240 V for combination switch + gG fuse maximum at 440 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum permissible l2t value with closed switch at 240 V for combination switch + gG fuse maximum at 440 V for combination switch + gG fuse maximum at 690 V for combination switch + gG fuse maximum for short-circuit protection of the main circuit required for short-circuit protection of the auxiliary switch required for short-circuit protection of the auxiliary switch required operational current of upstream fuse rated value according UL operational current at AC according to UL 508/UL 60947-4-1 rated value active power [hp] at AC at 480 V according to UL 508/UL 60947-4-1 rated value active power [hp] at AC at 480 V according to UL 508/UL 60947-4-1 rated value active power [hp] at AC at 600 V according to UL 508/UL 60947-4-1 rated value short-time withstand current (SCCR) at 600 V according to UL 508/UL 60947-4-1 	6 kA 4.5 kA 4.5 kA 5 kA 9 kA2.s 9 kA2.s 9 kA2.s fuse gL/gG: 25 A fuse gL/gG: 10 A 32 A 32 A 600 V 20 5 kA

Connections	
AWG number as coded connectable conductor cross section solid	
• maximum	6
• minimum	14
type of connectable conductor cross-sections for copper conductor	
• solid	1x (2.5 to 16 mm²)
 finely stranded with core end processing 	1x (2.516 mm²)
stranded	1x (2.5 to 16 mm²)
type of connectable conductor cross-sections for auxiliary contacts	
• solid	2x (0.75 2.5 mm²), 1x 4 mm²
 finely stranded with core end processing 	2x (0.75 1.5 mm²), 1x 2.5 mm²
• stranded	2x (0.75 2.5 mm²), 1x 4 mm²
type of electrical connection	
 for main current circuit 	box terminal
 for auxiliary contacts 	Box terminals
Mechanical Design	
height	60 mm
width	36 mm
depth	64 mm
type of device	fixed mounting
fastening method	Built-in unit fixed-mounted version
fastening method	
 4-hole front mounting 	No
 front mounting with central attachment 	No
rail mounting	Yes
net weight	200 g
Environmental conditions	
ambient temperature during operation	
• minimum	-25 °C
maximum	55 °C
ambient temperature during storage	
• minimum	-25 °C
• maximum	55 °C
General Product Approval	Declaration of Conformity

Confirmation











other Environment

<u>Miscellaneous</u> <u>Confirmation</u> <u>Environmental Confirmations</u>

Further information

Siemens has decided to exit the Russian market (see here).

https://press.siemens.com/global/en/pressrelease/siemens-wind-down-russian-business

Siemens is working on the renewal of the current EAC certificates.

Please contact your local Siemens office on the status of validity of the EAC certification if you intend to import or offer to supply these products to an EAC relevant market (other than the sanctioned EAEU member states Russia or Belarus).

Information on the packaging

https://support.industry.siemens.com/cs/ww/en/view/109813875

Information- and Downloadcenter (Catalogs, Brochures,...)

http://www.siemens.com/lowvoltage/catalogs

Industry Mall (Online ordering system)

 $\underline{https://mall.industry.siemens.com/mall/en/en/Catalog/product?mlfb=3LD3210-0TK05}$


Service&Support (Manuals, Certificates, Characteristics, FAQs,...) https://support.industry.siemens.com/cs/ww/en/ps/3LD3210-0TK05


Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, ...) http://www.automation.siemens.com/bilddb/cax en.aspx?mlfb=3LD3210-0TK05


CAx-Online-Generator


http://www.siemens.com/cax

Tender specifications
http://www.siemens.com/specifications









last modified:

6/20/2023

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Siemens:

3LD32100TK05