# **SIEMENS**

### Data sheet 3RA2125-4EA27-0BB4

	FUSELESS MOTOR STARTER DIRECT START 600V AC SZ S0 27-32A 24V DC SCREW CONNECTION FOR SCREW MOUNTING OR 35 MM RAIL-MOUNTING TYPE OF COORDINATION 2 IQ = 150 KA ALSO FULFILLS TYPE OF COORDINATION 1 1NO+1NC (MSP) 1NO+1NC (CONTACTOR)
product brand name	SIRIUS
product designation	non-fused motor starter 3RA2
design of the product	direct starter
manufacturer's article number	
<ul> <li>of the supplied contactor</li> </ul>	<u>3RT2027-1BB40</u>
<ul> <li>of the supplied circuit-breakers</li> </ul>	3RV2021-4EA15
of the supplied link module	3RA2921-1BA00
General technical data	
size of the circuit-breaker	S0
size of load feeder	S0
product extension auxiliary switch	Yes
insulation voltage with degree of pollution 3 at AC rated value	690 V
degree of pollution	3
surge voltage resistance rated value	6 kV
shock resistance according to IEC 60068-2-27	6g / 11 ms
mechanical service life (operating cycles) of contactor typical	10 000 000
type of assignment	2
Weight	0.95 kg
Ambient conditions	
ambient temperature	
<ul> <li>during operation</li> </ul>	-20 +60 °C
during storage	-50 +80 °C
during transport	-55 +80 °C
A. J. J. W.	
Main circuit	
number of poles for main current circuit	3
	3 electromechanical
number of poles for main current circuit	
number of poles for main current circuit design of the switching contact adjustable current response value current of the current-	electromechanical
number of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release	electromechanical
number of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage	electromechanical 27 32 A
number of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value	electromechanical 27 32 A 690 V
number of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum	electromechanical 27 32 A  690 V 690 V
number of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value	electromechanical 27 32 A  690 V 690 V 50 60 Hz
number of poles for main current circuit  design of the switching contact  adjustable current response value current of the current- dependent overload release  operating voltage  • rated value  • at AC-3 rated value maximum  operating frequency rated value  operational current at AC-3 at 400 V rated value	electromechanical 27 32 A  690 V 690 V 50 60 Hz
number of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage • rated value • at AC-3 rated value maximum operating frequency rated value operational current at AC-3 at 400 V rated value operating power at AC-3	electromechanical 27 32 A  690 V 690 V 50 60 Hz 29 A
number of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage	electromechanical 27 32 A  690 V 690 V 50 60 Hz 29 A
number of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage	electromechanical 27 32 A  690 V 690 V 50 60 Hz 29 A
number of poles for main current circuit  design of the switching contact  adjustable current response value current of the current- dependent overload release  operating voltage  • rated value  • at AC-3 rated value maximum  operating frequency rated value  operational current at AC-3 at 400 V rated value  operating power at AC-3  • at 400 V rated value  • at 500 V rated value  Control circuit/ Control	electromechanical 27 32 A  690 V  690 V  50 60 Hz  29 A  15 000 W  18 500 W
number of poles for main current circuit  design of the switching contact  adjustable current response value current of the current- dependent overload release  operating voltage  • rated value  • at AC-3 rated value maximum  operating frequency rated value  operational current at AC-3 at 400 V rated value  operating power at AC-3  • at 400 V rated value  • at 500 V rated value  Control circuit/ Control  control supply voltage at DC rated value	electromechanical 27 32 A  690 V 690 V 50 60 Hz 29 A  15 000 W 18 500 W
number of poles for main current circuit  design of the switching contact  adjustable current response value current of the current- dependent overload release  operating voltage  • rated value  • at AC-3 rated value maximum  operating frequency rated value  operational current at AC-3 at 400 V rated value  operating power at AC-3  • at 400 V rated value  • at 500 V rated value  Control circuit/ Control  control supply voltage at DC rated value  holding power of magnet coil at DC	electromechanical 27 32 A  690 V 690 V 50 60 Hz 29 A  15 000 W 18 500 W
number of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage	electromechanical 27 32 A  690 V 690 V 50 60 Hz 29 A  15 000 W 18 500 W
number of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage	electromechanical 27 32 A  690 V 690 V 50 60 Hz 29 A  15 000 W 18 500 W  24 V 5.9 W
number of poles for main current circuit  design of the switching contact  adjustable current response value current of the current- dependent overload release  operating voltage  • rated value  • at AC-3 rated value maximum  operating frequency rated value  operational current at AC-3 at 400 V rated value  operating power at AC-3  • at 400 V rated value  • at 500 V rated value  Control circuit/ Control  control supply voltage at DC rated value  holding power of magnet coil at DC  Auxiliary circuit  number of NC contacts for auxiliary contacts  number of NO contacts for auxiliary contacts	electromechanical 27 32 A  690 V 690 V 50 60 Hz 29 A  15 000 W 18 500 W  24 V 5.9 W
number of poles for main current circuit  design of the switching contact  adjustable current response value current of the current- dependent overload release  operating voltage  • rated value  • at AC-3 rated value maximum  operating frequency rated value  operational current at AC-3 at 400 V rated value  operating power at AC-3  • at 400 V rated value  • at 500 V rated value  Control circuit/ Control  control supply voltage at DC rated value  holding power of magnet coil at DC  Auxiliary circuit  number of NC contacts for auxiliary contacts  number of NO contacts for auxiliary contacts  Protective and monitoring functions	electromechanical 27 32 A  690 V 690 V 50 60 Hz 29 A  15 000 W 18 500 W  24 V 5.9 W
number of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage	electromechanical 27 32 A  690 V 690 V 50 60 Hz 29 A  15 000 W 18 500 W  24 V 5.9 W  CLASS 10
number of poles for main current circuit design of the switching contact adjustable current response value current of the current- dependent overload release operating voltage	electromechanical 27 32 A  690 V 690 V 50 60 Hz 29 A  15 000 W 18 500 W  24 V 5.9 W  CLASS 10 thermal (bimetallic)
number of poles for main current circuit  design of the switching contact  adjustable current response value current of the current- dependent overload release  operating voltage  • rated value  • at AC-3 rated value maximum  operating frequency rated value  operational current at AC-3 at 400 V rated value  operating power at AC-3  • at 400 V rated value  • at 500 V rated value  Control circuit/ Control  control supply voltage at DC rated value  holding power of magnet coil at DC  Auxiliary circuit  number of NC contacts for auxiliary contacts  number of NO contacts for auxiliary contacts  Protective and monitoring functions  trip class  design of the overload release  response value current of instantaneous short-circuit trip unit	electromechanical 27 32 A  690 V 690 V 50 60 Hz 29 A  15 000 W 18 500 W  24 V 5.9 W  CLASS 10 thermal (bimetallic)

at 600 V rated value	27 A		
yielded mechanical performance [hp]			
<ul> <li>for single-phase AC motor</li> </ul>			
— at 230 V rated value	5 hp		
• for 3-phase AC motor			
<ul> <li>— at 200/208 V rated value</li> </ul>	10 hp		
<ul> <li>at 220/230 V rated value</li> </ul>	10 hp		
— at 460/480 V rated value	20 hp		
— at 575/600 V rated value	25 hp		
Short-circuit protection			
product function short circuit protection	Yes		
design of the short-circuit trip	magnetic		
conditional short-circuit current (Iq)			
<ul> <li>at 400 V according to IEC 60947-4-1 rated value</li> </ul>	153 000 A		
at 500 V according to IEC 60947-4-1 rated value	100 000 A		
Installation/ mounting/ dimensions			
mounting position	vertical		
fastening method	Snap-mounted to DIN rail or sc	rew-mounted with addition	nal nush-in lug
height	193.1 mm	TOW INCUITOR WILL AGAIN	nai paon in lag
width	45 mm		
depth	107 mm		
required spacing	107 11111		
• for grounded parts			
— forwards	10 mm		
— backwards	0 mm		
	30 mm		
— upwards — at the side	9 mm		
— downwards	10 mm		
for live parts	10 111111		
— forwards	10 mm		
— backwards	0 mm		
— upwards	30 mm		
— downwards	10 mm		
— at the side	9 mm		
Connections/ Terminals			
type of electrical connection for main current circuit	screw-type terminals		
type of connectable conductor cross-sections for main contacts stranded	1 10 mm², 2x (2.5 6 mm²)		
connectable conductor cross-section for main contacts finely stranded with core end processing	1 6 mm²		
Safety related data			
proportion of dangerous failures with high demand rate according to SN 31920	73 %		
B10 value with high demand rate according to SN 31920	1 000 000		
Electrical Safety			
protection class IP on the front according to IEC 60529	IP20		
touch protection on the front according to IEC 60529	finger-safe, for vertical contact	from the front	
Approvals Certificates			
General Product Approval		For use in hazard- ous locations	Test Certificates











Type Test Certificates/Test Report

**Test Certificates** 

Marine / Shipping

Special Test Certificate











Marine / Shipping Railway other **Dangerous goods Environment** 





Confirmation

Special Test Certific-<u>ate</u>

**Transport Information** 

**Environmental Confirmations** 

#### Further information

Information on the packaging

https://support.industry.siemens.com/cs/ww/en/view/109813875

Information- and Downloadcenter (Catalogs, Brochures,...)

https://www.siemens.com/ic10

Industry Mall (Online ordering system)

https://mall.industry.siemens.com/mall/en/en/Catalog/product?mlfb=3RA2125-4EA27-0BB4

Cax online generator

http://support.automation.siemens.com/WW/CAXorder/default.aspx?lang=en&mlfb=3RA2125-4EA27-0BB4

Service&Support (Manuals, Certificates, Characteristics, FAQs,...)

https://support.industry.siemens.com/cs/ww/en/ps/3RA2125-4EA27-0BB4

Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, EPLAN macros, ...)

http://www.automation.siemens.com/bilddb/cax\_de.aspx?mlfb=3RA2125-4EA27-0BB4&lang=en

Characteristic: Tripping characteristics, I2t, Let-through current

https://support.industry.siemens.com/cs/ww/en/ps/3RA2125-4EA27-0BB4/char

Further characteristics (e.g. electrical endurance, switching frequency)
<a href="http://www.automation.siemens.com/bilddb/index.aspx?view=Search&mlfb=3RA2125-4EA27-0BB4&objecttype=14&gridview=view1">http://www.automation.siemens.com/bilddb/index.aspx?view=Search&mlfb=3RA2125-4EA27-0BB4&objecttype=14&gridview=view1</a>

last modified:	12/15/2020

# **Mouser Electronics**

**Authorized Distributor** 

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

## Siemens:

3RA21254EA270BB4