## **SIEMENS**

## Data sheet 3RA2155-4XD37-0AP6

	Combination Starter Non Reversing Fast Bus FLA Range 49-59A 3 Pole 240VAC Coil S2 Open Type 1NO <(>&<)> 1NC Aux	
product brand name	SIRIUS	
product brand name	non-fused motor starter 3RA2	
product designation	direct starter	
design of the product manufacturer's article number	unect starter	
of the supplied contactor	3RT2037-1AP60	
of the supplied circuit-breakers	3RV2032-4XA15	
of the supplied busbar adapter	8US1261-6MT10	
of the supplied link module	3RA2931-1AA00	
General technical data	<u>014 (2001 - 174 (00</u>	
size of the circuit-breaker	S2	
size of load feeder	S2	
product extension auxiliary switch	Yes	
insulation voltage with degree of pollution 3 at AC rated value	690 V	
degree of pollution	3	
surge voltage resistance rated value	6 kV	
shock resistance according to IEC 60068-2-27	6g / 11 ms	
mechanical service life (operating cycles) of contactor typical	10 000 000	
type of assignment	2	
Weight	2.87 kg	
Ambient conditions		
ambient temperature		
during operation	-20 +60 °C	
during storage	-50 +80 °C	
during transport	-55 +80 °C	
Main circuit		
number of poles for main current circuit	3	
design of the switching contact	electromechanical	
adjustable current response value current of the current- dependent overload release	49 59 A	
operating voltage		
rated value	690 V	
at AC-3 rated value maximum	690 V	
operating frequency rated value	50 60 Hz	
operational current at AC-3 at 400 V rated value	55 A	
operating power at AC-3		
at 400 V rated value	30 000 W	
Control circuit/ Control		
control supply voltage at AC		
• at 50 Hz rated value	220 V	
• at 50 Hz rated value	176 242 V	
at 60 Hz rated value	240 V	
at 60 Hz rated value	192 264 V	
apparent holding power of magnet coil at AC	16 VA	
inductive power factor with the holding power of the coil	0.37	
Auxiliary circuit		
number of NC contacts for auxiliary contacts	2	
number of NO contacts for auxiliary contacts	2	
Protective and monitoring functions		
trip class	CLASS 10	
design of the overload release	thermal (bimetallic)	
response value current of instantaneous short-circuit trip unit	767 A	

UL/CSA ratings			
full-load current (FLA) for 3-phase AC motor			
<ul> <li>at 600 V rated value</li> </ul>	52 A		
yielded mechanical performance [hp]			
• for single-phase AC motor			
— at 110/120 V rated value	5 hp		
— at 230 V rated value	10 hp		
• for 3-phase AC motor			
— at 220/230 V rated value	20 hp		
— at 575/600 V rated value	50 hp		
Short-circuit protection			
product function short circuit protection	Yes		
design of the short-circuit trip	magnetic		
conditional short-circuit current (Iq)	- J		
at 400 V according to IEC 60947-4-1 rated value	150 000 A		
Installation/ mounting/ dimensions			
mounting position	vertical		
fastening method	for snapping onto 60 mm busba	ar systems	
height	350 mm	,	
width	55 mm		
depth	208 mm		
required spacing			
for grounded parts			
— forwards	0 mm		
— backwards	6 mm		
— upwards	50 mm		
— at the side	10 mm		
— downwards	10 mm		
• for live parts			
— forwards	0 mm		
— backwards	6 mm		
— upwards	50 mm		
— downwards	10 mm		
— at the side	10 mm		
Connections/ Terminals	TO THIN		
type of electrical connection for main current circuit	screw-type terminals		
type of connectable conductor cross-sections for main contacts stranded	1 50 mm², 2x (1 25 mm²)		
connectable conductor cross-section for main contacts finely stranded with core end processing	1 35 mm²		
Safety related data			
proportion of dangerous failures with high demand rate according to SN 31920	73 %		
B10 value with high demand rate according to SN 31920	1 000 000		
Electrical Safety			
protection class IP on the front according to IEC 60529	IP20		
touch protection on the front according to IEC 60529	finger-safe, for vertical contact	from the front	
Approvals Certificates			
General Product Approval		For use in hazard- ous locations	Test Certificates











Special Test Certificate

Marine / Shipping













Marine / Shipping other Railway **Dangerous goods Environment** 



Confirmation Special Test Certific-**Transport Information Environmental Con-**<u>ate</u> **firmations** 

Information on the packaging

https://support.industry.siemens.com/cs/ww/en/view/109813875

Information- and Downloadcenter (Catalogs, Brochures,...)

https://www.siemens.com/ic10

Industry Mall (Online ordering system)

https://mall.industry.siemens.com/mall/en/en/Catalog/product?mlfb=3RA2155-4XD37-0AP6

Cax online generator

http://support.automation.siemens.com/WW/CAXorder/default.aspx?lang=en&mlfb=3RA2155-4XD37-0AP6

Service&Support (Manuals, Certificates, Characteristics, FAQs,...)

https://support.industry.siemens.com/cs/ww/en/ps/3RA2155-4XD37-0AP6

Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, EPLAN macros, ...)

http://www.automation.siemens.com/bilddb/cax\_de.aspx?mlfb=3RA2155-4XD37-0AP6&lang=en

Characteristic: Tripping characteristics, I2t, Let-through current

https://support.industry.siemens.com/cs/ww/en/ps/3RA2155-4XD37-0AP6/char

Further characteristics (e.g. electrical endurance, switching frequency)
<a href="http://www.automation.siemens.com/bilddb/index.aspx?view=Search&mlfb=3RA2155-4XD37-0AP6&objecttype=14&gridview=view1">http://www.automation.siemens.com/bilddb/index.aspx?view=Search&mlfb=3RA2155-4XD37-0AP6&objecttype=14&gridview=view1</a>

last modified:	12/15/2020

## **Mouser Electronics**

**Authorized Distributor** 

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Siemens:

3RA21554XD370AP6