SIEMENS

Data sheet 3RT1055-6AP30



power contactor, AC-3e/AC-3 150 A, 75 kW / 400 V AC (50-60 Hz) / DC Uc: 220-240 V 3-pole, without auxiliary contacts drive: conventional main circuit: busbar control and auxiliary circuit: screw terminal

product brand name	SIRIUS
product designation	Power contactor
product type designation	3RT1
General technical data	
size of contactor	S6
product extension	
 function module for communication 	No
auxiliary switch	Yes
power loss [W] for rated value of the current	
 at AC in hot operating state 	27 W
 at AC in hot operating state per pole 	9 W
 without load current share typical 	5.2 W
insulation voltage	
 of main circuit with degree of pollution 3 rated value 	1 000 V
 of auxiliary circuit with degree of pollution 3 rated value 	500 V
surge voltage resistance	
of main circuit rated value	8 kV
of auxiliary circuit rated value	6 kV
maximum permissible voltage for protective separation between coil and main contacts according to EN 60947-1	690 V
shock resistance at rectangular impulse	
• at AC	8,5g / 5 ms, 4,2g / 10 ms
• at DC	8,5g / 5 ms, 4,2g / 10 ms
shock resistance with sine pulse	
• at AC	13,4g / 5 ms, 6,5g / 10 ms
• at DC	13,4g / 5 ms, 6,5g / 10 ms
mechanical service life (operating cycles)	
of contactor typical	10 000 000
 of the contactor with added electronically optimized auxiliary switch block typical 	5 000 000
 of the contactor with added auxiliary switch block typical 	10 000 000
reference code according to IEC 81346-2	Q
Substance Prohibitance (Date)	05/01/2012
SVHC substance name	Blei - 7439-92-1
Ambient conditions	
installation altitude at height above sea level maximum	2 000 m
ambient temperature	
 during operation 	-25 +60 °C
during storage	-55 +80 °C
relative humidity minimum	10 %
relative humidity at 55 °C according to IEC 60068-2-30	95 %

maximum	
ain circuit	
number of poles for main current circuit	3
number of NO contacts for main contacts	3
operating voltage	
at AC-3 rated value maximum	1 000 V
at AC-3e rated value maximum	1 000 V
operational current	
at AC-1 at 400 V at ambient temperature 40 °C rated	185 A
value	
• at AC-1	
— up to 690 V at ambient temperature 40 °C rated	185 A
value	
— up to 690 V at ambient temperature 60 °C rated	160 A
value	00.4
 up to 1000 V at ambient temperature 40 °C rated value 	90 A
— up to 1000 V at ambient temperature 60 °C rated	90 A
value	
• at AC-3	
— at 400 V rated value	150 A
— at 500 V rated value	150 A
— at 690 V rated value	150 A
— at 1000 V rated value	65 A
• at AC-3e	
— at 400 V rated value	150 A
— at 500 V rated value	150 A
— at 690 V rated value	150 A
— at 1000 V rated value	65 A
at AC-4 at 400 V rated value	132 A
at AC-5a up to 690 V rated value	162 A
at AC-5b up to 400 V rated value	124 A
• at AC-6a	
— up to 230 V for current peak value n=20 rated value	150 A
— up to 400 V for current peak value n=20 rated value	150 A
— up to 500 V for current peak value n=20 rated value	150 A
— up to 690 V for current peak value n=20 rated value	150 A
— up to 1000 V for current peak value n=20 rated	65 A
value	00 A
• at AC-6a	
— up to 230 V for current peak value n=30 rated value	105 A
— up to 400 V for current peak value n=30 rated value	105 A
— up to 500 V for current peak value n=30 rated value	105 A
— up to 690 V for current peak value n=30 rated value	105 A
— up to 1000 V for current peak value n=30 rated	65 A
value	
ninimum cross-section in main circuit at maximum AC-1 rated	95 mm²
perational current for approx. 200000 operating cycles at	
AC-4	68 A
at 400 V rated valueat 690 V rated value	68 A 57 A
operational current	OI A
at 1 current path at DC-1	
-	160 A
— at 24 V rated value	160 A 160 A
— at 60 V rated value	
— at 110 V rated value	18 A
— at 220 V rated value	3.4 A
— at 440 V rated value	0.8 A
— at 600 V rated value	0.5 A
with 2 current paths in series at DC-1	
— at 24 V rated value	160 A
— at 60 V rated value	160 A

— at 110 V rated value	160 A
— at 220 V rated value	20 A
— at 440 V rated value	3.2 A
— at 600 V rated value	1.6 A
 with 3 current paths in series at DC-1 	
— at 24 V rated value	160 A
— at 60 V rated value	160 A
— at 110 V rated value	160 A
— at 220 V rated value	160 A
— at 440 V rated value	11.5 A
— at 600 V rated value	4 A
 at 1 current path at DC-3 at DC-5 	
— at 24 V rated value	160 A
— at 60 V rated value	7.5 A
— at 220 V rated value	0.6 A
— at 440 V rated value	0.17 A
— at 600 V rated value	0.12 A
 with 2 current paths in series at DC-3 at DC-5 	
— at 24 V rated value	160 A
— at 60 V rated value	160 A
— at 110 V rated value	160 A
— at 220 V rated value	2.5 A
— at 440 V rated value	0.65 A
— at 600 V rated value	0.37 A
 with 3 current paths in series at DC-3 at DC-5 	
— at 24 V rated value	160 A
— at 60 V rated value	160 A
— at 110 V rated value	160 A
— at 220 V rated value	160 A
— at 440 V rated value	1.4 A
— at 600 V rated value	0.75 A
operating power	
• at AC-3	
— at 230 V rated value	45 kW
— at 400 V rated value	75 kW
— at 500 V rated value	90 kW
— at 690 V rated value	132 kW
— at 1000 V rated value	90 kW
• at AC-3e	
— at 230 V rated value	45 kW
— at 400 V rated value	75 kW
— at 500 V rated value	90 kW
— at 690 V rated value	132 kW
— at 1000 V rated value	90 kW
operating power for approx. 200000 operating cycles at AC-	
at 400 V rated value	38 kW
at 690 V rated value	55 kW
operating apparent power at AC-6a	
up to 230 V for current peak value n=20 rated value	60 000 kVA
up to 400 V for current peak value n=20 rated value	100 000 VA
 up to 500 V for current peak value n=20 rated value 	130 000 VA
up to 690 V for current peak value n=20 rated value	170 000 VA
up to 1000 V for current peak value n=20 rated value	110 000 VA
operating apparent power at AC-6a	
up to 230 V for current peak value n=30 rated value	40 000 VA
up to 400 V for current peak value n=30 rated value	70 000 VA
up to 500 V for current peak value n=30 rated value	90 000 VA
• up to 690 V for current peak value n=30 rated value	120 000 VA
 up to 1000 V for current peak value n=30 rated value 	110 000 VA
short-time withstand current in cold operating state up to	

40 °C		
limited to 1 s switching at zero current maximum	2 727 A; Use minimum cross-section acc. to AC-1 rated value	
 limited to 5 s switching at zero current maximum 	1 831 A; Use minimum cross-section acc. to AC-1 rated value	
 limited to 10 s switching at zero current maximum 	1 300 A; Use minimum cross-section acc. to AC-1 rated value	
 limited to 30 s switching at zero current maximum 	850 A; Use minimum cross-section acc. to AC-1 rated value	
Iimited to 60 s switching at zero current maximum	703 A; Use minimum cross-section acc. to AC-1 rated value	
no-load switching frequency		
• at AC	2 000 1/h	
• at DC	2 000 1/h	
operating frequency		
• at AC-1 maximum	800 1/h	
at AC-2 maximum	300 1/h	
• at AC-3 maximum	750 1/h	
at AC-3e maximum	750 1/h	
at AC-4 maximum	130 1/h	
Control circuit/ Control		
type of voltage of the control supply voltage	AC/DC	
control supply voltage at AC		
at 50 Hz rated value	220 240 V	
at 60 Hz rated value	220 240 V	
control supply voltage at DC		
rated value	220 240 V	
operating range factor control supply voltage rated value of magnet coil at DC		
• initial value	0.8	
• full-scale value	1.1	
operating range factor control supply voltage rated value of magnet coil at AC		
• at 50 Hz	0.8 1.1	
• at 60 Hz	0.8 1.1	
design of the surge suppressor	with varistor	
apparent pick-up power		
 at minimum rated control supply voltage at AC 		
— at 50 Hz	250 VA	
— at 60 Hz	250 VA	
 at maximum rated control supply voltage at AC 		
— at 60 Hz	300 VA	
— at 50 Hz	300 VA	
apparent pick-up power of magnet coil at AC		
• at 50 Hz	300 VA	
• at 60 Hz	300 VA	
inductive power factor with closing power of the coil		
● at 50 Hz	0.9	
• at 60 Hz	0.9	
apparent holding power		
 at minimum rated control supply voltage at DC 	4.3 VA	
 at maximum rated control supply voltage at DC 	5.2 VA	
apparent holding power		
 at minimum rated control supply voltage at AC 		
— at 50 Hz	4.8 VA	
— at 60 Hz	4.8 VA	
 at maximum rated control supply voltage at AC 		
— at 50 Hz	5.8 VA	
— at 60 Hz	5.8 VA	
apparent holding power of magnet coil at AC		
• at 50 Hz	5.8 VA	
● at 60 Hz	5.8 VA	
inductive power factor with the holding power of the coil		
• at 50 Hz	0.8	
• at 60 Hz	0.8	
closing power of magnet coil at DC	360 W	

halding payon of mag	E O W
holding power of magnet coil at DC	5.2 W
closing delay	20 05 722
• at AC	20 95 ms
• at DC	20 95 ms
opening delay	40 00
• at AC	40 60 ms
• at DC	40 60 ms
arcing time	10 15 ms Standard A1 - A2
control version of the switch operating mechanism UL/CSA ratings	Standard AT - AZ
full-load current (FLA) for 3-phase AC motor	
at 480 V rated value	156 A
at 600 V rated value	144 A
yielded mechanical performance [hp]	
• for single-phase AC motor	
— at 230 V rated value	30 hp
• for 3-phase AC motor	33 mg
— at 200/208 V rated value	50 hp
— at 220/230 V rated value	60 hp
— at 460/480 V rated value	125 hp
— at 575/600 V rated value	150 hp
Short-circuit protection	
design of the fuse link	
for short-circuit protection of the main circuit	
with type of coordination 1 required	gG: 355 A (690 V, 100 kA)
with type of assignment 2 required	gG: 315 A (690 V, 100 kA), aM: 200 A (690 V, 50 kA), BS88: 315 A (415 V, 50
yps s. doolgiment 2 required	kA)
• for short-circuit protection of the auxiliary switch required	gG: 10 A (500 V, 1 kA)
Installation/ mounting/ dimensions	
mounting position	with vertical mounting surface +/-90° rotatable, with vertical mounting surface +/- 22.5° tiltable to the front and back
fastening method	screw fixing
fastening method • side-by-side mounting	screw fixing Yes
	•
side-by-side mounting	Yes
• side-by-side mounting height	Yes 172 mm
side-by-side mounting height width	Yes 172 mm 120 mm
side-by-side mounting height width depth	Yes 172 mm 120 mm
side-by-side mounting height width depth required spacing	Yes 172 mm 120 mm
side-by-side mounting height width depth required spacing • with side-by-side mounting	Yes 172 mm 120 mm 170 mm
side-by-side mounting height width depth required spacing • with side-by-side mounting — forwards	Yes 172 mm 120 mm 170 mm
side-by-side mounting height width depth required spacing • with side-by-side mounting	Yes 172 mm 120 mm 170 mm 20 mm 10 mm
side-by-side mounting height width depth required spacing • with side-by-side mounting — forwards — upwards — downwards	Yes 172 mm 120 mm 170 mm 20 mm 10 mm
side-by-side mounting height width depth required spacing with side-by-side mounting — forwards — upwards — downwards — at the side	Yes 172 mm 120 mm 170 mm 20 mm 10 mm
side-by-side mounting height width depth required spacing • with side-by-side mounting — forwards — upwards — downwards — at the side • for grounded parts	Yes 172 mm 120 mm 170 mm 20 mm 10 mm 10 mm 0 mm
side-by-side mounting height width depth required spacing • with side-by-side mounting — forwards — upwards — downwards — at the side • for grounded parts — forwards	Yes 172 mm 120 mm 170 mm 20 mm 10 mm 10 mm 0 mm
side-by-side mounting height width depth required spacing with side-by-side mounting — forwards — upwards — downwards — at the side for grounded parts — forwards — upwards — upwards — upwards	Yes 172 mm 120 mm 170 mm 20 mm 10 mm 0 mm 0 mm
side-by-side mounting height width depth required spacing with side-by-side mounting — forwards — upwards — downwards — at the side for grounded parts — forwards — upwards — at the side of the side at the side — at the side	Yes 172 mm 120 mm 170 mm 20 mm 10 mm 0 mm 0 mm 10 mm 10 mm
side-by-side mounting height width depth required spacing with side-by-side mounting — forwards — upwards — downwards — at the side for grounded parts — forwards — upwards — at the side — downwards — at the side — downwards — at the side — downwards	Yes 172 mm 120 mm 170 mm 20 mm 10 mm 0 mm 0 mm 10 mm 10 mm
side-by-side mounting height width depth required spacing with side-by-side mounting — forwards — upwards — downwards — at the side for grounded parts — forwards — upwards — at the side for downwards — at the side — downwards — at the side — forwards — at the side — for live parts	Yes 172 mm 120 mm 170 mm 20 mm 10 mm 0 mm 0 mm 10 mm
side-by-side mounting height width depth required spacing with side-by-side mounting — forwards — upwards — downwards — at the side for grounded parts — forwards — upwards — at the side for grounded parts — forwards — upwards — at the side — downwards — at the side — downwards for live parts — forwards	Yes 172 mm 120 mm 170 mm 20 mm 10 mm 10 mm 0 mm 10 mm
side-by-side mounting height width depth required spacing with side-by-side mounting — forwards — upwards — downwards — at the side for grounded parts — forwards — upwards — at the side for grounded parts — forwards — upwards — at the side — downwards for live parts — forwards — upwards — at the side — downwards — at the side — downwards — upwards — at the side	Yes 172 mm 120 mm 170 mm 20 mm 10 mm 0 mm 0 mm 10 mm
side-by-side mounting height width depth required spacing with side-by-side mounting — forwards — upwards — downwards — at the side for grounded parts — forwards — upwards — at the side for grounded parts — forwards — upwards — at the side — downwards for live parts — forwards — upwards — at the side — downwards — at the side — downwards — upwards — at the side Connections/ Terminals	Yes 172 mm 120 mm 170 mm 20 mm 10 mm 0 mm 0 mm 20 mm 10 mm
side-by-side mounting height width depth required spacing with side-by-side mounting — forwards — upwards — downwards — at the side for grounded parts — forwards — upwards — at the side — downwards — forwards — upwards — at the side — downwards — upwards — at the side Connections/ Terminals type of electrical connection	Yes 172 mm 120 mm 170 mm 20 mm 10 mm 10 mm 0 mm 20 mm 10 mm
side-by-side mounting height width depth required spacing with side-by-side mounting — forwards — upwards — downwards — at the side for grounded parts — forwards — upwards — at the side — downwards — upwards — upwards — at the side Connections/ Terminals type of electrical connection for main current circuit	Yes 172 mm 120 mm 170 mm 20 mm 10 mm 0 mm 20 mm 10 mm
side-by-side mounting height width depth required spacing with side-by-side mounting forwards upwards downwards at the side for grounded parts forwards upwards at the side for grounded parts forwards upwards at the side downwards for live parts forwards upwards at the side downwards for live parts forwards upwards at the side Connections/ Terminals type of electrical connection for main current circuit for auxiliary and control circuit	Yes 172 mm 120 mm 170 mm 20 mm 10 mm 0 mm 20 mm 10 mm
side-by-side mounting height width depth required spacing with side-by-side mounting — forwards — upwards — downwards — at the side for grounded parts — forwards — upwards — at the side — downwards — in the side — downwards — upwards — upwards — at the side Connections/ Terminals type of electrical connection for main current circuit for auxiliary and control circuit of magnet coil	Yes 172 mm 120 mm 170 mm 20 mm 10 mm 0 mm 20 mm 10 mm 10 mm 10 mm 10 mm 10 mm 10 mm Connection bar screw-type terminals Screw-type terminals
side-by-side mounting height width depth required spacing with side-by-side mounting - forwards - upwards - downwards - at the side for grounded parts - forwards - upwards - at the side - downwards - at the side - downwards - at the side - downwards of for live parts - forwards - upwards - at the side Connections/ Terminals type of electrical connection of magnet coil width of connection bar	Yes 172 mm 120 mm 170 mm 20 mm 10 mm 0 mm 20 mm 10 mm 10 mm 10 mm 10 mm 10 mm Connection bar screw-type terminals Screw-type terminals Screw-type terminals 17 mm
side-by-side mounting height width depth required spacing	Yes 172 mm 120 mm 170 mm 20 mm 10 mm 0 mm 20 mm 10 mm 3 mm
side-by-side mounting height width depth required spacing • with side-by-side mounting — forwards — upwards — downwards — at the side • for grounded parts — forwards — upwards — at the side — downwards • for live parts — forwards — upwards — at the side — downwards • for live parts — forwards — upwards — at the side Connections/ Terminals type of electrical connection • for main current circuit • for auxiliary and control circuit • of magnet coil width of connection bar	Yes 172 mm 120 mm 170 mm 20 mm 10 mm 0 mm 20 mm 10 mm 10 mm 10 mm 10 mm 10 mm Connection bar screw-type terminals Screw-type terminals Screw-type terminals 17 mm

connectable conductor cross-section for main contacts	
stranded	25 120 mm²
connectable conductor cross-section for auxiliary contacts	
 solid or stranded 	0.5 4 mm²
 finely stranded with core end processing 	0.5 2.5 mm²
type of connectable conductor cross-sections	
 for auxiliary contacts 	
— solid	2x (0.5 1.5 mm²), 2x (0.75 2.5 mm²), max. 2x (0.75 4 mm²)
— solid or stranded	2x (0,5 1,5 mm²), 2x (0,75 2,5 mm²), max. 2x (0,75 4 mm²)
 finely stranded with core end processing 	2x (0.5 1.5 mm²), 2x (0.75 2.5 mm²)
for AWG cables for auxiliary contacts	2x (20 16), 2x (18 14), 1x 12
AWG number as coded connectable conductor cross section	
 for auxiliary contacts 	18 14
Safety related data	
product function	
 positively driven operation according to IEC 60947-5-1 	No
suitability for use safety-related switching OFF	Yes
B10 value with high demand rate according to SN 31920	1 000 000
T1 value for proof test interval or service life according to IEC 61508	20 a
protection class IP on the front according to IEC 60529	IP00; IP20 with box terminal/cover
touch protection on the front according to IEC 60529	finger-safe, for vertical contact from the front with box terminal/cover
Certificates/ approvals	

General Product Approval





Confirmation



<u>KC</u>



EMC S	Functional Safety/Safety of Ma- chinery	Declaration of Conformity	Test Certificates
-------	---	---------------------------	-------------------



Type Examination Certificate





Special Test Certificate

Type Test Certificates/Test Report

Marine / Shipping other











Miscellaneous

other	Railway
-------	---------

<u>Confirmation</u> <u>Miscellaneous</u> <u>Confirmation</u> <u>Vibration and Shock</u> <u>Special Test Certificate</u>

Further informatio

Siemens has decided to exit the Russian market (see here).

https://press.siemens.com/global/en/pressrelease/siemens-wind-down-russian-business

Siemens is working on the renewal of the current EAC certificates.

Please contact your local Siemens office on the status of validity of the EAC certification if you intend to import or offer to supply these products to an EAC relevant market (other than the sanctioned EAEU member states Russia or Belarus).

Information on the packaging

https://support.industry.siemens.com/cs/ww/en/view/109813875

Information- and Downloadcenter (Catalogs, Brochures,...)

https://www.siemens.com/ic10

Industry Mall (Online ordering system)
https://mall.industry.siemens.com/mall/en/en/Catalog/product?mlfb=3RT1055-6AP30

Cax online generator

http://support.automation.siemens.com/WW/CAXorder/default.aspx?lang=en&mlfb=3RT1055-6AP30

Service&Support (Manuals, Certificates, Characteristics, FAQs,...)


https://support.industry.siemens.com/cs/ww/en/ps/3RT1055-6AP30


Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, EPLAN macros, ...) http://www.automation.siemens.com/bilddb/cax_de.aspx?mlfb=3RT1055-6AP30&lang=en


Characteristic: Tripping characteristics, I²t, Let-through current

https://support.industry.siemens.com/cs/ww/en/ps/3RT1055-6AP30/char

Further characteristics (e.g. electrical endurance, switching frequency)
http://www.automation.siemens.com/bilddb/index.aspx?view=Search&mlfb=3RT1055-6AP30&objecttype=14&gridview=view1







last modified:

8/15/2023

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Siemens:

3RT10556AP30