# **SIEMENS**

Data sheet 3RT2036-1NE30



power contactor, AC-3e/AC-3, 51 A, 22 kW / 400 V, 3-pole, 48-80 V AC/DC, 50/60 Hz, with integrated varistor, auxiliary contacts: 1 NO + 1 NC, screw terminal, size: S2

product brand name	SIRIUS
product designation	Power contactor
product type designation	3RT2
General technical data	
size of contactor	S2
product extension	
<ul> <li>function module for communication</li> </ul>	No
auxiliary switch	Yes
power loss [W] for rated value of the current	
<ul> <li>at AC in hot operating state</li> </ul>	12 W
<ul> <li>at AC in hot operating state per pole</li> </ul>	4 W
without load current share typical	1 W
insulation voltage	
<ul> <li>of main circuit with degree of pollution 3 rated value</li> </ul>	690 V
of auxiliary circuit with degree of pollution 3 rated value	690 V
surge voltage resistance	
<ul> <li>of main circuit rated value</li> </ul>	6 kV
of auxiliary circuit rated value	6 kV
maximum permissible voltage for protective separation between coil and main contacts according to EN 60947-1	400 V
shock resistance at rectangular impulse	
• at AC	7.7g / 5 ms, 4.5g / 10 ms
• at DC	7.7g / 5 ms, 4.5g / 10 ms
shock resistance with sine pulse	
• at AC	12g / 5 ms, 7g / 10 ms
• at DC	12g / 5 ms, 7g / 10 ms
mechanical service life (operating cycles)	
<ul> <li>of contactor typical</li> </ul>	10 000 000
<ul> <li>of the contactor with added electronically optimized auxiliary switch block typical</li> </ul>	5 000 000
of the contactor with added auxiliary switch block typical	10 000 000
reference code according to IEC 81346-2	Q
Substance Prohibitance (Date)	10/01/2014
SVHC substance name	Blei - 7439-92-1 Bleimonoxid (Bleioxid) - 1317-36-8
Ambient conditions	
installation altitude at height above sea level maximum	2 000 m
ambient temperature	
<ul> <li>during operation</li> </ul>	-25 +60 °C
during storage	-55 +80 °C
relative humidity minimum	10 %

relative humidity at 55 °C according to IEC 60068-2-30 maximum	95 %
ain circuit	
number of poles for main current circuit	3
number of NO contacts for main contacts	3
operating voltage	
<ul> <li>at AC-3 rated value maximum</li> </ul>	690 V
at AC-3e rated value maximum	690 V
operational current	
at AC-1 at 400 V at ambient temperature 40 °C rated value	70 A
<ul> <li>at AC-1         — up to 690 V at ambient temperature 40 °C rated value     </li> </ul>	70 A
— up to 690 V at ambient temperature 60 °C rated value	60 A
• at AC-3	
— at 400 V rated value	51 A
— at 500 V rated value	51 A
— at 690 V rated value	24 A
• at AC-3e	
— at 400 V rated value	51 A
— at 500 V rated value	51 A
— at 690 V rated value	24 A
at AC-4 at 400 V rated value	41 A
• at AC-5a up to 690 V rated value	61.6 A
at AC-5b up to 400 V rated value	41.5 A
• at AC-6a	
— up to 230 V for current peak value n=20 rated value	43.2 A
— up to 400 V for current peak value n=20 rated value	43.2 A
— up to 500 V for current peak value n=20 rated value	43.2 A
— up to 690 V for current peak value n=20 rated value	24 A
• at AC-6a	
— up to 230 V for current peak value n=30 rated value	28.8 A
— up to 400 V for current peak value n=30 rated value	28.8 A
— up to 500 V for current peak value n=30 rated value	28.8 A
— up to 690 V for current peak value n=30 rated value	24 A
minimum cross-section in main circuit at maximum AC-1 rated value	25 mm²
operational current for approx. 200000 operating cycles at AC-4	
at 400 V rated value	24 A
at 690 V rated value	20 A
operational current	
at 1 current path at DC-1	
— at 24 V rated value	55 A
— at 60 V rated value	23 A
— at 110 V rated value	4.5 A
— at 220 V rated value	1 A
— at 440 V rated value	0.4 A
— at 600 V rated value	0.25 A
<ul><li>with 2 current paths in series at DC-1</li></ul>	
— at 24 V rated value	55 A
— at 60 V rated value	45 A
— at 110 V rated value	45 A
— at 220 V rated value	5 A
— at 440 V rated value	1 A
— at 600 V rated value	0.8 A
<ul> <li>with 3 current paths in series at DC-1</li> </ul>	
— at 24 V rated value	55 A
— at 60 V rated value	55 A

— at 220 V rated value	45 A
— at 440 V rated value	2.9 A
— at 600 V rated value	1.4 A
<ul> <li>at 1 current path at DC-3 at DC-5</li> </ul>	
— at 24 V rated value	35 A
— at 60 V rated value	6 A
— at 220 V rated value	1 A
— at 440 V rated value	0.1 A
— at 600 V rated value	0.06 A
<ul> <li>with 2 current paths in series at DC-3 at DC-5</li> </ul>	
— at 24 V rated value	55 A
— at 60 V rated value	45 A
— at 110 V rated value	25 A
— at 220 V rated value	5 A
— at 440 V rated value	0.27 A
— at 600 V rated value	0.16 A
<ul> <li>with 3 current paths in series at DC-3 at DC-5</li> </ul>	
— at 24 V rated value	55 A
— at 60 V rated value	55 A
— at 110 V rated value	55 A
— at 220 V rated value	25 A
— at 440 V rated value	0.6 A
— at 600 V rated value	0.35 A
operating power	
at AC-2 at 400 V rated value	22 kW
• at AC-3	
— at 230 V rated value	15 kW
— at 400 V rated value	22 kW
— at 500 V rated value	22 kW
— at 690 V rated value	22 kW
• at AC-3e	
— at 400 V rated value	22 kW
— at 500 V rated value	22 kW
— at 690 V rated value	22 kW
operating power for approx. 200000 operating cycles at AC-	
4	
<ul> <li>at 400 V rated value</li> </ul>	12.6 kW
at 690 V rated value	18.2 kW
operating apparent power at AC-6a	
<ul> <li>up to 230 V for current peak value n=20 rated value</li> </ul>	17.2 kVA
• up to 400 V for current peak value n=20 rated value	29.9 kVA
• up to 500 V for current peak value n=20 rated value	37.4 kVA
• up to 690 V for current peak value n=20 rated value	28.6 kVA
operating apparent power at AC-6a	
• up to 230 V for current peak value n=30 rated value	11.4 kVA
• up to 400 V for current peak value n=30 rated value	19.9 kVA
• up to 500 V for current peak value n=30 rated value	24.9 kVA
• up to 690 V for current peak value n=30 rated value	28.6 kVA
short-time withstand current in cold operating state up to 40 °C	
<ul> <li>limited to 1 s switching at zero current maximum</li> </ul>	937 A; Use minimum cross-section acc. to AC-1 rated value
• limited to 5 s switching at zero current maximum	697 A; Use minimum cross-section acc. to AC-1 rated value
limited to 10 s switching at zero current maximum	468 A; Use minimum cross-section acc. to AC-1 rated value
• limited to 30 s switching at zero current maximum	282 A; Use minimum cross-section acc. to AC-1 rated value
• limited to 60 s switching at zero current maximum	229 A; Use minimum cross-section acc. to AC-1 rated value
no-load switching frequency	
• at AC	1 500 1/h
• at DC	1 500 1/h
operating frequency	
• at AC-1 maximum	1 000 1/h
• at AC-2 maximum	600 1/h

a at AC 2 maximum	900 4 lb
• at AC-3 maximum	800 1/h
• at AC-3e maximum	800 1/h
• at AC-4 maximum	250 1/h
Control circuit/ Control	
type of voltage of the control supply voltage	AC/DC
control supply voltage at AC	
at 50 Hz rated value	48 80 V
at 60 Hz rated value	48 80 V
control supply voltage at DC	
rated value	48 80 V
operating range factor control supply voltage rated value of	
magnet coil at DC	0.0
• initial value	0.8
full-scale value	1.1
operating range factor control supply voltage rated value of magnet coil at AC	
• at 50 Hz	0.8 1.1
• at 60 Hz	0.8 1.1
design of the surge suppressor	with varistor
inrush current peak	1 A
duration of inrush current peak	30 µs
locked-rotor current mean value	0.5 A
locked-rotor current mean value	1.A
duration of locked-rotor current	230 ms
holding current mean value	15 mA
apparent pick-up power of magnet coil at AC  • at 50 Hz	40 VA
• at 60 Hz	40 VA
apparent holding power	2.1/4
at minimum rated control supply voltage at DC	2 VA
at maximum rated control supply voltage at DC	2 VA
apparent holding power	
at minimum rated control supply voltage at AC	
— at 50 Hz	2 VA
— at 60 Hz	2 VA
<ul> <li>at maximum rated control supply voltage at AC</li> </ul>	
— at 50 Hz	2 VA
— at 60 Hz	2 VA
apparent holding power of magnet coil at AC	
• at 50 Hz	2 VA
at 60 Hz	2 VA
inductive power factor with the holding power of the coil	
• at 50 Hz	0.95
• at 60 Hz	0.95
closing power of magnet coil at DC	23 W
holding power of magnet coil at DC	1 W
closing delay	
• at AC	35 110 ms
at AC  at DC	35 110 ms 35 110 ms
• at DC	
at DC     opening delay	35 110 ms
at DC     opening delay     at AC	35 110 ms 30 55 ms
at DC  opening delay  at AC  at DC	35 110 ms 30 55 ms 30 55 ms
at DC  opening delay  at AC  at DC  arcing time	35 110 ms 30 55 ms 30 55 ms 10 20 ms
at DC  opening delay  at AC  at DC  arcing time  control version of the switch operating mechanism	35 110 ms 30 55 ms 30 55 ms 10 20 ms
at DC     opening delay         at AC         at DC     arcing time     control version of the switch operating mechanism     Auxiliary circuit number of NC contacts for auxiliary contacts instantaneous	35 110 ms  30 55 ms  30 55 ms  10 20 ms  Standard A1 - A2
at DC     opening delay         at AC         at DC     arcing time     control version of the switch operating mechanism     Auxiliary circuit     number of NC contacts for auxiliary contacts instantaneous contact     number of NO contacts for auxiliary contacts instantaneous	35 110 ms  30 55 ms 30 55 ms 10 20 ms Standard A1 - A2
at DC  opening delay     at AC     at DC  arcing time  control version of the switch operating mechanism  Auxiliary circuit  number of NC contacts for auxiliary contacts instantaneous contact  number of NO contacts for auxiliary contacts instantaneous contact	35 110 ms  30 55 ms  30 55 ms  10 20 ms  Standard A1 - A2
at DC  opening delay  at AC  at DC  arcing time  control version of the switch operating mechanism  Auxiliary circuit  number of NC contacts for auxiliary contacts instantaneous contact  number of NO contacts for auxiliary contacts instantaneous contact  operational current at AC-12 maximum	35 110 ms  30 55 ms  30 55 ms  10 20 ms  Standard A1 - A2

• at 400 V rated value	3 A
• at 500 V rated value	2 A
at 690 V rated value	1 A
operational current at DC-12	
• at 24 V rated value	10 A
at 48 V rated value	6 A
<ul> <li>at 60 V rated value</li> </ul>	6 A
<ul> <li>at 110 V rated value</li> </ul>	3 A
<ul> <li>at 125 V rated value</li> </ul>	2 A
<ul> <li>at 220 V rated value</li> </ul>	1 A
at 600 V rated value	0.15 A
operational current at DC-13	
<ul> <li>at 24 V rated value</li> </ul>	10 A
<ul> <li>at 48 V rated value</li> </ul>	2 A
at 60 V rated value	2 A
<ul> <li>at 110 V rated value</li> </ul>	1 A
• at 125 V rated value	0.9 A
at 220 V rated value	0.3 A
• at 600 V rated value	0.1 A
contact reliability of auxiliary contacts	1 faulty switching per 100 million (17 V, 1 mA)
UL/CSA ratings	, , ,
full-load current (FLA) for 3-phase AC motor	
• at 480 V rated value	52 A
at 400 V rated value     at 600 V rated value	52 A 52 A
yielded mechanical performance [hp]	32 A
for single-phase AC motor	
— at 110/120 V rated value	2 ha
	3 hp
— at 230 V rated value	10 hp
• for 3-phase AC motor	451
— at 200/208 V rated value	15 hp
— at 220/230 V rated value	15 hp
— at 460/480 V rated value	40 hp
— at 575/600 V rated value	50 hp
contact rating of auxiliary contacts according to UL	A600 / P600
Short-circuit protection	
design of the fuse link	
<ul> <li>for short-circuit protection of the main circuit</li> </ul>	
— with type of coordination 1 required	gG: 160 A (690 V, 100 kA), aM: 80 A (690 V, 100 kA), BS88: 125 A (415 V, 80 kA)
<ul><li>— with type of coordination 1 required</li><li>— with type of assignment 2 required</li></ul>	
	kA)
— with type of assignment 2 required	kA) gG: 80A (690V,100kA), aM: 50A (690V,100kA), BS88: 63A (415V,80kA)
with type of assignment 2 required  • for short-circuit protection of the auxiliary switch required	kA) gG: 80A (690V,100kA), aM: 50A (690V,100kA), BS88: 63A (415V,80kA)
with type of assignment 2 required     for short-circuit protection of the auxiliary switch required  Installation/ mounting/ dimensions	kA) gG: 80A (690V,100kA), aM: 50A (690V,100kA), BS88: 63A (415V,80kA) gG: 10 A (500 V, 1 kA)  +/-180° rotation possible on vertical mounting surface; can be tilted forward and
— with type of assignment 2 required  • for short-circuit protection of the auxiliary switch required  Installation/ mounting/ dimensions  mounting position	GS: 80A (690V,100kA), aM: 50A (690V,100kA), BS88: 63A (415V,80kA) gG: 10 A (500 V, 1 kA)  +/-180° rotation possible on vertical mounting surface; can be tilted forward and backward by +/- 22.5° on vertical mounting surface
— with type of assignment 2 required  • for short-circuit protection of the auxiliary switch required  Installation/ mounting/ dimensions  mounting position  fastening method	gG: 80A (690V,100kA), aM: 50A (690V,100kA), BS88: 63A (415V,80kA) gG: 10 A (500 V, 1 kA)  +/-180° rotation possible on vertical mounting surface; can be tilted forward and backward by +/- 22.5° on vertical mounting surface screw and snap-on mounting onto 35 mm DIN rail according to DIN EN 60715
— with type of assignment 2 required  • for short-circuit protection of the auxiliary switch required  Installation/ mounting/ dimensions  mounting position  fastening method  • side-by-side mounting	gG: 80A (690V,100kA), aM: 50A (690V,100kA), BS88: 63A (415V,80kA) gG: 10 A (500 V, 1 kA)  +/-180° rotation possible on vertical mounting surface; can be tilted forward and backward by +/- 22.5° on vertical mounting surface screw and snap-on mounting onto 35 mm DIN rail according to DIN EN 60715 Yes
— with type of assignment 2 required  • for short-circuit protection of the auxiliary switch required  Installation/ mounting/ dimensions  mounting position  fastening method  • side-by-side mounting  height	G: 80A (690V,100kA), aM: 50A (690V,100kA), BS88: 63A (415V,80kA) gG: 10 A (500 V, 1 kA)  +/-180° rotation possible on vertical mounting surface; can be tilted forward and backward by +/- 22.5° on vertical mounting surface screw and snap-on mounting onto 35 mm DIN rail according to DIN EN 60715 Yes 114 mm
— with type of assignment 2 required  • for short-circuit protection of the auxiliary switch required  Installation/ mounting/ dimensions  mounting position  fastening method  • side-by-side mounting  height  width	G: 80A (690V,100kA), aM: 50A (690V,100kA), BS88: 63A (415V,80kA) gG: 10 A (500 V, 1 kA)  +/-180° rotation possible on vertical mounting surface; can be tilted forward and backward by +/- 22.5° on vertical mounting surface screw and snap-on mounting onto 35 mm DIN rail according to DIN EN 60715 Yes 114 mm 55 mm
— with type of assignment 2 required  • for short-circuit protection of the auxiliary switch required  Installation/ mounting/ dimensions  mounting position  fastening method  • side-by-side mounting  height  width  depth	G: 80A (690V,100kA), aM: 50A (690V,100kA), BS88: 63A (415V,80kA) gG: 10 A (500 V, 1 kA)  +/-180° rotation possible on vertical mounting surface; can be tilted forward and backward by +/- 22.5° on vertical mounting surface screw and snap-on mounting onto 35 mm DIN rail according to DIN EN 60715 Yes 114 mm 55 mm
— with type of assignment 2 required  • for short-circuit protection of the auxiliary switch required  Installation/ mounting/ dimensions  mounting position  fastening method  • side-by-side mounting  height  width  depth  required spacing	G: 80A (690V,100kA), aM: 50A (690V,100kA), BS88: 63A (415V,80kA) gG: 10 A (500 V, 1 kA)  +/-180° rotation possible on vertical mounting surface; can be tilted forward and backward by +/- 22.5° on vertical mounting surface screw and snap-on mounting onto 35 mm DIN rail according to DIN EN 60715 Yes 114 mm 55 mm
— with type of assignment 2 required  • for short-circuit protection of the auxiliary switch required  Installation/ mounting/ dimensions  mounting position  fastening method  • side-by-side mounting  height  width  depth  required spacing  • with side-by-side mounting	G: 80A (690V,100kA), aM: 50A (690V,100kA), BS88: 63A (415V,80kA) gG: 10 A (500 V, 1 kA)  +/-180° rotation possible on vertical mounting surface; can be tilted forward and backward by +/- 22.5° on vertical mounting surface screw and snap-on mounting onto 35 mm DIN rail according to DIN EN 60715 Yes 114 mm 55 mm 130 mm
— with type of assignment 2 required  • for short-circuit protection of the auxiliary switch required  Installation/ mounting/ dimensions  mounting position  fastening method  • side-by-side mounting  height  width  depth  required spacing  • with side-by-side mounting  — forwards	KA) gG: 80A (690V,100kA), aM: 50A (690V,100kA), BS88: 63A (415V,80kA) gG: 10 A (500 V, 1 kA)  +/-180° rotation possible on vertical mounting surface; can be tilted forward and backward by +/- 22.5° on vertical mounting surface screw and snap-on mounting onto 35 mm DIN rail according to DIN EN 60715 Yes 114 mm 55 mm 130 mm
<ul> <li>with type of assignment 2 required</li> <li>for short-circuit protection of the auxiliary switch required</li> <li>Installation/ mounting/ dimensions</li> <li>mounting position</li> <li>fastening method</li> <li>side-by-side mounting</li> <li>height</li> <li>width</li> <li>depth</li> <li>required spacing</li> <li>with side-by-side mounting</li> <li>forwards</li> <li>upwards</li> </ul>	KA) gG: 80A (690V,100kA), aM: 50A (690V,100kA), BS88: 63A (415V,80kA) gG: 10 A (500 V, 1 kA)  +/-180° rotation possible on vertical mounting surface; can be tilted forward and backward by +/- 22.5° on vertical mounting surface screw and snap-on mounting onto 35 mm DIN rail according to DIN EN 60715 Yes 114 mm 55 mm 130 mm
<ul> <li>with type of assignment 2 required</li> <li>for short-circuit protection of the auxiliary switch required</li> <li>Installation/ mounting/ dimensions</li> <li>mounting position</li> <li>fastening method</li> <li>side-by-side mounting</li> <li>height</li> <li>width</li> <li>depth</li> <li>required spacing</li> <li>with side-by-side mounting</li> <li>forwards</li> <li>upwards</li> <li>downwards</li> </ul>	KA) gG: 80A (690V,100kA), aM: 50A (690V,100kA), BS88: 63A (415V,80kA) gG: 10 A (500 V, 1 kA)  +/-180° rotation possible on vertical mounting surface; can be tilted forward and backward by +/- 22.5° on vertical mounting surface screw and snap-on mounting onto 35 mm DIN rail according to DIN EN 60715 Yes 114 mm 55 mm 130 mm
<ul> <li>with type of assignment 2 required</li> <li>for short-circuit protection of the auxiliary switch required</li> <li>Installation/ mounting/ dimensions</li> <li>mounting position</li> <li>fastening method</li> <li>side-by-side mounting</li> <li>height</li> <li>width</li> <li>depth</li> <li>required spacing</li> <li>with side-by-side mounting</li> <li>forwards</li> <li>upwards</li> <li>downwards</li> <li>at the side</li> </ul>	KA) gG: 80A (690V,100kA), aM: 50A (690V,100kA), BS88: 63A (415V,80kA) gG: 10 A (500 V, 1 kA)  +/-180° rotation possible on vertical mounting surface; can be tilted forward and backward by +/- 22.5° on vertical mounting surface screw and snap-on mounting onto 35 mm DIN rail according to DIN EN 60715 Yes 114 mm 55 mm 130 mm
<ul> <li>with type of assignment 2 required</li> <li>for short-circuit protection of the auxiliary switch required</li> <li>Installation/ mounting/ dimensions</li> <li>mounting position</li> <li>fastening method         <ul> <li>side-by-side mounting</li> </ul> </li> <li>height         <ul> <li>width</li> <li>depth</li> </ul> </li> <li>required spacing         <ul> <li>with side-by-side mounting</li> <li>forwards</li> <li>upwards</li> <li>downwards</li> <li>at the side</li> </ul> </li> <li>for grounded parts</li> </ul>	KA) gG: 80A (690V,100kA), aM: 50A (690V,100kA), BS88: 63A (415V,80kA) gG: 10 A (500 V, 1 kA)  +/-180° rotation possible on vertical mounting surface; can be tilted forward and backward by +/- 22.5° on vertical mounting surface screw and snap-on mounting onto 35 mm DIN rail according to DIN EN 60715 Yes 114 mm 55 mm 130 mm  10 mm 10 mm 10 mm 0 mm
<ul> <li>with type of assignment 2 required</li> <li>for short-circuit protection of the auxiliary switch required</li> <li>Installation/ mounting/ dimensions</li> <li>mounting position</li> <li>fastening method</li> <li>side-by-side mounting</li> <li>height</li> <li>width</li> <li>depth</li> <li>required spacing</li> <li>with side-by-side mounting</li> <li>forwards</li> <li>upwards</li> <li>downwards</li> <li>at the side</li> <li>for grounded parts</li> <li>forwards</li> </ul>	KA) gG: 80A (690V,100kA), aM: 50A (690V,100kA), BS88: 63A (415V,80kA) gG: 10 A (500 V, 1 kA)  +/-180° rotation possible on vertical mounting surface; can be tilted forward and backward by +/- 22.5° on vertical mounting surface screw and snap-on mounting onto 35 mm DIN rail according to DIN EN 60715 Yes  114 mm 55 mm 130 mm  10 mm 10 mm 10 mm 10 mm
<ul> <li>with type of assignment 2 required</li> <li>for short-circuit protection of the auxiliary switch required</li> <li>Installation/ mounting/ dimensions</li> <li>mounting position</li> <li>fastening method         <ul> <li>side-by-side mounting</li> <li>height</li> <li>width</li> <li>depth</li> </ul> </li> <li>required spacing         <ul> <li>with side-by-side mounting</li> <li>forwards</li> <li>upwards</li> <li>downwards</li> <li>at the side</li> </ul> </li> <li>for grounded parts</li> <li>forwards</li> <li>upwards</li> <li>upwards</li> <li>upwards</li> </ul>	KA) gG: 80A (690V,100kA), aM: 50A (690V,100kA), BS88: 63A (415V,80kA) gG: 10 A (500 V, 1 kA)  +/-180° rotation possible on vertical mounting surface; can be tilted forward and backward by +/- 22.5° on vertical mounting surface screw and snap-on mounting onto 35 mm DIN rail according to DIN EN 60715 Yes  114 mm 55 mm 130 mm  10 mm 10 mm 10 mm 10 mm
<ul> <li>with type of assignment 2 required</li> <li>for short-circuit protection of the auxiliary switch required</li> <li>Installation/ mounting/ dimensions</li> <li>mounting position</li> <li>fastening method         <ul> <li>side-by-side mounting</li> </ul> </li> <li>height         <ul> <li>width</li> <li>depth</li> </ul> </li> <li>required spacing         <ul> <li>with side-by-side mounting</li> <li>forwards</li> <li>upwards</li> <li>downwards</li> <li>at the side</li> </ul> </li> <li>for grounded parts         <ul> <li>forwards</li> <li>upwards</li> <li>at the side</li> </ul> </li> </ul>	KA) gG: 80A (690V,100kA), aM: 50A (690V,100kA), BS88: 63A (415V,80kA) gG: 10 A (500 V, 1 kA)  +/-180° rotation possible on vertical mounting surface; can be tilted forward and backward by +/- 22.5° on vertical mounting surface screw and snap-on mounting onto 35 mm DIN rail according to DIN EN 60715 Yes 114 mm 55 mm 130 mm 10 mm

— forwards	10 mm
— upwards	10 mm
— downwards	10 mm
— at the side	6 mm
Connections/ Terminals	
type of electrical connection	
for main current circuit	screw-type terminals
<ul> <li>for auxiliary and control circuit</li> </ul>	screw-type terminals
<ul> <li>at contactor for auxiliary contacts</li> </ul>	Screw-type terminals
of magnet coil	Screw-type terminals
type of connectable conductor cross-sections for main contacts	
<ul> <li>solid or stranded</li> </ul>	2x (1 35 mm²), 1x (1 50 mm²)
<ul> <li>finely stranded with core end processing</li> </ul>	2x (1 25 mm²), 1x (1 35 mm²)
connectable conductor cross-section for main contacts	
<ul> <li>finely stranded with core end processing</li> </ul>	1 35 mm²
connectable conductor cross-section for auxiliary contacts	
<ul> <li>solid or stranded</li> </ul>	0.5 2.5 mm²
<ul> <li>finely stranded with core end processing</li> </ul>	0.5 2.5 mm²
type of connectable conductor cross-sections	
for auxiliary contacts	
— solid or stranded	2x (0.5 1.5 mm²), 2x (0.75 2.5 mm²)
<ul> <li>finely stranded with core end processing</li> </ul>	2x (0.5 1.5 mm²), 2x (0.75 2.5 mm²)
<ul> <li>for AWG cables for auxiliary contacts</li> </ul>	2x (20 16), 2x (18 14)
AWG number as coded connectable conductor cross section	
• for main contacts	18 1
for auxiliary contacts	20 14
Safety related data	
product function	
<ul> <li>mirror contact according to IEC 60947-4-1</li> </ul>	Yes
<ul> <li>positively driven operation according to IEC 60947-5-1</li> </ul>	No
suitability for use safety-related switching OFF	Yes
B10 value with high demand rate according to SN 31920	1 000 000
proportion of dangerous failures	
with low demand rate according to SN 31920	40 %
with high demand rate according to SN 31920	73 %
failure rate [FIT] with low demand rate according to SN 31920	100 FIT
T1 value for proof test interval or service life according to IEC 61508	20 a
protection class IP on the front according to IEC 60529	IP20
touch protection on the front according to IEC 60529	finger-safe, for vertical contact from the front
Certificates/ approvals	

### **General Product Approval**





Confirmation



Miscellaneous

<u>KC</u>

General Product Approval

EMC

Functional Safety/Safety of Machinery

**Declaration of Conformity** 

**Test Certificates** 

EHC



Type Examination Certificate





Type Test Certificates/Test Report

**Test Certificates** 

Marine / Shipping











Marine / Shipping other Railway **Dangerous Good** 





Vibration and Shock **Transport Information** Confirmation Confirmation

#### **Environment**

**Environmental Confirmations** 

#### Further information

Siemens has decided to exit the Russian market (see here).

https://press.siemens.com/global/en/pressrelease/siemens-wind-down-russian-business

Siemens is working on the renewal of the current EAC certificates.

Please contact your local Siemens office on the status of validity of the EAC certification if you intend to import or offer to supply these products to an EAC relevant market (other than the sanctioned EAEU member states Russia or Belarus).

Information on the packaging

https://support.industry.siemens.com/cs/ww/en/view/109813875

Information- and Downloadcenter (Catalogs, Brochures,...)

https://www.siemens.com/ic10

Industry Mall (Online ordering system)

https://mall.industry.siemens.com/mall/en/en/Catalog/product?mlfb=3RT2036-1NE30

Cax online generator

http://support.automation.siemens.com/WW/CAXorder/default.aspx?lang=en&mlfb=3RT2036-1NE30

Service&Support (Manuals, Certificates, Characteristics, FAQs,...)

https://support.industry.siemens.com/cs/ww/en/ps/3RT2036-1NE30


Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, EPLAN macros, ...)


http://www.automation.siemens.com/bilddb/cax\_de.aspx?mlfb=3RT2036-1NE30&lang=en


Characteristic: Tripping characteristics, I2t, Let-through current


https://support.industry.siemens.com/cs/ww/en/ps/3RT2036-1NE30/char

Further characteristics (e.g. electrical endurance, switching frequency)
http://www.automation.siemens.com/bilddb/index.aspx?view=Search&mlfb=3RT2036-1NE30&objecttype=14&gridview=view1










last modified:

8/15/2023



## **Mouser Electronics**

**Authorized Distributor** 

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Siemens:

3RT20361NE30