SIEMENS

Data sheet

3RT2046-3KB40



power contactor, AC-3e/AC-3, 95 A, 45 kW / 400 V, 3-pole, 24 V DC, 0.8-1.2* Us, with integrated varistor, auxiliary contacts: 1 NO + 1 NC, integrated varistor, main circuit: screw terminal, control and auxiliary circuit: spring-loaded terminal, size: S3, suitable for PLC outputs

product brand name	SIRIUS
product designation	Coupling contactor
product type designation	3RT2
General technical data	
size of contactor	S3
product extension	
 function module for communication 	No
 auxiliary switch 	Yes
power loss [W] for rated value of the current	
 at AC in hot operating state 	19.8 W
 at AC in hot operating state per pole 	6.6 W
 without load current share typical 	0.9 W
insulation voltage	
 of main circuit with degree of pollution 3 rated value 	1 000 V
 of auxiliary circuit with degree of pollution 3 rated value 	690 V
surge voltage resistance	
 of main circuit rated value 	8 kV
 of auxiliary circuit rated value 	6 kV
maximum permissible voltage for protective separation between coil and main contacts according to EN 60947-1	690 V
shock resistance at rectangular impulse	
• at AC	10.3g / 5 ms, 6,.g / 10 ms
• at DC	6.3 g / 5 ms, 3.6 g / 10 ms
shock resistance with sine pulse	
• at AC	16.3g / 5 ms, 10.g / 10 ms
• at DC	9.8 g / 5 ms, 5.6 g / 10 ms
mechanical service life (operating cycles)	
 of contactor typical 	10 000 000
 of the contactor with added electronically optimized auxiliary switch block typical 	5 000 000
 of the contactor with added auxiliary switch block typical 	10 000 000
reference code according to IEC 81346-2	Q
Substance Prohibitance (Date)	03/01/2017
SVHC substance name	Blei - 7439-92-1 Bleimonoxid (Bleioxid) - 1317-36-8
Ambient conditions	
installation altitude at height above sea level maximum	2 000 m
ambient temperature	
during operation	-25 +60 °C
during storage	-55 +80 °C
relative humidity minimum	10 %

relative humidity at 55 °C according to IEC 60068-2-30 maximum	95 %
lain circuit	
number of poles for main current circuit	3
number of NO contacts for main contacts	3
operating voltage	
 at AC-3 rated value maximum 	1 000 V
 at AC-3e rated value maximum 	1 000 V
operational current	
at AC-1 at 400 V at ambient temperature 40 °C rated value	130 A
 at AC-1 up to 690 V at ambient temperature 40 °C rated value 	130 A
— up to 690 V at ambient temperature 60 °C rated value	110 A
• at AC-3	
— at 400 V rated value	95 A
— at 500 V rated value	95 A
— at 690 V rated value	78 A
— at 1000 V rated value	30 A
• at AC-3e	
— at 400 V rated value	95 A
— at 500 V rated value	95 A
— at 690 V rated value	78 A
— at 1000 V rated value	30 A
• at AC-4 at 400 V rated value	80 A
 at AC-5a up to 690 V rated value 	114 A
 at AC-5b up to 400 V rated value 	95 A
• at AC-6a	
— up to 230 V for current peak value n=20 rated value	84.4 A
— up to 400 V for current peak value n=20 rated value	84.4 A
— up to 500 V for current peak value n=20 rated value	84.4 A
— up to 690 V for current peak value n=20 rated value	58 A
• at AC-6a	
— up to 230 V for current peak value n=30 rated value	56.3 A
— up to 400 V for current peak value n=30 rated value	56.3 A
— up to 500 V for current peak value n=30 rated value	56.3 A
— up to 690 V for current peak value n=30 rated value	56.3 A
minimum cross-section in main circuit at maximum AC-1 rated value	50 mm ²
operational current for approx. 200000 operating cycles at AC-4	
• at 400 V rated value	42 A
• at 690 V rated value	30 A
operational current	
 at 1 current path at DC-1 	
— at 24 V rated value	100 A
— at 60 V rated value	60 A
— at 110 V rated value	9 A
— at 220 V rated value	2 A
— at 440 V rated value	0.6 A
— at 600 V rated value	0.4 A
 with 2 current paths in series at DC-1 	
— at 24 V rated value	100 A
— at 60 V rated value	100 A
— at 110 V rated value	100 A
— at 220 V rated value	10 A
— at 440 V rated value	1.8 A
— at 600 V rated value	1 A
 with 3 current paths in series at DC-1 	
— at 24 V rated value	100 A

— at 60 V rated value	100 A
— at 110 V rated value	100 A
— at 220 V rated value	80 A
— at 440 V rated value	4.5 A
— at 600 V rated value	2.6 A
 at 1 current path at DC-3 at DC-5 	
— at 24 V rated value	40 A
— at 60 V rated value	6 A
— at 110 V rated value	2.5 A
— at 220 V rated value	1 A
— at 440 V rated value	0.15 A
— at 600 V rated value	0.06 A
 with 2 current paths in series at DC-3 at DC-5 	
— at 24 V rated value	100 A
— at 60 V rated value	100 A
— at 110 V rated value	100 A
— at 220 V rated value	7 A
— at 440 V rated value	0.42 A
— at 600 V rated value	0.16 A
 with 3 current paths in series at DC-3 at DC-5 	
— at 24 V rated value	100 A
— at 60 V rated value	100 A
— at 110 V rated value	100 A
— at 220 V rated value	35 A
— at 440 V rated value	0.8 A
— at 600 V rated value	0.35 A
operating power	
• at AC-2 at 400 V rated value	45 kW
• at AC-3	
— at 230 V rated value	22 kW
— at 400 V rated value	45 kW
— at 500 V rated value	55 kW
— at 690 V rated value	75 kW
— at 1000 V rated value	37 kW
• at AC-3e	
— at 230 V rated value	22 kW
— at 400 V rated value	45 kW
— at 500 V rated value	55 kW
— at 690 V rated value	75 kW
— at 1000 V rated value	37 kW
operating power for approx. 200000 operating cycles at AC- 4	
•	22 kW
 at 400 V rated value at 690 V rated value 	27.4 kW
operating apparent power at AC-6a	
up to 230 V for current peak value n=20 rated value	33 kVA
 up to 200 V for current peak value n=20 rated value up to 400 V for current peak value n=20 rated value 	58 kVA
• up to 500 V for current peak value n=20 rated value	73 kVA
 up to 500 V for current peak value n=20 rated value up to 690 V for current peak value n=20 rated value 	69 kVA
operating apparent power at AC-6a	
up to 230 V for current peak value n=30 rated value	22.4 kVA
 up to 250 V for current peak value n=30 rated value up to 400 V for current peak value n=30 rated value 	39 kVA
 up to 500 V for current peak value n=30 rated value 	48.7 kVA
 up to 500 V for current peak value n=30 rated value up to 690 V for current peak value n=30 rated value 	67.3 kVA
short-time withstand current in cold operating state up to	
40 °C	
 limited to 1 s switching at zero current maximum 	1 725 A; Use minimum cross-section acc. to AC-1 rated value
 limited to 5 s switching at zero current maximum 	1 297 A; Use minimum cross-section acc. to AC-1 rated value
 limited to 10 s switching at zero current maximum 	946 A; Use minimum cross-section acc. to AC-1 rated value
 limited to 30 s switching at zero current maximum 	610 A; Use minimum cross-section acc. to AC-1 rated value
 limited to 60 s switching at zero current maximum 	486 A; Use minimum cross-section acc. to AC-1 rated value

no-load switching frequency	
• at DC	1 000 1/h
operating frequency	
● at AC-1 maximum	900 1/h
• at AC-2 maximum	350 1/h
• at AC-3 maximum	850 1/h
• at AC-3e maximum	850 1/h
• at AC-4 maximum	250 1/h
Control circuit/ Control	
type of voltage of the control supply voltage	DC
control supply voltage at DC	
rated value	24 V
operating range factor control supply voltage rated value of magnet coil at DC	
initial value	0.8
• full-scale value	1.2
design of the surge suppressor	with varistor
inrush current peak	2.7 A
duration of inrush current peak	50 µs
locked-rotor current mean value	0.9 A
locked-rotor current peak	2.1 A
duration of locked-rotor current	150 ms
holding current mean value	40 mA
closing power of magnet coil at DC	25 W
holding power of magnet coil at DC	0.9 W
closing delay	
• at DC	50 70 ms
opening delay	
• at DC	38 57 ms
arcing time	10 20 ms
control version of the switch operating mechanism	Standard A1 - A2
control version of the switch operating mechanism Auxiliary circuit	Standard A1 - A2
Auxiliary circuit	Standard A1 - A2
Auxiliary circuit number of NC contacts for auxiliary contacts instantaneous contact	
Auxiliary circuit number of NC contacts for auxiliary contacts instantaneous	1
Auxiliary circuit number of NC contacts for auxiliary contacts instantaneous contact number of NO contacts for auxiliary contacts instantaneous	1
Auxiliary circuit number of NC contacts for auxiliary contacts instantaneous contact number of NO contacts for auxiliary contacts instantaneous contact	1
Auxiliary circuit number of NC contacts for auxiliary contacts instantaneous contact number of NO contacts for auxiliary contacts instantaneous contact operational current at AC-12 maximum	1
Auxiliary circuit number of NC contacts for auxiliary contacts instantaneous contact number of NO contacts for auxiliary contacts instantaneous contact operational current at AC-12 maximum operational current at AC-15	1 1 10 A
Auxiliary circuit number of NC contacts for auxiliary contacts instantaneous contact number of NO contacts for auxiliary contacts instantaneous contact operational current at AC-12 maximum operational current at AC-15 • at 230 V rated value	1 1 10 A 6 A
Auxiliary circuit number of NC contacts for auxiliary contacts instantaneous contact number of NO contacts for auxiliary contacts instantaneous contact operational current at AC-12 maximum operational current at AC-15 • at 230 V rated value • at 400 V rated value	1 1 10 A 6 A 3 A
Auxiliary circuit number of NC contacts for auxiliary contacts instantaneous contact number of NO contacts for auxiliary contacts instantaneous contact operational current at AC-12 maximum operational current at AC-15 • at 230 V rated value • at 400 V rated value • at 500 V rated value	1 1 10 A 6 A 3 A 2 A
Auxiliary circuit number of NC contacts for auxiliary contacts instantaneous contact number of NO contacts for auxiliary contacts instantaneous contact operational current at AC-12 maximum operational current at AC-15 • at 230 V rated value • at 400 V rated value • at 500 V rated value • at 690 V rated value	1 1 10 A 6 A 3 A 2 A
Auxiliary circuit number of NC contacts for auxiliary contacts instantaneous contact number of NO contacts for auxiliary contacts instantaneous contact operational current at AC-12 maximum operational current at AC-15 • at 230 V rated value • at 500 V rated value • at 690 V rated value • at 690 V rated value • at 690 V rated value	1 1 10 A 6 A 3 A 2 A 1 A
Auxiliary circuit number of NC contacts for auxiliary contacts instantaneous contact number of NO contacts for auxiliary contacts instantaneous contact operational current at AC-12 maximum operational current at AC-15 • at 230 V rated value • at 400 V rated value • at 500 V rated value • at 690 V rated value • at 400 V rated value • at 400 V rated value	1 1 10 A 6 A 3 A 2 A 1 A 10 A
Auxiliary circuit number of NC contacts for auxiliary contacts instantaneous contact number of NO contacts for auxiliary contacts instantaneous contact operational current at AC-12 maximum operational current at AC-15 • at 230 V rated value • at 400 V rated value • at 500 V rated value • at 690 V rated value • at 24 V rated value • at 24 V rated value • at 48 V rated value	1 1 10 A 6 A 3 A 2 A 1 A 10 A 6 A
Auxiliary circuit number of NC contacts for auxiliary contacts instantaneous contact number of NO contacts for auxiliary contacts instantaneous contact operational current at AC-12 maximum operational current at AC-15 • at 230 V rated value • at 400 V rated value • at 500 V rated value • at 690 V rated value • at 44 V rated value • at 24 V rated value • at 48 V rated value • at 60 V rated value	1 1 10 A 6 A 3 A 2 A 1 A 10 A 6 A 6 A 6 A
Auxiliary circuit number of NC contacts for auxiliary contacts instantaneous contact number of NO contacts for auxiliary contacts instantaneous contact operational current at AC-12 maximum operational current at AC-15 • at 230 V rated value • at 400 V rated value • at 500 V rated value • at 690 V rated value • at 690 V rated value • at 48 V rated value • at 48 V rated value • at 60 V rated value • at 60 V rated value • at 60 V rated value • at 110 V rated value	1 1 10 A 6 A 3 A 2 A 1 A 10 A 6 A 6 A 3 A 3 A
Auxiliary circuit number of NC contacts for auxiliary contacts instantaneous contact number of NO contacts for auxiliary contacts instantaneous contact operational current at AC-12 maximum operational current at AC-15 • at 230 V rated value • at 400 V rated value • at 500 V rated value • at 690 V rated value • at 690 V rated value • at 48 V rated value • at 48 V rated value • at 40 V rated value • at 410 V rated value • at 110 V rated value • at 125 V rated value	1 1 10 A 6 A 3 A 2 A 10 A 6 A 6 A 6 A 6 A 3 A 2 A
Auxiliary circuit number of NC contacts for auxiliary contacts instantaneous contact number of NO contacts for auxiliary contacts instantaneous contact operational current at AC-12 maximum operational current at AC-15 • at 230 V rated value • at 400 V rated value • at 500 V rated value • at 690 V rated value • at 24 V rated value • at 48 V rated value • at 400 V rated value • at 24 V rated value • at 48 V rated value • at 110 V rated value • at 125 V rated value • at 220 V rated value	1 1 10 A 6 A 3 A 2 A 1 A 10 A 6 A 6 A 3 A 2 A 1 A 10 A 10 A 10 A 10 A 10 A 10 A 10 A
Auxiliary circuit number of NC contacts for auxiliary contacts instantaneous contact number of NO contacts for auxiliary contacts instantaneous contact operational current at AC-12 maximum operational current at AC-15 at 230 V rated value at 400 V rated value at 500 V rated value at 690 V rated value at 24 V rated value at 48 V rated value at 400 V rated value at 24 V rated value at 20 V rated value at 110 V rated value at 220 V rated value at 220 V rated value at 600 V rated value 	1 1 10 A 6 A 3 A 2 A 1 A 10 A 6 A 6 A 3 A 2 A 1 A 10 A 10 A 10 A 10 A 10 A 10 A 10 A
Auxiliary circuit number of NC contacts for auxiliary contacts instantaneous contact number of NO contacts for auxiliary contacts instantaneous contact operational current at AC-12 maximum operational current at AC-15	1 1 10 A 6 A 3 A 2 A 1 A 10 A 6 A 3 A 2 A 1 A 10
Auxiliary circuit number of NC contacts for auxiliary contacts instantaneous contact number of NO contacts for auxiliary contacts instantaneous contact operational current at AC-12 maximum operational current at AC-15	1 1 10 A 6 A 3 A 2 A 1 A 10 A 6 A 6 A 6 A 3 A 2 A 1 A 10 1
Auxiliary circuit number of NC contacts for auxiliary contacts instantaneous contact number of NO contacts for auxiliary contacts instantaneous contact operational current at AC-12 maximum operational current at AC-15 at 230 V rated value at 400 V rated value at 690 V rated value at 690 V rated value at 48 V rated value at 110 V rated value at 125 V rated value at 220 V rated value at 24 V rated value at 600 V rated value at 600 V rated value at 600 V rated value at 24 V rated value at 48 V rated value at 60 V rated value at 60 V rated value at 60 V rated value at 60 V rated value at 60 V rated value at 60 V rated value	1 1 10 A 6 A 3 A 2 A 1 A 10 A 6 A 6 A 6 A 6 A 3 A 2 A 1 A 10 A
Auxiliary circuit number of NC contacts for auxiliary contacts instantaneous contact number of NO contacts for auxiliary contacts instantaneous contact operational current at AC-12 maximum operational current at AC-15 • at 230 V rated value • at 400 V rated value • at 500 V rated value • at 690 V rated value • at 690 V rated value • at 60 V rated value • at 48 V rated value • at 10 V rated value • at 220 V rated value • at 220 V rated value • at 220 V rated value • at 24 V rated value • at 10 V rated value • at 24 V rated value • at 60 V rated value • at 220 V rated value • at 24 V rated value • at 24 V rated value • at 24 V rated value • at 600 V rated value • at 48 V rated value • at 400 V rated value • at 400 V rated value • at 60 V rated value • at 60 V rated value <t< td=""><td>1 1 10 A 6 A 3 A 2 A 1 A 10 A 6 A 6 A 6 A 6 A 6 A 6 A 3 A 2 A 1 A 10 A 1</td></t<>	1 1 10 A 6 A 3 A 2 A 1 A 10 A 6 A 6 A 6 A 6 A 6 A 6 A 3 A 2 A 1 A 10 A 1
Auxiliary circuit number of NC contacts for auxiliary contacts instantaneous contact number of NO contacts for auxiliary contacts instantaneous contact operational current at AC-12 maximum operational current at AC-15 • at 230 V rated value • at 400 V rated value • at 500 V rated value • at 690 V rated value • at 690 V rated value • at 60 V rated value • at 60 V rated value • at 60 V rated value • at 110 V rated value • at 220 V rated value • at 24 V rated value • at 60 V rated value • at 60 V rated value • at 60 V rated value • at 110 V rated value • at 220 V rated value • at 24 V rated value • at 24 V rated value • at 24 V rated value • at 600 V rated value • at 600 V rated value • at 24 V rated value • at 48 V rated value • at 10 V rated value	1 1 1 10 A 6 A 3 A 2 A 1 A 10 A 6 A 6 A 6 A 6 A 6 A 6 A 3 A 2 A 1 A 10 1
Auxiliary circuit number of NC contacts for auxiliary contacts instantaneous contact number of NO contacts for auxiliary contacts instantaneous contact operational current at AC-12 maximum operational current at AC-15 • at 230 V rated value • at 400 V rated value • at 500 V rated value • at 690 V rated value • at 690 V rated value • at 690 V rated value • at 60 V rated value • at 24 V rated value • at 60 V rated value • at 220 V rated value • at 110 V rated value • at 220 V rated value • at 220 V rated value • at 24 V rated value • at 220 V rated value • at 24 V rated value • at 220 V rated value • at 24 V rated value • at 10 V rated value	1 1 10 A 6 A 3 A 2 A 1 A 10 A 6 A 3 A 2 A 1 A 10 A 6 A 6 A 1 A 10 A 6 A 6 A 6 A 1 A 10 A 2 A 1 A 0.15 A 10 A 2 A 1 A 0.9 A 0.3 A
Auxiliary circuit number of NC contacts for auxiliary contacts instantaneous contact number of NO contacts for auxiliary contacts instantaneous contact operational current at AC-12 maximum operational current at AC-15	1 1 10 A 6 A 3 A 2 A 1 A 10 A 6 A 3 A 2 A 1 A 10 A 6 A 6 A 1 A 10 A 2 A 1 A 0.15 A 10 A 2 A 1 A 0.9 A 0.3 A 0.1 A
Auxiliary circuit number of NC contacts for auxiliary contacts instantaneous contact number of NO contacts for auxiliary contacts instantaneous contact operational current at AC-12 maximum operational current at AC-15 • at 230 V rated value • at 400 V rated value • at 690 V rated value • at 690 V rated value • at 40 V rated value • at 690 V rated value • at 40 V rated value • at 690 V rated value • at 40 V rated value • at 40 V rated value • at 24 V rated value • at 40 V rated value • at 24 V rated value • at 60 V rated value • at 10 V rated value • at 220 V rated value • at 220 V rated value • at 24 V rated value • at 24 V rated value • at 600 V rated value • at 24 V rated value • at 48 V rated value • at 24 V rated value • at 24 V rated value • at 24 V rated value • at 20 V rated value • at 48 V rated value • at 20 V rated value • at 110 V rated value	1 1 10 A 6 A 3 A 2 A 1 A 10 A 6 A 3 A 2 A 1 A 10 A 6 A 6 A 1 A 10 A 6 A 6 A 6 A 1 A 10 A 2 A 1 A 0.15 A 10 A 2 A 1 A 0.9 A 0.3 A
Auxiliary circuit number of NC contacts for auxiliary contacts instantaneous contact number of NO contacts for auxiliary contacts instantaneous contact operational current at AC-12 maximum operational current at AC-15	1 1 10 A 6 A 3 A 2 A 1 A 10 A 6 A 3 A 2 A 1 A 10 A 6 A 0 A 2 A 1 A 0.15 A 10 A 2 A 1 A 0.9 A 0.3 A 0.1 A

• at 480 V rated value	96 A
at 600 V rated value	77 A
yielded mechanical performance [hp]	
 for single-phase AC motor 	
— at 110/120 V rated value	10 hp
— at 230 V rated value	20 hp
 for 3-phase AC motor 	
— at 200/208 V rated value	30 hp
— at 220/230 V rated value	30 hp
— at 460/480 V rated value	75 hp
— at 575/600 V rated value	75 hp
contact rating of auxiliary contacts according to UL	A600 / P600
Short-circuit protection	
design of the fuse link	
 for short-circuit protection of the main circuit 	
— with type of coordination 1 required	gG: 250 A (690 V, 100 kA), aM: 160 A (690 V, 100 kA), BS88: 200 A (415 V, 80 kA)
- with type of assignment 2 required	gG: 160 A (690 V, 100 kA), aM: 100 A (690 V, 100 kA), BS88: 125 A (415 V, 80 kA)
 for short-circuit protection of the auxiliary switch required 	gG: 10 A (500 V, 1 kA)
Installation/ mounting/ dimensions	
mounting position	+/-180° rotation possible on vertical mounting surface; can be tilted forward and backward by +/- 22.5° on vertical mounting surface
fastening method	screw and snap-on mounting onto 35 mm DIN rail according to DIN EN 60715
 side-by-side mounting 	Yes
height	140 mm
width	70 mm
depth	152 mm
required spacing	
with side-by-side mounting	
— forwards	20 mm
— upwards	10 mm
— downwards	10 mm
— at the side	0 mm
	0 1111
for grounded parts forwards	20
— forwards	20 mm
— upwards	10 mm
— at the side	10 mm
— downwards	10 mm
 for live parts 	
— forwards	20 mm
— upwards	10 mm
— downwards	10 mm
— at the side	10 mm
Connections/ Terminals	
type of electrical connection	
for main current circuit	screw-type terminals
 for auxiliary and control circuit 	spring-loaded terminals
 at contactor for auxiliary contacts 	Spring-type terminals
of magnet coil	Spring-type terminals
type of connectable conductor cross-sections for main contacts	
 finely stranded with core end processing 	2x (2.5 35 mm²), 1x (2.5 50 mm²)
connectable conductor cross-section for main contacts	
• solid	2.5 16 mm²
stranded	6 70 mm²
 finely stranded with core end processing 	2.5 50 mm²
connectable conductor cross-section for auxiliary contacts	
solid or stranded	0.5 2.5 mm²
 finely stranded with core end processing 	0.5 2.5 mm ²
 finely stranded with core end processing finely stranded without core end processing 	0.5 2.5 mm ²
type of connectable conductor cross-sections	
175 01 connectable conductor cross-sections	

 for auxiliary con 					
— solid or str	anded		2x (0.5 2.5 mm²)		
— finely strar	nded with core end process	ing	2x (0.5 1.5 mm²)		
-	nded without core end proc	÷	2x (0.5 2.5 mm ²)		
 for AWG cables 	for auxiliary contacts		2x (20 16)		
WG number as cod	ed connectable conducto	or cross			
• for main contact	ts		10 2		
 for auxiliary con 	tacts		20 14		
fety related data					
roduct function					
 mirror contact a 	ccording to IEC 60947-4-1		Yes		
 positively driven 	operation according to IEC	C 60947-5-1	No		
uitability for use safet	y-related switching OFF		Yes		
10 value with high de	emand rate according to SN	31920	1 000 000		
roportion of danger	ous failures				
 with low deman 	d rate according to SN 319	20	40 %		
•	nd rate according to SN 319		73 %		
	ow demand rate according		100 FIT		
1508	interval or service life acco	-	20 a		
	n the front according to I		IP20		
	the front according to IEC	60529	finger-safe, for vertical	contact from the front	
rtificates/ approvals					
SP M		<u>Confirmatio</u>		KC	EAC
CSA EMC	Functional Safety/Safety of Ma-	Confirmatio	(UL)	KC Test Certificates	EAC
	Functional		Conformity		Type Test Certific ates/Test Report
Ø	Functional Safety/Safety of Ma- chinery Type Examination Cer-	Declaration of	Conformity	Test Certificates Special Test Certific-	
RCM	Functional Safety/Safety of Ma- chinery Type Examination Cer-	Declaration of	Conformity	Test Certificates Special Test Certific-	
RCM	Functional Safety/Safety of Ma- chinery Type Examination Cer-	Declaration of UK CA	Conformity	Test Certificates Special Test Certific-	
Marine / Shipping	Functional Safety/Safety of Ma- chinery Type Examination Cer- tificate	Declaration of UK CA	Conformity EG-Konf.	Test Certificates Special Test Certific-	
Marine / Shipping	Functional Safety/Safety of Ma- chinery Type Examination Cer- tificate	Declaration of UK CA CA CA CA CA CA CA CA CA CA CA CA CA	Conformity EG-Konf.	Test Certificates Special Test Certific-	

Siemens is working on the renewal of the current EAC certificates. Please contact your local Siemens office on the status of validity of the EAC certification if you intend to import or offer to supply these products to an EAC relevant market (other than the sanctioned EAEU member states Russia or Belarus).

Information on the packaging

https://support.industry.siemens.com/cs/ww/en/view/109813875

Information- and Downloadcenter (Catalogs, Brochures,...)

https://www.siemens.com/ic10

Industry Mall (Online ordering system) https://mall.industry.siemens.com/mall/en/en/Catalog/product?mlfb=3RT2046-3KB40

Cax online generator

http://support.automation.siemens.com/WW/CAXorder/default.aspx?lang=en&mlfb=3RT2046-3KB40

Service&Support (Manuals, Certificates, Characteristics, FAQs,...)

https://support.industry.siemens.com/cs/ww/en/ps/3RT2046-3KB40


Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, EPLAN macros, ...) http://www.automation.siemens.com/bilddb/cax_de.aspx?mlfb=3RT2046-3KB40&lang=en


http://www.automation.siemens.com/bilddb/cax_de.aspx?mlfb


Characteristic: Tripping characteristics, I²t, Let-through current


https://support.industry.siemens.com/cs/ww/en/ps/3RT2046-3KB40/char

Further characteristics (e.g. electrical endurance, switching frequency) http://www.automation.siemens.com/bilddb/index.aspx?view=Search&mlfb=3RT2046-3KB40&objecttype=14&gridview=view1









last modified:

8/15/2023 🖸

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Siemens: 3RT20463KB40