SIEMENS

Data sheet 3RU2126-1CB0



Overload relay 1.8...2.5 A Thermal For motor protection Size S0, Class 10 Contactor mounting Main circuit: Screw Auxiliary circuit: Screw Manual-Automatic-Reset

product brand name	SIRIUS
product designation	thermal overload relay
product type designation	3RU2
General technical data	
size of overload relay	S0
size of contactor can be combined company-specific	S0
power loss [W] for rated value of the current at AC in hot operating state	5.7 W
• per pole	1.9 W
insulation voltage with degree of pollution 3 at AC rated value	690 V
surge voltage resistance rated value	6 kV
maximum permissible voltage for protective separation in networks with grounded star point	
 between auxiliary and auxiliary circuit 	440 V
 between auxiliary and auxiliary circuit 	440 V
 between main and auxiliary circuit 	440 V
between main and auxiliary circuit	440 V
shock resistance according to IEC 60068-2-27	8g / 11 ms
type of protection according to ATEX directive 2014/34/EU	Ex II (2) GD
certificate of suitability according to ATEX directive 2014/34/EU	DMT 98 ATEX G 001
reference code according to IEC 81346-2	F
Substance Prohibitance (Date)	10/01/2009
Ambient conditions	
installation altitude at height above sea level maximum	2 000 m
ambient temperature	
 during operation 	-40 +70 °C
 during storage 	-55 +80 °C
during transport	-55 +80 °C
temperature compensation	-40 +60 °C
relative humidity during operation	10 95 %
Main circuit	
number of poles for main current circuit	3
adjustable current response value current of the current- dependent overload release	1.8 2.5 A
operating voltage	
rated value	690 V
at AC-3e rated value maximum	690 V
operating frequency rated value	50 60 Hz
operational current rated value	2.5 A
operational current at AC-3e at 400 V rated value	2.5 A
operating power	

• at AC-3	
— at 400 V rated value	0.75 kW
— at 500 V rated value	1.1 kW
— at 690 V rated value	1.5 kW
• at AC-3e	
— at 400 V rated value	0.75 kW
— at 500 V rated value	1.1 kW
— at 690 V rated value	1.5 kW
Auxiliary circuit	
design of the auxiliary switch	integrated
number of NC contacts for auxiliary contacts	1
• note	for contactor disconnection
number of NO contacts for auxiliary contacts	1
• note	for message "Tripped"
number of CO contacts for auxiliary contacts	0
operational current of auxiliary contacts at AC-15	
● at 24 V	3 A
• at 110 V	3 A
• at 120 V	3 A
• at 125 V	3 A
• at 230 V	2 A
• at 400 V	1 A
• at 690 V	0.75 A
operational current of auxiliary contacts at DC-13	
• at 24 V	2 A
• at 60 V	0.3 A
• at 110 V	0.22 A
• at 125 V	0.22 A
• at 220 V	0.11 A
contact rating of auxiliary contacts according to UL	B600 / R300
Protective and monitoring functions	
Protective and monitoring functions trip class	CLASS 10
	CLASS 10 thermal
trip class	
trip class design of the overload release	
trip class design of the overload release UL/CSA ratings	
trip class design of the overload release UL/CSA ratings full-load current (FLA) for 3-phase AC motor	thermal
trip class design of the overload release UL/CSA ratings full-load current (FLA) for 3-phase AC motor • at 480 V rated value	thermal 2.5 A
trip class design of the overload release UL/CSA ratings full-load current (FLA) for 3-phase AC motor • at 480 V rated value • at 600 V rated value Short-circuit protection	thermal 2.5 A
trip class design of the overload release UL/CSA ratings full-load current (FLA) for 3-phase AC motor • at 480 V rated value • at 600 V rated value Short-circuit protection design of the fuse link	thermal 2.5 A 2.5 A
trip class design of the overload release UL/CSA ratings full-load current (FLA) for 3-phase AC motor • at 480 V rated value • at 600 V rated value Short-circuit protection design of the fuse link • for short-circuit protection of the auxiliary switch required	thermal 2.5 A
trip class design of the overload release UL/CSA ratings full-load current (FLA) for 3-phase AC motor • at 480 V rated value • at 600 V rated value Short-circuit protection design of the fuse link • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions	thermal 2.5 A 2.5 A fuse gG: 6 A, quick: 10 A
trip class design of the overload release UL/CSA ratings full-load current (FLA) for 3-phase AC motor	thermal 2.5 A 2.5 A fuse gG: 6 A, quick: 10 A any
trip class design of the overload release UL/CSA ratings full-load current (FLA) for 3-phase AC motor • at 480 V rated value • at 600 V rated value Short-circuit protection design of the fuse link • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method	thermal 2.5 A 2.5 A fuse gG: 6 A, quick: 10 A any Contactor mounting
trip class design of the overload release UL/CSA ratings full-load current (FLA) for 3-phase AC motor • at 480 V rated value • at 600 V rated value Short-circuit protection design of the fuse link • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method height	thermal 2.5 A 2.5 A fuse gG: 6 A, quick: 10 A any Contactor mounting 85 mm
trip class design of the overload release UL/CSA ratings full-load current (FLA) for 3-phase AC motor	thermal 2.5 A 2.5 A fuse gG: 6 A, quick: 10 A any Contactor mounting 85 mm 45 mm
trip class design of the overload release UL/CSA ratings full-load current (FLA) for 3-phase AC motor	thermal 2.5 A 2.5 A fuse gG: 6 A, quick: 10 A any Contactor mounting 85 mm
trip class design of the overload release UL/CSA ratings full-load current (FLA) for 3-phase AC motor	thermal 2.5 A 2.5 A 2.5 A fuse gG: 6 A, quick: 10 A any Contactor mounting 85 mm 45 mm 85 mm
trip class design of the overload release UL/CSA ratings full-load current (FLA) for 3-phase AC motor	thermal 2.5 A 2.5 A fuse gG: 6 A, quick: 10 A any Contactor mounting 85 mm 45 mm
trip class design of the overload release UL/CSA ratings full-load current (FLA) for 3-phase AC motor • at 480 V rated value • at 600 V rated value Short-circuit protection design of the fuse link • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method height width depth Connections/ Terminals product component removable terminal for auxiliary and	thermal 2.5 A 2.5 A 2.5 A fuse gG: 6 A, quick: 10 A any Contactor mounting 85 mm 45 mm 85 mm
trip class design of the overload release UL/CSA ratings full-load current (FLA) for 3-phase AC motor	thermal 2.5 A 2.5 A 2.5 A fuse gG: 6 A, quick: 10 A any Contactor mounting 85 mm 45 mm 85 mm
trip class design of the overload release UL/CSA ratings full-load current (FLA) for 3-phase AC motor	thermal 2.5 A 2.5 A 2.5 A fuse gG: 6 A, quick: 10 A any Contactor mounting 85 mm 45 mm 85 mm
trip class design of the overload release UL/CSA ratings full-load current (FLA) for 3-phase AC motor	thermal 2.5 A 2.5 A fuse gG: 6 A, quick: 10 A any Contactor mounting 85 mm 45 mm 85 mm No
trip class design of the overload release UL/CSA ratings full-load current (FLA) for 3-phase AC motor	thermal 2.5 A 2.5 A 2.5 A fuse gG: 6 A, quick: 10 A any Contactor mounting 85 mm 45 mm 85 mm No No
trip class design of the overload release UL/CSA ratings full-load current (FLA) for 3-phase AC motor	thermal 2.5 A 2.5 A 2.5 A fuse gG: 6 A, quick: 10 A any Contactor mounting 85 mm 45 mm 85 mm No No
trip class design of the overload release UL/CSA ratings full-load current (FLA) for 3-phase AC motor	thermal 2.5 A 2.5 A 2.5 A fuse gG: 6 A, quick: 10 A any Contactor mounting 85 mm 45 mm 85 mm No No
trip class design of the overload release UL/CSA ratings full-load current (FLA) for 3-phase AC motor • at 480 V rated value • at 600 V rated value Short-circuit protection design of the fuse link • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method height width depth Connections/ Terminals product component removable terminal for auxiliary and control circuit type of electrical connection • for main current circuit • for auxiliary and control circuit arrangement of electrical connectors for main current circuit type of connectable conductor cross-sections • for main contacts	thermal 2.5 A 2.5 A fuse gG: 6 A, quick: 10 A any Contactor mounting 85 mm 45 mm 85 mm No screw-type terminals screw-type terminals Top and bottom
trip class design of the overload release UL/CSA ratings full-load current (FLA) for 3-phase AC motor • at 480 V rated value • at 600 V rated value Short-circuit protection design of the fuse link • for short-circuit protection of the auxiliary switch required Installation/ mounting/ dimensions mounting position fastening method height width depth Connections/ Terminals product component removable terminal for auxiliary and control circuit type of electrical connection • for main current circuit • for auxiliary and control circuit arrangement of electrical connectors for main current circuit type of connectable conductor cross-sections • for main contacts — solid or stranded	thermal 2.5 A 2.5 A 2.5 A fuse gG: 6 A, quick: 10 A any Contactor mounting 85 mm 45 mm 85 mm No No screw-type terminals screw-type terminals Top and bottom 2x (1 2.5 mm²), 2x (2.5 10 mm²)
trip class design of the overload release UL/CSA ratings full-load current (FLA) for 3-phase AC motor	thermal 2.5 A 2.5 A 2.5 A fuse gG: 6 A, quick: 10 A any Contactor mounting 85 mm 45 mm 85 mm No No screw-type terminals screw-type terminals Top and bottom 2x (1 2.5 mm²), 2x (2.5 10 mm²) 2x (1 2.5 mm²), 2x (2.5 6 mm²), 1x 10 mm²
trip class design of the overload release UL/CSA ratings full-load current (FLA) for 3-phase AC motor	thermal 2.5 A 2.5 A 2.5 A fuse gG: 6 A, quick: 10 A any Contactor mounting 85 mm 45 mm 85 mm No No screw-type terminals screw-type terminals Top and bottom 2x (1 2.5 mm²), 2x (2.5 10 mm²) 2x (1 2.5 mm²), 2x (2.5 6 mm²), 1x 10 mm²

 — solid or stranded 	2x (0.5 1.5 mm²), 2x (0.75 2.5 mm²)
 finely stranded with core end processing 	2x (0.5 1.5 mm²), 2x (0.75 2.5 mm²)
 for AWG cables for auxiliary contacts 	2x (20 16), 2x (18 14)
tightening torque	
 for main contacts with screw-type terminals 	2 2.5 N·m
 for auxiliary contacts with screw-type terminals 	0.8 1.2 N·m
design of screwdriver shaft	Diameter 5 6 mm
size of the screwdriver tip	Pozidriv PZ 2
design of the thread of the connection screw	
• for main contacts	M4
 of the auxiliary and control contacts 	M3
Safety related data	
failure rate [FIT] with low demand rate according to SN 31920	50 FIT
MTTF with high demand rate	2 280 a
T1 value for proof test interval or service life according to IEC 61508	20 a
protection class IP on the front according to IEC 60529	IP20
touch protection on the front according to IEC 60529	finger-safe, for vertical contact from the front
Display	
display version for switching status	Slide switch
Certificates/ approvals	

m

Confirmation







For use in hazardous locations



Declaration of Conformity

General Product Approval

Test Certificates

Marine / Shipping





Type Test Certificates/Test Report

Special Test Certificate





Marine / Shipping





LRS







Confirmation

other

other

Railway



Vibration and Shock

Further information

Siemens has decided to exit the Russian market (see here).

https://press.siemens.com/global/en/pressrelease/siemens-wind-down-russian-business

Siemens is working on the renewal of the current EAC certificates.

Please contact your local Siemens office on the status of validity of the EAC certification if you intend to import or offer to supply these products to an EAC relevant market (other than the sanctioned EAEU member states Russia or Belarus).

Information on the packaging

https://support.industry.siemens.com/cs/ww/en/view/109813875

Information- and Downloadcenter (Catalogs, Brochures,...)

https://www.siemens.com/ic10

Industry Mall (Online ordering system)

https://mall.industry.siemens.com/mall/en/en/Catalog/product?mlfb=3RU2126-1CB0

Cax online generator

http://support.automation.siemens.com/WW/CAXorder/default.aspx?lang=en&mlfb=3RU2126-1CB0

Service&Support (Manuals, Certificates, Characteristics, FAQs,...)


https://support.industry.siemens.com/cs/ww/en/ps/3RU2126-1CB0


Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, EPLAN macros, ...) http://www.automation.siemens.com/bilddb/cax_de.aspx?mlfb=3RU2126-1CB0&lang=en


Characteristic: Tripping characteristics, I2t, Let-through current


https://support.industry.siemens.com/cs/ww/en/ps/3RU2126-1CB0/char

Further characteristics (e.g. electrical endurance, switching frequency)
http://www.automation.siemens.com/bilddb/index.aspx?view=Search&mlfb=3RU2126-1CB0&objecttype=14&gridview=view1









last modified: 3/8/2022 🖸

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Siemens:

3RU21261CB0