## 3SU1132-0AB70-1BA0-Z Y15

## **Data sheet**



Illuminated pushbutton, 22 mm, round, plastic with metal front ring, clear, pushbutton, flat, momentary contact type, with holder, 1NO, LED module with integrated LED 24 V AC/DC, screw terminal, with laser labeling, upper case and lower case, Always upper case at the beginning of the word

product brand name	SIRIUS ACT
product designation	Illuminated pushbuttons
design of the product	Complete unit
product type designation	3SU1
product line	Plastic with metal front ring, matt, 22 mm
manufacturer's article number	
<ul> <li>of supplied contact module at position 1</li> </ul>	3SU1400-1AA10-1BA0
<ul> <li>of supplied LED module</li> </ul>	3SU1401-1BB60-1AA0
<ul> <li>of the supplied holder</li> </ul>	3SU1550-0AA10-0AA0
of the supplied actuator	3SU1031-0AB70-0AA0
number of command points	1
Actuator	
design of the actuating element	Button, flat
principle of operation of the actuating element	momentary contact type
product extension optional light source	Yes
color of the actuating element	clear
material of the actuating element	plastic
shape of the actuating element	round
outer diameter of the actuating element	29.45 mm
marking of the actuating element	Customized labeling, text in lower case / capital letters, all words start with capital letters
number of contact modules	1
Front ring	
product component front ring	Yes
design of the front ring	Standard
material of the front ring	Metal, matt
color of the front ring	sand gray
Holder	
material of the holder	Plastic
Display	
number of LED modules	1
General technical data	
product function positive opening	No
product component light source	Yes
insulation voltage rated value	320 V
degree of pollution	3
type of voltage of the operating voltage	AC/DC
surge voltage resistance rated value	4 kV
protection class IP	IP66, IP67, IP69(IP69K)
• of the terminal	IP20

degree of protection NEMA rating	1, 2, 3, 3R, 4, 4X, 12, 13
shock resistance	
<ul><li>according to IEC 60068-2-27</li></ul>	sinusoidal half-wave 15g / 11 ms
for railway applications according to EN 61373	Category 1, Class B
vibration resistance	
<ul><li>according to IEC 60068-2-6</li></ul>	10 500 Hz: 5g
<ul> <li>for railway applications according to EN 61373</li> </ul>	Category 1, Class B
operating frequency maximum	3 600 1/h
mechanical service life (operating cycles) typical	3 000 000
electrical endurance (operating cycles) typical	10 000 000
thermal current	10 A
reference code according to IEC 81346-2	S
continuous current of the C characteristic MCB	10 A; for a short-circuit current smaller than 400 A
continuous current of the quick DIAZED fuse link	10 A
continuous current of the DIAZED fuse link gG	10 A
	10/01/2014
Substance Prohibitance (Date)	10/01/2014
operating voltage	
• at AC	
— at 50 Hz rated value	5 500 V
— at 60 Hz rated value	5 500 V
at DC rated value	5 500 V
Power Electronics	
contact reliability	One maloperation per 100 million (17 V, 5 mA), one maloperation per 10 million (5 V, 1 mA)
Supply voltage	
type of voltage of the supply voltage of the light source	AC/DC
supply voltage of the light source at AC	
at 50 Hz rated value	24 V
at 60 Hz rated value	24 V
supply voltage 1 of the light source at DC rated value	24 V
Control circuit/ Control	
Control circuit/ Control	2 A
inrush current of LED module maximum	2 A
inrush current of LED module maximum  Auxiliary circuit	
inrush current of LED module maximum  Auxiliary circuit  design of the contact of auxiliary contacts	Silver alloy
inrush current of LED module maximum  Auxiliary circuit  design of the contact of auxiliary contacts  number of NC contacts for auxiliary contacts	Silver alloy 0
inrush current of LED module maximum  Auxiliary circuit  design of the contact of auxiliary contacts number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts	Silver alloy
inrush current of LED module maximum  Auxiliary circuit  design of the contact of auxiliary contacts  number of NC contacts for auxiliary contacts	Silver alloy 0 1
inrush current of LED module maximum  Auxiliary circuit  design of the contact of auxiliary contacts number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts	Silver alloy 0
inrush current of LED module maximum  Auxiliary circuit  design of the contact of auxiliary contacts number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts  Connections/ Terminals  type of electrical connection  • of modules and accessories	Silver alloy 0 1
inrush current of LED module maximum  Auxiliary circuit  design of the contact of auxiliary contacts number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts  Connections/ Terminals  type of electrical connection	Silver alloy 0 1 screw-type terminals
inrush current of LED module maximum  Auxiliary circuit  design of the contact of auxiliary contacts number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts  Connections/ Terminals  type of electrical connection  • of modules and accessories	Silver alloy 0 1 screw-type terminals
inrush current of LED module maximum  Auxiliary circuit  design of the contact of auxiliary contacts number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts  Connections/ Terminals  type of electrical connection  • of modules and accessories  type of connectable conductor cross-sections	Silver alloy 0 1 screw-type terminals Screw-type terminal
inrush current of LED module maximum  Auxiliary circuit  design of the contact of auxiliary contacts number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts  Connections/ Terminals  type of electrical connection  of modules and accessories  type of connectable conductor cross-sections solid with core end processing	Silver alloy 0 1 screw-type terminals Screw-type terminal 2x (0.5 0.75 mm²)
inrush current of LED module maximum  Auxiliary circuit  design of the contact of auxiliary contacts number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts  Connections/ Terminals  type of electrical connection  of modules and accessories  type of connectable conductor cross-sections  solid with core end processing solid without core end processing	Silver alloy  0 1  screw-type terminals Screw-type terminal  2x (0.5 0.75 mm²) 2x (1.0 1.5 mm²)
inrush current of LED module maximum  Auxiliary circuit  design of the contact of auxiliary contacts number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts  Connections/ Terminals  type of electrical connection  of modules and accessories  type of connectable conductor cross-sections  solid with core end processing of solid without core end processing of finely stranded with core end processing	Silver alloy 0 1  screw-type terminals Screw-type terminal  2x (0.5 0.75 mm²) 2x (1.0 1.5 mm²) 2x (0.5 1.5 mm²)
inrush current of LED module maximum  Auxiliary circuit  design of the contact of auxiliary contacts number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts  Connections/ Terminals  type of electrical connection  of modules and accessories  type of connectable conductor cross-sections  solid with core end processing of inely stranded with core end processing of finely stranded without core end processing	Silver alloy  0 1  screw-type terminals  Screw-type terminal  2x (0.5 0.75 mm²)  2x (1.0 1.5 mm²)  2x (0.5 1.5 mm²)
inrush current of LED module maximum  Auxiliary circuit  design of the contact of auxiliary contacts number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts  Connections/ Terminals  type of electrical connection	Silver alloy  0  1  screw-type terminals  Screw-type terminal  2x (0.5 0.75 mm²)  2x (1.0 1.5 mm²)  2x (0.5 1.5 mm²)  2x (1,0 1,5 mm²)
inrush current of LED module maximum  Auxiliary circuit  design of the contact of auxiliary contacts number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts  Connections/ Terminals  type of electrical connection  of modules and accessories  type of connectable conductor cross-sections  solid with core end processing of solid without core end processing of finely stranded with core end processing of inely stranded without core end processing of new year and without core end processing of new year and without core end processing of new year and without core end processing of the year and year year.	Silver alloy  0  1  screw-type terminals  Screw-type terminal  2x (0.5 0.75 mm²)  2x (1.0 1.5 mm²)  2x (0.5 1.5 mm²)  2x (0.5 1.5 mm²)  2x (1,0 1,5 mm²)
inrush current of LED module maximum  Auxiliary circuit  design of the contact of auxiliary contacts number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts  Connections/ Terminals  type of electrical connection  of modules and accessories  type of connectable conductor cross-sections  solid with core end processing of inely stranded with core end processing of inely stranded without core end processing of nAWG cables  tightening torque of the screws in the bracket tightening torque with screw-type terminals  Lamp	Silver alloy  0  1  screw-type terminals  Screw-type terminal  2x (0.5 0.75 mm²)  2x (1.0 1.5 mm²)  2x (0.5 1.5 mm²)  2x (0.5 1.5 mm²)  2x (1,0 1,5 mm²)
inrush current of LED module maximum  Auxiliary circuit  design of the contact of auxiliary contacts number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts  Connections/ Terminals  type of electrical connection	Silver alloy  0 1  screw-type terminals  Screw-type terminal  2x (0.5 0.75 mm²)  2x (1.0 1.5 mm²)  2x (0.5 1.5 mm²)  2x (1,0 1,5 mm²)  2x (1,0 1,5 mm²)  2x (18 14)  1 1.2 N·m  0.8 0.9 N·m
inrush current of LED module maximum  Auxiliary circuit  design of the contact of auxiliary contacts number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts  Connections/ Terminals  type of electrical connection	Silver alloy  0  1  screw-type terminals  Screw-type terminal  2x (0.5 0.75 mm²)  2x (1.0 1.5 mm²)  2x (0.5 1.5 mm²)  2x (1,0 1,5 mm²)  2x (1,0 1,5 mm²)  2x (18 14)  1 1.2 N·m  0.8 0.9 N·m
inrush current of LED module maximum  Auxiliary circuit  design of the contact of auxiliary contacts number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts  Connections/ Terminals  type of electrical connection	Silver alloy  0 1  screw-type terminals  Screw-type terminal  2x (0.5 0.75 mm²)  2x (1.0 1.5 mm²)  2x (0.5 1.5 mm²)  2x (1,0 1,5 mm²)  2x (1,0 1,5 mm²)  2x (18 14)  1 1.2 N·m  0.8 0.9 N·m
inrush current of LED module maximum  Auxiliary circuit  design of the contact of auxiliary contacts number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts  Connections/ Terminals  type of electrical connection  of modules and accessories  type of connectable conductor cross-sections  solid with core end processing  finely stranded with core end processing  finely stranded without core end processing  for AWG cables  tightening torque of the screws in the bracket  tightening torque with screw-type terminals  Lamp  type of light source  color of the light source  light intensity  Ambient conditions	Silver alloy  0  1  screw-type terminals  Screw-type terminal  2x (0.5 0.75 mm²)  2x (1.0 1.5 mm²)  2x (0.5 1.5 mm²)  2x (1,0 1,5 mm²)  2x (1,0 1,5 mm²)  2x (18 14)  1 1.2 N·m  0.8 0.9 N·m
inrush current of LED module maximum  Auxiliary circuit  design of the contact of auxiliary contacts number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts  Connections/ Terminals  type of electrical connection  of modules and accessories  type of connectable conductor cross-sections  solid with core end processing  finely stranded with core end processing  finely stranded without core end processing  for AWG cables  tightening torque of the screws in the bracket  tightening torque with screw-type terminals  Lamp  type of light source  color of the light source  light intensity  Ambient conditions  ambient temperature	Silver alloy  0 1  screw-type terminals  Screw-type terminal  2x (0.5 0.75 mm²)  2x (1.0 1.5 mm²)  2x (0.5 1.5 mm²)  2x (1,0 1,5 mm²)  2x (1,0 1,5 mm²)  2x (18 14)  1 1.2 N·m  0.8 0.9 N·m  LED  white  900 1 400 mcd
inrush current of LED module maximum  Auxiliary circuit  design of the contact of auxiliary contacts number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts  Connections/ Terminals  type of electrical connection	Silver alloy 0 1  screw-type terminals Screw-type terminal  2x (0.5 0.75 mm²) 2x (1.0 1.5 mm²) 2x (0.5 1.5 mm²) 2x (1,0 1,5 mm²) 2x (1,0 1,5 mm²) 2x (18 14) 1 1.2 N·m 0.8 0.9 N·m  LED white 900 1 400 mcd
inrush current of LED module maximum  Auxiliary circuit  design of the contact of auxiliary contacts number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts  Connections/ Terminals  type of electrical connection	Silver alloy 0 1  screw-type terminals Screw-type terminal  2x (0.5 0.75 mm²) 2x (1.0 1.5 mm²) 2x (0.5 1.5 mm²) 2x (1,0 1,5 mm²) 2x (1,0 1,5 mm²) 2x (18 14) 1 1.2 N·m 0.8 0.9 N·m  LED white 900 1 400 mcd
inrush current of LED module maximum  Auxiliary circuit  design of the contact of auxiliary contacts number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts  Connections/ Terminals  type of electrical connection	Silver alloy 0 1  screw-type terminals Screw-type terminal  2x (0.5 0.75 mm²) 2x (1.0 1.5 mm²) 2x (0.5 1.5 mm²) 2x (1,0 1,5 mm²) 2x (1,0 1,5 mm²) 2x (1,0 1,5 mm²) 4x (1,0 1,5 mm²) 5x (1,0 1,5 mm²) 6x (1,0
inrush current of LED module maximum  Auxiliary circuit  design of the contact of auxiliary contacts number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts  Connections/ Terminals  type of electrical connection	Silver alloy 0 1  screw-type terminals Screw-type terminal  2x (0.5 0.75 mm²) 2x (1.0 1.5 mm²) 2x (0.5 1.5 mm²) 2x (1,0 1,5 mm²) 2x (1,0 1,5 mm²) 2x (1,0 1,5 mm²) 2x (18 14) 1 1.2 N·m 0.8 0.9 N·m  LED white 900 1 400 mcd
inrush current of LED module maximum  Auxiliary circuit  design of the contact of auxiliary contacts number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts  Connections/ Terminals  type of electrical connection  of modules and accessories  type of connectable conductor cross-sections  solid with core end processing  finely stranded with core end processing  finely stranded without core end processing  for AWG cables  tightening torque of the screws in the bracket  tightening torque with screw-type terminals  Lamp  type of light source  color of the light source  light intensity  Ambient conditions  ambient temperature  during operation  during storage  environmental category during operation according to IEC 60721  Installation/ mounting/ dimensions	Silver alloy  0  1  screw-type terminals Screw-type terminal  2x (0.5 0.75 mm²) 2x (1.0 1.5 mm²) 2x (0.5 1.5 mm²) 2x (1,0 1,5 mm²) 2x (1,0 1,5 mm²) 2x (1,0 1,5 mm²) 2x (1,0 1,5 mm²) 2x (1,0 1,4) 1 1.2 N·m 0.8 0.9 N·m  LED white 900 1 400 mcd  -25 +70 °C -40 +80 °C 3M6, 3S2, 3B2, 3K6 (with relative air humidity of 10 95%, no condensation in operation permitted for all devices behind front panel)
inrush current of LED module maximum  Auxiliary circuit  design of the contact of auxiliary contacts number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts  Connections/ Terminals  type of electrical connection  • of modules and accessories  type of connectable conductor cross-sections  • solid with core end processing  • solid without core end processing  • finely stranded with core end processing  • finely stranded without core end processing  • for AWG cables  tightening torque of the screws in the bracket  tightening torque with screw-type terminals  Lamp  type of light source  color of the light source  light intensity  Ambient conditions  ambient temperature  • during operation  • during storage  environmental category during operation according to IEC 60721  Installation/ mounting/ dimensions  fastening method	Silver alloy  0  1  screw-type terminals  Screw-type terminal  2x (0.5 0.75 mm²)  2x (1.0 1.5 mm²)  2x (0.5 1.5 mm²)  2x (1,0 1,5 mm²)  2x (1,0 1,5 mm²)  2x (1,0 1,5 mm²)  2x (1,0 1,5 mm²)  1x (1,0 1,5 mm²)  2x
inrush current of LED module maximum  Auxiliary circuit  design of the contact of auxiliary contacts number of NC contacts for auxiliary contacts number of NO contacts for auxiliary contacts  Connections/ Terminals  type of electrical connection  of modules and accessories  type of connectable conductor cross-sections  solid with core end processing  finely stranded with core end processing  finely stranded without core end processing  for AWG cables  tightening torque of the screws in the bracket  tightening torque with screw-type terminals  Lamp  type of light source  color of the light source  light intensity  Ambient conditions  ambient temperature  during operation  during storage  environmental category during operation according to IEC 60721  Installation/ mounting/ dimensions	Silver alloy  0  1  screw-type terminals Screw-type terminal  2x (0.5 0.75 mm²) 2x (1.0 1.5 mm²) 2x (0.5 1.5 mm²) 2x (1,0 1,5 mm²) 2x (1,0 1,5 mm²) 2x (1,0 1,5 mm²) 2x (1,0 1,5 mm²) 2x (1,0 1,4) 1 1.2 N·m 0.8 0.9 N·m  LED white 900 1 400 mcd  -25 +70 °C -40 +80 °C 3M6, 3S2, 3B2, 3K6 (with relative air humidity of 10 95%, no condensation in operation permitted for all devices behind front panel)

width	30 mm
shape of the installation opening	round
mounting diameter	22.3 mm
positive tolerance of installation diameter	0.4 mm
mounting height	11 mm
installation width	29.5 mm
installation depth	49.7 mm
Certificates/ approvals	

Siemens has decided to exit the Russian market (see here).

https://press.siemens.com/global/en/pressrelease/siemens-wind-down-russian-business

Siemens is working on the renewal of the current EAC certificates.

Please contact your local Siemens office on the status of validity of the EAC certification if you intend to import or offer to supply these products to an EAC relevant market (other than the sanctioned EAEU member states Russia or Belarus).

## Information on the packaging

https://support.industry.siemens.com/cs/ww/en/view/109813875

Information- and Downloadcenter (Catalogs, Brochures,...)

https://www.siemens.com/ic10

Industry Mall (Online ordering system)

https://mall.industry.siemens.com/mall/en/en/Catalog/product?mlfb=3SU1132-0AB70-1BA0-Z Y15

Cax online generator

http://support.automation.siemens.com/WW/CAXorder/default.aspx?lang=en&mlfb=3SU1132-0AB70-1BA0-Z Y15

Service&Support (Manuals, Certificates, Characteristics, FAQs,...)

https://support.industry.siemens.com/cs/ww/en/ps/3SU1132-0AB70-1BA0-Z Y15

Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, EPLAN macros, ...) <a href="http://www.automation.siemens.com/bilddb/cax\_de.aspx?mlfb=3SU1132-0AB70-1BA0-Z Y15&lang=en">http://www.automation.siemens.com/bilddb/cax\_de.aspx?mlfb=3SU1132-0AB70-1BA0-Z Y15&lang=en</a>

-P 24 V AC/DC X 90 90 4:

last modified: 1/26/2022 🖸

## **Mouser Electronics**

**Authorized Distributor** 

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Siemens:

A6X30144050