SIEMENS

Data sheet



SITOP PSU8200/3AC/24VDC/40A

SITOP PSU8200 24 V/40 A stabilized power supply input: 400-500 V 3 AC output: 24 V DC/40 A *Ex approval no longer available*

type of the power supply network	3-phase AC
supply voltage at AC	
minimum rated value	400 V
maximum rated value	500 V
initial value	320 V
full-scale value	575 V
design of input wide range input	Yes
operating condition of the mains buffering	at Vin = 400 V
buffering time for rated value of the output current in the event of power failure minimum	10 ms
operating condition of the mains buffering	at Vin = 400 V
line frequency	
• 1 rated value	50 Hz
2 rated value	60 Hz
line frequency	45 65 Hz
input current	
 at rated input voltage 400 V 	2.1 A
 at rated input voltage 500 V 	1.7 A
current limitation of inrush current at 25 °C maximum	13 A
I2t value maximum	2.24 A²·s
fuse protection type	none
• in the feeder	Required: 3-pole connected miniature circuit breaker 10 16 A characteristic C or circuit breaker 3RV2011-1DA10 (setting 3 A) or 3RV2711-1DD10 (UL 489)
Output	
voltage curve at output	Controlled, isolated DC voltage
output voltage at DC rated value	24 V
output voltage	
at output 1 at DC rated value	24 V
relative overall tolerance of the voltage	3 %
relative control precision of the output voltage	
 on slow fluctuation of input voltage 	0.1 %
 on slow fluctuation of ohm loading 	0.2 %
residual ripple	
maximum	100 mV
voltage peak	
• maximum	240 mV
adjustable output voltage	24 28 V
product function output voltage adjustable	Yes
type of output voltage setting	via potentiometer; max. 960 W
display version for normal operation	Green LED for 24 V OK

type of signal at output	Relay contact (NO contact, rating 60 V DC/ 0.3 A) for "24 V OK"
behavior of the output voltage when switching on	minimal overshooting (< 2 %)
response delay maximum	0.1 s
voltage increase time of the output voltage	
maximum	100 ms
output current	Too me
• rated value	40 A
• rated range	0 40 A; +60 +70 °C: Derating 4%/K
supplied active power typical	960 W
short-term overload current	
at short-circuit during operation typical	120 A
duration of overloading capability for excess current	
at short-circuit during operation	25 ms
constant overload current	20 110
on short-circuiting during the start-up typical	44 A
product feature	77.A
bridging of equipment	Yes; switchable characteristic
number of parallel-switched equipment resources for increasing	2
the power	
Efficiency	04.07
efficiency in percent	94 %
power loss [W]	00.04
 at rated output voltage for rated value of the output current typical 	66 W
during no-load operation maximum	4 W
Closed-loop control	
relative control precision of the output voltage with rapid	1 %
fluctuation of the input voltage by +/- 15% typical	1 /0
relative control precision of the output voltage load step of resistive load 50/100/50 % typical	3 %
setting time	
maximum	10 ms
Protection and monitoring	
design of the overvoltage protection	< 31.8 V
• typical	44 A
property of the output short-circuit proof	Yes
design of short-circuit protection	Alternatively, constant current characteristic approx. 44 A or latching shutdown
enduring short circuit current RMS value	
• typical	50 A
overcurrent overload capability in normal operation	overload capability 150 % lout rated up to 5 s/min
display version for overload and short circuit	LED yellow for "overload", LED red for "latching shutdown"
Safety	
galvanic isolation between input and output	Ven
galvanic isolation	Yes
operating resource protection class	Safety extra-low output voltage Uout acc. to EN 60950-1 and EN 50178
leakage current	
iounage ourrein	Safety extra-low output voltage Uout acc. to EN 60950-1 and EN 50178
maximum	Safety extra-low output voltage Uout acc. to EN 60950-1 and EN 50178
•	Safety extra-low output voltage Uout acc. to EN 60950-1 and EN 50178 Class I
• maximum	Safety extra-low output voltage Uout acc. to EN 60950-1 and EN 50178 Class I 1 mA
maximum typical	Safety extra-low output voltage Uout acc. to EN 60950-1 and EN 50178 Class I 1 mA 0.6 mA
maximum typical protection class IP	Safety extra-low output voltage Uout acc. to EN 60950-1 and EN 50178 Class I 1 mA 0.6 mA
maximum typical protection class IP Approvals	Safety extra-low output voltage Uout acc. to EN 60950-1 and EN 50178 Class I 1 mA 0.6 mA
maximum typical protection class IP Approvals certificate of suitability	Safety extra-low output voltage Uout acc. to EN 60950-1 and EN 50178 Class I 1 mA 0.6 mA IP20
maximum typical protection class IP Approvals certificate of suitability CE marking	Safety extra-low output voltage Uout acc. to EN 60950-1 and EN 50178 Class I 1 mA 0.6 mA IP20 Yes Yes; cULus-Listed (UL 508, CSA C22.2 No. 107.1), File E197259; cCSAus
maximum typical protection class IP Approvals certificate of suitability CE marking UL approval	Safety extra-low output voltage Uout acc. to EN 60950-1 and EN 50178 Class I 1 mA 0.6 mA IP20 Yes Yes; cULus-Listed (UL 508, CSA C22.2 No. 107.1), File E197259; cCSAus (CSA C22.2 No. 60950-1, UL 60950-1) Yes; cULus-Listed (UL 508, CSA C22.2 No. 107.1), File E197259; cCSAus
maximum typical protection class IP Approvals certificate of suitability CE marking UL approval CSA approval	Safety extra-low output voltage Uout acc. to EN 60950-1 and EN 50178 Class I 1 mA 0.6 mA IP20 Yes Yes; cULus-Listed (UL 508, CSA C22.2 No. 107.1), File E197259; cCSAus (CSA C22.2 No. 60950-1, UL 60950-1) Yes; cULus-Listed (UL 508, CSA C22.2 No. 107.1), File E197259; cCSAus (CSA C22.2 No. 60950-1, UL 60950-1)
maximum typical protection class IP Approvals certificate of suitability CE marking UL approval CSA approval cCSAus, Class 1, Division 2	Safety extra-low output voltage Uout acc. to EN 60950-1 and EN 50178 Class I 1 mA 0.6 mA IP20 Yes Yes; cULus-Listed (UL 508, CSA C22.2 No. 107.1), File E197259; cCSAus (CSA C22.2 No. 60950-1, UL 60950-1) Yes; cULus-Listed (UL 508, CSA C22.2 No. 107.1), File E197259; cCSAus (CSA C22.2 No. 60950-1, UL 60950-1) No
maximum typical protection class IP Approvals certificate of suitability	Safety extra-low output voltage Uout acc. to EN 60950-1 and EN 50178 Class I 1 mA 0.6 mA IP20 Yes Yes; cULus-Listed (UL 508, CSA C22.2 No. 107.1), File E197259; cCSAus (CSA C22.2 No. 60950-1, UL 60950-1) Yes; cULus-Listed (UL 508, CSA C22.2 No. 107.1), File E197259; cCSAus (CSA C22.2 No. 60950-1, UL 60950-1) No
maximum typical protection class IP Approvals certificate of suitability CE marking UL approval CSA approval cCSAus, Class 1, Division 2 ATEX certificate of suitability	Safety extra-low output voltage Uout acc. to EN 60950-1 and EN 50178 Class I 1 mA 0.6 mA IP20 Yes Yes; cULus-Listed (UL 508, CSA C22.2 No. 107.1), File E197259; cCSAus (CSA C22.2 No. 60950-1, UL 60950-1) Yes; cULus-Listed (UL 508, CSA C22.2 No. 107.1), File E197259; cCSAus (CSA C22.2 No. 60950-1, UL 60950-1) No No

FM registration	No
type of certification CB-certificate	Yes
certificate of suitability	165
EAC approval	Yes
• C-Tick	Yes
Regulatory Compliance Mark (RCM)	Yes
certificate of suitability shipbuilding approval	Yes
shipbuilding approval	ABS, DNV GL
Marine classification association	ABO, BIV OL
American Bureau of Shipping Europe Ltd. (ABS)	Yes
French marine classification society (BV)	No
• DNV GL	Yes
Lloyds Register of Shipping (LRS)	No
Nippon Kaiji Kyokai (NK)	No
EMC	
standard	
for emitted interference	EN 55022 Class B
for mains harmonics limitation	EN 61000-3-2
for interference immunity	EN 61000-6-2
environmental conditions	
ambient temperature	
during operation	-25 +70 °C; With natural convection
during transport	-40 +85 °C
during storage	-40 +85 °C
environmental category according to IEC 60721	Climate class 3K3, 5 95% no condensation
Mechanics	
Mechanics type of electrical connection	screw-type terminals
	screw-type terminals L1, L2, L3, PE: 1 screw terminal each for 0.5 4 mm² single-core/finely stranded
type of electrical connection	L1, L2, L3, PE: 1 screw terminal each for 0.5 4 mm² single-core/finely
type of electrical connection • at input	L1, L2, L3, PE: 1 screw terminal each for 0.5 4 mm² single-core/finely stranded +: 2 screw terminals each for 0.5 16 mm²; -: 3 screw terminals each for 0.5
type of electrical connection	L1, L2, L3, PE: 1 screw terminal each for 0.5 4 mm² single-core/finely stranded +: 2 screw terminals each for 0.5 16 mm²; -: 3 screw terminals each for 0.5 16 mm² 13, 14 (alarm signal), 15, 16 (Remote): 1 screw terminal each for 0.05 2.5
type of electrical connection	L1, L2, L3, PE: 1 screw terminal each for 0.5 4 mm² single-core/finely stranded +: 2 screw terminals each for 0.5 16 mm²; -: 3 screw terminals each for 0.5 16 mm² 13, 14 (alarm signal), 15, 16 (Remote): 1 screw terminal each for 0.05 2.5 mm²
type of electrical connection	L1, L2, L3, PE: 1 screw terminal each for 0.5 4 mm² single-core/finely stranded +: 2 screw terminals each for 0.5 16 mm²; -: 3 screw terminals each for 0.5 16 mm² 13, 14 (alarm signal), 15, 16 (Remote): 1 screw terminal each for 0.05 2.5 mm² 135 mm
type of electrical connection	L1, L2, L3, PE: 1 screw terminal each for 0.5 4 mm² single-core/finely stranded +: 2 screw terminals each for 0.5 16 mm²; -: 3 screw terminals each for 0.5 16 mm² 13, 14 (alarm signal), 15, 16 (Remote): 1 screw terminal each for 0.05 2.5 mm² 135 mm 145 mm
type of electrical connection	L1, L2, L3, PE: 1 screw terminal each for 0.5 4 mm² single-core/finely stranded +: 2 screw terminals each for 0.5 16 mm²; -: 3 screw terminals each for 0.5 16 mm² 13, 14 (alarm signal), 15, 16 (Remote): 1 screw terminal each for 0.05 2.5 mm² 135 mm 145 mm
type of electrical connection	L1, L2, L3, PE: 1 screw terminal each for 0.5 4 mm² single-core/finely stranded +: 2 screw terminals each for 0.5 16 mm²; -: 3 screw terminals each for 0.5 16 mm² 13, 14 (alarm signal), 15, 16 (Remote): 1 screw terminal each for 0.05 2.5 mm² 135 mm 145 mm 150 mm
type of electrical connection • at input • at output • for auxiliary contacts width of the enclosure height of the enclosure depth of the enclosure required spacing • top	L1, L2, L3, PE: 1 screw terminal each for 0.5 4 mm² single-core/finely stranded +: 2 screw terminals each for 0.5 16 mm²; -: 3 screw terminals each for 0.5 16 mm² 13, 14 (alarm signal), 15, 16 (Remote): 1 screw terminal each for 0.05 2.5 mm² 135 mm 145 mm 150 mm
type of electrical connection • at input • at output • for auxiliary contacts width of the enclosure height of the enclosure depth of the enclosure required spacing • top • bottom	L1, L2, L3, PE: 1 screw terminal each for 0.5 4 mm² single-core/finely stranded +: 2 screw terminals each for 0.5 16 mm²; -: 3 screw terminals each for 0.5 16 mm² 13, 14 (alarm signal), 15, 16 (Remote): 1 screw terminal each for 0.05 2.5 mm² 135 mm 145 mm 150 mm
type of electrical connection	L1, L2, L3, PE: 1 screw terminal each for 0.5 4 mm² single-core/finely stranded +: 2 screw terminals each for 0.5 16 mm²; -: 3 screw terminals each for 0.5 16 mm² 13, 14 (alarm signal), 15, 16 (Remote): 1 screw terminal each for 0.05 2.5 mm² 135 mm 145 mm 150 mm 40 mm 40 mm 0 mm
type of electrical connection	L1, L2, L3, PE: 1 screw terminal each for 0.5 4 mm² single-core/finely stranded +: 2 screw terminals each for 0.5 16 mm²; -: 3 screw terminals each for 0.5 16 mm² 13, 14 (alarm signal), 15, 16 (Remote): 1 screw terminal each for 0.05 2.5 mm² 135 mm 145 mm 150 mm 40 mm 0 mm 0 mm
type of electrical connection • at input • at output • for auxiliary contacts width of the enclosure height of the enclosure depth of the enclosure required spacing • top • bottom • left • right net weight	L1, L2, L3, PE: 1 screw terminal each for 0.5 4 mm² single-core/finely stranded +: 2 screw terminals each for 0.5 16 mm²; -: 3 screw terminals each for 0.5 16 mm² 13, 14 (alarm signal), 15, 16 (Remote): 1 screw terminal each for 0.05 2.5 mm² 135 mm 145 mm 150 mm 40 mm 0 mm 0 mm 0 mm
type of electrical connection • at input • at output • for auxiliary contacts width of the enclosure height of the enclosure depth of the enclosure required spacing • top • bottom • left • right net weight product feature of the enclosure housing can be lined up	L1, L2, L3, PE: 1 screw terminal each for 0.5 4 mm² single-core/finely stranded +: 2 screw terminals each for 0.5 16 mm²; -: 3 screw terminals each for 0.5 16 mm² 13, 14 (alarm signal), 15, 16 (Remote): 1 screw terminal each for 0.05 2.5 mm² 135 mm 145 mm 150 mm 40 mm 40 mm 0 mm 0 mm 0 mm 3.3 kg Yes
type of electrical connection • at input • at output • for auxiliary contacts width of the enclosure height of the enclosure depth of the enclosure required spacing • top • bottom • left • right net weight product feature of the enclosure housing can be lined up fastening method electrical accessories mechanical accessories	L1, L2, L3, PE: 1 screw terminal each for 0.5 4 mm² single-core/finely stranded +: 2 screw terminals each for 0.5 16 mm²; -: 3 screw terminals each for 0.5 16 mm² 13, 14 (alarm signal), 15, 16 (Remote): 1 screw terminal each for 0.05 2.5 mm² 135 mm 145 mm 150 mm 40 mm 0 mm 0 mm 0 mm 3.3 kg Yes Snaps onto DIN rail EN 60715 35x15
type of electrical connection • at input • at output • for auxiliary contacts width of the enclosure height of the enclosure depth of the enclosure required spacing • top • bottom • left • right net weight product feature of the enclosure housing can be lined up fastening method electrical accessories	L1, L2, L3, PE: 1 screw terminal each for 0.5 4 mm² single-core/finely stranded +: 2 screw terminals each for 0.5 16 mm²; -: 3 screw terminals each for 0.5 16 mm² 13, 14 (alarm signal), 15, 16 (Remote): 1 screw terminal each for 0.05 2.5 mm² 135 mm 145 mm 150 mm 40 mm 0 mm 0 mm 0 mm 3.3 kg Yes Snaps onto DIN rail EN 60715 35x15 Buffer module



Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Siemens:

6EP34378SB000AY0