SIEMENS

Data sheet for SINAMICS G120X

Article No. :

6SL3220-1YC32-0UB0



Figure similar

Client order no. :
Order no. :
Offer no. :
Remarks :

	Rate	d data	
Input			
Number of	phases	3 AC	
Line voltage	e	200 240 V +10 %	b -20 %
Line freque	ncy	47 63 Hz	
Rated volta	age	200V IEC	240V NEC
Rated cu	rrent (LO)	76.00 A	76.00 A
Rated cu	rrent (HO)	64.00 A	64.00 A
Output			
Number of	phases	3 AC	
Rated volta	age	200V IEC	240V NEC ¹⁾
Rated po	wer (LO)	22.00 kW	30.00 hp
Rated po	wer (HO)	18.50 kW	25.00 hp
Rated cu	rrent (LO)	80.00 A	80.00 A
Rated cu	rrent (HO)	68.00 A	68.00 A
Rated cur	rrent (IN)	82.00 A	
Max. out	put current	108.00 A	
Pulse frequen	cy	4 kHz	
Output freque	ency for vector control	0 200 Hz	
Output freque	ency for V/f control	0 550 Hz	

Overload capability

Low Overload (LO)

110% base load current IL for 60 s in a 300 s cycle time

High Overload (HO)

150% x base load current IH for 60 s within a 600 s cycle time

General tech	. specifications
Power factor λ	0.90 0.95
Offset factor $\cos \phi$	0.99
Efficiency η	0.97
Sound pressure level (1m)	70 dB
Power loss 3)	0.937 kW
Filter class (integrated)	Unfiltered
EMC category (with accessories)	without
Safety function "Safe Torque Off"	without SIRIUS device (e.g. via S7- 1500F)
Comm	unication

Communication

USS, Modbus RTU, BACnet MS/TP

ltem no. : Consignment no. : Project :

ſ

Inputs /	outputs
Standard digital inputs	
Number	6
Switching level: $0 \rightarrow 1$	11 V
Switching level: $1 \rightarrow 0$	5 V
Max. inrush current	15 mA
Fail-safe digital inputs	
Number	1
Digital outputs	
Number as relay changeover contact	2
Output (resistive load)	DC 30 V, 5.0 A
Number as transistor	0
Analog / digital inputs	
Number	2 (Differential input)
Resolution	10 bit
Switching threshold as digital input	
0 → 1	4 V
1 → 0	1.6 V
Analog outputs	
Number	1 (Non-isolated output)
PTC/ KTY interface	
1 motor temperature sensor input, ser Thermo-Click, accuracy ±5 °C	nsors that can be connected PTC, KTY and
Closed-loop co	ntrol techniques

Closed-loop cor	ntrol techniques
V/f linear / square-law / parameterizable	Yes
V/f with flux current control (FCC)	Yes
V/f ECO linear / square-law	Yes
Sensorless vector control	Yes
Vector control, with sensor	No
Encoderless torque control	No
Torque control, with encoder	No

SIEMENS

Data sheet for SINAMICS G120X

Article No. :

6SL3220-1YC32-0UB0

Ambien	at conditions
Standard board coating type	Class 3C2, according to IEC 60721-3-3: 2002
Cooling	Air cooling using an integrated fan
Cooling air requirement	0.083 m³/s (2.931 ft³/s)
Installation altitude	1,000 m (3,280.84 ft)
Ambient temperature	
Operation	-20 45 °C (-4 113 °F)
Transport	-40 70 °C (-40 158 °F)
Storage	-25 55 °C (-13 131 °F)
Relative humidity	
Max. operation	95 % At 40 °C (104 °F), condensation and icing not permissible
Con	nections
Signal cable	
Conductor cross-section	0.15 1.50 mm² (AWG 24 AWG 16)
Line side	
Version	screw-type terminal
Conductor cross-section	25.00 70.00 mm² (AWG 6 AWG 3/0)
Motor end	
Version	Screw-type terminals
Conductor cross-section	25.00 70.00 mm ² (AWG 6 AWG 3/0)
DC link (for braking resistor)	
PE connection	Screw-type terminals
Max. motor cable length	
Shielded	200 m (656.17 ft)
Unshielded	300 m (984.25 ft)

Me	chanical data	
Degree of protection	IP20 / UL open type	
Frame size	FSE	
Net weight	16.6 kg (36.60 lb)	
Dimensions		
Width	275 mm (10.83 in)	
Height	551 mm (21.69 in)	
Depth	248 mm (9.76 in)	
	Standards	
Compliance with standards	UL, cUL, CE, C-Tick (RCM), EAC, KCC SEMI F47, REACH	-,
CE marking	EMC Directive 2004/108/EC, Low- Voltage Directive 2006/95/EC	
Converter lo	osses to IEC61800-9-2*	
Efficiency class	IE2	
Comparison with the reference converter (90% / 100%)	57.9 %	
· · · · · · · · · · · · · · · · · · ·		
648.0 W (2.0 %)	762.0 W (2.3 %) 937.0 W (2.8 %)	
I ▲ 648.0 W (2.0 %)	762.0 W (2.3 %) 937.0 W (2.8 %)	
I ▲ 648.0 W (2.0 %)	762.0 W (2.3 %) 937.0 W (2.8 %)	
I ▲ 648.0 W (2.0 %)	762.0 W (2.3 %) 937.0 W (2.8 %)	
648.0 W (2.0 %) 100% 380.0 W (1.1 %)	762.0 W (2.3 %) 937.0 W (2.8 %) 423.0 W (1.3 %) 483.0 W (1.5 %)	
648.0 W (2.0 %) 100% ●	••••••••••••••••••••••••••••••••••••••	

50% 90% ${\rm f}$ The percentage values show the losses in relation to the rated apparent power of the converter.

The diagram shows the losses for the points (as per standard IEC61800-9-2) of the relative torque generating current (I) over the relative motor stator frequency (f). The values are valid for the basic version of the converter without options/components.

*converted values

25%

¹⁾The output current and HP ratings are valid for the voltage range 220V-240V

³⁾Typical value. More information can be found in the element group "Converter losses to IEC 61800-9-2" in this datasheet.

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Siemens: 6SL32201YC320UB0