# SIEMENS

Data sheet for SINAMICS G120X

#### Article No. :

#### 6SL3230-2YC16-0UF0



Figure similar

Client order no. :
Order no. :
Offer no. :
Remarks :

Rated data		
Input		
Number of phases	3 AC	
Line voltage	200 240 V +10	% -20 %
Line frequency	47 63 Hz	
Rated voltage	200V IEC	240V NEC
Rated current (LO)	9.60 A	9.60 A
Rated current (HO)	6.70 A	6.70 A
Output		
Number of phases	3 AC	
Rated voltage	200V IEC	240V NEC 1)
Rated power (LO)	2.20 kW	3.00 hp
Rated power (HO)	1.50 kW	2.00 hp
Rated current (LO)	10.40 A	10.40 A
Rated current (HO)	7.40 A	7.40 A
Rated current (IN)	10.80 A	
Max. output current	14.10 A	
Pulse frequency	4 kHz	
Output frequency for vector control	0 200 Hz	
Output frequency for V/f control	0 550 Hz	

#### **Overload capability**

Low Overload (LO)

110% base load current IL for 60 s in a 300 s cycle time

High Overload (HO)

150% x base load current IH for 60 s within a 600 s cycle time

General tech. specifications		
Power factor $\lambda$	0.70 0.85	
Offset factor $\cos \phi$	0.96	
Efficiency η	0.96	
Sound pressure level (1m)	63 dB	
Power loss 3)	0.123 kW	
Filter class (integrated)	Unfiltered	
EMC category (with accessories)	without	
Safety function "Safe Torque Off" without SIRIUS device (e.g. via S7- 1500F)		
Communication		

Communication

PROFINET, EtherNet/IP

ltem no. : Consignment no. : Project :

Г

Inputs / outputs		
Standard digital inputs		
Number	6	
Switching level: $0 \rightarrow 1$	11 V	
Switching level: $1 \rightarrow 0$	5 V	
Max. inrush current	15 mA	
Fail-safe digital inputs		
Number	1	
Digital outputs		
Number as relay changeover contact	2	
Output (resistive load)	DC 30 V, 5.0 A	
Number as transistor	0	
Analog / digital inputs		
Number	2 (Differential input)	
Resolution	10 bit	
Switching threshold as digital input		
0 → 1	4 V	
$1 \rightarrow 0$	1.6 V	
Analog outputs		
Number	1 (Non-isolated output)	
PTC/ KTY interface		
1 motor temperature sensor input, sensors that can be connected PTC, KTY and Thermo-Click, accuracy $\pm 5~^\circ\text{C}$		
Closed-loop co	ntrol techniques	

Closed-loop control techniques		
V/f linear / square-law / parameterizable	Yes	
V/f with flux current control (FCC)	Yes	
V/f ECO linear / square-law	Yes	
Sensorless vector control	Yes	
Vector control, with sensor	No	
Encoderless torque control	No	
Torque control, with encoder	No	

## SIEMENS

#### Data sheet for SINAMICS G120X

#### Article No. :

#### 6SL3230-2YC16-0UF0

Ambie	ent conditions
Standard board coating type	Class 3C3, according to IEC 60721-3-3: 2002
Cooling	Air cooling using an integrated fan
Cooling air requirement	0.009 m³/s (0.325 ft³/s)
Installation altitude	1,000 m (3,280.84 ft)
Ambient temperature	
Operation	-20 45 °C (-4 113 °F)
Transport	-40 70 °C (-40 158 °F)
Storage	-25 55 °C (-13 131 °F)
Relative humidity	
Max. operation	95 % At 40 °C (104 °F), condensation and icing not permissible
Connections	
Signal cable	
Conductor cross-section	0.15 1.50 mm² (AWG 24 AWG 16)
Line side	
Version	screw-type terminal
Conductor cross-section	1.50 6.00 mm² (AWG 16 AWG 10)
Motor end	
Version	Screw-type terminals
Conductor cross-section	1.50 6.00 mm² (AWG 16 AWG 10)
DC link (for braking resistor)	
PE connection	On housing with M4 screw
Max. motor cable length	
Shielded	150 m (492.13 ft)
Unshielded	300 m (984.25 ft)

Me	echanical data	
Degree of protection	IP20 / UL open	type
Frame size	FSB	
Net weight	5.8 kg (12.79 l	b)
Dimensions		
Width	100 mm (3.94	in)
Height	275 mm (10.8	3 in)
Depth	218 mm (8.58	in)
	Standards	
Compliance with standards	UL, cUL, CE, C- SEMI F47, REA	Tick (RCM), EAC, KCC, CH
CE marking	EMC Directive Voltage Directi	2004/108/EC, Low- ve 2006/95/EC
Converter l	osses to IEC61800-	9-2*
Efficiency class	IE2	
Comparison with the reference converter (90% / 100%)	42.4 %	
94.0 W (2.2 %)	106.0 W (2.5 %) 	123.0 W (2.8 %)
70.5 W (1.6 %)	76.3 W (1.8 %)	83.4 W (1.9 %)

25% 60.9 W (1.4 %) 63.7 W (1.5 \%) 63

The percentage values show the losses in relation to the rated apparent power of the converter.

The diagram shows the losses for the points (as per standard IEC61800-9-2) of the relative torque generating current (I) over the relative motor stator frequency (f). The values are valid for the basic version of the converter without options/components.

\*converted values

<sup>1)</sup>The output current and HP ratings are valid for the voltage range 220V-240V

<sup>3)</sup> Typical value. More information can be found in the element group "Converter losses to IEC 61800-9-2" in this datasheet.

### SIEMENS

### Data sheet for SINAMICS G120X

#### Article No. :

#### 6SL3230-2YC16-0UF0

#### Operator panel: Basic Operator Panel (BOP-2)

Screen		
LCD, monochrome		
Mechanical data		
IP55 / UL type 12		
0.140 kg (0.31 lb)		
70.00 mm (2.76 in)		
106.85 mm (4.21 in)		
19.60 mm (0.77 in)		

Ambient conditions		
Ambient temperature		
Operation	0 50 °C (32 122 °F)	
Storage	-40 70 °C (-40 158 °F)	
Transport	-40 70 °C (-40 158 °F)	
Relative humidity at 25°C during	3	
Max. operation	95 %	
Approvals		
Certificate of suitability	CE, cULus, EAC, KCC, RCM	

### **Mouser Electronics**

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Siemens: 6SL32302YC160UF0