

Single Pedal With Cover

STANDARD

TWO STAGE OPERATION


LATCHING











Standard OFF-ON Operation -Push pedal to change contact state. Release pedal to return to original state. Two Stage Operation-Press Pedal to change the state of the first set of contacts. Continue to press further to change the second set of contacts. Latching Operation Push pedal to change contact
state. When you release the pedal ,
the contacts remain in that state.
Push again to return to original
state.











Single pedal foot switch F1			
Article number	Cable entry	Designation	Switching contacts
Snap-action contact:			

			Pedal 1
606.1800.012	1 x M20	F1-SU1Z UN	1NC / 1NO
606.1900.062	1 x M20	F1-SU2Z UN	2NC / 2NO

Slow-action contact (IP65 Protection Rating):

			Pedal 1
606.1600.006	1 x M20	F1-U1Z UN	1NC / 1NO
606.1700.004	1 x M20	F1-U2Z UN	2NC / 2NO

Slow-action contact (IP67 Protection Rating):

606.1600.345	3 x M20	F1-U1Z UN	1NC / 1NO
606.1600.538	1 x M20	F1-U1Z UN	1NC / 1NO
			Pedal 1

Single pedal foot switch F1

Article number	Designation	Switching contacts	Pressure point
Snap-action contact:			

		Pedal 1	Pedal 1
616.1800.073	F1-SU1ZD UN	1NC / 1NO	200 N
606.1900.433	F1-SU2ZD UN	2NC/2NO	200 N

Slow-action contact:

			Pedal 1
606.1600.010	F1-U1ZD UN	1NC / 1NO	200 N
606.1700.008	F1-U2ZD UN	2NC / 2NO	200 N

Single pedal foot switch F1			
Article number	Designation	Switching contacts	
Snap-action contact:		Pedal 1	
616.1800.247	F1-SU1Y UN	1NC / 1NO	
Slow-action contact:			
616.1600.295	F1-U1Y UN	1NC / 1NO	

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Altech:

<u>606.1600.006</u> <u>606.1900.062</u> <u>606.1600.010</u> <u>616.1800.073</u> <u>606.1700.004</u> <u>606.1700.008</u> <u>606.1800.012</u> 606.1900.433 616.1600.295 616.1800.247