

### Quality Products. Service Excellence.

## **Heavy Duty Outlet Strip 1581 Series**

10A | 100-240V | C13 Outlets





- Rated 100-240VAC (TUV), 120-240VAC (UL), 10 A, 50/60 Hz and designed for use with IEC power cords.
- All-metal housing. Case is made of tough extruded aluminum with a black powder-coated steel cover.
- Available with either rocker type on/off switch with green light or a green pilot light to indicate power on.
- Mounting feet with keyhole slots allow temporary work station mounting if desired.

### **Specifications**













- One IEC 320 C14 inlet, and 4, 5, 6 or 8 IEC 320 C13 outlets.
- Includes 10A circuit breaker to prevent accidental line overload.
- cULus Listed UL 62368-1 (2nd Edition), 2014-12-01, and CAN/CSA C22.2 No. 62368-1-14 (2nd Edition)
- TÜV-SUD Certified to EN 62368-1:2020/A11:2020, and IEC 62368-1:2018.
- TÜV-SUD tested for EMC Compliance to EN 55032:2015+A11:2020 (CISPR 32:2015+A1:2019) & EN 55035:2017+A11:2020 (CISPR 35:2016).
- CE compliant to the European Low Voltage Directive 2014/35/EU.
- CE compliant to the European EMC Directive 2014/30/EU.
- UKCA compliant to British Electrical Equipment (Safety) Regulations 2016 (S.I. 2016/1101).
- UKCA compliant to British Electromagnetic Compatibility Regulations 2016 (S.I. 2016/1091).
- TAA compliant for GSA Schedule purchases.
- · RoHS Compliant.
- · Manufactured in North America.

#### **Accessories**

Rack Cabinet Vertical Mount Adaptor

Power Cords

Illuminated	Illuminated						
On/Off Switch	Light Only	Overall Dimensions			Outlet	Outlet	Inlet
Part No.	Part No.	Height	Width	Length	Qty	Type	Type
1581H4	1581T4	2.33	2.13	10.18	4	C13	C14
1581H5	1581T5	2.33	2.13	11.75	5	C13	C14
1581H6	1581T6	2.33	2.13	13.36	6	C13	C14
1581H8	1581T8	2.33	2.13	16.51	8	C13	C14

**Replacement Mounting Foot (One Foot)** 

Part No. 1584MF

Tags: **IEC** 

Data subject to change without notice

© 2025. Hammond Manufacturing Ltd. All rights reserved.

# **Mouser Electronics**

**Authorized Distributor** 

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

## Hammond:

1581T6 1581T4 1581T5 1581T8 1581H8 1581H5 1581H6 1581H4