

DRAWING FOR REFERENCE: This is subject to change without notice
08/11/2012

TO
RF

1			2			3			4		
COUNT	DESCRIPTION OF REVISIONS	BY	CHKD	DATE	COUNT	DESCRIPTION OF REVISIONS	BY	CHKD	DATE		
△					△						
△					△						
△					△						

RECOMMENDED PC BOARD HOLE PATTERN

24.65±0.7
PRICK PUNCH
(4 POINTS)
BRAZING
PRESS FITTING
5±0.15
10.7±0.5
22±0.7
(17)
5±0.7
φ1.4^{+0.05}_{-0.1}
φ9.2^{+0.1}_{-0.05}
φ11.2^{+0.05}_{-0.1}
10.16±0.05
5.08±0.05
5.08±0.05
10.16±0.05
5-φ1.6^{+0.1}₀
12±0.18
4-1^{+0.05}_{-0.1}
12±0.18

NO.	MATERIAL	FINISH, REMARKS	NO.	MATERIAL	FINISH, REMARKS
3	BERYLLIUM COPPER	SILVER PLATING	5	PTFE	
2	BRASS	NICKEL PLATING	4	PTFE	
1	BRASS	NICKEL PLATING			

CODE NO. (OLD)
CL

DRAWN
Y. Sugiyama
6.6.09

DESIGNED
T. Katayama
06.08.10

CHECKED
H. Shimizu
06.08.10

APPROVED
J. Matsuda
06.08.10

RELEASED

RoHS COMPLIANT

DRAWING NO.
EDC4-009061-40

PART NO.
BNC-LR-PC(40)

SCALE
2 : 1

UNITS
mm

CODE NO.
CL302-0242-7-40

1
1

1

2

3

4

FORM NO. 228

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

[Hirose Electric:](#)

[BNC-LR-PC\(40\)](#)