



JX-26

CHARACTERISTICS WITH ISX1-T BASIC SWITCH INSTALLED OPERATING FORCE — — — 1.5 OZ MAX RELEASE FORCE — — — 4 GRAMS MIN DIFFERENTIAL TRAVEL — — .030 MAX OVERTRAVEL — — — — .015 MIN	ELECTRICAL DATA		SCALE 2 TO 1
	CONTACT ARRANGEMENT		DO NOT SCALE PRINT
			UNLESS OTHERWISE NOTED DIMENSIONS ARE IN INCHES TOLERANCES ARE: ONE PLACE (.0) ±.030 TWO PLACE (.00) ±.015 THREE PLACE (.000) ±.005 ANGLES ±
			WEIGHT

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

[Honeywell:](#)

[JX-26](#)