

126-104XYW-B01

( [Home](#) : [Products](#) : [Sensors](#) : [Temperature Sensors](#) : [Discrete Thermistors](#) : [126](#) )



126 Series, matched large glass bead, 100,000 Ohm resistance,  $\pm 1,0\text{ }^{\circ}\text{C}$  [1.8  $^{\circ}\text{F}$ ] tolerance, 25/85 BETA = 3669

Actual product  
appearance may vary.

Product Specifications

Availability	Global
Resistance	100,000 Ohm
Tolerance	$\pm 1,0\text{ }^{\circ}\text{C}$ [1.8 $^{\circ}\text{F}$ ]
Accuracy	0 $^{\circ}\text{C}$ to 120 $^{\circ}\text{C}$ [32 $^{\circ}\text{F}$ to 248 $^{\circ}\text{F}$ ]
Beta	3669
Operating Temperature	-60 $^{\circ}\text{C}$ to 300 $^{\circ}\text{C}$ [-76 $^{\circ}\text{F}$ to 572 $^{\circ}\text{F}$ ]
Diameter	2,54 mm [0.10 in]
Termination Material	Platinum iridium
Lead Length	9,6 mm [0.375 in]
Time Constant in Air	4.0 s
Dissipation Constant	0,8 m/W $^{\circ}\text{C}$
Series Name	126
R-T Curve	<b>14</b>

# Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

[Honeywell:](#)

[126-104XYW-B01](#)