

## CSNE151-200

( [Home](#) : [Products](#) : [Sensors](#) : [Current Sensors](#) : [Closed Loop](#) : [CSN](#) )



**CSN Series closed loop current sensor, measures ac, dc or impulse current, 50 amp-turns nominal,  $\pm 90$  amp-turns range, 1000 turn**

Actual product appearance may vary.

### Product Specifications

Product Type	Closed Loop Linear
Sensed Current Type	ac or dc
Sensed Current Range	$\pm 90$ A
Package Type	Series Connect PCB Mount
Output Type	Current
Continuous Current	$\pm 50$ A
Operate Current	50 A RMS @ 25 °C
Supply Current	$\pm 12$ mA + Output
Supply Voltage	$\pm 12.0$ Vdc to $\pm 15.0$ Vdc
Offset Current	$< \pm 0.15$ mA
Offset Current Drift	$< \pm 0.6$ mA
Coil Resistance	66 Ohm
Response Time	$< 0.2$ $\mu$ s
Coil Turns	1000
Output Nominal	50 mA
Operating Temperature	-40 °C to 85 °C [-40 °F to 185 °F]
Storage Temperature	-40 °C to 90 °C [-40 °F to 194 °F]
Measuring Resistance	54 Ohm min., 150 Ohm max.
Housing Material	Glass-filled PBT (UL94-V0)
Mounting	PCB on 11 Pins
Pinout Style	4 Pin
Accuracy	$\pm 0.5$ %
Availability	Global
Comment	Miniature 50 A sensor with four integral primary turns. (Accuracy guaranteed to 90 A.)
UNSPSC Code	41111928
UNSPSC Commodity	41111928 Current Sensors
Series Name	CSN

# Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

[Honeywell:](#)

[CSNE151-200](#)