

12-Slot Media Converter Rack

Flexible Design for growing networks simplify your installation of Transition Networks' stand-alone media converters with the Media Converter Rack. This 19" rack-mountable unit supports up to twelve media converters while the unique design allows for multiple connections, consolidated into a single device, making network connections easier and more efficient.



(Media Converters Sold Separately)

- **Space Saving Design:** This device is powered by a single internal universal power supply; eliminating the need for the multiple power connections often associated with multiple converter installations. The unit saves space in the wiring closet by providing a means for mounting (12) converters in (3) units of rack space while reducing the number of wall outlet power connections required.
- **Convenience:** The media converters are hot-swappable. They can also be removed from the rack, powered externally, and used as stand-alone units in new applications as your network needs change in the future.
- **Cost Effective:** Easily rack mount the single-wide, 12 volt powered, Transition Networks' media converters that you already own, or buy stand-alone units today and rack mount them in the future.
- **Includes:** (12) Universal rack mount media converter brackets.

Specifications

Dimensions	Width: 17" [432 mm] Depth: 15" [381 mm] Height: 4.75" [121 mm]
Power Supply	Universal, internal power supply; AC 85 – 264V, 47 – 63 Hz.
Environment	Operating: 0°C to 50°C Humidity: 10% to 90% (non-condensing) Altitude: 0 – 10,000 ft.
Weight	12 lbs. [5.2 kg]
MTBF	46,000 Hours (MIL-HDBK-217F) 126,500 Hours (Bellcore)
Certifications	UL Listed, cUL Listed (Canada), CISPR/EN55022 Class A, FCC Class A, CE Mark
Warranty	Lifetime

Ordering Information

E-MCR-05

12-Slot Media Converter Rack

Mounting Options (sold separately)

RMBU

Universal Rack Mount Bracket
for Stand-Alone Converters

RMBM

Rack Mount Bracket for
Mini Media Converters

Power Cord Included

To order the corresponding country specific power cord, add the extension from the list below to the end of the SKU; Ex: E-MCR-05-NA

-NA = Country Code

-NA = North America
-LA = Latin America
-EU = Europe
-UK = United Kingdom
-SA = South Africa
-JP = Japan
-OZ = Australia
-BR = Brazil

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Lantronix:

[E-MCR-05](#) [E-MCR-05-BR](#) [E-MCR-05-EU](#) [E-MCR-05-JP](#) [E-MCR-05-LA](#) [E-MCR-05-NA](#) [E-MCR-05-OZ](#) [E-MCR-05-SA](#) [E-MCR-05-UK](#)