

Easy to use, reliable, industrial modems

Maestro 100 CDMA has been specifically design to stand harsh environment. Compact, high voltage range and power surge resistant, the Maestro 100 CDMA can easily be integrated into demanding industrial application from electricity meters to intrusion alarms or vending machines. Maestro 100 CDMA modem also embed gpsOne features and can be use for location aware applications. Maestro 100 CDMA is available on Sprint, Verizon and Aeris networks in the US, a generic version is also available.

100cdma



- Industrial and robust design CDMA modem
- High Voltage Range 9 to 60V DC
- Embedded gpsOne

About Mestro Wireless Solutions

Applying more than 15 years experience and know how of M2M communications, the Maestro team provides effective and highly reliable wireless solutions from off-the-shelf, generic easy to use modems, up to specific and optimized custom vertical application integration.











Technical information

FEATURES/PRODUCTS	M100 CDMA	
TECHNOLOGY	TECHNOLOGY	
CDMA	CDMA 2000 1xRTT 800 / 1900MHz	
SMS	1	
TCP/IP	Full TCP/IP Stack	

FUNCTIONAL FEATURES	
gpsOne	/
Download Over The Air	Optional
CMUX	/
OTHER FEATURES	
Operating status LED	/
Casing	Metal
DIN rail mounting	/

INTERFACES	
RS232 on 15 pin Sub-D connector	✓
RS232 on 9 pin Sub-D connector	optional (with OTH-006)
Pin power supply connector	4 pin DC
SMA antenna connector (50 ohm)	2 (CDMA / gpsOne)
DIMENSIONS Metal casing	
Size (mm)	88x60x26
Weight (g)	70
TEMPERATURE RANGE (module)	
Operating / Storage	-30~+75°C / -40~+85°C
POWER SUPPLY	
Input voltage	9 - 60V DC
AC/DC	DC

CERTIFICATIONS/COMPLIANCES		
FCC	/	
Verizon ODC	/	
Aeris	/	
Sprint Certification	/	
RoHS	/	

Recommended Accessories	
ACC-CA01	DB 15 for M100 RS-232(M) to DB 9 RS-232(F) - Cable L=1100mm
ACC-PS09	Industrial grade 1.2 A Power Adaptor (with NEMA 2 Pins plug cable - USA)
ACC-A05	GSM 850/1900 Magnetic Mount Antenna - Cable L= 2500mm
ACC-DIN	DIN Rail Mounting Clip for Maestro 100 Series
OTH-006	DB15 to DB 9(F) Adaptor for M100 CDMA

B - Bundle (include data cable, power supply and antenna)

SMA antenna connector (50 ohm)	2 (CDMA / gpsOne)	
DIMENSIONS Metal casing		
Size (mm)	88x60x26	
Weight (g)	70	
TEMPERATURE RANGE (module)		
Operating / Storage	-30~+75°C / -40~+85°C	
POWER SUPPLY		
Input voltage	9 - 60V DC	
AC/DC	DC	
CERTIFICATIONS/COMPLIANCES		
ECC	/	

CERTIFICATIONS/COMPLIANCES	CERTIFICATIONS/COMPLIANCES	
FCC	/	
Verizon ODC	/	
Aeris	/	
Sprint Certification	/	
RoHS	/	

Recommended Accessories	
ACC-CA01	DB 15 for M100 RS-232(M) to DB 9 RS-232(F) - Cable L=1100mm
ACC-PS09	Industrial grade 1.2 A Power Adaptor (with NEMA 2 Pins plug cable - USA)
ACC-A05	GSM 850/1900 Magnetic Mount Antenna - Cable L= 2500mm
ACC-DIN	DIN Rail Mounting Clip for Maestro 100 Series
OTH-006	DB15 to DB 9(F) Adaptor for M100 CDMA

Ordering Information M100CDMA-S B

Product code

Carrier Selection:

Bundle Selection:

- A Aeris
- V Verizon
- S Sprint G - Generic

Maestro Wireless Solutions Ltd Maestro wireless Solutions Ltd 3603-9, 36/F 118 Connaught Road West Hong Kong Tel: (852) 2869 0688 Fax: (852) 2525 4701 contact@maestro-wireless.com

www.maestro-wireless.com



{} - Leave blank for modem only



M100 CDMA



ACC-CA01



OTH-006



ACC-DIN

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Lantronix: BR350