

# RAD.1S.250.CTM

# **SUMMARY**

#### # Wires

Coax

ial



Image is for illustrative purpose only

Series	1S			
Termination type	Female crimp Coaxi			
IP rating	50			
AWG wire size	0.00 - 0.00			
Cable Ø	0.00 - 0.00 mm			
Status	active			

1

#### Download

Request a quote Catalog

# **TECHNICAL DETAILS**

#### **Mechanics**

Shell Style/Model	RAD*: Fixed coupler, nut fixing
Keying	Circular, flange side: female contacts, other side: female contacts
Housing Material	Brass (chrome plated [SAE AMS 2460]) shell and collet nut, nickel plated [SAE AMS QQ N 290] brass latch sleeve and mid pieces
Weight	11.30 g
Performance	
Configuration	1S.250 : 1 Coax (50 Ohm)
Insulator	T: PTFE
Rated Current	12 Amps
Specifications	

#### Specifications


Contact Type: Coaxial 50 Ohm Contact Dia.: 1.6 mm (0.06in) Vtest: 3000 V (AC), 4200 V (DC) Impedance: 50 Ohm VSWR: 1.01 + 0.23 \* f/GHz Cable type: RG 178 B/U, RG 196 A/U, RG 188 A/U, RG 316 B/U, RG 174 A/U, HF-2114, RG 122 /U


#### Others

LEMO products and services are provided "as is". LEMO makes no warranties or representations with regard to LEMO product & services or use of them, express, implied or statutory, including for accuracy, completeness, or security. The user is fully responsible for his products and applications using LEMO components.

Endurance (Shell): 5000 mating cycles Temp (min / max): -55°C / +250°C Humidity (max): <=95% [at 60 deg C /140 F] Vibration: 15 g [10 Hz - 2000 Hz] Shock Resistance: 100 g [ 6 ms] Climatical Category: 50/175/21 Shielding (min): 75 dB (10 MHz) Shielding (min): 40 dB (1 GHz) Salt Spray Corrosion: >1000 hr

### DRAWINGS





#### Dimensions

	А	В	E	L	Μ	S1	S2	e
mm.	14	16	7.5	28.5	1.5	10.5	14	M12x1.0
in.	0,55	0,63	0,30	1,12	0,06	0,41	0,55	

## **RECOMMENDED BY LEMO**

Tools

LEMO products and services are provided "as is". LEMO makes no warranties or representations with regard to LEMO product & services or use of them, express, implied or statutory, including for accuracy, completeness, or security. The user is fully responsible for his products and applications using LEMO components.

LEMO products and services are provided "as is". LEMO makes no warranties or representations with regard to LEMO product & services or use of them, express, implied or statutory, including for accuracy, completeness, or security. The user is fully responsible for his products and applications using LEMO components.

### **Mouser Electronics**

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

LEMO: RAD.1S.250.CTM