


# THDB SERIES





# Wiring Diagram



V = Voltage UTL = Optional Untimed Load L = Timed Load S1 = Initiate Switch

R<sub>T</sub> is used when external adjustment is ordered.

# Description

The THDB Series combines accurate timing circuitry with high power, solid-state switching. It can switch motors, lamps, and heaters directly without a contactor. You can reduce labor, component cost, and increase reliability with these small, easy-to-use, timers.

#### Operation (Delay-on-Break)

Input voltage must be applied before and during timing. Upon closure of the initiate switch, the output energizes. The time delay begins when the initiate switch is opened. The output remains energized during timing. At the end of the time delay, the output de-energizes. The output energizes if the initiate switch is closed when input voltage is applied.

**Reset:** Reclosing the initiate switch during timing resets the time delay. Loss of input voltage resets the time delay and output.

# Features & Benefits

| FEATURES                                  | BENEFITS   |
|---|--|
| Microcontroller based                     | Repeat accuracy + / - 0.5%,<br>Factory calibration + / - 1%  |
| High load currents up to 20A, 200A inrush | Allows direct operation of motors, lamps and heaters without a contactor   |
| Totally solid state and encapsulated      | No moving parts to arc and wear out over time and<br>encapsulated to protect against shock, vibration,<br>and humidity |
| Metalized<br>mounting surface             | Facilitates heat transfer in high current applications   |
| Compact, low<br>cost design               | Allows flexibility for OEM applications and reduces labor and components costs   |

# Accessories



P1004-95, P1004-95-X Versa-Pot

Panel mountable, industrial potentiometer recommended for remote time delay adjustment.



**P0700-7 Versa-Knob** Designed for 0.25 in (6.35 mm) shaft of Versa-Pot. Semi-gloss industrial black finish.



P1015-64 (AWG 14/16) Female Quick Connect These 0.25 in. (6.35 mm) female terminals are constructed with an insulator barrel to provide strain relief.



**P1015-18 Quick Connect to Screw Adapter** Screw adapter terminal designed for use with all modules with 0.25 in. (6.35 mm) male quick connect terminals.

# **Ordering Information**

| MODEL    | INPUT<br>VOLTAGE | ADJUSTMENT | TIME DELAY | OUTPUT<br>RATING |
|----------|------------------|------------|------------|------------------|
| THDB421A | 120VAC           | External   | 1 - 100s   | 6A               |
| THDB434C | 120VAC           | Onboard    | 1 - 100m   | 20A              |


If you don't find the part you need, call us for a custom product 800-843-8848

THDB SERIES



### **External Resistance vs. Time Delay**

In Secs. or Mins.




This chart applies to externally adjustable part numbers. The time delay is adjustable over the time delay range selected by varying the resistance across the  $R_T$  terminals; as the resistance increases the tie delay increases

When selecting an external  $R_{T}$ , add the tolerances of the timer and the  $R_{T}$  for the full time range adjustment.

Examples: 1 to 50 S adjustable time delay, select time delay range 1 and a 50 K ohn  $R_T.$  For 1 to 100 S use a 100 K ohm  $R_T.$ 

### **Function Diagram**



V = Voltage S1 = Initiate Switch NO = Normally **Open Contact** NC = Normally**Closed Contact** TD = Time Delay t = Incomplete Time Delay R = Reset -<del>⟨\_</del> = Undefined Time

#### **Specifications**

**Time Delay** Range **Repeat Accuracy** Tolerance (Factory Calibration) **Reset Time Initiate Time** Time Delay vs Temp. & Voltage Input Voltage Tolerance **AC Line Frequency Power Consumption** Output Type Form **Maximum Load Current** 

**Voltage Drop Off State Leakage Current Minimum Load Current** Protection Circuitry **Dielectric Breakdown Insulation Resistance Mechanical** Mounting \*\* Dimensions

### Termination

**Environmental Operating/Storage** Temperature Humidity Weight

0.1s - 1000m in 6 adjustable ranges or fixed ±0.5% or 20ms, whichever is greater

≤ ±1%

≤ 150ms ≤ 20ms  $\leq \pm 2\%$ 24, 120, or 230VAC ±20% 50/60 Hz  $\leq 2VA$ Solid state NO, closed before & during timing Inrush\*\* **Steady State** Output А 6A 60A В 10A 100A С 20A 200A ≈ 2.5V @ rated current ≈ 5mA @ 230VAC 100mA Encapsulated ≥ 2000V RMS terminals to mounting surface  $\geq 100 \text{ M}\Omega$ Surface mount with one #10 (M5 x 0.8) screw **H** 50.8 mm (2.0"); **W** 50.8 mm (2.0"); **D** 38.4 mm (1.51") 0.25 in. (6.35 mm) male quick connect terminals -40° to 60°C / -40° to 85°C 95% relative, non-condensing ≅ 3.9 oz (111 g)

\*\*Must be bolted to a metal surface using the included heat sink compound. The maximum surface temperature is 90°C. Inrush: Non-repetitive for 16ms.

# **Mouser Electronics**

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Littelfuse: THDB421A THDB434C